

and memory card corruptions beyond this range.

Select the option of your choice and reboot the device. Once rebooted, you can check the current frequency by 'vcgencmd get_config arm_freq' command.

Multiple OS distributions on single SD card

Now that we have some added power in Raspberry Pi due to over-clocking for XMBC Media Center, let us see how to install it on the same SD card together with other OS like Raspbian Wheezy. This is done using 'Berryboot.' Berryboot is a simple bootloader/universal operating system installer which also works for Android. This allows you to put multiple Linux distributions on a single SD card. In addition, it also allows you to put the operating system files on an external USB hard drive instead of the SD card itself.

Follow the steps below to download Berryboot and install as many operating systems as you like.

First of all, download Berryboot from 'http://sourceforge.net/projects/berryboot/files/berryboot-20130528.zip/download?use_mirror=jaist.'

Now extract the contents of the .zip file to the SD card, and put it in your Raspberry Pi. This can be done simply under Windows without any special image writer software.

Once you start your Raspberry Pi, it will start an installer that reformats



Fig. 10: Berryboot installation settings



Fig. 11: OS options

the SD card and downloads the operating systems files from the Internet. The first screen that you come across is the welcome screen shown in Fig. 10.

Time zone will be automatically detected if your device is connected to the

Internet. Select the network type as 'Wired' or 'Wi-Fi.' If you see green lines at the top and bottom, select 'Yes' in the video section to disable overscan and press 'OK.'

Now disk selection window will appear. Select where you want to store the operating system files, and press 'Format.' You can install the operating system files on the SD card or on an external USB disk. Be aware that if you choose an external drive, the files of the operating system will be stored there, but you still need to keep the SD card in the Raspberry Pi to boot from.

Once the format is done, you will be provided with the options of operating systems that can be installed as shown in Fig. 11. Select the one you want to install and you can keep adding the others later.

This will download the corresponding files from the Internet and install the selected OS on the SD card/disk. In the menu editor of Berryboot, there are provisions to add, delete and rename the OS.

I installed Media Center software for playing videos shown in Fig. 11 as second option. The difference in performance is very much visible due to overclocking that we did in the first section. ●

The author is working as an assistant manager at Samtel Avionics & Defence Systems

Raspberry Pi
ORDER TODAY,
DELIVERED NEXT DAY!

in element14.com **element14**

Read more stories on Components in
www.electronicshobby.com

TOP COMPONENTS STORIES

- The latest in power converters
- The latest in microcontrollers
- Growth of Indian electronic components industry
- India continues to import significant amount of components every year
- The latest in LEDs, MOSFETs and relays
- Top 12 connector brands available in India

ELECTRONICS B2B
INDUSTRY IS AT A

CLICK OF A BUTTON

Log on to **www.electronicshobby.com** and be in touch with the Electronics B2B Fraternity 24x7