


Now you can see the pulse train and it is fairly easy to decode.



An important thing to note is that the pulse train is inverted. From the SIRC protocol discussed earlier, you will see that there are seven command bits and five address bits with LSBs transmitted first

So from above example:


COMMAND: (LSB)010000(MSB) = 0000010 (binary) = 2 (decimal)

ADDRESS: (LSB)10000(MSB) = 00001 (binary) = 1 (decimal)

Which means key '3' on this remote gives the above command and address.

Pulse trains of some more keys


Standby key



COMMAND: 0010101 = 21(d)

ADDRESS : 00001 = 1(d)


Key '8'



COMMAND: 0000111 = 7(d)

ADDRESS : 00001 = 1(d)

VOL+ key



COMMAND: 0010010 = 18(d)

ADDRESS : 00001 = 1(d)

Things to remember

1. There is no protection circuit used, so take care not to damage the sound card.
2. You cannot get the timing details of the pulse train due to low sampling rate of the sound card and therefore you should know the protocol and its details beforehand.
3. The input given to the sound card is actual pulse train inverted.
4. You won't be able to get sharp edges of the digital pulses due to inbuilt AC coupling of the sound card.
5. Software should be licenced. ●

ELECTRONICS

BAZAAR

INDIA'S FIRST ELECTRONICS SOURCING MAGAZINE

COMPONENTS.

PRODUCTS.

MACHINERY.