

followed by '*' key on your mobile handset, it will change the status of that device and inform the changed device status. '#' key controls the voice_control subroutine and acts like

a mute key.

EFY note. The source code of this project has been included in this month's EFY-CD and is also available on www.efymag.com website.

DEVICE_CONTROL.BAS

```
$large
$regfile = "89c51cc.DAT"
$crystal = 11059200

' DECLARATION OF FUNCTIONS
Declare Sub Keypad
Declare Sub Device_action
Declare Sub Voice_alert
Declare Sub Dtmf_input
Declare Sub Dtmf_rewind

' INPUT FROM DTMF DECODER
Dtmf_a Alias P2.4
Dtmf_b Alias P2.3
Dtmf_c Alias P2.2
Dtmf_d Alias P2.1
Dtmf_ack Alias P2.0

' INPUT FROM KEYPAD
Key_1 Alias P1.0
Key_2 Alias P1.1
Key_3 Alias P1.2
Key_4 Alias P1.3
Key_5 Alias P1.4
Key_6 Alias P1.5
Key_a Alias P1.6
Key_v Alias P1.7

' OUTPUT TO AUDIO SELECTION
Aud_1 Alias P0.0
Aud_2 Alias P0.1
Aud_3 Alias P0.2
Aud_4 Alias P0.3
Aud_5 Alias P0.4
Aud_6 Alias P0.5
Aud_on Alias P0.6
Aud_off Alias P0.7

'Aud_rewind Alias P2.6

'INPUT FROM APR9600
Aud_busy Alias P2.7

'OUTPUT TO DEVICE
Device_1 Alias P3.0
Device_2 Alias P3.1
Device_3 Alias P3.2
Device_4 Alias P3.3
Device_5 Alias P3.4
Device_6 Alias P3.5

'CONTROLLING MODE SELECTION
Device_a Alias P3.6
Device_b Alias P3.7

' DECLARING VARIABLES
Dim Keypad_value As Byte
Dim Device_1_status As Bit
Dim Device_2_status As Bit
Dim Device_3_status As Bit
Dim Device_4_status As Bit
Dim Device_5_status As Bit
Dim Device_6_status As Bit
Dim Common_status As Bit
Dim Voice As Bit
Dim Status_enable As Bit

'INITIALIZING VALUES
Keypad_value = 15

Aud_1 = 1
Aud_2 = 1
Aud_3 = 1
Aud_4 = 1
Aud_5 = 1
Aud_6 = 1
Aud_on = 1
Aud_off = 1

'Aud_rewind = 0

Device_1_status = 0
Device_2_status = 0
Device_3_status = 0
Device_4_status = 0
Device_5_status = 0
Device_6_status = 0

Device_1 = 0
Device_2 = 0
Device_3 = 0
Device_4 = 0
Device_5 = 0
Device_6 = 0

Voice = 1

Do

If Device_a = 0 And Device_b = 0 Then
P2.5 = 0

Elseif Device_a = 0 And Device_b = 1
Then
P2.5 = 1

Call Keypad

'If Keypad_value < 9 Then

Call Device_action

'End If

Elseif Device_a = 1 And Device_b = 0
Then
P2.5 = 1
Call Dtmf_input

'If Keypad_value < 9 Then

Call Device_action

'End If

Elseif Device_a = 1 And Device_b = 1
Then
P2.5 = 1

Call Keypad
Call Dtmf_input

'If Keypad_value < 9 Then
Call Device_action

' End If
End If
```

ATTENTION UPS/Inverter manufacturers

**Precimec introduces
new range of products**


- Sine Wave HUPS Cards 650VA-4KVA
- Sine Wave Line Interactive UPS Cards 1KVA-3KVA
- Quasi Square Wave 3 in one Cards 650VA-1.8KVA
- High Frequency Transformerless HUPS Cards 400VA-1.2KVA
- Priority Solar Charge Controller 12V/24V /36V/48V in Capacities upto 40 Amps
- Solar Steel Light Controller-for Single & Twin CFL
- SMPS Capacity 12V-48V DC upto 20Amps current
- Solar Inverter with RTC and Programmable Logic Control with LCD Display



Precimec Solar charge controller



Precimec Hybrid solar charge controller



Precimec 300W HF inverter



Precimec 1KVA Line interactive sine wave

Precimec Products

No 14/6, Old No 31, Last Building,
2nd Floor, 2nd Lane from SBI,
GNT Compound, J C Road,
Bangalore-02 Ph: +91-80-41226078,
22112908 Fax: +91 80 2211 6908
Mobile: +91-9342813082
Email: info@precimecproducts.com
precimecind@yahoo.co.in
Web: www.precimecproducts.com