



Fig. 6: PSoCRocks application image




Fig. 7: Bubble levels application flowchart

in internal and external peripheral communication.

It supports CapSense component, which supports manual and auto-tuning, which, in turn, is helpful in waterproofing application. The PSoC directly drives LCDs and graphical displays for displaying different menu options.

PSoC Creator IDE tool has a readily-available component block for designing interface and logics like SARADC and PGA for analogue sensors and other analogue inputs. Components like PWM, CLK, MUX and comparator are used for electronic toy applications. Character LCD and segment LCD components

directly (does not require external buffers) drive LCD/graphical LCDs.

IDE tool also has RTC component for real-time measurements. PSoC Creator has an internal system clock and does not require external clock/oscillator circuitry. Other components include timer, buzzer, CapSense, segment LCD, character LCD, graphical LCD and so on.

PSoC Creator also enables users to make use of an entire tools ecosystem with integrated compiler tool chains, RTOS solutions and production programmers. With PSoC Creator and PSoC Designer, users can create and share user-defined custom peripherals using hierarchical schematic designs. They can automatically place and route select components and integrate simple glue logic, normally located in discrete devices.

Pros and cons of using PSoC

A PSoC supports CapSense technology, which replaces mechanical buttons with CapSense based keypad. This reduces failure due to mechanical buttons and provides better product reliability.

PSoC Creator and PSoC Designer support CapSense SmartSense component (CapSense algorithm continuously compensates for system, manufacturing and environmental changes), which auto-tunes the sensitivity of CapSense buttons and sliders. So it does not require manual tuning.

A PSoC supports waterproofing application. It does not detect false triggers due to water droplets and buttons operate in normal conditions in this case. It ensures robust button performance even in noisy operating conditions.

PSoC supports proximity detection using PCB trace, single-wire, ganged-button or single-button implementations. So the front keypad is activated when a user places a hand near the keypad.

TRMS DIGITAL CLAMPMETERS

3% Digit 6000 Count LCD with Backlight

- Auto / Manual Ranging
- 600mV ~ 750V DC
- 600mV ~ 1000V AC TRMS
- 600µA ~ 1000A AC TRMS (1008-TRMS)
- 600µA ~ 1200A DC (1080-TRMS)
- 600µA ~ 1200A AC TRMS (1080-TRMS)
- 600Ω ~ 60MΩ
- 9.999Hz ~ 9.999MHz
- 99.99Hz ~ 20.00MHz
- 0.1% ~ 99.9% Duty Cycle
- -20°C ~ 1000°C (0°F ~ 1832°F)
- K Type Thermocouple (Up to 260°C)
- Jaw Opening 30mm
- Diode Test, Data Hold, Audible Continuity, Low Battery Indicator & Auto Power off

Meco Meters Private Limited

Plot No. EL-60, MIDC Electronic Zone,
TTC Industrial Area, Mahape,
Navi Mumbai - 400710 (INDIA)

Tel : 0091-22-2767 3300 (Board), 2767 3311-16 (Sales)

Fax : 0091-22-27673310, 27673330

Email : sales@mecoinst.com

Web : www.mecoinst.com