

HI-LITE, 810VA

Features

- Noiseless, high-frequency combo system
- Combination of a UPS and an inverter in one unit as it provides pure sine wave from no load to full load
- Microcontroller digital technology
- Weighs only 2.5 kg
- Smart multilevel charging provides good battery health, which results in longer battery life with low battery maintenance
- Auto overload resetting. HI-LITE shuts down automatically if exposed to a load more than its specified limit. In wide range, it keeps on beeping and sensing the load to switch itself on to find the load within its specified limit, eliminating the manual resetting by the user. In narrow range, it permanently shuts itself off if exposed to excessive load and the user has to reset the HI-LITE manually after decreasing the load within its specified limit
- Any battery option. Be it a local ordinary battery, branded/automotive battery, sealed maintenance-free battery or tubular battery, HI-LITE auto adjusts its charging characteristics according to any battery you connect
- No-load shut down
- Configurable charging modes. In areas where power cut is longer than eight hours, high-charging mode should be configured. Normal charging mode, which is set by default, always enhances the battery life. Customer can switch into these modes as and when required
- Soft touch switch. With this easy-to-use switch, all the configurations including on, off, reset and mode changes can be done

Price: ₹ 5990



ment, take into account this surge load (startup load) and not the lower running load. Typically, the startup load is two times the running load. In the case of appliances like air-conditioners, refrigerators and pumps, it could be more than three times the continuous load rating.

Calculating the battery capacity

The battery capacity determines the back-up hours. It is primarily defined in ampere hours (Ah) and selected on the basis of backup requirements of an individual. The more the Ah, the longer the backup. The number of plates

The number of plates and the total battery-plate surface area of the cells determine the length of backup. A 180Ah normal battery has 25 plates, while a 180Ah normal tubular battery has only 13 plates but greater plate area

and the total battery-plate surface area of the cells determine the length of backup. A 180Ah normal battery has 25 plates, while a 180Ah normal tubular battery has only 13 plates but greater plate area.

A standard battery provides three hours of backup time at full load and six hours at half load. You can increase the backup duration by installing a higher-capacity battery or adding extra batteries in parallel.

The battery capacity can be calculated from the following relationship:

Required power (in VA) × Required backup hours (in hours) = Inverter voltage (in volts) × Battery capacity (in ampere hours)

Let's say you want the inverter to provide power back-up for up to three hours. So for an 800VA inverter, the battery capacity can be calculated as under:

$800 \text{ VA} \times 3 \text{ hours} = 12\text{V} \times \text{Battery capacity, or}$

Battery capacity = $(800 \times 3) / 12 = 200$ ampere hours

Thus if you go for an 800VA inverter with 200Ah battery, you can run two tubelights, three fans, one TV and one laptop for up to three hours.

Standard, tubular or SMF?

Battery selection is very important as it's a recurring cost every 2-3 years. An ideal solution for inverters is either a thick-, flat-plate (standard) battery or a tubular battery. Both the thick-plate and tubular batteries need topping up. Of the two, tubular is better because it lasts longer. Flat batteries generally

Other things to look for

- UPS/inverter mode selection switch
- Battery charging selection switch
- Battery selection switch
- No-load shut down. When no load is in use and the mains goes off, the inverter will shut down automatically. It will turn on as soon as any load is applied. This saves power consumption during no-load period
- Compatibility with DG sets
- Easy-to-understand interface
- Wide service network and good after-sales support
- Reliability. Buy from a reputed and closeby dealer. This will save you time and effort during the servicing requirements