

available in TO-18 package. It is a high-speed and highly sensitive silicon npn phototransistor. The device is matched to visible light and infrared radiation. Opto-isolated triac MOC3021 consists of a gallium-arsenide infrared emitting diode, optically coupled to a silicon bilateral switch. Since coin-type CR2032 lithium-manganese dioxide battery has a nominal voltage of 3V (nominal capacity 220mAh), the entire circuit can be powered from it without any difficulty.

Construction and testing

An actual-size PCB layout for optical slave flash trigger is shown in Fig. 3 and its components layout in Fig. 4. After assembling the circuit on the PCB, enclose it in a suitable box.

Interconnection. For interconnection between the assembled slave flash trigger circuit and the slave flashgun, a female hot shoe




Fig. 3: Actual-size PCB layout of optical slave flash trigger




Fig. 4: Components layout for the PCB

is required. All that needs to be done to trigger the flashgun when it is in the hot shoe is to short the two trigger contacts. So just extend the switch output (from SW1 and



Fig. 5: Hot shoe connection for the circuit

SW2) of the circuit to the hot shoe's electrical (trigger) contacts through a built-in/freestanding sync cable as shown in Fig. 5. **EFY**



T.K. Hareendran is founder and promoter of TechNode Protolabz

PHOENIX MECANO

ROSE

Enclosures, accessories & customised solutions
2,500 standard components ...

BOPLA



Phoenix Mecano India Pvt. Ltd.

Registered Office: 408, Urse I Taluka Maval I Talegaon Urse Road Pune - 410 506, India

☎ +91 2114 335151 | +91 20 6674 5101 ✉ info@phoenixmecano.in 🌐 www.phoenixmecano.co.in | www.rose-pw.de | www.bopla.de