

Name : **Giryaasan J R**

Roll no : **7376191EC141**

College name : **Bannari Amman Institute of Technology**

## **HOME AUTOMATION CIRCUIT**

### **CODE:**

```
#include<Servo.h>

const int pingPin = 7;

int servoPin = 8;

Servo servo1;

void setup() {
    // initialize serial communication:
    Serial.begin(9600);
    servo1.attach(servoPin);
    pinMode(2,INPUT);
    pinMode(4,OUTPUT);
    pinMode(11,OUTPUT);
    pinMode(12,OUTPUT);
    pinMode(13,OUTPUT);
    pinMode(A0,INPUT);
    digitalWrite(2,LOW);
    digitalWrite(11,HIGH);
}

void loop() {
    long duration, inches, cm;
    pinMode(pingPin, OUTPUT);
    digitalWrite(pingPin, LOW);
    delayMicroseconds(2);
    digitalWrite(pingPin, HIGH);
    delayMicroseconds(5);
    digitalWrite(pingPin, LOW);
```

```

// The same pin is used to read the signal from the PING))) a HIGH pulse
// whose duration is the time (in microseconds) from the sending of the ping
// to the reception of its echo off of an object.
pinMode(pingPin, INPUT);
duration = pulseIn(pingPin, HIGH);
// convert the time into a distance
inches = microsecondsToInches(duration);
cm = microsecondsToCentimeters(duration);
servo1.write(0);
if(cm < 40)
{
    servo1.write(90);
    delay(2000);
}
else
{
    servo1.write(0);
}
// PIR with LED starts
int pir = digitalRead(2);

if(pir == HIGH)
{
    digitalWrite(4,HIGH);
    delay(1000);
}
else if(pir == LOW)
{
    digitalWrite(4,LOW);
}
//temp with fan
float value=analogRead(A0);

```

```
float temperature=value*0.48;
Serial.println("temperature");
Serial.println(temperature);
if(temperature > 20)
{
    digitalWrite(12,HIGH);
    digitalWrite(13,LOW);
}
else
{
    digitalWrite(12,LOW);
    digitalWrite(13,LOW);
}
}
long microsecondsToInches(long microseconds) {
    return microseconds / 74 / 2;
}
long microsecondsToCentimeters(long microseconds) {
    return microseconds / 29 / 2;
}
```