Name : **Gathiravan G**

Roll no : **7376191EC139**

College name : **Bannari Amman Institute of Technology**

HOME AUTOMATION CIRCUIT

CODE:

```
#include<Servo.h>
const int pingPin = 7;
int servoPin = 8;
Servo servo1;
void setup() {
  // initialize serial communication:
  Serial.begin(9600);
  servo1.attach(servoPin);
  pinMode(2,INPUT);
  pinMode(4,OUTPUT);
  pinMode(11,OUTPUT);
  pinMode(12,OUTPUT);
  pinMode(13,OUTPUT);
  pinMode(A0,INPUT);
  digitalWrite(2,LOW);
  digitalWrite(11,HIGH);
}

void loop() {
  long duration, inches, cm;
  pinMode(pingPin, OUTPUT);
  digitalWrite(pingPin, LOW);
  delayMicroseconds(2);
  digitalWrite(pingPin, HIGH);
  delayMicroseconds(5);
  digitalWrite(pingPin, LOW);
```

```
// The same pin is used to read the signal from the PING))): a HIGH pulse
// whose duration is the time (in microseconds) from the sending of the ping
// to the reception of its echo off of an object.
pinMode(pingPin, INPUT);
duration = pulseIn(pingPin, HIGH);
// convert the time into a distance
inches = microsecondsToInches(duration);
cm = microsecondsToCentimeters(duration);
servo1.write(0);
if(cm < 40)
{
  servo1.write(90);
  delay(2000);
}
else
{
  servo1.write(0);
}
// PIR with LED starts
int pir = digitalRead(2);

if(pir == HIGH)
{
  digitalWrite(4,HIGH);
  delay(1000);
}
else if(pir == LOW)
{
  digitalWrite(4,LOW);
}
//temp with fan
float value=analogRead(A0);
```

```
  float temperature=value*0.48;
  Serial.println("temperature");
  Serial.println(temperature);
  if(temperature > 20)
  {
    digitalWrite(12,HIGH);
    digitalWrite(13,LOW);
  }
  else
  {
    digitalWrite(12,LOW);
    digitalWrite(13,LOW);
  }
}
long microsecondsToInches(long microseconds) {
  return microseconds / 74 / 2;
}
long microsecondsToCentimeters(long microseconds) {
  return microseconds / 29 / 2;
}
```