ASSIGNMENT-4

Date	30 October 2022
Team ID	PNT2022TMID39619
Name	Yokesh J
Student Roll Number	510619104077
Maximum Marks	2 Marks

Problem Statement:

Write code and connections in wokwi for ultrasonic sensor. Whenever distance is less than
100 cm send "alert" to IBM cloud and display in device recent events.

CODE :

```
36    pinMode(trig,OUTPUT);
37    pinMode(echo,INPUT);
38    pinMode(LED, OUTPUT);
39    delay(10);
40    wificonnect();
41    mqttconnect();
42    }
43    void loop()// Recursive Function
44    {
45
46     digitalWrite(trig,LOW);
47      digitalWrite(trig,HIGH);
48      delayMicroseconds(10);
49      digitalWrite(trig,LOW);
50      float dur = pulseIn(echo,HIGH);
51      float dist = (dur * 0.0343)/2;
52      Serial.print ("Distancein cm");
53      Serial.println(dist);
54
55
56      PublishData(dist);
57      delay(1000);
58      if (!client.loop()) {
59        mqttconnect();
60      }
61    }
62
63
64
65    /*.............................retrieving to Cloud.............................*/
66
67    void PublishData(float dist) {
68      mqttconnect();//function call for connecting to ibm
69      /*
70        creating the String in in form Json to update the data to ibm cloud
```

```
70        creating the String in in form Json to update the data to ibm cloud
71      */
72      String object;
73      if (dist <100)
74      {
75        digitalWrite(LED,HIGH);
76        Serial.println("object is near");
77        object = "Near";
78      }
79      else
80      {
81        digitalWrite(LED,LOW);
82        Serial.println("no object found");
83        object = "No";
84      }
85
86      String payload = "{\"distance\":";
87      payload += dist;
88      payload += "," "\"object\":\"";
89      payload += object;
90      payload += "\"}";
91
92
93      Serial.print("Sending payload: ");
94      Serial.println(payload);
95
96
97
98
```

```cpp
      if (client.publish(publishTopic, (char*) payload.c_str())) {
        Serial.println("Publish ok");// if it successfully upload data on the cloud then it will print publish ok in Serial monitor or else it will print publish failed
      } else {
        Serial.println("Publish failed");
      }

  }
  void mqttconnect() {
    if (!client.connected()) {
      Serial.print("Reconnecting client to ");
      Serial.println(server);
      while (!!client.connect(clientId, authMethod, token)) {
        Serial.print(".");
        delay(500);
      }

      initManagedDevice();
      Serial.println();
    }
  }
  void wificonnect() //function definition for wificonnect
  {
    Serial.println();
    Serial.print("Connecting to ");

    WiFi.begin("Wokwi-GUEST", "", 6);//passing the wifi credentials to establish the connection
    while (WiFi.status() != WL_CONNECTED) {
      delay(500);
      Serial.print(".");
    }
    Serial.println("");
    Serial.println("WiFi connected");
    Serial.println("IP address: ");
    Serial.println(WiFi.localIP());
```

```
123
124      WiFi.begin("Wokwi-GUEST", "", 6);//passing the wifi credentials to establish the connection
125      while (WiFi.status() != WL_CONNECTED) {
126        delay(500);
127        Serial.print(".");
128      }
129      Serial.println("");
130      Serial.println("WiFi connected");
131      Serial.println("IP address: ");
132      Serial.println(WiFi.localIP());
133    }
134
135    void initManagedDevice() {
136      if (client.subscribe(subscribetopic)) {
137        Serial.println((subscribetopic));
138        Serial.println("subscribe to cmd OK");
139      } else {
140        Serial.println("subscribe to cmd FAILED");
141      }
142    }
143
144    void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
145    {
146
147      Serial.print("callback invoked for topic: ");
148      Serial.println(subscribetopic);
149      for (int i = 0; i < payloadLength; i++) {
150        //Serial.print((char)payload[i]);
151        data3 += (char)payload[i];
152      }
153
154    //    Serial.println("data: "+ data3);
155    //    if(data3=="Near")
156    //    {
157    // Serial.println(data3);
```

```
142    }
143
144    void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
145    {
146
147      Serial.print("callback invoked for topic: ");
148      Serial.println(subscribetopic);
149      for (int i = 0; i < payloadLength; i++) {
150        //Serial.print((char)payload[i]);
151        data3 += (char)payload[i];
152      }
153
154    //    Serial.println("data: "+ data3);
155    //    if(data3--"Near")
156    //    {
157    // Serial.println(data3);
158    // digitalWrite(LED,HIGH);
159
160    //    }
161
162    //    else
163    //    {
164    // Serial.println(data3);
165    // digitalWrite(LED,LOW);
166
167    //    }
168    data3="";
169
170
171    }
```

OUTPUT:

Data send to the IBM cloud device when the object is far

when object is near to the ultrasonic sensor

object is near
Sending payload: {"distance":97.82,"object":"Near"}
Publish ok
Distancein cm97.82
object is near
Sending payload: {"distance":97.82,"object":"Near"}
Publish ok

Data sent to the IBM Cloud Device when the object is near