ASSIGNMENT 4

Date	6 nov 2022
Team ID	PNT2022TMID26079
Project Name	Gas Leakage Monitoring and Alerting System
Name	SAIRAJ M

Write code and connections in wokwi for ultrasonic sensor. Whenever distance is less than 100 cms send alert to ibm cloud and display in device recent events. Upload document with wokwi share link and images of ibmcloud.

CODE:

```
#include <WiFi.h>
#include <PubSubClient.h>
WiFiClient wifiClient;
String data3;
#define ORG "9djwz2"//IBM ORGANITION ID
#define DEVICE_TYPE "sanjay"//Device type mentioned in ibm watson IOT Platform
#define DEVICE_ID "1234567"//Device ID mentioned in ibm watson IOT Platform
#define TOKEN "12345678"
#define speed 0.034
#define led 14
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/event_1/fmt/json";
char topic[] = "iot-2/cmd/led/fmt/String";
char authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
PubSubClient client(server, 1883, wifiClient);
```

```
const int trigpin=5;
const int echopin=18;
String command;
String data="";

long duration;
float dist;



void setup()
{
  Serial.begin(115200);
  pinMode(led, OUTPUT);
  pinMode(trigpin, OUTPUT);
  pinMode(echopin, INPUT);
  wifiConnect();
  mqttConnect();
}

void loop() {
  bool isNearby = dist < 100;
  digitalWrite(led, isNearby);

  publishData();
  delay(500);

  if (!client.loop()) {
    mqttConnect();
  }
}

void wifiConnect() {
  Serial.print("Connecting to "); Serial.print("Wifi");
  WiFi.begin("Wokwi-GUEST", "", 6);
  while (WiFi.status() != WL_CONNECTED) {
    delay(500);
    Serial.print(".");
  }
  Serial.print("WiFi connected, IP address: "); Serial.println(WiFi.localIP());
}
```

```
void mqttConnect() {
  if (!client.connected()) {
    Serial.print("Reconnecting MQTT client to "); Serial.println(server);
    while (!client.connect(clientId, authMethod, token)) {
      Serial.print(".");
      delay(500);
    }
    initManagedDevice();
    Serial.println();
  }
}

void initManagedDevice() {
  if (client.subscribe(topic)) {
    // Serial.println(client.subscribe(topic));
    Serial.println("IBM subscribe to cmd OK");
  } else {
    Serial.println("subscribe to cmd FAILED");
  }
}
void publishData()
{
  digitalWrite(trigpin,LOW);
  digitalWrite(trigpin,HIGH);
  delayMicroseconds(10);
  digitalWrite(trigpin,LOW);
  duration=pulseIn(echopin,HIGH);
  dist=duration*speed/2;
  if(dist<100){
    String payload = "{\"Alert Distance\":";
    payload += dist;
    payload += "}";

    Serial.print("\n");
    Serial.print("Sending payload: ");
    Serial.println(payload);
    if (client.publish(publishTopic, (char*) payload.c_str())) {
      Serial.println("Publish OK");
    }
```

```
}
  if(dist>100){
  String payload = "{\"Distance\":";
  payload += dist;
  payload += "}";

  Serial.print("\n");
  Serial.print("Sending payload: ");
  Serial.println(payload);
   if(client.publish(publishTopic, (char*) payload.c_str())) {
    Serial.println("Publish OK");
  }else {
    Serial.println("Publish FAILED");
  }

}


}
```

Wokwi link:

https://wokwi.com/projects/347956062652990036

output:



WOKWI:


ESP32
HC-SR04
Vcc
Trig
Echo
Gnd
ding payload: {"Distance":399.96}
lish OK

IBM CLOUD:


Browse
Action
Device Types
Interfaces
Add Device
1234567
Connected
sanjay
Device
Nov 10, 2022 9:14 PM
Identity
Device Information
Recent Events
State
Logs
The recent events listed show the live stream of data that is coming and going from this device.
Event
Value
Format
Last Received
event_1
{"Distance":399.98}
json
a few seconds ago
event_1
{"Distance":399.96}
json
a few seconds ago
event_1
{"Distance":399.96}
json
a few seconds ago
event_1
{"Distance":399.94}
json
a few seconds ago
event_1
{"Distance":399.96}
1 Simulation running