

PROJECT DEVELOPMENT PHASE

DELIVERY OF SPRINT-2

Date	7 November 2022
Team ID	PNT2022TMID09807
Project Name	Industry Specific Intelligence Fire Management System

```
#include <WiFi.h>
```

```
#include <Wire.h>
```

```
#include <SPI.h>
```

```
#include "ThingSpeak.h" #include  
<WiFiClient.h>
```

```
unsigned long myChannelNumber = 2; const char * myWriteAPIKey  
= "25V40ZAPI6KIZFGY";
```

```
int LED_PIN = 32; // the current reading from the input pin
```

```
int BUZZER_PIN= 12; const int
```

```
mq2 = 4;
```

```
int value = 0;
```

```
//Flame int flame_sensor_pin = 10 ;// initializing pin 10 as the sensor digital  
output pin int flame_pin = HIGH ; // current state of sensor
```

```
char ssid[] = "Dhinesh"; char
```

```
pass[] = "Dhineshkumar";
```

```
WiFiClient client;
```

```
#define PIN_LM35 39
```

```
#define ADC_VREF_mV 3300.0
```

```
#define ADC_RESOLUTION 4096.0
```

```
#define RELAY_PIN 17
```

```
#define RELAY_PIN1 27
```

```
void setup()
```

```

{
  Serial.begin(115200);
pinMode(RELAY_PIN, OUTPUT);  pinMode(RELAY_PIN1, OUTPUT);
  Serial.print("Connecting to ");
Serial.println(ssid);
WiFi.begin(ssid, pass);  int
wifi_ctr = 0;
  while (WiFi.status() != WL_CONNECTED)
  {
    delay(1000);
Serial.print(".");
  }
  Serial.println("WiFi connected");
ThingSpeak.begin(client); pinMode(LED_PIN, OUTPUT); pinMode(mq2, INPUT);
pinMode ( flame_sensor_pin , INPUT ); // declaring sensor pin as input pin for Arduino
pinMode(BUZZER_PIN, OUTPUT);
}

```

```

void temperature()
{
  int adcVal = analogRead(PIN_LM35);  float milliVolt = adcVal *
(ADC_VREF_mV / ADC_RESOLUTION); float tempC = milliVolt /
10; Serial.print("Temperature: ");
  Serial.print(tempC);
Serial.print("°C");  if(tempC
> 60)
  {
    Serial.println("Alert");
    digitalWrite(BUZZER_PIN, HIGH); // turn on
  } else
  {
    digitalWrite(BUZZER_PIN, LOW); // turn on
  }
  int x = ThingSpeak.writeField(myChannelNumber,1, tempC, myWriteAPIKey);  }

```

```

void GasSensors()
{

```

```

//mq2

int gassensorAnalogmq2 = analogRead(mq2);
Serial.print("mq2 Gas Sensor: ");
Serial.print(gassensorAnalogmq2);
Serial.print("\t");
Serial.print("\t");
Serial.print("\t");

if (gassensorAnalogmq2 > 1500)
{
    Serial.println("mq2Gas");    Serial.println("Alert");
    digitalWrite(RELAY_PIN1, HIGH); // turn on fan 10 seconds    delay(100);
} else
{
    Serial.println("No mq2Gas");    digitalWrite(RELAY_PIN1,
LOW); // turn off fan 10 seconds    delay(100);

}

int a = ThingSpeak.writeField(myChannelNumber,4, gassensorAnalogmq2,
myWriteAPIKey);

}

void flamesensor()
{ flame_pin = digitalRead ( flame_sensor_pin ) ; // reading from the sensor
if (flame_pin == LOW ) // applying condition
{
    Serial.println ( " ALERT: FLAME DETECTED" ) ;    digitalWrite (BUZZER_PIN,
HIGH ) ;// if state is high, then turn high the BUZZER } else
{
    Serial.println ( " NO FLAME DETECTED " ) ;
    digitalWrite (BUZZER_PIN , LOW ) ; // otherwise turn it low
} int value = digitalRead(flame_sensor_pin); // read the analog value from sensor

    if      (value      ==LOW)      {
Serial.print("FLAME");    digitalWrite(RELAY_PIN,
HIGH);

```

```
    } else {  
        Serial.print("NO FLAME");    digitalWrite(RELAY_PIN,  
LOW);  
    }  
  
} void loop() { temperature();  
GasSensors();  flamesensor();  
}
```