

Assignment -1
Thinkercad Programming

| | |
|---------------------|-------------------------|
| Assignment Date | 19 September 2022 |
| Student Name | Mr. A. Mogamath Jaleell |
| Student Roll Number | 610819106035 |
| Maximum Marks | 2 Marks |

Question-1:

Assignment: Make a smart home with 2-3 sensors, LED, Buzzer. in single code and connections.
submit it in the platform, any doubts ask in chat with mentor option

Solution:

```
#include <SPI.h>
#include <Wire.h>

#include <IRremote.h>

const int relay_1 = 12;
const int relay_2 = 11;
const int relay_3 = 10;
const int relay_4 = 9;

const int mswitch_1 = 8;
const int mswitch_2 = 7;
const int mswitch_3 = 6;
const int mswitch_4 = 5;

int RECV_PIN = 3;

IRrecv irrecv(RECV_PIN);
decode_results results;

int toggleState_1 = 0;
int toggleState_2 = 0;
int toggleState_3 = 0;
int toggleState_4 = 0;

void setup() {

  Serial.begin(9600);
  irrecv.enableIRIn();

  pinMode(relay_1, OUTPUT);
```

```

pinMode(relay_2, OUTPUT);
pinMode(relay_3, OUTPUT);
pinMode(relay_4, OUTPUT);

pinMode(mswitch_1, INPUT_PULLUP);
pinMode(mswitch_2, INPUT_PULLUP);
pinMode(mswitch_3, INPUT_PULLUP);
pinMode(mswitch_4, INPUT_PULLUP);
}

void relayOnOff(int relay){

switch(relay){
case 1:
    if(toggleState_1 == 0){
        digitalWrite(relay_1, HIGH); // turn on relay 1
        toggleState_1 = 1;
    }
    else{
        digitalWrite(relay_1, LOW); // turn off relay 1
        toggleState_1 = 0;
    }
    delay(100);
break;
case 2:
    if(toggleState_2 == 0){
        digitalWrite(relay_2, HIGH); // turn on relay 2
        toggleState_2 = 1;
    }
    else{
        digitalWrite(relay_2, LOW); // turn off relay 2
        toggleState_2 = 0;
    }
    delay(100);
break;
case 3:
    if(toggleState_3 == 0){
        digitalWrite(relay_3, HIGH); // turn on relay 3
        toggleState_3 = 1;
    }else{
        digitalWrite(relay_3, LOW); // turn off relay 3
        toggleState_3 = 0;
    }
    delay(100);
break;
case 4:

```

```

        if(toggleState_4 == 0){
            digitalWrite(relay_4, HIGH); // turn on relay 4
            toggleState_4 = 1;
        }
        else{
            digitalWrite(relay_4, LOW); // turn off relay 4
            toggleState_4 = 0;
        }
        delay(100);
        break;

        default : break;
    }

}

```

```

void loop() {

    if (digitalRead(mswitch_1) == LOW){
        delay(200);
        relayOnOff(1);
    }
    else if (digitalRead(mswitch_2) == LOW){
        delay(200);
        relayOnOff(2);
    }
    else if (digitalRead(mswitch_3) == LOW){
        delay(200);
        relayOnOff(3);
    }
    else if (digitalRead(mswitch_4) == LOW){
        delay(200);
        relayOnOff(4);
    }

    if (irrecv.decode(&results)) {
        switch(results.value){
            case 0xFD08F7:
                relayOnOff(1);
                break;
            case 0xFD8877:
                relayOnOff(2);
                break;
            case 0xFD48B7:
                relayOnOff(3);

```

```

        break;
    case 0xFD28D7:
        relayOnOff(4);
        break;
    default : break;
    }
    irrecv.resume();
}
}

```

