ASSIGNMENT4

DATE	01 November 2022
Team ID	PNT2022TMID 00982

Ultrasonic sensor simulation in Wokwi

Question:

Writeacodeandconnectionsinwokwifortheultrasonicsensor.Whenteverthedistanceislessthan100cmssend an“Alert” to IBM cloudanddisplayinthedevicerecentevents.

Code:

```
#include
<WiFi.h>#include<PubSubC
lient.h>
voidcallback(char*subscribetopic,byte*payload,unsignedintpayloadLe
ngth);
//-------credentialsofIBMAccounts------
#defineORG"kotoq5"//IBMORGANITIONID
#defineDEVICE_TYPE"ESP32"//DevicetypementionedinibmwatsonIOTPlatform#define
DEVICE_ID "12345"//Device ID mentioned in ibmwatson IOT
Platform#defineTOKEN"12345678"//Token
Stringdata3;
charserver[]=ORG".messaging.internetofthings.ibmcloud.com";charpub
lishTopic[]="iot-2/evt/Data/fmt/json";
charsubscribetopic[]="iot-
2/cmd/test/fmt/String";charauthMethod[]="use-token-
auth";
```

```
chartoken[]=TOKEN;
charclientId[]="d:"ORG":"DEVICE_TYPE":"DEVICE_ID;
WiFiClientwifiClient;
PubSubClientclient(server,1883,callback,wifiClient);constin
t trigPin =5;
const int echoPin =
18;#defineSOUND_SPEED0.0
34longduration;
floatdistance;
voidsetup(){
Serial.begin(115200);pinMod
e(trigPin,OUTPUT);pinMode(e
choPin,
INPUT);wificonnect();mqttco
nnect();
}
voidloop()
{
digitalWrite(trigPin,
LOW);delayMicroseconds(2);digitalWr
ite(trigPin,
HIGH);delayMicroseconds(10);digital
Write(trigPin,LOW);duration =
pulseIn(echoPin,
HIGH);distance=duration*SOUND_SPEED
/2;Serial.print("Distance (cm):
");Serial.println(distance);if(dist
ance<100)
{
Serial.println("ALERT!!");de
lay(1000);
```

```
PublishData(distance);
delay(1000);
if(!client.loop()){mq
ttconnect();
}
}
delay(1000);
}
voidPublishData(floatdist){mqttconnect(
);
Stringpayload="{\"Distance\":";payload+
=dist;
payload+=",\"ALERT!!\":""\"Distancelessthan100cms\"";payload+=
"}";
Serial.print("Sendingpayload:");
Serial.println(payload);

if(client.publish(publishTopic,(char*)payload.c_str())){
Serial.println("Publishok");
}else{
Serial.println("Publishfailed");
}
}
voidmqttconnect(){
if (!client.connected())
{Serial.print("Reconnectingclientto");S
erial.println(server);
while(!!!client.connect(clientId,authMethod,token)){
Serial.print(".");
delay(500);
}
```

```
initManagedDevice();
Serial.println();
}
}
voidwificonnect()
{
Serial.println(); Serial.print("Connecting to
");WiFi.begin("Wokwi-GUEST", "", 6); while (WiFi.status()
!=WL_CONNECTED){delay(500);
Serial.print(".");
}
Serial.println("");
Serial.println("WiFiconnected");
Serial.println("IP address:
");Serial.println(WiFi.localIP());
}
voidinitManagedDevice(){
if (client.subscribe(subscribetopic))
{Serial.println((subscribetopic)); Serial.println("subscribe
tocmdOK");
}else{
Serial.println("subscribetocmdFAILED");
}
}
voidcallback(char*subscribetopic,byte*payload,unsignedintpayloadLength)
{
Serial.print("callbackinvokedfortopic:");
Serial.println(subscribetopic);
for(inti=0;i<payloadLength;i++){
```

```
//Serial.print((char)payload[i]);
data3+=(char)payload[i];
}
Serial.println("data:"+data3);data3="";
}
```

Diagram.json:

```
{
  "version":1,
  "author":
  "sweetysharon","editor":
  "wokwi","parts":[
    {"type":"wokwi-esp32-devkit-v1","id":"esp","top":-4.67,"left":-114.67,"attrs":{}},
    {"type":"wokwi-hc-sr04","id":"ultrasonic1","top":15.96,"left":89.17,"attrs":{}}
  ],
  "connections":[
    ["esp:TX0","$serialMonitor:RX","",[]],
    ["esp:RX0","$serialMonitor:TX","",[]],[
      "esp:VIN","ultraso
      nic1:VCC","red",
      ["h-37.16","v-178.79","h200","v173.33","h100.67"]
    ],
    ["esp:GND.1","ultrasonic1:GND","black",["h39.87","v44.04","h170"]],
    ["esp:D5","ultrasonic1:TRIG","green",["h54.54","v85.07","h130.67"]],
    ["esp:D18","ultrasonic1:ECHO","green",["h77.87","v80.01","h110"]]
```

```
  ]
}
```

CircuitDiagram:



Output:

Wokwioutput:

```
Connecting to ....
WiFi connected
IP address:
10.10.0.2
Reconnecting client to ytluse.messaging.internetofthings.ibmcloud.com
iot-2/cmd/test/fmt/String
subscribe to cmd OK

Distance (cm): 399.92
Distance (cm): 399.96
Distance (cm): 399.94
Distance (cm): 399.98
Distance (cm): 399.94
Distance (cm): 399.92
Distance (cm): 399.94
```

IBMcloudoutput: