**Assignment -4**

Python Programming

| | |
|---|---|
| Assignment Date | 28 October 2022 |
| Student Name | V.L.CHAKRADHAR |
| Student Roll Number | 111719106174 |
| Maximum Marks | 2 Marks |

**Question-1:**

Write code and connections in wokwi for ultrasonic sensor.
Whenever distance is less than 100 cms send "alert" to ibm cloud and display in device recent events.
Upload document with wokwi share link and images of ibm cloud.

**Solution:**


wokwi.com/projects/346566226034557523
WOKWI
SAVE
SHARE
Docs
sketch.ino
diagram.json
libraries.txt
Library Manager
#include<WiFi.h>//library for wifi
#include<PubSubClient.h>//library for MQTT
void callback(char* subscribetopic, byte* payload,unsigned int payloadlength);
//-------------credentials of IBM Account------
#define ORG "izyy6o"// IBM ORGANIZATION ID
#define DEVICE_TYPE "iotdeviceproject"//DEVICE TYPE MENTIONED IN IOT WATSON PLATFORM
#define DEVICE_ID "229714"//DEVICE ID MENTIONED IN IOT WATSON PLATEFORM
#define TOKEN "24681012"//Token
String data3;
float dist;
//-----------customize the above value-------
char server[]=ORG ".messaging.internetofthings.ibmcloud.com";//server name
char publishtopic[]="ultrasonic/evt/Data/fmt/json";/*topic name and type of event perform
and format in which data to be send*/
char subscribetopic[]="ultrasonic/cmd/test/fmt/String";/*cmd REPRESENT Command tope and
COMMAND IS TEST OF FORMAT STRING*/
char authMethod[]="use-token-auth";//authentication method
char token[]=TOKEN;
char clientId[]="d:" ORG ":" DEVICE_TYPE":" DEVICE_ID;//CLIENT ID
//-----------------------------------
WiFiClient wifiClient;// creating an instance for wificlient
PubSubClient client(server, 1883 , callback , wifiClient);/*calling the predefined client id
by passing parameter like server id,portand wificredential*/
int LED =4;
int trig =5;
Int echo=18;
void setup()
{
Serial.begin(115200);
pinMode(trig,OUTPUT);
Co
nn
ec
ti
ng
to


wokwi.com/projects/346566226034557523
WOKWI
SAVE
SHARE
Docs
sketch.ino
diagram.json
libraries.txt
Library Manager
Simu
Serial.println("no object Is near");
object="Near";
}
else
{
digitalWrite(LED,LOW);
Serial.println("no object found");
object="No";
}
String payload="{\"distance\":";
payload +=dist;
payload +="," "\"object\":\"";
payload += object;
payload += "\"}";
Serial.print("Sending payload: ");
Serial.println(payload);
if(client.publish(publishtopic, (char*) payload.c_str())){
Serial.println("Publish ok");/* If its sucessfully upload data on the cloud then it will print
publish ok in serial monitor or else it will print publish failed*/
} else{
Serial.println("Publish failed");
}
}
void mqttconnect(){
if(!client.connected()){
Serial.print("Reconnecting client to ");
Serial.println(server);
while(!!!client.connect(clientId,authMethod, token)){
Serial.print(".");
delay(500);
Co
nn
ec
ti
ng
to


wokwi.com/projects/346566226034557523
WOKWI
SAVE
SHARE
Docs
sketch.ino
diagram.json
libraries.txt
Library Manager
Simu
}
initManagedDevice();
Serial.println();
}
}
void wificonnect()//function defenition for wificonnect
{
Serial.println();
Serial.print("Connecting to ");
WiFi.begin("Wokwi-GUEST", "",6);//PASSING THE WIFI CREDIDENTIALS TO ESTABLISH CONNECTION
while (WiFi.status() !=WL_CONNECTED){
delay(500);
Serial.print(".");
}
Serial.println("");
Serial.println("WiFi connected");
Serial.println("IP address");
Serial.println(WiFi.localIP());
}
void initManagedDevice(){
if(client.subscribe(subscribetopic)){
Serial.println((subscribetopic));
Serial.println("subscribe to cmd OK");
}else{
Serial.println("subscribe to cmd failed");
}
}
void callback(char* subscribetopic,byte*payload,unsigned int payloadLength)
{
Serial.print("callback invoked for topic: ");
Serial.println(subscribetopic);
Co
nn
ec
ti
ng
to




OUTPUT:

DATA IS SENT TO IBM CLOUD WHEN NO OBJECT IS DETECTED



When no object is detected




When object is detected in ultrasonic detector