

## PROJECT DEVELOPMENT PHASE

### DELIVERY OF SPRINT-4

Date	13 November 2022
Team ID	PNT2022TMID09975
Project Name	Industry Specific Intelligence Fire Management System

```
#include
<WiFi.h>
#include
<Wire.h>
#include <SPI.h>
#include "ThingSpeak.h" #include
<WiFiClient.h>

unsigned long myChannelNumber = 2; const char * myWriteAPIKey
= "25V40ZAPI6KIZFGY";
int LED_PIN = 32; // the current reading from the input
pinint BUZZER_PIN= 12; const int mq2
= 4; int
value = 0;

//Flame int flame_sensor_pin = 10 ;// initializing pin 10 as the sensor digital
outputpin int flame_pin = HIGH ;// current state of sensor

char ssid[] = "Rathi"; char pass[]
= "Rathidevi";
WiFiClien
tclient;
#define PIN_LM35 39
#define ADC_VREF_mV 3300.0
#define ADC_RESOLUTION 4096.0
#define RELAY_PIN 17
#define RELAY_PIN1 27

void setup()
{
Serial.begin(115200);
```

```

pinMode(RELAY_PIN, OUTPUT); pinMode(RELAY_PIN1, OUTPUT);
  Serial.print("Connecting to ");
  Serial.println(ssid);
  WiFi.begin(ssid, pass); int wifi_ctr
= 0;
  while (WiFi.status() != WL_CONNECTED)
  {
    delay(1000);
    Serial.print(".");
  }
  Serial.println("WiFi connected");
  ThingSpeak.begin(client); pinMode(LED_PIN, OUTPUT); pinMode(mq2,
INPUT); pinMode ( flame_sensor_pin , INPUT ); // declaring sensor pin as input
pin for Arduino pinMode(BUZZER_PIN, OUTPUT);
}

```

```

void temperature()
{
  int adcVal = analogRead(PIN_LM35); float milliVolt = adcVal *
(ADC_VREF_mV / ADC_RESOLUTION); float tempC =
milliVolt /10; Serial.print("Temperature: ");
  Serial.print(tempC);
  Serial.print("'°C");
      if(temp
C
> 60)
  {
    Serial.println("Alert");
    digitalWrite(BUZZER_PIN, HIGH); // turn
on
  } else
  {
    digitalWrite(BUZZER_PIN, LOW); // turn on
  }
  int x = ThingSpeak.writeField(myChannelNumber,1, tempC, myWriteAPIKey);}

```

```

void GasSensors()
{
  //mq2

  int gassensorAnalogmq2 = analogRead(mq2);

```

```

Serial.print("mq2 Gas Sensor: ");
Serial.print(gassensorAnalogmq2);
Serial.print("\t");
Serial.print("\t");
Serial.print("\t");

if (gassensorAnalogmq2 > 1500)
{
    Serial.println("mq2Gas"); Serial.println("Alert");
digitalWrite(RELAY_PIN1, HIGH); // turn on fan 10 seconds
    delay(100);
} else
{
    Serial.println("No mq2Gas");
        digitalWrite(RELAY_PIN
1,LOW); // turn off fan 10 seconds delay(100);

}

int a = ThingSpeak.writeField(myChannelNumber,4, gassensorAnalogmq2,
myWriteAPIKey);

}

void flamesensor()
{ flame_pin = digitalRead ( flame_sensor_pin ) ; // reading from the sensor if
(flame_pin == LOW ) // applying condition
{
Serial.println ( " ALERT: FLAME IS DETECTED" ) ;    digitalWrite
(BUZZER_PIN,HIGH ) ;// if state is high, then turn high the BUZZER } else
{
Serial.println ( " NO FLAME DETECTED " ) ;
digitalWrite (BUZZER_PIN , LOW ) ; // otherwise turn it low
} int value = digitalRead(flame_sensor_pin); // read the analog value from sensor

    if (value ==LOW) {
        Serial.print("FLAME
");digitalWrite(RELAY_PIN, HIGH);
    } else {
        Serial.print("NO FLAME");
            digitalWrite(RELAY_PI
N,LOW);
    }
}

```

```
} void loop() {  
temperature(); GasSensors();    flamesensor();  
}
```