PROJECT DEVELOPMENT PHASE

DELIVERY OF SPRINT-1

Date	28 October 2022
Team ID	PNT2022TMID09975
Project Name	Industry Specific Intelligent Fire Management System

```
#include <WiFi.h>
#include <Wire.h>
#include <SPI.h>
#include "ThingSpeak.h"
#include <WiFiClient.h>

unsigned long myChannelNumber = 2;
const char * myWriteAPIKey = "25V40ZAPI6KIZFGY";
int LED_PIN = 32; // the current reading from the input pinint
BUZZER_PIN= 12;
const int mq2 = 4;
int value = 0;

//Flame
int flame_sensor_pin = 10 ;// initializing pin 10 as the sensor digital outputpin
int flame_pin = HIGH ; // current state of sensor

char ssid[] = "Jenito";
char pass[] = "Jose Jenito";
WiFiClient client;
#define PIN_LM35 39
#define ADC_VREF_mV 3300.0
#define ADC_RESOLUTION 4096.0


void setup()
{
   Serial.begin(115200);
Serial.print("Connecting to ");
Serial.println(ssid); WiFi.begin(ssid,
pass);
  int wifi_ctr = 0;
  while (WiFi.status() != WL_CONNECTED)
  {
  delay(1000);
  Serial.print(".");
  }
```

```
  Serial.println("WiFi connected");


  ThingSpeak.begin(client);
pinMode(LED_PIN, OUTPUT);
pinMode(mq2, INPUT); pinMode (
flame_sensor_pin , INPUT ); // declaring
sensor pin as input pin for Arduino
pinMode(BUZZER_PIN, OUTPUT);
}


void temperature()
{
  int adcVal = analogRead(PIN_LM35);
  float milliVolt = adcVal * (ADC_VREF_mV /
ADC_RESOLUTION); float tempC = milliVolt / 10;
Serial.print("Temperature: "); Serial.print(tempC);
Serial.print("°C");
if(tempC > 60)
  {
    Serial.println("Alert");
    digitalWrite(BUZZER_PIN, HIGH); // turn on
  }
else
  {
     digitalWrite(BUZZER_PIN, LOW); // turn on
  }
   int x = ThingSpeak.writeField(myChannelNumber,1, tempC, myWriteAPIKey);

}


void GasSensors()
{
  //mq2

  int gassensorAnalogmq2 = analogRead(mq2);
  Serial.print("mq2 Gas Sensor: ");
  Serial.print(gassensorAnalogmq2);
  Serial.print("\t");
  Serial.print("\t");
  Serial.print("\t");

  if (gassensorAnalogmq2 > 1500)
  {
    Serial.println("mq2Gas");
    Serial.println("Alert");
  }
else
```

```
  {
    Serial.println("No mq2Gas");
  }

  int a = ThingSpeak.writeField(myChannelNumber,4, gassensorAnalogmq2,
myWriteAPIKey); }

void  flamesensor()
{
flame_pin = digitalRead ( flame_sensor_pin ) ; // reading from thesensor if
(flame_pin == LOW ) // applying condition
{
Serial.println ( " ALERT: FLAME DETECTED" ) ;
digitalWrite ( buz_pin , HIGH ) ;// if state is high, then turn high theBUZZER }

else
{
Serial.println ( " NO FLAME DETECTED " ) ; digitalWrite
(buz_pin , LOW ) ; // otherwise turn it low
}
}

void loop() { temperature(
)
;
GasSensors()
;
flamesensor()
;
```