ASSIGNMENT 4

Date	05 NOV 2022
Name	4 MARKS
Team ID	PNT2022TMID34358
Project Name	Smart Waste Management For Metropolitan Cities

QUESTION:

Write code and connections in wokwi for ultrasonic sensor.

Whenever distance is less than 100 cms send "alert" to ibm cloud and display in device recent events.

Upload document with wokwi share link and images of ibm cloud

CODE:

```
#include <WiFi.h>
#include <PubSubClient.h>
WiFiClient;

#define ORG "nhpwjc"
#define DEVICE_TYPE "NodeMCU"
#define DEVICE_ID "USE YOUR ID"
#define TOKEN "USE YOUR TOKEN"
#define speed 0.034

char server[] = ORG
".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-
2/evt/Data/fmt/json"; char topic[] = "iot-
2/cmd/home/fmt/String"; char authMethod[] =
"use-token- auth"; char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE
":" DEVICE_ID; PubSubClient client(server,
1883, wifiClient); void publishData();
 const int trigpin=5; const int echopin=18;
String command;
String data=""; long
duration; float dist;

 void
setup()
{
  Serial.begin(115200); pinMode(trigpin,
  OUTPUT);
```

```
 pinMode(echopin, INPUT); wifiConnect();
 mqttConnect();
}      void      loop()      {

  publishData(); delay(500);


  if (!client.loop()) {
mqttConnect(); } }

void wifiConnect() {
 Serial.print("Connecting to "); Serial.print("Wifi");
 WiFi.begin("Wokwi-GUEST", "", 6); while (WiFi.status() !=
 WL_CONNECTED) { delay(500);
   Serial.print(".");
 }
 Serial.print("WiFi connected, IP address: "); Serial.println(WiFi.localIP());
}

void mqttConnect() { if
 (!client.connected()) {
   Serial.print("Reconnecting MQTT client to "); Serial.println(server); while
   (!client.connect(clientId,   authMethod,   token))   {   Serial.print(".");
   delay(500);
   } initManagedDevice();
 Serial.println(); } }

void initManagedDevice() { if
 (client.subscribe(topic)) {
   // Serial.println(client.subscribe(topic)); Serial.println("subscribe to cmd
   OK");
 } else {
    Serial.println("subscribe to cmd FAILED"); } }
void publishData()
{ digitalWrite(trigpin,LOW);
  digitalWrite(trigpin,HIGH);
```

```
 delayMicroseconds(10);
 digitalWrite(trigpin,LOW);
 duration=pulseIn(echopin,HIGH);
 dist=duration*speed/2;
 if(dist<100){
   String payload = "{\"Alert distance\":";
   payload += dist; payload += "}";
   Serial.print("\n");
   Serial.print("Sending payload: ");
   Serial.println(payload);
   if (client.publish(publishTopic, (char*) payload.c_str())) {
     Serial.println("Publish OK");
   } else {
```

```
      Serial.println("Publish FAILED");
    }
  }
}
```

CONNECTIONS:



OUTPUT:




```
Sending payload: {"Alert distance":93.99}
Publish OK

Sending payload: {"Alert distance":93.96}
Publish OK

Sending payload: {"Alert distance":93.96}
Publish OK

Sending payload: {"Alert distance":93.96}
Publish OK

Sending payload: {"Alert distance":93.96}
Publish OK

Sending payload: {"Alert distance":93.96}
Publish OK
```


Browse
Action
Device Types
Interfaces
Add Device
This table shows a summary of all devices that have been added. It can be filtered, organized, and searched on using different criteria. To get started, you can add devices by using the Add Device button, or by using API.
Search by Device ID
Device Simulator
Device ID
Status
Device Type
Class ID
Date Added
Descriptive Location
Added By
Device Class
Firmware Version
12345
Connected
NodeMCU
Device
Oct 17, 2022 2:36 PM
111719106009@smartinternz.com
Identity
Device Information
Recent Events
State
Logs
The recent events listed show the live stream of data that is coming and going from this device.
Event
Value
Format
Last Received
Data
{"Alert distance":93.96}
json
a few seconds ago
Data
{"Alert distance":93.96}
json
a few seconds ago
Data
{"Alert distance":93.96}
json
a few seconds ago
Data
{"Alert distance":93.96}
json
a few seconds ago
Data
{"Alert distance":93.96}
json
a few seconds ago
Items per page 100
1–1 of 1 item
1 of 1 page
1