

Assignment 1


Ukash Kumar G

412719104039

Make a home automation with tinkercad, add 2-3 sensors, LED, buzzer and make a common code and alarms should be given.

Ticker Cad link: [Click Here](#)

If does not works use this link: <https://www.tinkercad.com/things/ifJwfCqPZIV>



CODE:

```
#include <Servo.h>

int output1Value = 0;

int sen1Value = 0;

int sen2Value = 0;

int const gas_sensor = A1;

int const LDR = A0;

int limit = 400;
```

```

long readUltrasonicDistance(int triggerPin, int echoPin)
{
    pinMode(triggerPin, OUTPUT); // Clear the trigger
    digitalWrite(triggerPin, LOW);
    delayMicroseconds(2);
    // Sets the trigger pin to HIGH state for 10 microseconds
    digitalWrite(triggerPin, HIGH);
    delayMicroseconds(10);
    digitalWrite(triggerPin, LOW);
    pinMode(echoPin, INPUT);
    // Reads the echo pin, and returns the sound wave travel time in microseconds
    return pulseIn(echoPin, HIGH);
}

```

```

Servo servo_7;

```

```

void setup()
{
    Serial.begin(9600);           //initialize serial communication
    pinMode(A0, INPUT);           //LDR
    pinMode(A1, INPUT);           //gas sensor
    pinMode(13, OUTPUT);          //connected to relay
    servo_7.attach(7, 500, 2500); //servo motor

    pinMode(8, OUTPUT);           //signal to piezo buzzer
    pinMode(9, INPUT);            //signal to PIR
    pinMode(10, OUTPUT);          //signal to npn as switch
    pinMode(4, OUTPUT);           //Red LED
    pinMode(3, OUTPUT);           //Green LED
}

```

```
}
```

```
void loop()
```

```
{
```

```
    //-----light intensity control-----//
```

```
//-----
```

```
    int val1 = analogRead(LDR);
```

```
    if (val1 > 500)
```

```
    {
```

```
        digitalWrite(13, LOW);
```

```
        Serial.print("Bulb ON = ");
```

```
        Serial.print(val1);
```

```
    }
```

```
else
```

```
    {
```

```
        digitalWrite(13, HIGH);
```

```
        Serial.print("Bulb OFF = ");
```

```
        Serial.print(val1);
```

```
    }
```

```
//-----
```

```
    //----- light & fan control -----//
```

```
//-----
```

```
    sen2Value = digitalRead(9);
```

```
    if (sen2Value == 0)
```

```
    {
```

```
        digitalWrite(10, LOW); //npn as switch OFF
```

```
        digitalWrite(4, HIGH); // Red LED ON,indicating no motion
```

```

        digitalWrite(3, LOW); //Green LED OFF, since no Motion detected
Serial.print("    || NO Motion Detected    ");

    }

if (sen2Value == 1)
{
    digitalWrite(10, HIGH); //npn as switch ON
    delay(5000);
    digitalWrite(4, LOW); // RED LED OFF
    digitalWrite(3, HIGH); //GREEN LED ON , indicating motion detected
    Serial.print("        || Motion Detected!    ");
}

//-----
// ----- Gas Sensor -----//
//-----

int val = analogRead(gas_sensor);    //read sensor value
Serial.print("|| Gas Sensor Value = ");
Serial.print(val);                    //Printing in serial monitor
//val = map(val, 300, 750, 0, 100);
if (val > limit)
{
    tone(8, 650);
}
    delay(300);
    noTone(8);

//-----
//----- servo motor -----//

```

```
//-----  
  
sen1Value = 0.01723 * readUltrasonicDistance(6, 6);  
  
if (sen1Value < 100)  
{  
    servo_7.write(90);  
    Serial.print("    || Door Open! ; Distance = ");  
    Serial.print(sen1Value);  
    Serial.print("\n");  
  
    }  
else  
{  
    servo_7.write(0);  
    Serial.print("    || Door Closed! ; Distance = ");  
    Serial.print(sen1Value);  
    Serial.print("\n");  
}  
delay(10); // Delay a little bit to improve simulation performance  
}
```