ASSIGNMENT-3

Date	16 OCTOBER 2022
Team ID	PNT2022TMID28844
Project Name	Industry-specific intelligent fire management system
Maximum Marks	2 Marks

NAME: SIRIPIREEDDY BHUMIKA

TOPIC: Write python code for blinking LED and Traffic lights for Raspberry pi.

CODE:

1) PYTHON CODE FOR BLINKING LED

```python
import RPi.GPIO as GPIO # Import Raspberry Pi GPIO library

from time import sleep # Import the sleep function from the time module

GPIO.setwarnings(False) # Ignore warning for now

GPIO.setmode(GPIO.BOARD) # Use physical pin numbering

GPIO.setup(8, GPIO.OUT, initial=GPIO.LOW) # Set pin 8 to be an output pin and set initial value to low

(off)

while True: # Run forever

GPIO.output(8, GPIO.HIGH) # Turn on

sleep(1) # Sleep for 1 second
```

2) PYTHON CODE FOR TRAFFIC LIGHT

```python
GPIO.output(8, GPIO.LOW) # Turn off

Sleep (1) # Sleep for 1 second

import RPi.GPIO as GPIO

import time

import signal

import sys

# Setup

GPIO.setmode(GPIO.BCM)

GPIO.setup(9, GPIO.OUT)

GPIO.setup(10, GPIO.OUT)

GPIO.setup(11, GPIO.OUT)


# Turn off all lights when user ends demo

def allLightsOff(signal, frame):

GPIO.output(9, False)

GPIO.output(10, False)

GPIO.output(11, False)

GPIO.cleanup()

sys.exit(0)

signal.signal(signal.SIGINT, allLightsOff)


# Loop forever

while True:

# Red

GPIO.output(9, True)
```

```python
time.sleep(3)
# Red and amber
GPIO.output(10, True)
time.sleep(1)
# Green
GPIO.output(9, False)
GPIO.output(10, False)
GPIO.output(11, True)
time.sleep(5)
# Amber
GPIO.output(11, False)
GPIO.output(10, True)
time.sleep(2)
# Amber off (red comes on at top of loop)
GPIO.output(10, False)
```