

Assignment -1
Arduino Programming

Assignment Date	15 September 2022
Student Name	Mr. GOWTHAM R
Student Roll Number	GCTC1914112
Maximum Marks	2 Marks

Question-1:

Make a smart home with 2-3 sensors, LED , Buzzer. in single code and connections

Solution:

```
// C++ code
//SMART HOME

const int pingPin = 7; // Trigger Pin of Ultrasonic Sensor
const int echoPin = 6; // Echo Pin of Ultrasonic Sensor
int tempPin=0;
void setup()
{
  Serial.begin(9600); // Starting Serial Terminal
  pinMode(LED_BUILTIN, OUTPUT);
  pinMode(3,OUTPUT);
}

void loop()
{
  long distcm,duration;
  float temp;
  temp=analogRead(tempPin);
  temp=temp*0.4882815;
  if(temp>70)
  {
    digitalWrite(3, HIGH);
  }
  else
  {
    digitalWrite(3,LOW);
  }

  delay(1000);
  pinMode(pingPin, OUTPUT);
  digitalWrite(pingPin, LOW);
  delayMicroseconds(2);
  digitalWrite(pingPin, HIGH);
```

```

delayMicroseconds(10);
digitalWrite(pingPin, LOW);
pinMode(echoPin, INPUT);
duration = pulseIn(echoPin, HIGH);

distcm = duration*0.0343/2;
// Turns the LED ON when the water level drops below 100cm.
if(distcm<100)
{
    digitalWrite(LED_BUILTIN, HIGH);
}
else
{
    digitalWrite(LED_BUILTIN, LOW);
}
}

```

