Assignment-3

Python Programming

Assignment Date	08 October 2022
Student Name	K.Vasanthakumar
Student Roll Number	710419106030
Marks	2 Marks

Question-1:

Write a python code for blinking LED for Raspberry pi.

Solution:

```
#!/user/bin/env  python
import RPi.GPIO as GPIO # RPi.GPIO can be referred as GPIO from now
import time

ledPin = 22  # pin22def

setup():
        GPIO.setmode(GPIO.BOARD)       # GPIO Numbering of Pins
        GPIO.setup(ledPin, GPIO.OUT) # Set ledPin as output
        GPIO.output(ledPin, GPIO.LOW) # Set ledPin to LOW to turn Off
```

the LED

```
 def loop():
      while True:
            print 'LED on'
            GPIO.output(ledPin, GPIO.HIGH) # LED On
            time.sleep(1.0  )  # wait 1 sec
            print 'LED off'
            GPIO.output(ledPin, GPIO.LOW)     # LED
            Offtime.sleep(1.0)  # wait 1 sec
def endprogram():

            GPIO.output(ledPin, GPIO.LOW)          # LED Off
            GPIO.cleanup()                    # Release resources
```

```
if_name_=='_main_': # Program starts from here
        setup()
        try:
            loop()
        except KeyboardInterrupt:  # When 'Ctrl+C' is pressed, the destroy() will
be executed.
            endprogram()
```

Question-2:

Write a python code for Traffic lights for Raspberry pi.

Solution:

```
#!/usr/bin/python3.4
import RPi.GPIO as GPIO
import time

GPIO.setmode(GPIO.BCM)
GPIO.setwarnings(False)
GPIO.setup(4, GPIO.IN, pull_up_down = GPIO.PUD_DOWN)  # Button
GPIO.setup(17, GPIO.OUT, initial = GPIO.HIGH)        # RED
GPIO.setup(27, GPIO.OUT, initial = GPIO.HIGH)        # YELLOW
GPIO.setup(18, GPIO.OUT, initial = GPIO.HIGH)        # GREEN
GPIO.setup(22, GPIO.OUT, initial = GPIO.LOW)         # Buzzer

 x = 1  # Variable to control traffic light systemtry:
while True:
        if(GPIO.input(4) == True):
            while(x == 1):
              GPIO.output(17, GPIO.LOW)
               GPIO.output(22, GPIO.HIGH)
```

```
            time.sleep(2)
          GPIO.output(22, GPIO.LOW)
          GPIO.output(27, GPIO.LOW)
          time.sleep(3)
         GPIO.output(17, GPIO.HIGH)
         GPIO.output(27,GPIO.HIGH)
         GPIO.output(18, GPIO.LOW)
         time.sleep(5) GPIO.output(18,
        GPIO.HIGH)
         time.sleep(2)
except Exception as ex:
   print("error occured",ex)finally:
   GPIO.cleanup()
```