Assignment -4
Wowki & IBM Cloud

Assignment Date	04 October 2022
Student Name	Muthuraj S
Student Roll Number	310819106301
Maximum Marks	2 Marks

Question-1:

Write code and connections in wowki for the ultrasonic sensor. Whenever the distance is less than 100cms sent "alert" to IBM cloud and display in device recent events.

Code:

```
#include <WiFi.h>

#include <PubSubClient.h>

#include <ArduinoJson.h>

WiFiClient wifiClient;

String data3;

#define ORG "sf54ab"

#define DEVICE_TYPE "MyDeviceType"

#define DEVICE_ID "12345"

#define TOKEN "ZIA1zf@zL9s)Pumv11"

#define speed 0.034

#define led 14

char server[] = ORG ".messaging.internetofthings.ibmcloud.com";

char publishTopic[] = "iot-2/evt/shreedharen/fmt/json";
```

```
char topic[] = "iot-2/cmd/led/fmt/String";
char authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
PubSubClient client(server, 1883, wifiClient);
const int trigpin=5;
const int echopin=18;
String command;
String data="";
long duration;
float dist;
void setup()
{
Serial.begin(115200);
pinMode(led, OUTPUT);
pinMode(trigpin, OUTPUT);
pinMode(echopin, INPUT);
wifiConnect();
mqttConnect();
}
void loop() {
bool isNearby = dist < 100;
digitalWrite(led, isNearby);
publishData();
delay(500);
if (!client.loop()) {
mqttConnect();
```

```
}
}
void wifiConnect() {
Serial.print("Connecting to "); Serial.print("Wifi");
WiFi.begin("Wokwi-GUEST", "", 6);
while (WiFi.status() != WL_CONNECTED) {
delay(500);
Serial.print(".");
}
Serial.print("WiFi connected, IP address: ");
Serial.println(WiFi.localIP());
}
void mqttConnect() {
if (!client.connected()) {
Serial.print("Reconnecting MQTT client to ");
Serial.println(server);
while (!client.connect(clientId, authMethod, token)) {
Serial.print(".");
delay(500);
}
initManagedDevice();
Serial.println();
}
}
void initManagedDevice() {
if (client.subscribe(topic)) {
// Serial.println(client.subscribe(topic));
```

```
Serial.println("IBM subscribe to cmd OK");
} else {
Serial.println("subscribe to cmd FAILED");
}
}
void publishData()
{
digitalWrite(trigpin,LOW);
digitalWrite(trigpin,HIGH);
delayMicroseconds(10);
digitalWrite(trigpin,LOW);
duration=pulseIn(echopin,HIGH);
dist=duration*speed/2;
if(dist<100){
String payload = "{\"Alert Distance\":";
payload += dist;
payload += "}";
Serial.print("\n");
Serial.print("Sending payload: ");
Serial.println(payload);
if (client.publish(publishTopic, (char*) payload.c_str())) {
Serial.println("Publish OK");
}
}
if(dist>100){
String payload = "{\"Distance\":";
payload += dist;
```

```
payload += "}";

Serial.print("\n");

Serial.print("Sending payload: ");

Serial.println(payload);

if(client.publish(publishTopic, (char*) payload.c_str())) {

Serial.println("Publish OK");

}else

{

Serial.println("Publish FAILED");

}

}

}
```

Connections:



Output:




```
#include <WiFi.h>
#include <PubSubClient.h>
#include <ArduinoJson.h>

WiFiClient wifiClient;

#define ORG "sf54ab"
#define DEVICE_TYPE "MyDeviceType"
#define DEVICE_ID "12345"
#define TOKEN "ZIA1zf@zL9s)Pumv11"
#define speed 0.034

char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/abcd_1/fmt/json";
char topic[] = "iot-2/cmd/home/fmt/String";
char authMethod[] = "use-token-auth";
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;
PubSubClient client(server, 1883, wifiClient);
void publishData();

const int trigpin=5;
const int echopin=18;
String command;
String data="";
String lat="14.167589";
String lon="80.248510";
String name="point2";
String icon="";

long duration;
int dist;
```

Output:(IBM Cloud)



Link : https://wokwi.com/projects/346858583508386388