Assignment - 4

Assignment Date	25 OCTOBER 2022
Team ID	PNT2022TMID52849

Question-1:

Write code and connections in wowki for ultrasonic sensor.

Whenever distance is less than 100 cms send “alert” to IBM cloud and display in device recent events.

Solution:

WOWKI LINK: https://wokwi.com/projects/346235465961046612

```
#include <WiFi.h>
#include <PubSubClient.h>
#define TRIGGER 2
#define ECHO 15
#define sound_speed 0.034
int distance;

void callback(char* subscribetopic, byte* payload, unsigned int payloadLength);

//-------credentials of IBM Accounts------

#define ORG "xvcxef"
#define DEVICE_TYPE "iot-device-1"
#define DEVICE_ID "123456789"
#define TOKEN "987654321"
String data3;


//-------- Customise the above values --------
char server[] = ORG ".messaging.internetofthings.ibmcloud.com";
char publishTopic[] = "iot-2/evt/Data/fmt/json";
char subscribetopic[] = "iot-2/cmd/test/fmt/String";
char authMethod[] = "use-token-auth";
```

```
char token[] = TOKEN;
char clientId[] = "d:" ORG ":" DEVICE_TYPE ":" DEVICE_ID;


//-------------------------------------
WiFiClient wifiClient;
PubSubClient client(server, 1883, callback ,wifiClient);
void setup()
{
  Serial.begin(115200);
  pinMode(TRIGGER, OUTPUT);
  pinMode(ECHO, INPUT);
  delay(10);
  Serial.println();
  wificonnect();
  mqttconnect();
}

void loop()
{

  digitalWrite(TRIGGER, HIGH);
  delayMicroseconds(10);
  digitalWrite(TRIGGER, LOW);

  int duration=pulseIn(ECHO,HIGH);
  distance=(duration*sound_speed)/2;
  Serial.print("Distance:");
  Serial.print(distance);
  Serial.println("cms");
  if(distance<100){
    PublishData(distance);
  }
  delay(1000);
  if (!client.loop()) {
    mqttconnect();
  }
}



/*.....................................retrieving to
Cloud.............................*/

void PublishData(int d) {
  mqttconnect();

  String payload = "{\"message\":alert}";
```

```
  Serial.print("Sending payload: ");
  Serial.println(payload);


  if (client.publish(publishTopic, (char*) payload.c_str())) {
    Serial.println("Publish ok");
  } else {
    Serial.println("Publish failed");
  }

}
void mqttconnect() {
  if (!client.connected()) {
    Serial.print("Reconnecting client to ");
    Serial.println(server);
    while (!!!client.connect(clientId, authMethod, token)) {
      Serial.print(".");
      delay(500);
    }

     initManagedDevice();
     Serial.println();
  }
}
void wificonnect()
{
  Serial.println();
  Serial.print("Connecting to ");

  WiFi.begin("Wokwi-GUEST", "", 6);
  while (WiFi.status() != WL_CONNECTED) {
    delay(500);
    Serial.print(".");
  }
  Serial.println("");
  Serial.println("WiFi connected");
  Serial.println("IP address: ");
  Serial.println(WiFi.localIP());
}

void initManagedDevice() {
  if (client.subscribe(subscribetopic)) {
    Serial.println((subscribetopic));
    Serial.println("subscribe to cmd OK");
  } else {
    Serial.println("subscribe to cmd FAILED");
  }
}
```

```
void callback(char* subscribetopic, byte* payload, unsigned int payloadLength)
{

  Serial.print("callback invoked for topic: ");
  Serial.println(subscribetopic);
  for (int i = 0; i < payloadLength; i++) {
    data3 += (char)payload[i];
  }

  Serial.println("data: "+ data3);

data3="";


}
```

CIRCUIT :



IBM CLOUD RECENT EVENTS: