DEVELOP THE CODE

The Arduino code is successfully developed.

```
#define BLYNK_AUTH_TOKEN "V7n_OUDHMQyQH4lhFPo0wQjrVtpgSIu2"
#define BLYNK_PRINT Serial
#include <WiFi.h>
#include <Wire.h>
#include <SPI.h>
#include "ThingSpeak.h"
#include <WiFiClient.h>
#include <BlynkSimpleEsp32.h>
#include "twilio.hpp"
bool success;
// Values from Twilio (find them on the dashboard)
static const char *account_sid = "AC81129e9ae95e871e1a75e0460ac07bf3";
static const char *auth_token = "29ec1c1ce54c88b4d4b1704bb5f74cc8";
// Phone number should start with +13862725645";
static const char *from_number = "+13862725645";
// Phone number should start with "+<countrycode>"
static const char *to_number = "+919150429149";
//static const char *message = "Alert";
String response;
unsigned long myChannelNumber = 2;
const char * myWriteAPIKey = "25V40ZAPI6KIZFGY";
int LED_PIN = 32; // the current reading from the input pin
int BUZZER_PIN= 12;
const int mq2 = 4;
int value = 0;
char auth[] = BLYNK_AUTH_TOKEN;
WiFiClient client;
```

```
BlynkTimer timer;
Twilio *twilio;



//Flame
int flame_sensor_pin = 10 ;// initializing pin 10 as the sensor digital output pin
int flame_pin = HIGH ; // current state of sensor

char ssid[] = "Amirtha";
char pass[] = "Amirtharavi";
#define PIN_LM35 39
#define ADC_VREF_mV 3300.0
#define ADC_RESOLUTION 4096.0
#define RELAY_PIN    17
#define RELAY_PIN1  27



void setup()
{
  Serial.begin(115200);
  pinMode(RELAY_PIN, OUTPUT);
  pinMode(RELAY_PIN1, OUTPUT);
  Serial.print("Connecting to ");
  Serial.println(ssid);
  WiFi.begin(ssid, pass);
  int wifi_ctr = 0;
  while (WiFi.status() != WL_CONNECTED)
  {
  delay(1000);
  Serial.print(".");
  }
```

```
 Serial.println("WiFi connected");
 Blynk.begin("V7n_OUDHMQyQH4lhFPo0wQjrVtpgSIu2", ssid, pass);
 timer.setInterval(2500L,temperature);
 timer.setInterval(2500L,GasSensors);
 timer.setInterval(2500L,flamesensor);
 twilio = new Twilio(account_sid, auth_token);
 ThingSpeak.begin(client);
 pinMode(LED_PIN, OUTPUT);
 pinMode(mq2, INPUT);
 pinMode ( flame_sensor_pin , INPUT ); // declaring sensor pin as input pin for Arduino
 pinMode(BUZZER_PIN, OUTPUT);
}
void temperature()
{
 int adcVal = analogRead(PIN_LM35);
 float milliVolt = adcVal * (ADC_VREF_mV / ADC_RESOLUTION);
 float tempC = milliVolt / 10;
 Serial.print("Temperature: ");
 Serial.print(tempC);
 Serial.print("°C");
 if(tempC > 60)
 {
  Serial.println("Alert");
  digitalWrite(BUZZER_PIN, HIGH); // turn on
  success=twilio->send_message(to_number, from_number, "Temperature over 60C!", response);
  Blynk.email("amirthavarshiniravi@gmail.com", "Alert", "Temperature over 60C!");
 }
 else
 {
   digitalWrite(BUZZER_PIN, LOW); // turn on
 }
```

```
  Blynk.virtualWrite(V0,tempC);
  int x = ThingSpeak.writeField(myChannelNumber,1, tempC, myWriteAPIKey);
}



void GasSensors()
{
  //mq2

  int gassensorAnalogmq2 = analogRead(mq2);
  Serial.print("mq2 Gas Sensor: ");
  Serial.print(gassensorAnalogmq2);
  Serial.print("\t");
  Serial.print("\t");
  Serial.print("\t");

  if (gassensorAnalogmq2 > 1500)
  {
    Serial.println("mq2Gas");
    Blynk.email("amirthavarshiniravi@gmail.com", "Alert", "FLAMMABLE GAS EXCEEDED LIMIT");
    Serial.println("mq2Gas");
    Serial.println("Alert");
    digitalWrite(RELAY_PIN1, HIGH); // turn on fan 10 seconds
    success=twilio->send_message(to_number, from_number,"FLAMMABLE GAS EXCEEDED LIMIT",
response);
    delay(100);
  }
  else
  {
    Serial.println("No mq2Gas");
    digitalWrite(RELAY_PIN1, LOW);  // turn off fan 10 seconds
```

```
   delay(100);

  }
  Blynk.virtualWrite(V3,gassensorAnalogmq2);
  int a = ThingSpeak.writeField(myChannelNumber,4, gassensorAnalogmq2, myWriteAPIKey);

}

void flamesensor()
{
flame_pin = digitalRead ( flame_sensor_pin ) ; // reading from the sensor
if (flame_pin == LOW ) // applying condition
{
Serial.println ( " ALERT: FLAME DETECTED" ) ;
digitalWrite (BUZZER_PIN, HIGH ) ;// if state is high, then turn high the BUZZER
Blynk.email("amirthavarshiniravi@gmail.com", "Alert", "FLAME DETECTED");
success=twilio->send_message(to_number, from_number,"FLAME DETECTED", response);
}

else
{
Serial.println ( " NO FLAME DETECTED " ) ;
digitalWrite (BUZZER_PIN , LOW ) ; // otherwise turn it low
}
 int value = digitalRead(flame_sensor_pin); // read the analog value from sensor

  if (value ==LOW) {
    Serial.print("FLAME");
    digitalWrite(RELAY_PIN, HIGH);
  } else {
    Serial.print("NO FLAME");
```

```
    digitalWrite(RELAY_PIN, LOW);
  }
  int a = ThingSpeak.writeField(myChannelNumber,2, flame_pin, myWriteAPIKey);
}

void loop()
{
  temperature();
  GasSensors();
  flamesensor();
}
```

TEAM LEADER:
HARSHAVARTHANA M (1904012)
TEAM MEMBERS:
AMIRTHAVARSHINI R (1904001)
ATCHAYA B (1904004)
RAGHAVI R (1904038)
RAKSHEKA R (1904039)