

# Wireless Shock Door/Window Sensor

- Easy to install.
- Easy to “learn” into wireless control panels; 319.5 MHz and 345 MHz,
- Compact size: 2.25” L x 1” W x .5” D
- LED activates on shock activation and goes out on shock restoral.
- LED for test mode.
- Low battery detection - LED flashes until battery is replaced.
- Sensitivity adjustment via. potentiometer.
- Reed & shock zones use separate ID’s.
- Cover tamper switch.
- Built with MaxOut™ Technology for maximum Radio Frequency (RF) security sensor reliability. MaxOut high performance sensors deliver the maximum FCC allow-able output for maximum signal strength and range.
- 

The Wireless Shock Door-Window sensor is a supervised, wireless sensor designed to detect vibrations made by an intruder attempting to break a window or door.

The shock sensor contains a piezo detection device that detects vibrations when mounted on a window or door frame.



## Specifications

Model Number and Ordering:	RF-SHK-319-NN 319.5 MHz RF-SHK-345-NN 345 MHz
RF Frequency:	319.5 MHz 345 MHz
Compatibility:	319.5 MHz: Interlogix®, UTC®, GE®, ITI®, and Qolsys® 345 MHz: Honeywell® and 2GIG®
Battery Type: (Requires 2)	3-VDC Lithium Coin-Cell Battery, Varta or Panasonic CR2032
Operating Temperature Range:	32 to 120°F (0 to 49°C)
Storage Temperature Range:	-30 to 140°F (-34 to 60°C)
Relative Humidity:	95% Non-Condensing
Dimensions (L x W x D):	2.25 in. x 1.0 in. x 0.50 in.

## Regulatory

FCC Compliant  
IC Compliant

This device complies with part 15 of the FCC Rules.  
Operation is subject to the following two conditions:  
(1) This device may not cause harmful interference, and  
(2) this device must accept any interference received,  
including interference that may cause undesired operation.

This Class B digital apparatus complies with Canadian ICES-003.

Cet appareil numérique de la classe B est conforme à la norme  
NMB-003 du Canada.