NM27C512 Lite / READ-ONLY / 5 V ONLY

USB power and CH340C

J1
USB Micro-B

U4
CH340C

Two 74HC595 / A0-A15

U1
ATmega328P-AU

U2
74HC595D

U3
74HC595D

C1
10uF / 10V

C2
100nF

C3
100nF

CH340C internal clock: no 12 MHz crystal.
R232 = GND; unused modem pins = NC.

J2
AVR ISP

J2: 1 MISO / 2 +5V / 3 SCK
4 MOSI / 5 RESET / 6 GND

C4
100nF

C5
100nF

C6
100nF

C10
100nF

C7
100nF

C8
100nF

U3 high byte first, U2 low byte last; MSB first.
CE#/OE# pull-ups keep EPROM outputs inactive during RESET/ISP.

Y1
16MHz / CL -18pF

R1
10k

D4
BAT54WS

SW1
RESET

U5
NM27C512Q SOCKET

R8
10k

R9
10k

Q1
MMBT3906

Q2
MMBT3906

C11
22pF

C12
22pF

C13
100nF

R4
10k LATCH

R2
10k CE

R3
10k OE

R5
1k

R6
1k

R7
1k

C9
100nF

D2
RX BLUE

D3
TX ORANGE

R10
1k

R11
1k

DTR# -> C13 -> RESET: D4 clamps positive reset edge.

RX/TX: PNP buffers, UART LOW = ON, idle HIGH = OFF.

RGB: PB0=R / PB1=G / PD2=B; LOW = ON.

D1
RGB CA / 5050 OR THT5

NO VPP / NO PROGRAMMING / one sheet / no PCB layout

Sheet: /
File: NM27C512_Dumper_Lite.kicad_sch

Title: Lunar Dumper – 5V read-only

Size: A3	Date: 2026-10-06	Rev: A
KiCad E.D.A. 10.0.6		Id: 1/1