

JPMixer

Live Monitor Mix Controller — User Guide

VERSION 1.0.0 · DIGICO SD / QUANTUM

CONTENTS

1. **Overview**
2. **Installation**
3. **First Launch & Settings**
4. **Connecting to the Console**
5. **Setting Up Channels**
6. **Setting Up Aux Mixes**
7. **Using the Mixer (Musicians)**
8. **Ear Scenes — Save & Recall**
9. **Monitor Engineer View**
10. **iPad OSC Connections**
11. **Installing on iPhone / iPad**
12. **Troubleshooting**

1. Overview

JPMixer is a Mac application that bridges a DiGiCo SD or Quantum console to any web browser on the same network. Musicians open a webpage on their iPhone or iPad and control their own monitor mix — no app store download required.

The system works over your stage network using OSC (Open Sound Control). JPMixer runs silently in the Mac menu bar, serves the mixer page to any connected device, and relays fader moves to the console in real time.

What you can do

- Each musician controls their own aux send levels from their phone
- Save "ear scenes" per snapshot so mixes recall automatically with the show
- Monitor engineer sees every aux mix on one full-screen grid
- Relay console data to iPad OSC apps (TouchOSC, Lemur, etc.)
- Install the mixer as a home screen app on iPhone / iPad

IMPORTANT

DiGiCo's OSC protocol only exposes aux send levels and pan. Main channel faders and mutes are not accessible via OSC — this is a DiGiCo hardware limitation, not a JPMixer limitation.

2. Installation

Which file do I use?

- **JPMixer-1.0.0-arm64.dmg / .pkg** — Apple Silicon Macs (M1, M2, M3, M4)
- **JPMixer-1.0.0.dmg / .pkg** — Intel Macs

Use the **.dmg** to drag the app to your Applications folder manually. Use the **.pkg** for a guided installer wizard that installs automatically.

Installing from the DMG

- 1 Double-click the **.dmg** file to mount it
- 2 Drag **JPMixer** into the **Applications** folder shortcut
- 3 Eject the DMG and open JPMixer from Applications

Installing from the PKG

- 1 Double-click the **.pkg** file
- 2 Follow the installer wizard — click Continue, Agree, Install
- 3 Enter your Mac password when prompted
- 4 Click Close when finished — JPMixer is now in Applications

GATEKEEPER WARNING

Because JPMixer is not signed with an Apple Developer certificate, macOS may block it. To open it: right-click (or Control-click) the app →

OPEN

→

OPEN ANYWAY

. You only need to do this once.

3. First Launch & Settings

JPMixer lives in the **menu bar** — there is no Dock icon. When you launch it, look for the JPMixer icon in the top-right of your screen near the clock.

Opening Settings

Click the menu bar icon → **Settings...**

Settings Tabs

Connection

Start/stop the server, enter console IP and OSC ports, view your Mac's IP address.

Channels

Name channel groups, assign icons, label overrides, and control which channels appear in the mixer.

Auxes

Set names, colours, and visibility for each aux bus. Hidden auxes won't appear in the musician's picker.

iPad OSC

Add iPad connections for relaying console OSC data to TouchOSC or other iPad apps.

Monitor

Open the Monitor Engineer View and see the direct browser link for the full-screen grid.

General

Console type, channel/aux counts, auto-start on launch, and ear scene recall toggle.

4. Connecting to the Console

Network Setup

JPMixer, the DiGiCo console, and all musician devices must be on the **same network**. This is typically your dedicated stage WiFi or wired LAN.

Required Settings

- 1 Open Settings → **Connection** tab
- 2 Enter the console's IP address in **Console IP Address**
- 3 Set **Send Port** (OSC port JPMixer sends to the desk — typically 8000)
- 4 Set **Listen Port** (OSC port JPMixer receives from the desk — typically 9000)
- 5 Set your **Server Port** (the port musicians use to open the mixer — default 8080)
- 6 Click **Save & Apply**
- 7 Click **Start** in the Connection tab — the status dot turns green when the console responds

TIP

Your Mac's IP address is shown in the Connection tab under "This Mac's IP." Share this address with musicians — they open `HTTP://[YOUR-MAC-IP]:8080` in Safari.

Use Port 80 (Optional)

Click **Use Port 80** to forward port 80 to your server port. This lets musicians open **http://[your-mac-ip]** without typing a port number. Requires your Mac admin password and sets up a persistent background service.

5. Setting Up Channels

Channel Groups

Groups organise channels into labelled sections in the mixer (e.g. Drums, Guitars, Keys, Vocals). Click **+ Add Group**, give it a name and colour, then assign channels to it.

Channel Settings

In the **Channels** tab, each row represents one input channel. You can:

- **Icon** — pick an emoji or instrument icon to identify the channel visually
- **Label Override** — rename the channel (overrides the console name)
- **Group** — assign to a group for ordering and section headers
- **On/Off** — hide a channel from the mixer entirely

TIP

Channel names are pulled automatically from the console when the server starts. You only need label overrides if you want a different name than what's on the desk.

6. Setting Up Aux Mixes

Each aux bus becomes one "mix" that a musician can select in the mixer. In the **Auxes** tab:

- **Name** — rename the aux (e.g. "Drums IEM", "Vocals Wedge")
- **Color** — pick a colour shown in the musician's mixer header
- **Show** — toggle off to hide unused auxes from the musician's picker

Click **Save & Apply** after making changes. The server restarts automatically and all connected devices update.

7. Using the Mixer (Musicians)

Opening the Mixer

- 1 Connect your phone or tablet to the stage WiFi
- 2 Open **Safari** (recommended) or any browser
- 3 Type the Mac's IP address and port: **http://192.168.x.x:8080**
- 4 The mixer loads — tap the aux name at the top to select your mix

Mixer Controls

- **Aux picker (top bar)** — tap to switch between your assigned mixes
- **Faders** — drag up/down to adjust each channel's level in your mix
- **PAN button** — toggles pan controls alongside each fader
- **Connection dot** — green means live, grey means reconnecting
- **Save button** () — saves your current mix as an ear scene for the active snapshot

TIP

The mixer works best in Safari on iOS. Add it to your home screen (see Section 11) for a full-screen experience with no browser chrome.

8. Ear Scenes — Save & Recall

An **ear scene** is a saved snapshot of your entire aux mix at a specific console snapshot. When a snapshot fires, JPMixer can automatically push your saved mix back to the console.

Saving a Scene

- 1 Fire the console snapshot you want to save a mix for
- 2 Adjust your mix in the browser to exactly how you want it
- 3 Tap the  **Save** button — a confirmation toast appears

Recalling Scenes Automatically

- 1 Open Settings → **General** tab
- 2 Enable **Auto-recall scenes on snapshot change**
- 3 Click Save & Apply

Now whenever the console fires a snapshot, JPMixer checks if you have a saved ear scene for that snapshot and your aux, and instantly sends those fader values to the console.

Deleting a Scene

When a scene is saved for the current snapshot, the save button shows . Tap it to delete the scene for that snapshot and aux.

NOTE

Ear scenes are stored per-aux per-snapshot. Each musician's mix is independent — saving a scene for Drums does not affect the Vocals mix.

9. Monitor Engineer View

The Monitor Engineer View is a full-screen grid showing **every aux mix at once** — all channels, all faders, live. Designed for a second screen or a dedicated iPad at the monitor position.

Opening the Monitor View

- **From the menu bar:** click the JPMixer icon → **Open Monitor Engineer View**
- **From Settings:** go to the Monitor tab → click **Open Monitor View**
- **From any browser:** open [http://\[mac-ip\]:8080/monitor.html](http://[mac-ip]:8080/monitor.html)

Using the Monitor View

- Each column is one aux mix — scroll horizontally to see all
- Faders are fully interactive — the monitor engineer can adjust any mix
- Changes sync instantly to the musician's view and to the console
- The current snapshot name is shown in the header

10. iPad OSC Connections

JPMixer can relay DiGiCo OSC data to one or more iPads running OSC apps like TouchOSC or Lemur. This lets you use a custom iPad layout alongside JPMixer.

Adding an iPad

- 1 Open Settings → **iPad OSC** tab
- 2 Click **+ Add iPad**
- 3 Enter a name, the iPad's IP address, the send port, and the listen port
- 4 Toggle it **On**
- 5 Click **Save & Apply**

JPMixer creates one UDP connection per enabled iPad. OSC messages from the console are forwarded to all connected iPads, and commands from iPads are forwarded to the console.

TIP

You can add multiple iPads — useful for a FOH engineer and monitor engineer each having their own OSC controller.

11. Installing on iPhone / iPad

The JPMixer web page can be installed as a home screen app on any iPhone or iPad — no App Store required. It opens full-screen with no browser chrome, just like a native app.

Adding to Home Screen (Safari on iOS)

- 1 Open the mixer URL in **Safari** on the iPhone or iPad
- 2 Tap the **Share** button (box with arrow pointing up)
- 3 Scroll down and tap **Add to Home Screen**
- 4 Tap **Add** — the JPMixer icon appears on the home screen

From now on, tap the home screen icon to open the mixer in full-screen mode. The connection watchdog keeps the session alive automatically and reconnects if the WiFi drops.

NOTE

This feature requires Safari on iOS. Chrome and other browsers on iPhone do not support Add to Home Screen with full PWA behaviour.

12. Troubleshooting

Console status shows Offline

- Check the console IP address is correct in Settings → Connection
- Confirm the console has OSC enabled and the ports match
- Make sure the Mac and console are on the same network
- Try stopping and restarting the server

Mixer page won't load on iPhone

- Confirm the iPhone is on the same WiFi as the Mac
- Double-check the IP address and port number
- Make sure the JPMixer server is running (menu bar icon → status shows port number)
- Try disabling the Mac firewall temporarily: System Settings → Network → Firewall

Faders don't affect the console

- Check the Console status dot in Settings — it must be green
- Confirm the correct aux channel numbers match your DiGiCo session
- DiGiCo OSC only works on aux sends — main channel faders cannot be controlled via OSC

Ear scenes not recalling

- Enable **Auto-recall scenes on snapshot change** in Settings → General
- Confirm a scene is saved for that snapshot — the  button shows  when a scene exists
- The console must be connected (green dot) for recall to work

App blocked by macOS Gatekeeper

- Right-click the app in Finder → **Open** → **Open Anyway**
- Or go to System Settings → Privacy & Security → scroll down → click **Open Anyway**

Mixer shows "Reconnecting..."

This means the browser lost its WebSocket connection to JPMixer. It will reconnect automatically within a few seconds. If it stays disconnected, check that the server is still running from the menu bar.

JPMixer v1.0.0 · Built for DiGiCo SD / Quantum · jpmixing.com

JPMixer User Guide · Version 1.0.0