

文件说明

- `VoodooPS2Controller.kext` 和 `ApplePS2SmartTouchPad.kext` 两者选其一，不可全用
- `IntelGraphicsDVMTFixup.kext` 用于五代以上机器，四代及以下删除
- `XHCI` 开头的三个 `kext` 对应适用于 `x99`、`200` 和 `300` 系主板，非此类主板删除
- `AzulPatcher4600.kext` 只适用于核心显卡 `HD4600`，其他型号删除
- `CoreDisplayFixup.kext` 用于破解 `4K` 支持，合理选用
- `ATH9KFixup.kext` 用于驱动 `AR946x`、`AR956X`、`AR9485` 高通无线网卡，合理选用
- `NoTouchID` 用于禁止 `TouchID` 的检测，合理选用
- `WhateverGreen.kext` 已经更新，合并了 `igfx`、`ngfx`，以及 `Shiki`，启动参数和以前一样，不论 `A` 卡、`N` 卡还是 `Intel` 核心显卡，都建议使用
- `ACPIBatteryManager.kext` 用于实现电量显示，如遇五国卡 `BAT0` 之类的请删除
- `AppleALC.kext` 和 `VoodooHDA-2.9.1.kext` 任选其一
- `RTL8100.kext`、`RTL8111.kext`、`IntelMausiEthernet.kext`、`AppleIGB`、`SmallTree-Intel-211-AT-PCIe-GBE.kext`、`ALXEthernet.kext`、`AtherosE2200Ethernet.kext` 分别对应不同的网卡合理选用

对应关系如下

RTL8100.kext	RTL8107E、RTL810X、RTL8139
RTL8111.kext	Realtek RTL8111/8168 B/C/D/E/F/G/H
IntelMausiEthernet.kext	82578LM、82578LC、82578DM、82578DC、82579LM、82579V、I217LM、I217V、I218LM、I218V、I218LM2、I218V2、I218LM3、I219V、I219LM、I219V2、I219LM2、I219LM2
AtherosE2200Ethernet.kext	AR816x、AR817x、Killer E220x、Killer E2400、Killer E2500
SmallTree-Intel-211-AT-PCIe-GBE.kext	Intel I211
AppleIntelE1000.kext	Intel系列 82540, 82541, 82542, 82543, 82544, 82545, 82546, 82547, 82578 (P55/H55) 82579 (P67/H67) 82574L 82571 82572 82573 82574 82583 I217V
AppleIGB.kext	Intel 82575, 82576, 82580, dh89xxcc, i350, i210 and i211
ALXEthernet.kext	Atheros alx Ethernet
FakePCIID_BCM57XX_as_BCM57765.kext	BCM57XX
FakePCIID_Intel_GbX.kext	Small Tree drivers for Intel chipset

- FakePCIID_BCM57XX_as_BCM57765.kext** 详细支持列表
 - Broadcom NetXtreme BCM5700 Gigabit Ethernet [14e4:1644]
 - Broadcom NetXtreme BCM5701 Gigabit Ethernet PCIe [14e4:1645]
 - Broadcom NetXtreme BCM5702 Gigabit Ethernet PCIe [14e4:1646]
 - Broadcom NetXtreme BCM5703 Gigabit Ethernet PCIe [14e4:1647]
 - Broadcom NetXtreme BCM5717 Gigabit Ethernet PCIe [14e4:1655]
 - Broadcom NetXtreme BCM5717 Gigabit Ethernet PCIe [14e4:1665]
 - Broadcom NetXtreme BCM5718 Gigabit Ethernet PCIe [14e4:1656]
 - Broadcom NetXtreme BCM5719 Gigabit Ethernet PCIe [14e4:1657]
 - Broadcom NetXtreme BCM5725 Gigabit Ethernet PCIe [14e4:1643]
 - Broadcom NetXtreme BCM5727 Gigabit Ethernet PCIe [14e4:16f3]
 - Broadcom NetXtreme BCM5761 10/100/1000BASE-T Ethernet [14e4:1688]
 - Broadcom NetXtreme BCM5762 Gigabit Ethernet PCIe [14e4:1687]
 - Broadcom NetXtreme BCM57760 Gigabit Ethernet PCIe [14e4:1690]
 - Broadcom NetXtreme BCM57764 Gigabit Ethernet PCIe [14e4:1642]
 - Broadcom NetXtreme BCM57767 Gigabit Ethernet PCIe [14e4:1683]
 - Broadcom NetLink BCM57781 Gigabit Ethernet PCIe [14e4:16b1]
 - Broadcom NetXtreme BCM57782 Gigabit Ethernet PCIe [14e4:16b7]
 - Broadcom NetLink BCM57785 Gigabit Ethernet PCIe [14e4:16b5] -- Confirmed
 - Broadcom NetXtreme BCM57786 Gigabit Ethernet PCIe [14e4:16b3] -- Confirmed
 - Broadcom NetXtreme BCM57787 Gigabit Ethernet PCIe [14e4:1641]

- Broadcom NetLink BCM57788 Gigabit Ethernet PCIe [14e4:1691]
 - Broadcom NetLink BCM57790 Gigabit Ethernet PCIe [14e4:1694]
 - Broadcom NetLink BCM57791 Gigabit Ethernet PCIe [14e4:16b2]
 - Broadcom NetLink BCM57795 Gigabit Ethernet PCIe [14e4:16b6]
 - Broadcom NetLink BCM5785 Gigabit Ethernet [14e4:1699]
 - Broadcom NetLink BCM5785 Fast Ethernet [14e4:16a0]
 - Broadcom NetLink BCM5787M Gigabit Ethernet PCI Express [14e4:1693]
 - Broadcom Network Adapter [14e4:1689]
-

- `FakePCIID_Intel_GbX.kext` 详细支持列表

- Supported devices for SmallTreeIntel8254x.kext:
 - 8086:1010 82546EB Gigabit Ethernet Controller (Copper)
 - 8086:1011 82545EM Gigabit Ethernet Controller (Fiber)
 - 8086:1012 82546EB Gigabit Ethernet Controller (Fiber)
 - 8086:101d 82546EB Gigabit Ethernet Controller
 - 8086:1026 82545GM Gigabit Ethernet Controller
 - 8086:1027 82545GM Gigabit Ethernet Controller
 - 8086:1028 82545GM Gigabit Ethernet Controller
 - 8086:105e 82571EB Gigabit Ethernet Controller (Also covered by AppleIntel8254XEthernet.kext)
 - 8086:105f 82571EB Gigabit Ethernet Controller
 - 8086:1079 82546GB Gigabit Ethernet Controller
 - 8086:107a 82546GB Gigabit Ethernet Controller
 - 8086:107b 82546GB Gigabit Ethernet Controller
 - 8086:107c 82541PI Gigabit Ethernet Controller
 - 8086:107d 82572EI Gigabit Ethernet Controller (Copper)
 - 8086:107e 82572EI Gigabit Ethernet Controller (Fiber)
 - 8086:10a4 82571EB Gigabit Ethernet Controller
 - 8086:10b5 82546GB Gigabit Ethernet Controller (Copper)
 - 8086:10b9 82572EI Gigabit Ethernet Controller (Copper)
 - 8086:10bc 82571EB Gigabit Ethernet Controller (Copper)
- SmallTreeIntel82576.kext:
 - 8086:1521 I350 Gigabit Network Connection
 - 8086:1522 I350 Gigabit Fiber Network Connection
 - 8086:1533 I210 Gigabit Network Connection (Also covered by AppleIntelI210Ethernet.kext)
- SmallTreeIntel8259x.kext:
 - 8086:10c6 82598EB 10-Gigabit AF Dual Port Network Connection
 - 8086:10c7 82598EB 10-Gigabit AF Network Connection
 - 8086:10c8 82598EB 10-Gigabit AT Network Connection
 - 8086:10ec 82598EB 10-Gigabit AT CX4 Network Connection
 - 8086:10d8 82599EB 10 Gigabit Network Connection
 - 8086:10fb 82599ES 10-Gigabit SFI/SFP+ Network Connection
 - 8086:10f1 82598EB 10-Gigabit AF Dual Port Network Connection
 - 8086:151c 82599 10 Gigabit TN Network Connection
 - 8086:150b 82598EB 10-Gigabit AT2 Server Adapter

- 8086:1528 Ethernet Controller 10-Gigabit X540-AT2
- 8086:10fc 82599 10 Gigabit Dual Port Network Connection
- 8086:1560 Ethernet Controller X540