

High-Speed Interception Multicopter Control by Image-Based Visual Servoing

Kun Yang^{ID}, Chenggang Bai^{ID}, Zhikun She^{ID}, and Quan Quan^{ID}, *Senior Member, IEEE*

Abstract—In recent years, reports of illegal drones threatening public safety have increased. For the invasion of fully autonomous drones, traditional methods, such as radio frequency interference and GPS shielding, may fail. This article proposes a scheme that uses an autonomous multicopter with a strapdown camera to intercept a maneuvering intruder unmanned aerial vehicle (UAV). The interceptor multicopter can autonomously detect and intercept intruders moving at high speed in the air. The strapdown camera avoids the complex mechanical structure of the electro-optical pod, making the interceptor multicopter compact. However, the coupling of the camera and multicopter motion makes interception tasks difficult. To solve this problem, an image-based visual servoing (IBVS) controller is proposed to make the interception fast and accurate. Then, in response to the time delay of sensor imaging and image processing relative to attitude changes in high-speed scenarios, a delayed Kalman filter (DKF) observer is generalized to predict the current image position and increase the update frequency. Finally, hardware-in-the-loop (HITL) simulations and outdoor flight experiments verify that this method has a high interception accuracy and success rate. In the flight experiments, a high-speed interception is achieved with a terminal speed of 20 m/s.

Index Terms—Anti-drone system, delayed Kalman filter (DKF), high-speed interception, image-based visual servoing (IBVS).

I. INTRODUCTION

ADVANCES in micro air vehicles, also known as drones, are exploiting opportunities in industrial, agricultural, and military fields [1], [2]. The rapid expansion of the drone industry has outpaced regulations for the safe operation of drones, making them representative means of illegal and destructive terror and crime [3]. This has spurred the development of anti-drone (or counter-drone) technologies [4] to mitigate risks from drone accidents or terrorism, particularly against increasingly autonomous drones.

The drone interceptors can be classified as radio frequency interference [5], [6] and hard kill of enemy drones [7], [8]. However, due to the small size and high flexibility of fully




Fig. 1. Interception with drones.

autonomous drones [9], [10], using these ground-based devices to rapidly deploy and intercept intruders is a challenging task. A proposed solution is the use of drones with onboard sensors for effective interception, as depicted in Fig. 1.

A. Problem Statement and Challenges

Our previous research developed an image-based visual servoing (IBVS) algorithm with a forward-looking monocular camera for real flight experiments at 5 m/s [11]. This approach, however, struggles with high-speed interception tasks due to its reliance on the small-angle approximation, which fails at higher pitch angles observed during rapid movements, reaching up to 50°.

High-speed multicopter movement highlights significant challenges, particularly in camera imaging and processing. Delays around 100 ms lead to notable control errors, up to 2 m at speeds such as 20 m/s, challenging the assumption of flawless image processing. Moreover, the camera's imaging frequency falls short of the requirements for effective control. To solve the high-speed interception problem, two main research challenges are concluded.

C-1: The interceptor's high-speed and aggressive maneuverability necessitate a comprehensive attitude

Manuscript received 17 November 2023; revised 22 June 2024; accepted 21 August 2024. Date of publication 11 September 2024; date of current version 31 December 2024. This work was supported in part by the National Key Research and Development Program of China under Grant 2022YFA1005103 and in part by the National Natural Science Foundation of China under Grant 12371452. Recommended by Associate Editor C. Yang. (Corresponding author: Quan Quan.)

Kun Yang, Chenggang Bai, and Quan Quan are with the School of Automation Science and Electrical Engineering, Beihang University, Beijing 100191, China (e-mail: yangkun_buaa@buaa.edu.cn; bcg@buaa.edu.cn; qq_buaa@buaa.edu.cn).

Zhikun She is with the School of Mathematical Sciences, Beihang University, Beijing 100191, China (e-mail: zhikun.she@buaa.edu.cn).

Digital Object Identifier 10.1109/TCST.2024.3451293

1063-6536 © 2024 IEEE. Personal use is permitted, but republication/redistribution requires IEEE permission.
See <https://www.ieee.org/publications/rights/index.html> for more information.




Fig. 2. Classic architecture for an autonomous interception and racing system.

model and a redesigned controller that can handle extensive state space. This involves working within the 3-D special orthogonal group space, $SO(3)$, requiring the development of a controller for large-maneuver interception tasks.

C-2: The delayed, low frame rate, and easy loss of image feedback during the high-speed motion of the interceptor will lead to large interception errors. Accurate, real-time estimation of target coordinates on image is thus essential.

B. Related Work

1) Review on Autonomous Interception and Racing:

Drone racing's objective of precise gate traversal aligns with autonomous interception goals, meriting inclusion in our review [18]. Typical autonomous interception and racing systems, as shown in Fig. 2, consist of hardware (drones and sensors) and software (perception, planning, and control modules). Research in this field falls into three categories: location estimation-based, learning-based, and IBVS-based methods, as summarized in Table I.

Location estimation-based methods, using a perception-planning-control pipeline, were evident in MBZIRC 2020, with teams implementing such strategies to intercept both stationary and moving targets [12], [13], [14], [19]. These methods depend heavily on estimation accuracy, planning rationality, and control accuracy for interception accuracy.

Learning-based methods involve neural networks replacing traditional perception, planning, and control modules. They focus on learning trajectories and predicting commands from visual inputs, offering robustness against system latencies and sensor noise [15], [16]. Despite their potential, the complexity of real-world data collection limits their application in actual flight scenarios.

IBVS-based methods eliminate the planning module to reduce errors from inaccurate location estimation and planning. These methods, focusing on bearing measurements, have led to innovations such as 3-D helical guidance laws [17] and the use of virtual cameras for tracking targets [20], [21]. This article particularly explores the IBVS controller within the $SO(3)$ space for effective large-maneuver interceptions.

2) *Review on Delayed State Estimation:* Indoor and outdoor localization systems frequently encounter measurement delays and losses, especially in non-line-of-sight (NLOS) situations. This is akin to the challenges posed by visual sensor delays in drone technology. In indoor systems, strategies, such as finite impulse response (FIR) filters, have been developed, where lost measurements are predicted based on previous estimates [22], [23]. For outdoor systems, particularly those using GPS in obstacle-rich environments, variational Bayesian




Fig. 3. Relationship among visual servo model, controller, and state observer.

(VB)-based Kalman filters are employed, utilizing Bernoulli variables for time delay and state variable estimation [24].

Despite these developments, modeling visual sensor delays in state estimation remains a challenge. Our approach, inspired by [25], recalculates states over the delay period to address this challenge. To minimize computational demands, we update the covariance matrix as if there were no delay, adjusting it with an additional correction term when the delayed measurement arrives. This results in suboptimal estimates during the delay but optimal ones post-delay. We introduce the delayed Kalman filter (DKF) to manage delayed image measurements and real-time multicopter feedback, achieving high frame rate real-time image state estimates. This method, validated through simulations and experiments, effectively addresses issues related to delayed, low frame rate, and easily lost image feedback.

C. Proposed Methods and Main Contributions

This article introduces a novel approach for using multicopters to intercept aerial targets. We propose a controller on $SO(3)$ based on IBVS for high-speed, large-maneuver interceptions, and a DKF observer to counteract image delays in high-speed situations.







The contributions of this article are summarized as follows.

- 1) An IBVS scheme is applied to high-speed interception, addressing the challenge of coupling between aircraft motion and feature point imaging when the camera is fixedly mounted on the aircraft body. This ensures that the target remains within the camera's field of view (FOV) during high-speed and large-maneuver interception control.
- 2) A delay filtering scheme is proposed to address the limitations associated with delayed feedback, low frame rates, and potential loss of image feedback.
- 3) The experiments verified the effectiveness of the algorithm. These experiments are rare in showcasing a multicopter flying at high speeds exceeding 20 m/s, with a maximum pitch angle reaching 50° , relying solely on its onboard perception and control.

D. Outline

The overall system architecture is shown in Fig. 3. In Section II, the high-speed multicopter interception problem

TABLE I
AUTONOMOUS INTERCEPTION AND RACING OF DRONES

Category	Method	Feature	Target speed	Interceptor speed	Pipeline
Location estimation-based	Classical perception-planning-control pipeline [12], [13]	Second place in Challenge 1 in MBZIRC 2020	0 m/s; 7 m/s	2 - 3 m/s; Almost no mobility	
	Optimal terminal-velocity-control guidance [14]	Make further improvement on the basis of Challenge 1 in MBZIRC 2020 (first place)	10 m/s	10 m/s	
Learning-based	Imitation learning and low-level control [15]	The neural network generates a minimum-jerk trajectory and the controller tracks it. First to demonstrate zero-shot sim-to-real transfer on drone racing	Simulation: move slowly; Real flight: static narrow gates	4 - 12 m/s; 1 - 3 m/s	
	End to end, imitation learning [16]	The neural network predicts commands directly from vision. Inputs are a sequence of images and drone state but no globally-consistent position	Simulation: static gates	>10 m/s	
IBVS-based	Pseudo-linear Kalman filter and 3-D helical guidance law [17]	A new 3-D helical guidance law is designed based on the theoretical conclusion of the observability enhancement	5 m/s	Helical tracking	
	Perception and IBVS controller [11]	Use only a camera for autonomous UAV interception tasks, no global position is required	Simulation: 10 m/s; Real flight: 2 m/s	12 m/s; 5 m/s	

is formulated and divided into the optimal state estimation problem and the attitude loop controller design problem. Then, the attitude loop controller is designed based on the Lyapunov control theory and its stability is shown in Section III, and the DKF is proposed as a state observer to solve the optimal state estimation problem in Section IV. Finally, necessary simulations and real flight experiments are shown in Sections V and VI, respectively, and a conclusion is drawn in Section VII.

II. MODEL AND PROBLEM FORMULATION

In this section, the six-degree-of-freedom (6-DOF) rigid model of multicopter and the IBVS model are proposed. With them, the interception controller design problem is formulated. Furthermore, the sensor measurement model is proposed and the state observer problem is conducted.

The relationship among the multicopter and IBVS models, the controller, and the state observer is shown in Fig. 3. The interception controller calculates the control signal by the image error and the multicopter state, and the DKF state observer estimates the current image features based on the multicopter state and the delayed image features. The specific forms of the three parts are introduced separately to achieve precise interception control under high-speed conditions.

A. Coordinate Systems and Models

1) *Coordinate Systems*: There are five coordinate systems used in this article, as shown in Fig. 4.

- 1) $\{e\} = \{o_e - x_e y_e z_e\}$ is the Earth-fixed coordinate system (EFCS), which is used to represent the position and velocity of interceptors and targets in the global inertial system.
- 2) $\{b\} = \{o_b - x_b y_b z_b\}$ is the body coordinate system (BCS), which is used to represent the variables of the current attitude of interceptors.
- 3) $\{c\} = \{o_c - x_c y_c z_c\}$ is the camera coordinate system (CCS).
- 4) $\{i\} = \{o_i - x_i y_i\}$ is the image coordinate system (ICS), used to express the image position of target features in the first-person view (FPV) of cameras.

Throughout this article, superscripts $(^F \mathbf{r})$ ($F = e, b, c, i$) are used to specify in which coordinate frame a 3-D vector $\mathbf{r}$ is formulated. Matrix $\mathbf{R}_{F_1}^{F_2}$ represents a rotation matrix from coordinate system F_1 to F_2 , $\mathbf{R}_{F_1}^{F_2} \in \text{SO}(3)$, where the 3-D special orthogonal group is given by

$$\text{SO}(3) = \left\{ \mathbf{R} \in \mathbb{R}^{3 \times 3} \mid \mathbf{R}^T \mathbf{R} = \mathbf{I}, \det(\mathbf{R}) = 1 \right\}.$$

2) *Multicopter Model*: The multicopter (interceptor) is modeled as a rigid body of mass m with a rotor drag proportional to its velocity [26], [27]. Its flight control rigid




Fig. 4. Description of the interception problem. ${}^e\mathbf{p}$ and ${}^e\mathbf{p}_t$, respectively, represent the position of the intercepting multicopter and the target in EFCS. ${}^i\mathbf{p} = [p_{x_i} \ p_{y_i}]^T$ is the coordinate of the target in ICS; $\mathbf{n}_t$ represents the target unit vector along the line of sight (LOS) in EFCS; $\mathbf{n}_c$ represents the optical axis unit vector in EFCS; $\mathbf{n}_d$ is defined as the unit vector of the designed LOS in EFCS, called the designed LOS vector; and ${}^i\mathbf{p}_{td}$ is the intersection of $\mathbf{n}_{td}$ with the image plane in ICS, called the intercept point.

model is summarized as

$$\begin{cases} {}^e\dot{\mathbf{p}} = {}^e\mathbf{v} \\ {}^e\dot{\mathbf{v}} = \mathbf{g} + \frac{1}{m}({}^e\mathbf{f} + {}^e\mathbf{f}_{\text{drag}}) \\ \dot{\mathbf{R}}_b^e = \mathbf{R}_b^e [{}^b\boldsymbol{\omega}]_{\times} \\ \mathbf{J} \cdot {}^b\dot{\boldsymbol{\omega}} = -{}^b\boldsymbol{\omega} \times (\mathbf{J} \cdot {}^b\boldsymbol{\omega}) + \mathbf{G}_a + \boldsymbol{\tau} \end{cases} \quad (1)$$

where ${}^e\mathbf{p} = [p_{x_e} \ p_{y_e} \ p_{z_e}]^T$ is the position of the multicopter under EFCS; ${}^e\mathbf{v} = [v_{x_e} \ v_{y_e} \ v_{z_e}]^T$ is the velocity under EFCS; ${}^e\mathbf{a} = \mathbf{g} + (1/m)({}^e\mathbf{f} + {}^e\mathbf{f}_{\text{drag}})$ is the accelerate under EFCS; m is the mass of the multicopter; $\mathbf{g}$ is the local gravitational acceleration, $\mathbf{g} = [0 \ 0 \ g]^T$; ${}^e\mathbf{f} \in \mathbb{R}^3$ is the controllable force of the multicopter in EFCS; ${}^e\mathbf{f}_{\text{drag}} = -\mathbf{R}_b^e \mathbf{D} \mathbf{R}_b^{eT} {}^e\mathbf{v}$ is the aerodynamic drag force of the multicopter in EFCS, in which $\mathbf{D} = \text{diag}(d_x, d_y, d_z)$ is a constant diagonal matrix that defines the rotor-drag coefficients; ${}^b\boldsymbol{\omega} = [\omega_{x_b} \ \omega_{y_b} \ \omega_{z_b}]^T$ is the angular velocity under BCS; $\mathbf{J}$ is the multicopter moments of inertia; $\mathbf{G}_a$ is gyroscopic torque; and $\boldsymbol{\tau}$ is the moments generated by the propellers in the body axes. Matrix $[{}^b\boldsymbol{\omega}]_{\times}$ is a skew-symmetric matrix, which is a cross-product map of the angular velocity ${}^b\boldsymbol{\omega}$.

The cross-product map $[\cdot]_{\times}: \mathbb{R}^3 \rightarrow \mathfrak{so}(3)$ is defined such that $[\mathbf{x}]_{\times} \mathbf{y} = \mathbf{x} \times \mathbf{y}$ and $[\mathbf{x}]_{\times}^T = -[\mathbf{x}]_{\times}$ for any $\mathbf{x}, \mathbf{y} \in \mathbb{R}^3$. The inverse of the cross-product map is denoted by the vex map $\text{vex}(\cdot): \mathfrak{so}(3) \rightarrow \mathbb{R}^3$, where the set of 3×3 skew-symmetric matrices is denoted by $\mathfrak{so}(3) = \{\mathbf{S} \in \mathbb{R}^{3 \times 3} | \mathbf{S} = -\mathbf{S}^T\}$. For $\mathbf{x} \triangleq$

$[x_1 \ x_2 \ x_3]^T \in \mathbb{R}^3$, the cross-product map and the vex map are summarized as

$$[\mathbf{x}]_{\times} \triangleq \begin{bmatrix} 0 & -x_3 & x_2 \\ x_3 & 0 & -x_1 \\ -x_2 & x_1 & 0 \end{bmatrix}, \quad \text{vex}([\mathbf{x}]_{\times}) \triangleq \mathbf{x}.$$

For multicopters, the controllable force is generated by the thrust of the propellers as

$${}^e\mathbf{f} = f \mathbf{R}_b^e \mathbf{R}_f \mathbf{e}_3 = f \mathbf{n}_f \quad (2)$$

where $0 \leq f \leq f_m$, in which f_m is the maximum thrust; $\mathbf{R}_f \in \text{SO}(3)$ is the rotation matrix transforming the thrust vector to $o_b z_b$ -axis in BCS; and $\mathbf{R}_f$ is constant for multicopters because the propellers provide thrust in a fixed direction relative to the fuselage and variable for tiltrotor aircraft. Vector $\mathbf{e}_3$ is the third column of the 3×3 identity matrix $\mathbf{I}$, $\mathbf{I} = [\mathbf{e}_1 \ \mathbf{e}_2 \ \mathbf{e}_3]$, $\mathbf{e}_3 = [0 \ 0 \ 1]^T$. Vector $\mathbf{n}_f$ is the unit vector of ${}^e\mathbf{f}$.

3) *Target Model*: The target model's motion is represented using a point-mass model as

$$\begin{cases} {}^e\dot{\mathbf{p}}_t = {}^e\mathbf{v}_t \\ {}^e\dot{\mathbf{v}}_t = {}^e\mathbf{a}_t \end{cases} \quad (3)$$

where ${}^e\mathbf{p}_t \in \mathbb{R}^3$, ${}^e\mathbf{v}_t \in \mathbb{R}^3$, and ${}^e\mathbf{a}_t \in \mathbb{R}^3$ are the target's position, velocity, and acceleration under EFCS, respectively.

Using $\mathbf{p}_r$ to indicate the relative position of the interceptor and target in EFCS, $\mathbf{p}_r = {}^e\mathbf{p} - {}^e\mathbf{p}_t$. Furthermore, the relative velocity is defined as $\mathbf{v}_r = {}^e\mathbf{v} - {}^e\mathbf{v}_t$ and $\dot{\mathbf{p}}_r = \mathbf{v}_r$; the relative acceleration is defined as $\mathbf{a}_r = {}^e\mathbf{a} - {}^e\mathbf{a}_t$ and $\dot{\mathbf{v}}_r = \mathbf{a}_r$. Note that measuring the target's motion acceleration ${}^e\mathbf{a}_t$ using visual sensors is challenging. Therefore, in the design of both the controller and the state observer, ${}^e\mathbf{a}_t$ is considered as a disturbance.

4) *Camera Imaging Model*: As shown in Fig. 4, the perspective projection performs a mapping from the 3-D space to the 2-D image plane: $\mathbb{R}^3 \rightarrow \mathbb{R}^2$.

Assumption 1: The origin of CCS coincides with the origin of BCS, that is, their translation vector $\mathbf{t}_c^b = \mathbf{0}$. Due to the strapdown camera configuration, the rotation matrix $\mathbf{R}_c^b$ is constant.

The camera used in this article is fixed to the body, and it is considered a successful interception when the camera is in contact with the target. Thus, the optical axis has a constant rotation $\mathbf{R}_c^b$ with the multicopter head direction.

The LOS is a line between the interceptor and the target. The unit vector along it from the interceptor to the target is called the *LOS vector*, denoted as $\mathbf{n}_t$. When the target is in the sensor's FOV, all types of sensors above can be transformed into the perspective view through a unified imaging model [28, Ch. 11]. Vector $\mathbf{n}_t$ is expressed as the unit vector in the negative direction of $\mathbf{p}_r$ or obtained by image coordinates and focal of length f_{oc} as

$$\begin{aligned} \mathbf{n}_t &= -\frac{\mathbf{p}_r}{\|\mathbf{p}_r\|} \\ &= \mathbf{R}_b^e \mathbf{R}_c^b \frac{[p_{x_i} \ p_{y_i} \ f_{oc}]^T}{\|[p_{x_i} \ p_{y_i} \ f_{oc}]^T\|}. \end{aligned} \quad (4)$$

The FOV is the range of the observable area that a perception sensor can image, including the horizontal FOV (HFOV) and vertical FOV (VFOV). The parameters α_{hfov} and α_{vfov} are the angles of HFOV and VFOV of the perception sensor, respectively. The FOV is defined as $\mathcal{C} = \{\mathbf{x} \mid |\arctan(x_{c1}/x_{c3})| \leq (1/2)\alpha_{\text{hfov}}, |\arctan(x_{c2}/x_{c3})| \leq (1/2)\alpha_{\text{vfov}}\}$, where ${}^c\mathbf{x} \triangleq [x_{c1} \ x_{c2} \ x_{c3}]^T$ is $\mathbf{x}$ in CCS.

The camera imaging is subject to the FOV constraint that the target is within the sensor's FOV

$$\mathbf{n}_t \in \mathcal{C}. \quad (5)$$

The designed LOS vector $\mathbf{n}_{td}$ can be simply conceptualized as the optical axis vector $\mathbf{n}_c$. In pursuit of enhancing the interceptor's maneuverability, $\mathbf{n}_{td}$ is crafted to approximate the force vector $\mathbf{n}_f$ as closely as possible within the FOV. Upon achieving the collinear control objective, a greater component of acceleration is directed along $\mathbf{n}_{td}$, thereby endowing the interceptor with increased interception velocity.

5) *IBVS Model*: The image Jacobian matrix [29] can represent the relationship between camera motion and image features motion as

$$\begin{aligned} \dot{{}^i\mathbf{p}} &= \mathbf{L}_s {}^c\tilde{\mathbf{v}} \\ \mathbf{L}_s &= \begin{bmatrix} -\frac{1}{p_{zc}} & 0 & \frac{\bar{p}_{xi}}{p_{zc}} & \bar{p}_{xi}\bar{p}_{yi} & -(1+\bar{p}_{xi}^2) & \bar{p}_{yi} \\ 0 & -\frac{1}{p_{zc}} & \frac{\bar{p}_{yi}}{p_{zc}} & 1+\bar{p}_{yi}^2 & -\bar{p}_{xi}\bar{p}_{yi} & -\bar{p}_{xi} \end{bmatrix} \end{aligned} \quad (6)$$

where ${}^c\tilde{\mathbf{v}} = [{}^c\mathbf{v}^T \ {}^c\omega^T]^T$ represents the twist in CCS, including the linear and angular velocity of a rigid body; and ${}^i\mathbf{p} = [\bar{p}_{xi} \ \bar{p}_{yi}]^T = [p_{xi}/f_{oc} \ p_{yi}/f_{oc}]^T$ represents the normalized image coordinate of features in ICS.

B. State Equation and Measurement Equations

In addition to the multicopter rigid model and the IBVS model, the description of the multicopter interception process requires knowledge of the measurement equations, including inertial measurement unit (IMU) measurement and delayed image measurement.

1) *System Model*: Logarithmic mapping $\ln(\cdot) : \text{SO}(3) \rightarrow \mathfrak{so}(3)$ converts rotation matrix $\mathbf{R}_b^e$ into a rotation angle $\theta \in [-\pi, \pi)$ and a unit rotation vector $\mathbf{a} \in \mathbb{R}^3$, that is,

$$[\theta\mathbf{a}]_{\times} = \ln(\mathbf{R}_b^e) = \sum_{i=0}^{\infty} \frac{(-1)^i}{i+1} (\mathbf{R}_b^e - \mathbf{I})^{i+1}.$$

A 4-D vector is used to compactly represent interceptor's rotation matrix $\mathbf{R}_b^e$, called orientation quaternion $\mathbf{q} = [\cos(\theta/2) \ \mathbf{n}^T \sin(\theta/2)]^T \in \mathbb{R}^4$. The normalized image coordinate of the center of the target is considered the feature point and is denoted as ${}^i\mathbf{p}$. The state variable $\mathbf{x} = [\mathbf{q}^T \ \mathbf{p}_r^T \ \mathbf{v}_r^T \ {}^i\mathbf{p}^T \ \mathbf{b}_{\text{gyr}}^T \ \mathbf{b}_{\text{acc}}^T]^T \in \mathbb{R}^{18}$ consists of some necessary states, including interceptor's orientation quaternion $\mathbf{q}$, relative position $\mathbf{p}_r$ and relative velocity $\mathbf{v}_r$, image feature point ${}^i\mathbf{p}$, gyroscope bias $\mathbf{b}_{\text{gyr}} = [b_{\text{gyr},x} \ b_{\text{gyr},y} \ b_{\text{gyr},z}]^T$, and accelerometer bias $\mathbf{b}_{\text{acc}} = [b_{\text{acc},x} \ b_{\text{acc},y} \ b_{\text{acc},z}]^T$.

The discrete state equation is written as

$$\mathbf{x}_k = \mathbf{F}_k \mathbf{x}_{k-1} + \mathbf{G}_k \mathbf{w}_{k-1}$$

where $\mathbf{F}_k \in \mathbb{R}^{18 \times 18}$ and $\mathbf{G}_k \in \mathbb{R}^{18 \times 6}$ are the state transition matrix and the noise matrix from time t_{k-1} to time t_k , respectively; and $\mathbf{w}_k$ is the process noise vector, where the elements follow the Gaussian distribution with zero mean and uncorrelated, $\mathbf{w}_k \sim \mathcal{N}(\mathbf{0}_{6 \times 1}, \mathbf{Q}_k)$, $\mathbf{Q}_k \in \mathbb{R}^{6 \times 6}$. Vector $\mathbf{w}_k$ consists of gyroscope bias noise $\mathbf{n}_{\text{gyr}}$ and accelerometer bias noise $\mathbf{n}_{\text{acc}}$, $\mathbf{w}_k = [\mathbf{n}_{\text{gyr}}^T \ \mathbf{n}_{\text{acc}}^T]^T$.

2) *IMU Measurements*: IMU provides gyroscope angle increment and accelerometer velocity increment under BCS. Combining these measurements with the multicopter rigid model (1), the recursive expressions of states $\mathbf{q}$ and $\mathbf{v}_r$ are obtained.

- 1) The derivative of the orientation quaternion $\mathbf{q}$, which is the angular velocity ${}^b\omega$, is obtained from the gyroscope measurement as

$${}^b\omega = \omega_{\text{gyr}} - \mathbf{b}_{\text{gyr}} - \mathbf{n}_{\text{gyr}} \quad (7)$$

where the gyroscope measurement noise $\mathbf{n}_{\text{gyr}}$ is a zero-mean Gaussian random variable; the bias $\mathbf{b}_{\text{gyr}}$ obeys the Wiener process

$$\dot{\mathbf{b}}_{\text{gyr}} = \mathbf{n}_{\text{b}_{\text{gyr}}}. \quad (8)$$

- 2) The derivative of the velocity $\mathbf{v}_r$, which is the acceleration ${}^e\mathbf{a}$, is obtained from the measured value of the accelerometer as

$${}^e\mathbf{a} = g\mathbf{e}_3 + \mathbf{R}_b^e (\mathbf{a}_{\text{acc}} - \mathbf{b}_{\text{acc}} - \mathbf{n}_{\text{acc}}) \quad (9)$$

where the accelerometer measurement noise $\mathbf{n}_{\text{acc}}$ is a zero-mean Gaussian random variable; the bias $\mathbf{b}_{\text{acc}}$ obeys the Wiener process

$$\dot{\mathbf{b}}_{\text{acc}} = \mathbf{n}_{\text{b}_{\text{acc}}}. \quad (10)$$

3) *Delayed Image Measurements*: Image processing provides the image coordinates of the target point, and the state ${}^i\mathbf{p}$ is obtained after normalization. Since camera imaging and image processing take time, the measured value obtained is data from a period ago. Suppose that the measured delay is D cycles based on the IMU update frequency, and the delay time $t_D > 0$ is known. Then, the image measurement at time t is expressed as

$${}^i\tilde{\mathbf{p}}_{\text{img},k} = {}^i\tilde{\mathbf{p}}_{k-D} + \mathbf{n}_{\text{img}} \quad (11)$$

where the image measurement noise $\mathbf{n}_{\text{img}}$ is a zero-mean Gaussian random variable. Note that the delay time t_D involves camera imaging and image processing time and was estimated using two methods: 1) direct calculation based on camera parameters and internal program timers and 2) experimental measurement involving capturing a timer with the camera.

C. Controller Design and State Observer Problem Formulation

Based on Assumption 1, the controller design and state observer problems are summarized as follows.

Problem 1 (Controller Design Problem): Under Assumption 1, it is assumed that the state information, including the multicopter and the image measurement, is accurately




Fig. 5. High-speed interception control process. The process for intercepting a lower target is (a)–(b), and the process for intercepting a higher target is (c)–(d)–(b).

available. At the same time, the positions of target and interceptor in the inertial system are unknown. For the interceptor model (1), design controllers for f and ${}^b\omega$ such that the target unit vector remains proximate to the designed LOS vector, i.e., $1 - \mathbf{n}_{td}^T \mathbf{n}_t < \epsilon$, where $\epsilon > 0$ is a range threshold, and the interceptor multicopter further approaches the target, i.e., $\mathbf{p}_r \rightarrow \mathbf{0}$.

Problem 2 (State Observer Problem): Given the initial value $\mathbf{x}(0)$, model error and measurement error distribution, how can we use IMU measurements and delayed image measurements to calculate more accurate status information?

In Problem 1, a controller is designed to perform the interception task with accurate image measurement and IMU information feedback. However, due to the time required for camera imaging and processing, around 80 ms for color recognition in our experiments, significant errors can occur in high-speed flights. To mitigate control quality degradation from such delays, image estimation methods are essential. The challenge of choosing a suitable state vector $\mathbf{x}$ and estimating the position of image features in real time with a filter is addressed in Problem 2.

III. HIGH-SPEED INTERCEPTION CONTROL BASED ON ROTATION MATRIX

In this section, Problem 1 is solved by designing the angular velocity controller so that the designed LOS vector $\mathbf{n}_{td}$, the velocity vector $\mathbf{v}_r$, and the target unit vector $\mathbf{n}_t$ are collinear. The detailed derivations and proof of the theorem in this section are placed in Appendix A.




Fig. 6. Entire control scheme. The high-speed interception controller is divided into a collinear controller in the outer loop and an attitude controller in the inner loop.

Algorithm 1 f_d and $\omega_d = \text{InterceptionController}(\bar{\mathbf{p}}, \mathbf{v}_r, \mathbf{R}_b^e)$

Input: Image measurement, relative velocity and self attitude

Output: Interception controller commands

- 1: Initialize $\mathbf{a}_d = \mathbf{0}$, $\mathbf{R}_d = \mathbf{R}_b^e$
- 2: **while** Interception in progress **do**
- 3: Calculate $\mathbf{n}_t$ from $\bar{\mathbf{p}}$ and Eq. (4)
- 4: Calculate the attitude controller commands f_d , ω_d according to Eqs. (23), (26)
- 5: **if** $\bar{\mathbf{p}}$ comes **then**
- 6: Calculate the collinear controller commands ω_1 and attitude controller desired value $\mathbf{a}_d$, $\mathbf{R}_d$ according to Eqs. (13), (19), (22)
- 7: $\omega_d = \omega_d + \omega_1$
- 8: **end if**
- 9: wait(T). T = iteration time - this loop time
- 10: **end while**

A. High-Speed Interception Control Process

Fig. 5(a)–(c) illustrates the design of the attitude rate loop controller, aiming to align the designed LOS vector $\mathbf{n}_{td}$ and the target unit vector $\mathbf{n}_t$ for effective target locking and interception. However, in initial states where the target is above the interceptor, as shown in Fig. 5(c), this alignment alone can cause backward acceleration. Given the multicopter's underactuated nature, where acceleration and attitude are coupled, it is crucial to also ensure the collinearity of the velocity vector $\mathbf{v}_r$ and the target unit vector $\mathbf{n}_t$. This approach allows for the calculation of desired force $\mathbf{f}_d$ and rotation matrix $\mathbf{R}_d$ in achieving the desired velocity.

The controller follows two main objectives: ensuring the collinearity of the LOS vector and the target unit vector, and aligning the velocity vector with the target unit vector. The high-speed interception controller comprises two parts: a collinear controller (Section III-B) as the outer loop running at 50 Hz and an attitude controller (Section III-C) as the inner loop running at 200 Hz. The collinear controller ensures that the target remains within FOV, while the attitude controller guarantees that the multicopter's velocity and attitude accurately track the reference values from the outer loop controller. This controller is outlined in Fig. 6 and Algorithm 1.

B. Collinear Control Design for Designed LOS Vector and Target Unit Vector

Let LOS tracking error as $z_1 = 1 - \mathbf{n}_{td}^T \mathbf{n}_t$ and take the derivative of it, and we have

$$\begin{aligned}\dot{z}_1 &= -(\mathbf{n}_{td}^T \dot{\mathbf{n}}_t + \mathbf{n}_t^T \dot{\mathbf{n}}_{td}) \\ &= -\frac{1}{\|\mathbf{p}_r\|} \mathbf{n}_{td}^T (-\mathbf{I} + \mathbf{n}_r \mathbf{n}_t^T) \mathbf{v}_r - (\mathbf{n}_{td} \times \mathbf{n}_t)^T e \omega.\end{aligned}$$

Choose the following barrier Lyapunov candidate function:

$$L_1 = \frac{1}{2} \log \frac{k_b^2}{k_b^2 - z_1^2} \quad (12)$$

where $\log(\cdot)$ denotes the natural logarithm and k_b is constant on z_1 , that is, we require $|z_1| < k_b$. The derivative of (12) along (37) is

$$\begin{aligned}\dot{L}_1 &= \frac{z_1 \dot{z}_1}{k_b^2 - z_1^2} \\ &= -\frac{z_1}{k_b^2 - z_1^2} \frac{1}{\|\mathbf{p}_r\|} \mathbf{n}_{td}^T (-\mathbf{I} + \mathbf{n}_r \mathbf{n}_t^T) \mathbf{v}_r \\ &\quad - \frac{z_1}{k_b^2 - z_1^2} (\mathbf{n}_{td} \times \mathbf{n}_t)^T e \omega.\end{aligned}$$

The first term is equal to 0 when $\mathbf{v}_r$ and $\mathbf{n}_t$ are collinear, which will be designed in Section III-C. The designed angular velocity makes the second term negative. For control purposes, designed LOS vector $\mathbf{n}_{td}$ and target unit vector $\mathbf{n}_t$ are collinear. Then,

$$\begin{aligned}e \omega &= \frac{z_1}{k_b^2 - z_1^2} (\mathbf{n}_{td} \times \mathbf{n}_t) \\ \Rightarrow b \omega_1 &= \frac{z_1}{k_b^2 - z_1^2} \mathbf{R}_b^T (\mathbf{n}_{td} \times \mathbf{n}_t).\end{aligned} \quad (13)$$

According to the physical meaning of the vector cross product, this control command represents the rotational angular velocity from $\mathbf{n}_{td}$ to $\mathbf{n}_t$. The term $(z_1/(k_b^2 - z_1^2))$ acts as a proportional coefficient, which becomes larger as the LOS tracking error z_1 approaches the barrier k_b .

C. Collinear Control Design for Velocity Vector and Target Unit Vector

The Lyapunov candidate function is designed as

$$L_2 = \frac{1}{2} \mathbf{p}_r^T \mathbf{p}_r \geq 0. \quad (14)$$

The derivative of (14) is

$$\dot{L}_2 = \mathbf{p}_r^T \mathbf{v}_r. \quad (15)$$

According to Lyapunov's second method, in order to make the system stable, $\dot{L}_2$ is expected to be negative definite. Let $\mathbf{v}_{rd} = -k_1 \mathbf{p}_r = k_1 \|\mathbf{p}_r\| \mathbf{n}_t$ with k_1 being a positive constant, which means that desired relative velocity vector $\mathbf{v}_r$ is collinear with target unit vector $\mathbf{n}_t$. Then, rewrite (15) as

$$\begin{aligned}\dot{L}_2 &= \mathbf{p}_r^T (\mathbf{v}_r - \mathbf{v}_{rd} + \mathbf{v}_{rd}) \\ &= \mathbf{p}_r^T \mathbf{z}_2 - k_1 \mathbf{p}_r^T \mathbf{p}_r.\end{aligned} \quad (16)$$

Let a tracking error as $\mathbf{z}_2 = \mathbf{v}_r - \mathbf{v}_{rd} = \mathbf{v}_r + k_1 \mathbf{p}_r$ and take the derivative of it, and we have

$$\dot{\mathbf{z}}_2 = \mathbf{a}_r + k_1 \mathbf{v}_r.$$

Define a new Lyapunov candidate function as

$$L_3 = L_1 + L_2 + \frac{1}{2} \mathbf{z}_2^T \mathbf{z}_2 \geq 0. \quad (17)$$

The derivative of (17) is

$$\begin{aligned}\dot{L}_3 &= -\frac{z_1}{k_b^2 - z_1^2} \frac{1}{\|\mathbf{p}_r\|} \mathbf{n}_{td}^T (-\mathbf{I} + \mathbf{n}_r \mathbf{n}_t^T) \mathbf{z}_2 \\ &\quad - \frac{z_1}{k_b^2 - z_1^2} (\mathbf{n}_{td} \times \mathbf{n}_t)^T e \omega \\ &\quad + \mathbf{p}_r^T \mathbf{z}_2 - k_1 \mathbf{p}_r^T \mathbf{p}_r + \mathbf{z}_2^T (\mathbf{a}_r + k_1 \mathbf{v}_r).\end{aligned} \quad (18)$$

In order for the system to be stable, $\dot{L}_3$ is expected to be negative definite. Thus, let $\mathbf{a}_r = -k_1 \mathbf{v}_r - k_2 \mathbf{z}_2 - \mathbf{p}_r + (z_1/(k_b^2 - z_1^2))(\mathbf{n}_{td} \times \mathbf{n}_t)^T e \omega$ and k_2 is a positive constant. The desired acceleration $\mathbf{a}_d$ is designed as

$$\begin{aligned}\mathbf{a}_d &= -k_1 \mathbf{v}_r - k_2 \mathbf{z}_2 - \mathbf{p}_r + \frac{z_1}{k_b^2 - z_1^2} \frac{m}{\|\mathbf{p}_r\|} (-\mathbf{I} + \mathbf{n}_r \mathbf{n}_t^T) \mathbf{n}_{td} \\ &\quad + e \mathbf{a}_t.\end{aligned} \quad (19)$$

1) *Control Design for Desired Acceleration $\mathbf{a}_d$* : The desired acceleration $\mathbf{a}_d$ is designed to realize the difference between the actual velocity and the desired velocity. According to the multicopter dynamics model (1), we have

$$\mathbf{a}_d = \mathbf{g} + \frac{f}{m} \mathbf{n}_{fd} + \frac{1}{m} e \mathbf{f}_{\text{drag}}. \quad (20)$$

Then,

$$\mathbf{n}_{fd} = \frac{m \mathbf{a}_d - m \mathbf{g} - e \mathbf{f}_{\text{drag}}}{f_d}.$$

Because $\mathbf{n}_{fd}$ satisfies $\mathbf{n}_{fd}^T \mathbf{n}_{fd} = 1$, the above equation becomes

$$\mathbf{n}_{fd} = \frac{\mathbf{a}_d - \mathbf{g} - e \mathbf{f}_{\text{drag}}/m}{\|\mathbf{a}_d - \mathbf{g} - e \mathbf{f}_{\text{drag}}/m\|}. \quad (21)$$

Since the yaw motion of the interceptor will cause the target to move laterally on the image, it is better to maintain the current yaw to achieve the desired attitude $\mathbf{R}_d$. A rotation that includes only pitch-roll is defined as $\mathbf{R}_{\text{tilt}}$, and the calculation of $\mathbf{R}_{\text{tilt}}$ takes the cross product of the current frame and the desired frame [30]. The cross product of $\mathbf{n}_f$ and $\mathbf{n}_{fd}$ is the rotation axis $\mathbf{r}$ of $\mathbf{R}_{\text{tilt}}$, $\mathbf{r} = \mathbf{n}_f \times \mathbf{n}_{fd}$. Also, the angle ϕ between these two axes is the rotation angle, $\phi = \arccos(\mathbf{n}_f^T \mathbf{n}_{fd})$. Therefore, the desired attitude of interceptor $\mathbf{R}_d$ is obtained as

$$\begin{aligned}\mathbf{R}_d &= \mathbf{R}_{\text{tilt}} \mathbf{R}_b^e \\ \mathbf{R}_{\text{tilt}} &= e^{\phi[\mathbf{r}]_{\times}} = \mathbf{I} + [\mathbf{r}]_{\times} \sin \phi + [\mathbf{r}]_{\times}^2 (1 - \cos \phi)\end{aligned} \quad (22)$$

where the exponential map $e^{(\cdot)}: \mathfrak{so}(3) \rightarrow \text{SO}(3)$ converts the rotation angle $\phi \in [-\pi, \pi)$ and unit rotation vector $\mathbf{r} \in \mathbb{R}^3$ into a rotation matrix $\mathbf{R}_{\text{tilt}}$.

Combining (19) and (21), the desired thrust is calculated as

$$f_d = \mathbf{n}_f^T (m \mathbf{a}_d - m \mathbf{g} - e \mathbf{f}_{\text{drag}}).$$

In practice, the thrust of a multicopter cannot be negative. Therefore, a saturation limit must be added as

$$f_d = \min \left(\max \left(\mathbf{n}_f^T (\mathbf{a}_d - m\mathbf{g} - {}^e\mathbf{f}_{\text{drag}}), 0 \right), f_m \right). \quad (23)$$

2) *Control Design for Desired Attitude Matrix $\mathbf{R}_d$* : The Lyapunov candidate function is designed as

$$L_4 = \text{tr}(\mathbf{I} - \mathbf{R}_d^T \mathbf{R}_b^e). \quad (24)$$

When the actual attitude $\mathbf{R}_b^e$ of the interceptor is consistent with the desired attitude $\mathbf{R}_d$, $\mathbf{R}_d^T \mathbf{R}_b^e = \mathbf{I}$. The Frobenius norm is used to define the matrix error

$$\begin{aligned} \|\mathbf{I} - \mathbf{R}_d^T \mathbf{R}_b^e\|_F &= \sqrt{\text{tr}((\mathbf{I} - \mathbf{R}_d^T \mathbf{R}_b^e)(\mathbf{I} - \mathbf{R}_d^T \mathbf{R}_b^e)^T)} \\ &= \sqrt{2\text{tr}(\mathbf{I} - \mathbf{R}_d^T \mathbf{R}_b^e)}. \end{aligned}$$

Therefore, $L_4 = \|\mathbf{I} - \mathbf{R}_d^T \mathbf{R}_b^e\|_F^2 / 2 \geq 0$. The derivative of (24) along (1) is [31], [32]

$$\begin{aligned} \dot{L}_4 &= -\text{tr} \left(\mathbf{R}_d^T \mathbf{R}_b^e \left[{}^b\omega \right]_{\times} \right) \\ &= \text{vex} \left(\mathbf{R}_d^T \mathbf{R}_b^e - \mathbf{R}_b^e \mathbf{R}_d \right)^T {}^b\omega. \end{aligned} \quad (25)$$

The angular velocity controller is designed as

$${}^b\omega_2 = -\text{vex} \left(\mathbf{R}_d^T \mathbf{R}_b^e - \mathbf{R}_b^e \mathbf{R}_d \right) \quad (26)$$

Then,

$$\dot{L}_4 = -\left\| \text{vex} \left(\mathbf{R}_d^T \mathbf{R}_b^e - \mathbf{R}_b^e \mathbf{R}_d \right) \right\|^2 \leq 0. \quad (27)$$

D. Stability Analysis

Based on the previous control objectives, the multicopter interceptor attitude loop controller is summarized as

$$\begin{cases} {}^b\omega_d = \text{sat}({}^b\omega_1 + {}^b\omega_2, \omega_m) \\ f_d = \min \left(\max \left(\mathbf{n}_f^T (\mathbf{a}_d - m\mathbf{g} - {}^e\mathbf{f}_{\text{drag}}), 0 \right), f_m \right). \end{cases} \quad (28)$$

The multicopter's maximum angular velocity is represented by ω_m , where $\omega_m > 0$. The function $\text{sat}(\cdot)$ is a saturation function defined as [33]

$$\begin{aligned} \text{sat}(\mathbf{a}, a_m) &= \kappa_{a_m}(\mathbf{a}) \mathbf{a}, \quad \mathbf{a} \in \mathbb{R}^n, \quad a_m \in \mathbb{R}_+ \\ \kappa_{a_m}(\mathbf{a}) &= \begin{cases} 1, & \|\mathbf{a}\| \leq a_m \\ a_m / \|\mathbf{a}\|, & \|\mathbf{a}\| > a_m. \end{cases} \end{aligned} \quad (29)$$

Remark 1: The angular velocity control component ${}^b\omega_1$ is designed to keep the target within the FOV by aligning the designed LOS vector with the target unit vector. Another component, ${}^b\omega_2$, aligns the velocity vector with the target unit vector to ensure that the interceptor's relative position converges to zero, achieving interception.

In practical applications, to ensure safety, saturation is applied to both angular velocity and thrust. The saturation function $\text{sat}(\cdot)$ and the saturation of thrust alter only the magnitude of the control variables, not their direction, thereby affecting the convergence speed but not the system's stability.

Theorem 1: Under Assumption 1, for a multicopter with strapdown camera model (1)–(4), the attitude controller is designed by (28). If the initial state satisfies $\mathbf{n}_t(0) \in \mathcal{S} = \{\mathbf{x} \mid |\mathbf{n}_{td}^T \mathbf{x}| > 1 - k_b\}$, then $\mathbf{n}_t \in \mathcal{S}$ and $\mathbf{p}_r \rightarrow 0$, as $t \rightarrow \infty$.

Proof: See Appendix A. $\square$

IV. DKF OBSERVER

In this section, we design a state observer to address Problem 2, using the multicopter's state and delayed image features to estimate current image features in real time. Our method employs an extended Kalman filter with Gaussian distributions, where the state progresses according to kinematics equations without process noise, and the covariance follows its linearized form. The approach includes both propagation and correction steps. Two main challenges are integrating delayed image measurements with concurrent IMU data during correction and handling the rotation matrix that evolves on the compact Lie group. These are tackled by treating the integration as an optimal prediction and representing the distribution using quaternions.

A. Prediction

The distribution at t_{k-1} is given by $\hat{\mathbf{x}}_{k-1}$ and $\mathbf{P}_{k-1}$. The goal of the prediction is to propagate them to the next time step t_k via (1)–(10). The one-step prediction of state $\mathbf{x}$ is

$$\hat{\mathbf{x}}_{k|k-1} = \mathbf{F}_k \hat{\mathbf{x}}_{k-1}. \quad (30)$$

As part of the propagation step, the covariance matrix $\mathbf{P}$ is updated by the well-known Kalman filter

$$\mathbf{P}_{k|k-1} = \mathbf{F}_k \mathbf{P}_{k-1} \mathbf{F}_k^T + \mathbf{G}_k \mathbf{Q}_k \mathbf{G}_k^T \quad (31)$$

where $\mathbf{F}_k \in \mathbb{R}^{18 \times 18}$ and $\mathbf{G}_k \in \mathbb{R}^{18 \times 6}$ are the state transition matrix and the noise matrix from time t_{k-1} to time t_k , respectively.

According to the continuous form of the state vector relation (1) and (6)–(11), the partial derivative of the state vector $\mathbf{x}_k$ at time t_k with respect to the state vector $\mathbf{x}_{k-1}$ at time t_{k-1} is obtained as $\mathbf{F}_k$ and $\mathbf{G}_k$

$$\begin{aligned} \mathbf{F}_k &= \begin{bmatrix} \mathbf{F}_{qk-1}^{qk} & \mathbf{0} & \mathbf{0} & \mathbf{0} & \mathbf{F}_{b_{gyr,k-1}}^{qk} & \mathbf{0} \\ \mathbf{0} & \mathbf{I}_{3 \times 3} & \mathbf{F}_{v_{r,k-1}}^{p_{r,k}} & \mathbf{0} & \mathbf{0} & \mathbf{0} \\ \mathbf{F}_{qk-1}^{v_{r,k}} & \mathbf{0} & \mathbf{I}_{3 \times 3} & \mathbf{0} & \mathbf{0} & \mathbf{F}_{b_{acc,k-1}}^{v_{r,k}} \\ \mathbf{F}_{qk-1}^{i_{p_k}} & \mathbf{0} & \mathbf{F}_{v_{r,k-1}}^{i_{p_k}} & \mathbf{F}_{i_{p_{k-1}}}^{i_{p_k}} & \mathbf{F}_{b_{gyr,k-1}}^{i_{p_k}} & \mathbf{0} \\ \mathbf{0} & \mathbf{0} & \mathbf{0} & \mathbf{0} & \mathbf{I}_{3 \times 3} & \mathbf{0} \\ \mathbf{0} & \mathbf{0} & \mathbf{0} & \mathbf{0} & \mathbf{0} & \mathbf{I}_{3 \times 3} \end{bmatrix} \\ \mathbf{G}_k &= \begin{bmatrix} \mathbf{G}_{b_{\omega k-1}}^{qk} & \mathbf{0} \\ \mathbf{0} & \mathbf{0} \\ \mathbf{0} & \mathbf{G}_{e_{a_{k-1}}}^{v_{r,k}} \\ \mathbf{G}_{b_{\omega k-1}}^{i_{p_k}} & \mathbf{0} \\ \mathbf{0} & \mathbf{0} \\ \mathbf{0} & \mathbf{0} \end{bmatrix}. \end{aligned}$$

The relationships between orientation quaternion, position, velocity, image features, gyroscope bias, accelerometer bias, and state are derived in Appendix B. The state transfer and measurement equations introduced by image measurement are discussed next.




Fig. 7. Data flow diagram. Each block represents the data saved between the delayed image measurements.

B. Correction With Delayed Image Measurement

Image processing provides the image coordinates of the target, and the state $i \bar{\mathbf{p}}$ is obtained after normalization. Since camera imaging and image processing take time, the measurement is obtained from a period ago. Suppose that the delay time is $t_D > 0$, and then, the image measurement at time t is expressed as (11). After discretization, the measurement equation is

$$\mathbf{z}_{k-D} = \mathbf{H}\mathbf{x}_{k-D} + \mathbf{v} \quad (32)$$

where $\mathbf{z} = [\bar{p}_{x_i} \ \bar{p}_{y_i}]^T \in \mathbb{R}^2$; $\mathbf{H}$ is the measurement matrix; and $\mathbf{v}$ is the system noise vector, in which the elements follow a Gaussian distribution with zero-mean values that are not correlated with each other, $\mathbf{v} \sim \mathcal{N}(\mathbf{0}_{2 \times 1}, \mathbf{R})$, $\mathbf{R} \in \mathbb{R}^{2 \times 2}$. Due to the measurement delay, $\mathbf{z}_{k-D}$ is obtained at time t_k . The measurement matrix $\mathbf{H}$ is

$$\mathbf{H} = [\mathbf{0}_{2 \times 4} \ \mathbf{0}_{2 \times 3} \ \mathbf{0}_{2 \times 3} \ \mathbf{I}_{2 \times 2} \ \mathbf{0}_{2 \times 3} \ \mathbf{0}_{2 \times 3}]. \quad (33)$$

This essentially estimates the current state by utilizing a past prior state estimate and a past measurement. More explicitly, it is solved by: 1) correcting the prior state at time t_{k-D} using the current measurement $\mathbf{z}_{k-D}$ and 2) propagating it to time t_k by repeating the IMU prediction step. In step 2), IMU prediction and propagation are presented in detail as follows.

The delay processing is shown in Fig. 7, and the image measurement delay is spread over four IMU measurement cycles. The main point of discussion here is how the currently measured image features are used to correct the historical state estimate and to estimate the current state further.

From the measurement [see (33)], the estimated state is

$$\hat{\mathbf{x}}_{k-D} = \hat{\mathbf{x}}_{k-D|k-D-1} + \mathbf{K}(\mathbf{z}_{k-D} - \mathbf{H}\hat{\mathbf{x}}_{k-D|k-D-1}). \quad (34)$$

The covariance $\mathbf{P}_{k-D}$ of the state $\mathbf{x}_{k-D}$ is given by

$$\mathbf{P}_{k-D} = (\mathbf{I} - \mathbf{K}\mathbf{H}) \mathbf{P}_{k-D|k-D-1} \quad (35)$$

where $\mathbf{K}$ is the filter gain

$$\begin{aligned} \mathbf{K} &= \mathbf{P}_{k-D|k-D-1} \mathbf{H}^T \mathbf{S}^{-1} \\ \mathbf{S} &= \mathbf{H} \mathbf{P}_{k-D|k-D-1} \mathbf{H}^T + \mathbf{R}. \end{aligned} \quad (36)$$

After the above steps, the optimal state estimation at time t_{k-D} is obtained, and then, the state is propagated to the current time t_k according to (30) and (31).

Algorithm 2 $\hat{\mathbf{x}} = \text{DelayedFilter}(\omega_{\text{gyr}}, \mathbf{a}_{\text{acc}}, \text{ and } i \bar{\mathbf{p}}_{\text{img}})$

Input: IMU measurement, image measurement

Output: Estimated state

```

1: Initialize  $\hat{\mathbf{x}}_0, \mathbf{P}_0, \mathbf{K}_0$ 
2: for  $t = 1 : n$  do
3:   if  $i \bar{\mathbf{p}}_{\text{img}}$  is not available then
4:     Follow (30) and (31) to recursive state  $\hat{\mathbf{x}}_t$  with
       IMU data
5:   else
6:     According to (34), (35), (36), estimate the state
        $\hat{\mathbf{x}}_{t-D}$  at time  $t_{k-D}$ 
7:     for  $i = D - 1 : 0$  do
8:       Follow (30) and (31) to recursive state  $\hat{\mathbf{x}}_t$  with
       stored IMU data
9:     end for
10:  end if
11: end for

```

V. HITL SIMULATIONS

In this section, the proposed interception controller and the DKF observer are implemented in the hardware-in-the-loop (HITL) simulations to verify the algorithm's effectiveness and perform statistical analysis with a large number of simulations.

A. Introduction to Simulation Platform

RflySim is an ecosystem for control and safety testing of unmanned systems, utilizing model-based design (MBD) to validate algorithms and system applicability through high-fidelity digital scenes and an unmanned aerial vehicle (UAV) model library [34]. Utilizing automated test software, RflySim enables extensive simulation verification based on metrics such as circular error probable (CEP), defined as the radius of a circle centered on a target within which 50% of projectiles are expected to land [35].

As shown in Fig. 8(a), RflySim supports HITL simulations by providing simulated sensor data, maintaining the same hardware and software architecture as real flights, including the onboard computer, Pixhawk autopilot, and interception algorithm. In HITL simulations, the onboard computer processes simulated image and IMU data from RflySim, performs state estimation, and generates control signals sent to the Pixhawk. RflySim simulates the interceptor's motion and updates the sensor data, creating a closed-loop system.

B. Image Filtering Effect Experiments

1) *Filtering Algorithm:* Algorithm 2 outlines our state estimation method, and Fig. 7 illustrates data transmission. High-frequency, real-time IMU data are used for state recursion when image measurements are pending. Once a delayed image measurement arrives, it corrects the state variable from D cycles prior, updating it to the current moment for enhanced accuracy. C++ and eigen are employed for real-time computation efficiency.




Fig. 8. HITL simulation statistics. (a) HITL simulations settings. (b) Trajectories in statistics. (c) Error distribution with or without DKF observer. (d) Error distribution with different DKF frequencies. (e) Error distribution with different target speeds.

2) *Analysis of Influence of Delay on Control Accuracy:* This section evaluates the impact of the DKF observer on interception control accuracy. Simulations on RflySim, run 50 times each scenario with the IMU and controller at 200 Hz and target perception at 30 Hz, compare interception accuracies without and with the DKF observer. Fig. 8(b) shows 50 trial trajectories without and with the DKF observer, demonstrating smoother interceptor movements and earlier aggressive maneuvers due to image prediction, enhancing interception success rates.

Two experiment sets are conducted: 1) direct control using target detection and 2) control using DKF-based target estimation. Using the same random seed, 50 experiments are performed in both sets, with the control error box plot shown in Fig. 8(c). The results and circular probability errors are displayed in error distribution plots, specifically, $CEP_{\text{direct}} = 0.408$ m and $CEP_{50\text{Hz}} = 0.332$ m. The results show that the DKF observer significantly improves control accuracy.

3) *Analysis of Influence of DKF Frequency:* This section investigates the effect of the DKF observer frequency on interception control accuracy. In all simulations, the IMU frequency and inner loop controller are set to 200 Hz. The DKF observer run frequency is set to 10, 30, and 50 Hz, with each set of simulations run 50 times to obtain the CEP.

Using the same random seed, the control error box plot is shown in Fig. 8(d). The results and circular probability errors are shown in error distribution plots, specifically, $CEP_{10\text{Hz}} = 0.425$ m, $CEP_{30\text{Hz}} = 0.423$ m, and $CEP_{50\text{Hz}} = 0.332$ m. The results indicate that increasing the frequency of the DKF observer enhances control accuracy. Therefore, for practicality and computational efficiency, the DKF observer frequency is set at 50 Hz in real flight experiments.

4) *Analysis of Target Speed Influence:* This section discusses the estimation accuracy and interception precision of the DKF under varying target speeds. The DKF observer's




Fig. 9. HITL simulation process. (a) Trajectory. (b) Image coordinates. (c) Local image coordinates. (d) Target on image. (e) Interceptor attitude. (f) Local Interceptor attitude.




Fig. 10. Statistical results and single intercept details for comparison with previous IBVS methods. (a) Trajectories in statistics. (b) Error distribution of the previous IBVS and the proposed method. (c) Trajectory of a single interception. (d) Image coordinates. (e) Interceptor attitude.

frequency is set to 50 Hz, and the target moves in a figure-8 pattern at speeds of 5, 7.5, and 10 m/s. Each speed condition is tested in 50 experiments. The trajectories of the interceptor and the target are depicted in Fig. 8(b). Box plots illustrating the interception errors and DKF estimation errors are shown in Fig. 8(e). The DKF estimation error is defined as the angle between the estimated LOS vector $\hat{\mathbf{n}}_t$, calculated using the estimated state $\hat{\mathbf{x}}$ per (4), and the LOS vector derived from the true relative position $\mathbf{p}_r$ in the simulation.

As the target speed increases, the interception error slightly increases. Specifically, $\text{CEP}_{5\text{m/s}} = 0.330$ m, $\text{CEP}_{7.5\text{m/s}} =$

0.371 m, and $\text{CEP}_{10\text{m/s}} = 0.390$ m, all of which are less than the physical size of the interceptor. The DKF estimation error remains relatively stable, indicating that the DKF observer effectively adapts to different target speeds.

5) *Details of DKF Observer:* In a simulation with the DKF observer set at 50 Hz, one of 50 trials is depicted in Fig. 9. The interceptor multicopter initially ascends to 3 m before starting its mission, adjusting its motion direction early in the interception and constantly refining its speed, direction, and attitude. The image coordinates plot and the local image coordinates plot illustrate the target's pixel coordinates and




Fig. 11. Interception process of static target. In (a), the left is the third-person view (TPV) and the right is the FPV of the onboard camera. (a) Interception process. (b) Trajectory. (c) Image coordinates. (d) Local image coordinates. (e) Target on image. (f) Interceptor attitude. (g) Local Interceptor attitude.

the filter-estimated coordinates from target acquisition to interception completion. Despite an 80 ms image delay, the DKF observer effectively estimates the actual image coordinates, quickly converging early in the filtering process and aligning well with the measured values' overall trend.

The results demonstrate that: 1) the filter-estimated value changes before the observed value in the rising and falling segments, showing a clear delay compensation effect; 2) the filter's update frequency is higher than the image measurement update frequency; and 3) after the intercept is completed at 36.6 s, the filter continues to estimate based on the last known target position. These aspects enhance control quality, with the IMU compensating for image delays and the higher update frequency allowing for more current target estimations for control calculations. In addition, if the target is lost mid-interception, the interceptor has a chance to reacquire it. Overall, the DKF observer successfully mitigates the impact of image delay on control, increasing confidence for its use in real flight experiments.

C. Experiments Comparing With Previous IBVS Method

To validate our proposed method, we compared it with the previously established IBVS method [11] by conducting 50 simulation experiments under the same initial conditions.

The main difference in this study was the controller, while the DKF observer was consistently set at 50 Hz in both cases.

Fig. 10 presents the results of these comparative experiments. Fig. 10(a) illustrates the aggregated trajectory data from all 50 experiments. A direct comparison between Figs. 8(d) and 10(b) reveals a significant improvement in interception accuracy and a denser clustering of interception points in our proposed method, supported by the CEP values of $CEP_{\text{previous}} = 0.457$ m versus $CEP_{50\text{Hz}} = 0.332$ m.

Additional plots in Fig. 10(c)–(e) detail one experimental trajectory, image coordinates over time, and interceptor attitude, respectively. These plots underscore a key advantage of our method: the ability to induce more agile attitude adjustments. Such agility is crucial for enhancing the precision of interception, as demonstrated by the reduced CEP value. Overall, this comparative analysis highlights the enhanced interception accuracy and responsiveness of our approach compared to the previous IBVS method.

VI. HIGH-SPEED INTERCEPTION FLIGHT EXPERIMENTS

Extensive HITL simulations verify the effectiveness and robustness of our proposed method. Building on these simulations, real flight experiments were conducted, mirroring




Fig. 12. Interception process of moving target. (a) Interception process. (b) Trajectory. (c) Image coordinates. (d) Local image coordinates. (e) Target on image. (f) Interceptor attitude. (g) Local Interceptor attitude.

the steps of the simulation process to actualize the experiments.

A. Static Target Flight Experiments

1) *Design of Flight Experiments:* The real flight experiments used the same multicopter as the HITL simulations shown in Fig. 8(a), equipped with a T-Motor propulsion system, Pixhawk Nano V5 flight controller, NVIDIA Jetson Xavier NX onboard computer, and a front CSI camera with a 120° FOV. The multicopter has a thrust-to-weight ratio of about 3, can accelerate up to 5 m/s², and has a 20-min flight time. The target, a red balloon, was placed 3 m above ground level in open space, as illustrated in Fig. 11.

The multicopter intercepted the balloon at varying speeds, 5, 10, 15, 19, and 21 m/s, as shown in Fig. 11(a). It can be observed that the multicopter kept approaching the target and kept the target in the FOV until the final interception task was completed. During the experiment, the interceptor's inclination reached 50°, and the maximum speed was 21 m/s. Experiment videos are available at <https://youtu.be/146Km6c30Ww>.

2) *Flight Data Analysis:* Fig. 11(b) shows the interceptor's trajectory, with GPS data used for position and velocity analysis. Note that the designed interception controller does not need to use GPS position data. In the flight trajectory plot, the

start position of the multicopter is about (−1, −1.8, 3) m, and the target position is about (−3, −12, 4) m. The multicopter smoothly adjusted its attitude in the initial interception stages and continuously adapted its attitude and acceleration for accurate final interception.

Fig. 11(c) displays the time-varying curve of estimated and measured target coordinates during flight. The DKF filter effectively estimates the target position even when the target is momentarily lost or leaves the FOV, as seen in the local image coordinates plot in Fig. 11(d). The filter compensates for image measurement delay and maintains target estimation even with extended target loss.

The movement of the target on the image is depicted in Fig. 11(e), where the controller effectively maintains the target within the image's central area. The interceptor's attitude variation over time is illustrated in Fig. 11(f) and (g), with the maximum pitch angle reaching 50° during the interception process.

B. Moving Target Flight Experiments

1) *Design of Flight Experiments:* In the experiments illustrated in Fig. 12, a target attached to a multicopter moves in a circular path at 6 m/s, with its motion affected by wind. Fig. 12(a) shows the interceptor tracking and approaching



Fig. 13. Interception process of PBVS.

the irregularly moving target, keeping it within its FOV until interception. The interceptor's trajectory, detailed in Fig. 12(b), displays effective target locking and agile movements, reaching speeds up to 10.5 m/s. Additional experiments involving a freely floating helium balloon are included in the linked video.

2) *Flight Data Analysis*: The recorded data of a flight experiment using the filtered estimates are shown in Fig. 12(c)–(e). The image coordinates plot reveals the DKF filter's effectiveness in smoothing image measurement anomalies and correcting delay. Despite the delay, the estimation remained accurate without impacting autonomous flight performance. The interceptor's attitude variations, depicted in Fig. 12(f) and (g), demonstrate its excellent maneuverability.

In summary, the DKF-based state observer compensates for delays in perception module imaging and processing. This integration allows the controller to access more accurate real-time image measurements, enhancing control performance despite lower imaging frame rates and potential target loss.

C. Compared Flight Experiments

For comparison, we implemented simple experiments with a position-based visual servo (PBVS) controller following the pipeline of [12]. As shown in Fig. 13, the helium-filled balloon floats about 2 m above the ground. It can be observed that the interceptor misses the target due to two reasons: 1) the PBVS controller's inability to maintain target lock in the image and 2) wind disturbances leading to inaccurate and delayed 3-D target position estimation.

VII. CONCLUSION

This article presents a high-speed autonomous interception method for UAV intrusion, effectively overcoming the limitations of existing radio frequency interference techniques. The main results include: 1) design of an IBVS interception controller, ensuring collinearity between the designed LOS vector, the velocity vector, and the target unit vector, with proven

stability of the angular velocity controller; 2) development of a DKF observer to address issues of delayed, low frame rate, and easily loss image feedback, enhancing feedback data quality; and 3) successful validation of the method through unique, high-speed autonomous flight experiments, and HITL simulations, achieving speeds over 20 m/s. Future work will focus on refining the interception strategy using game theory, considering the strategies of intruding drones, and exploring collaborative interceptions involving multiple interceptors and multiple intruders.

APPENDIX

A. Detailed Derivatives and Proof of Theorem 1

1) *Derivatives of Key Elements*: First, the derivatives of its elements are considered to analyze the properties of the Lyapunov candidate function. By the property of the derivative of $\text{SO}(3)$ [31], $\dot{\mathbf{n}}_{td} = {}^e\omega \times \mathbf{n}_{td}$, where ${}^e\omega$ is the angular velocity under EFCS. The vector 2-norm is defined as $\|\mathbf{p}_r\| = \sqrt{\mathbf{p}_r^T \mathbf{p}_r}$, so the derivatives of $\mathbf{n}_t$ and z_1 are

$$\begin{aligned} \dot{\mathbf{n}}_t &= -\frac{\dot{\mathbf{p}}_r \|\mathbf{p}_r\| - \mathbf{p}_r (\mathbf{p}_r^T \dot{\mathbf{p}}_r)^{-\frac{1}{2}} \mathbf{p}_r^T \dot{\mathbf{p}}_r}{\|\mathbf{p}_r\|^2} \\ &= -\frac{\dot{\mathbf{p}}_r}{\|\mathbf{p}_r\|} + \frac{\mathbf{p}_r \mathbf{p}_r^T \dot{\mathbf{p}}_r}{\|\mathbf{p}_r\|^3} \\ &= \left(-\frac{1}{\|\mathbf{p}_r\|} \mathbf{I} + \frac{\mathbf{p}_r \mathbf{p}_r^T}{\|\mathbf{p}_r\|^3} \right) \dot{\mathbf{p}}_r \\ &= (-\mathbf{I} + \mathbf{n}_t \mathbf{n}_t^T) \frac{1}{\|\mathbf{p}_r\|} \mathbf{v}_r \end{aligned} \quad (37)$$

$$\begin{aligned} \dot{z}_1 &= -(\mathbf{n}_{td}^T \dot{\mathbf{n}}_t + \mathbf{n}_t^T \dot{\mathbf{n}}_{td}) \\ &= -\frac{1}{\|\mathbf{p}_r\|} \mathbf{n}_{td}^T (-\mathbf{I} + \mathbf{n}_t \mathbf{n}_t^T) \mathbf{v}_r - \mathbf{n}_t^T ({}^e\omega \times \mathbf{n}_{td}) \\ &= -\frac{1}{\|\mathbf{p}_r\|} \mathbf{n}_{td}^T (-\mathbf{I} + \mathbf{n}_t \mathbf{n}_t^T) \mathbf{v}_r - (\mathbf{n}_{td} \times \mathbf{n}_t)^T {}^e\omega. \end{aligned} \quad (38)$$

2) *Derivative of L_1* : The derivative of (12) along (38) is

$$\begin{aligned} \dot{L}_1 &= \frac{z_1 \dot{z}_1}{k_b^2 - z_1^2} \\ &= -\frac{z_1}{k_b^2 - z_1^2} \frac{1}{\|\mathbf{p}_r\|} \mathbf{n}_{td}^T (-\mathbf{I} + \mathbf{n}_t \mathbf{n}_t^T) \mathbf{v}_r \\ &\quad - \frac{z_1}{k_b^2 - z_1^2} (\mathbf{n}_{td} \times \mathbf{n}_t)^T {}^e\omega. \end{aligned} \quad (39)$$

Due to $\mathbf{v}_r = \mathbf{v}_{rd} + \mathbf{z}_2 = -k_1 \mathbf{p}_r + \mathbf{z}_2 = k_1 \|\mathbf{p}_r\| \mathbf{n}_t + \mathbf{z}_2$, (39) is rewritten as

$$\begin{aligned} \dot{L}_1 &= \frac{z_1}{k_b^2 - z_1^2} \left(\mathbf{n}_{td}^T (-\mathbf{I} + \mathbf{n}_t \mathbf{n}_t^T) \mathbf{n}_t - \frac{1}{\|\mathbf{p}_r\|} \mathbf{n}_{td}^T (-\mathbf{I} + \mathbf{n}_t \mathbf{n}_t^T) \mathbf{z}_2 \right) \\ &\quad - \frac{z_1}{k_b^2 - z_1^2} (\mathbf{n}_{td} \times \mathbf{n}_t)^T {}^e\omega \\ &= \frac{z_1}{k_b^2 - z_1^2} \left(\mathbf{n}_{td}^T (-\mathbf{n}_t + \mathbf{n}_t \mathbf{n}_t^T \mathbf{n}_t) - \frac{1}{\|\mathbf{p}_r\|} \mathbf{n}_{td}^T (-\mathbf{I} + \mathbf{n}_t \mathbf{n}_t^T) \mathbf{z}_2 \right) \\ &\quad - \frac{z_1}{k_b^2 - z_1^2} (\mathbf{n}_{td} \times \mathbf{n}_t)^T {}^e\omega \end{aligned}$$

$$\begin{aligned}
 &= -\frac{z_1}{k_b^2 - z_1^2} \frac{1}{\|\mathbf{p}_r\|} \mathbf{n}_{td}^T (-\mathbf{I} + \mathbf{n}_r \mathbf{n}_t^T) \mathbf{z}_2 \\
 &\quad - \frac{z_1}{k_b^2 - z_1^2} (\mathbf{n}_{td} \times \mathbf{n}_t)^T e \omega. \quad (40)
 \end{aligned}$$

3) *Derivative of L_3* : Combining (16) and (40), the derivative of (17) is

$$\begin{aligned}
 \dot{L}_3 &= -\frac{z_1}{k_b^2 - z_1^2} (\mathbf{n}_{td} \times \mathbf{n}_t)^T e \omega - k_1 \mathbf{p}_r^T \mathbf{p}_r + \mathbf{z}_2^T (\mathbf{a}_r + k_1 \mathbf{v}_r) \\
 &= -\frac{z_1}{k_b^2 - z_1^2} (\mathbf{n}_{td} \times \mathbf{n}_t)^T e \omega - k_1 \mathbf{p}_r^T \mathbf{p}_r - k_2 \mathbf{z}_2^T \mathbf{z}_2. \quad (41)
 \end{aligned}$$

4) *Proof of Theorem 1*: A total Lyapunov candidate function is designed as

$$\begin{aligned}
 L &= L_3 + L_4 \\
 &= \frac{1}{2} \log \frac{k_b^2}{k_b^2 - z_1^2} + \frac{1}{2} \mathbf{p}_r^T \mathbf{p}_r + \frac{1}{2} \mathbf{z}_2^T \mathbf{z}_2 + \text{tr}(\mathbf{I} - \mathbf{R}_d^T \mathbf{R}_b^e). \quad (42)
 \end{aligned}$$

Combining (25) and (41), the derivative of (42) is

$$\begin{aligned}
 \dot{L} &= -k_1 \mathbf{p}_r^T \mathbf{p}_r - k_2 \mathbf{z}_2^T \mathbf{z}_2 \\
 &\quad - \frac{z_1}{k_b^2 - z_1^2} (\mathbf{n}_{td} \times \mathbf{n}_t)^T e \omega + \text{vex}(\mathbf{R}_d^T \mathbf{R}_b^e - \mathbf{R}_b^e \mathbf{R}_d)^T b \omega \\
 &= -k_1 \mathbf{p}_r^T \mathbf{p}_r - k_2 \mathbf{z}_2^T \mathbf{z}_2 \\
 &\quad - \left(\frac{z_1}{k_b^2 - z_1^2} (\mathbf{n}_{td} \times \mathbf{n}_t)^T \mathbf{R}_b^e - \text{vex}(\mathbf{R}_d^T \mathbf{R}_b^e - \mathbf{R}_b^e \mathbf{R}_d)^T \right) b \omega \\
 &= -k_1 \mathbf{p}_r^T \mathbf{p}_r - k_2 \mathbf{z}_2^T \mathbf{z}_2 - \mathbf{w}^T \text{sat}(\mathbf{w}, \omega_m) \\
 &= -k_1 \mathbf{p}_r^T \mathbf{p}_r - k_2 \mathbf{z}_2^T \mathbf{z}_2 - \kappa \omega_m(\mathbf{w}) \mathbf{w}^T \mathbf{w} \\
 &\leq 0 \quad (43)
 \end{aligned}$$

where $\mathbf{w} = (z_1/(k_b^2 - z_1^2)) \mathbf{R}_b^e \mathbf{n}_{td} \times \mathbf{n}_t - \text{vex}(\mathbf{R}_d^T \mathbf{R}_b^e - \mathbf{R}_b^e \mathbf{R}_d)$ and $b \omega = \text{sat}(\mathbf{w}, \omega_m)$.

According to [36, Lemma 1], we have

$$\mathbf{p}_r \rightarrow \mathbf{0}, \quad \mathbf{n}_t \in \mathcal{S} = \{\mathbf{x} \mid |\mathbf{n}_{td}^T \mathbf{x}| > 1 - k_b\}$$

provided that the initial state satisfies $\mathbf{n}_t(0) \in \mathcal{S}$. This ensures that the interceptor's relative position to the target converges to zero. In addition, throughout the interception process, the target vector remains close to the designed LOS vector, ensuring that the target remains locked within the interceptor's FOV.

B. DKF Propagation With IMU Measurements

1) *Quaternion Status Transfer*: The discrete-time recurrence relation of state $\mathbf{q}$ is

$$\mathbf{q}_k = \mathbf{q}_{k-1} \otimes \Delta \mathbf{q}_{k-1} = \mathbf{M}(\Delta \mathbf{q}_{k-1}) \mathbf{q}_{k-1} \quad (44)$$

where $\mathbf{M}(\Delta \mathbf{q}_{k-1})$ is given in Appendix C, $b \omega$ is the estimated value at time t_k , and the relationship with the measured value of the gyroscope is (7).

Therefore, $\mathbf{F}_{\mathbf{q}_{k-1}}^{\mathbf{q}_k} = \mathbf{M}(\Delta \mathbf{q}_{k-1})$. Because the estimated value and the bias of gyroscope have the same order and coefficient, their partial derivatives have the same form

$$\begin{aligned}
 \mathbf{F}_{\mathbf{b}_{\text{gyr},k-1}}^{\mathbf{q}_k} &= \begin{bmatrix} \frac{q_1}{2} & \frac{q_2}{2} & \frac{q_3}{2} \\ -\frac{q_0}{2} & \frac{q_3}{2} & -\frac{q_2}{2} \\ -\frac{q_3}{2} & -\frac{q_0}{2} & \frac{q_1}{2} \\ \frac{q_2}{2} & -\frac{q_1}{2} & -\frac{q_0}{2} \end{bmatrix} \Delta t \\
 \mathbf{G}_{\mathbf{b}_{\omega k-1}}^{\mathbf{q}_k} &= \mathbf{F}_{\mathbf{b}_{\text{gyr},k-1}}^{\mathbf{q}_k}. \quad (45)
 \end{aligned}$$

2) *Position and Velocity Status Transfer*: For low-cost integrated navigation systems embedded in small multicopters, relative positions are generally used for navigation, while the influence of coning and sculling errors is ignored [37]. The position transfer equation is written as

$$\mathbf{p}_{r,k} = \mathbf{p}_{r,k-1} + \frac{1}{2} (\mathbf{v}_{r,k-1} + \mathbf{v}_{r,k}) \Delta t. \quad (46)$$

The corresponding state transition matrix is

$$\mathbf{F}_{\mathbf{v}_{r,k-1}}^{\mathbf{p}_{r,k}} = \mathbf{I} \Delta t. \quad (47)$$

Ignoring the angular velocity of the earth's rotation, the velocity (9) is discretized into a transfer equation, and we can get

$$\mathbf{v}_{r,k} = \mathbf{v}_{r,k-1} + \left(\mathbf{R}_b^e \cdot b \mathbf{a}_{k-1} + g \mathbf{e}_3 \right) \Delta t \quad (48)$$

where Δt is the period of the discrete system. Because there is a coordinate system transformation between the acceleration measurement in BCS and the velocity state in EFCS, there is a transfer relationship between the acceleration and the orientation quaternion, that is,

$$\mathbf{F}_{\mathbf{q}_{k-1}}^{\mathbf{v}_{r,k}} = 2[\mathbf{M}_1 b \mathbf{a} \quad \mathbf{M}_2 b \mathbf{a} \quad \mathbf{M}_3 b \mathbf{a}]^T \Delta t \quad (49)$$

where $b \mathbf{a} = [a_{xb} \ a_{yb} \ a_{zb}]^T = \mathbf{a}_{\text{acc}} - \mathbf{b}_{\text{acc}}$, and $\mathbf{M}_1$ – $\mathbf{M}_3$ are given in Appendix C.

Since the estimated value and the bias of accelerometer have the same order and coefficient, their partial derivatives have the same form

$$\begin{aligned}
 \mathbf{F}_{\mathbf{b}_{\text{acc},k-1}}^{\mathbf{v}_{r,k}} &= -\mathbf{R}_b^e \Delta t \\
 \mathbf{G}_{\mathbf{e}_{\mathbf{a}_{k-1}}}^{\mathbf{v}_{r,k}} &= \mathbf{F}_{\mathbf{b}_{\text{acc},k-1}}^{\mathbf{v}_{r,k}}. \quad (50)
 \end{aligned}$$

3) *Image Measurement State Transfer*: The IBVS (6) describes the relationship between the change of image feature points and the twist in CCS. Converting the twist in the equation from CCS to BCS and discretizing it, we get the transfer equation of image feature as

$$\begin{aligned}
 {}^i \bar{\mathbf{p}}_k &= {}^i \bar{\mathbf{p}}_{k-1} + \begin{bmatrix} -\frac{1}{p_{z_c}} & 0 & \frac{\bar{p}_{x_i}}{p_{z_c}} \\ 0 & -\frac{1}{p_{z_c}} & \frac{\bar{p}_{y_i}}{p_{z_c}} \end{bmatrix} \mathbf{R}_c^b \mathbf{R}_b^e \mathbf{v}_{r,k-1} \Delta t \\
 &\quad + \begin{bmatrix} \bar{p}_{x_i} \bar{p}_{y_i} & -(1 + \bar{p}_{x_i}^2) & \bar{p}_{y_i} \\ 1 + \bar{p}_{y_i}^2 & -\bar{p}_{x_i} \bar{p}_{y_i} & -\bar{p}_{x_i} \end{bmatrix} \mathbf{R}_c^b \mathbf{b}_{\omega k-1} \Delta t. \quad (51)
 \end{aligned}$$

$$\mathbf{F}_{\mathbf{p}_{k-1}}^{i\bar{\mathbf{p}}_k} = \mathbf{I} + \begin{bmatrix} \frac{v_{z_c}}{p_{z_c}} + \bar{p}_{y_i}\omega_{x_c} - 2\bar{p}_{x_i}\omega_{y_c} & \bar{p}_{x_i}\omega_{x_c} + \omega_{z_c} \\ -\bar{p}_{y_i}\omega_{y_c} - \omega_{z_c} & \frac{v_{z_c}}{p_{z_c}} + 2\bar{p}_{y_i}\omega_{x_c} - \bar{p}_{x_i}\omega_{y_c} \end{bmatrix} \Delta t \quad (54)$$

The state transition matrix of the image feature $i\bar{\mathbf{p}}_k$ to the orientation quaternion $\mathbf{q}_{k-1}$ is

$$\mathbf{F}_{\mathbf{q}_{k-1}}^{i\bar{\mathbf{p}}_k} = \frac{1}{p_{z_c}} [\mathbf{M}_4 \mathbf{v}_r \quad \mathbf{M}_5 \mathbf{v}_r]^T \Delta t \quad (52)$$

where $\mathbf{M}_4$ and $\mathbf{M}_5$ are given in Appendix C.

The state transition matrix of the image feature $i\bar{\mathbf{p}}_k$ to the velocity $\mathbf{v}_{r,k-1}$ is

$$\mathbf{F}_{\mathbf{v}_{r,k-1}}^{i\bar{\mathbf{p}}_k} = \begin{bmatrix} -\frac{1}{p_{z_c}} & 0 & \frac{\bar{p}_{x_i}}{p_{z_c}} \\ 0 & -\frac{1}{p_{z_c}} & \frac{\bar{p}_{y_i}}{p_{z_c}} \end{bmatrix} \mathbf{R}_c^b \mathbf{R}_b^e \Delta t. \quad (53)$$

The state transition matrix of the image feature $i\bar{\mathbf{p}}_k$ of the k th frame to the image feature $i\bar{\mathbf{p}}_{k-1}$ of the $(k-1)$ th frame is given as (54), as shown at the top of the page.

The state transition matrix and the system noise driving matrix of the image feature $i\bar{\mathbf{p}}_k$ to the gyroscope bias $\mathbf{b}_{\text{gyr},k-1}$ are

$$\begin{aligned} \mathbf{F}_{\mathbf{b}_{\text{gyr},k-1}}^{i\bar{\mathbf{p}}_k} &= - \begin{bmatrix} \bar{p}_{x_i} \bar{p}_{y_i} & -(1 + \bar{p}_{x_i}^2) & \bar{p}_{y_i} \\ 1 + \bar{p}_{y_i}^2 & -\bar{p}_{x_i} \bar{p}_{y_i} & -\bar{p}_{x_i} \end{bmatrix} \mathbf{R}_c^b \\ \mathbf{G}_{\mathbf{b}_{\text{gyr},k-1}}^{i\bar{\mathbf{p}}_k} &= \mathbf{F}_{\mathbf{b}_{\text{gyr},k-1}}^{i\bar{\mathbf{p}}_k}. \end{aligned} \quad (55)$$

Equations (52)–(55) complete the state transition matrix $\mathbf{F}_k$ and the system noise driving matrix $\mathbf{G}_k$, and the state propagation can be realized according to (30) and (31).

C. State Recurrence Equations

$$\begin{aligned} \mathbf{M}(\Delta \mathbf{q}_{k-1}) &= \begin{bmatrix} 1 & -\frac{\omega_{x_b} \Delta t}{2} & -\frac{\omega_{y_b} \Delta t}{2} & -\frac{\omega_{z_b} \Delta t}{2} \\ \frac{\omega_{x_b} \Delta t}{2} & 1 & \frac{\omega_{z_b} \Delta t}{2} & -\frac{\omega_{y_b} \Delta t}{2} \\ \frac{\omega_{y_b} \Delta t}{2} & -\frac{\omega_{z_b} \Delta t}{2} & 1 & \frac{\omega_{x_b} \Delta t}{2} \\ \frac{\omega_{z_b} \Delta t}{2} & \frac{\omega_{y_b} \Delta t}{2} & -\frac{\omega_{x_b} \Delta t}{2} & 1 \end{bmatrix} \\ \mathbf{M}_1 &= \begin{bmatrix} q_0 & -q_3 & q_2 \\ q_1 & q_2 & q_3 \\ -q_2 & q_1 & q_0 \\ -q_3 & -q_0 & q_1 \end{bmatrix} \\ \mathbf{M}_2 &= \begin{bmatrix} q_3 & q_0 & -q_1 \\ q_2 & -q_1 & -q_0 \\ q_1 & q_2 & q_3 \\ q_0 & -q_3 & q_2 \end{bmatrix} \\ \mathbf{M}_3 & \end{aligned}$$

$$\begin{aligned} &= \begin{bmatrix} -q_2 & q_1 & q_0 \\ q_3 & q_0 & -q_1 \\ -q_0 & q_3 & -q_2 \\ q_1 & q_2 & q_3 \end{bmatrix} \\ \mathbf{M}_4 &= \begin{bmatrix} 2\bar{p}_{x_i}q_0 + 2q_3 & 2\bar{p}_{x_i}q_3 - 2q_0 & -2\bar{p}_{x_i}q_2 - 2q_1 \\ 2\bar{p}_{x_i}q_1 - 2q_2 & 2\bar{p}_{x_i}q_2 + 2q_1 & 2\bar{p}_{x_i}q_3 - 2q_0 \\ 2\bar{p}_{x_i}q_2 - 2q_1 & 2\bar{p}_{x_i}q_1 - 2q_2 & -2\bar{p}_{x_i}q_0 - 2q_3 \\ 2\bar{p}_{x_i}q_3 + 2q_0 & 2\bar{p}_{x_i}q_0 + 2q_3 & 2\bar{p}_{x_i}q_1 - 2q_2 \end{bmatrix} \\ \mathbf{M}_5 &= \begin{bmatrix} 2\bar{p}_{y_i}q_0 - 2q_2 & 2\bar{p}_{y_i}q_3 + 2q_1 & -2\bar{p}_{y_i}q_2 - 2q_0 \\ 2\bar{p}_{y_i}q_1 - 2q_3 & 2\bar{p}_{y_i}q_2 + 2q_0 & 2\bar{p}_{y_i}q_3 + 2q_1 \\ 2\bar{p}_{y_i}q_2 - 2q_0 & 2\bar{p}_{y_i}q_1 - 2q_3 & -2\bar{p}_{y_i}q_0 + 2q_2 \\ 2\bar{p}_{y_i}q_3 - 2q_1 & 2\bar{p}_{y_i}q_0 - 2q_2 & 2\bar{p}_{y_i}q_1 - 2q_3 \end{bmatrix}. \end{aligned}$$

ACKNOWLEDGMENT

Video of the experiments: <https://youtu.be/146Km6c30Ww>.

REFERENCES

- [1] S. Lee and H. Son, "Antisway control of a multirotor with cable-suspended payload," *IEEE Trans. Control Syst. Technol.*, vol. 29, no. 6, pp. 2630–2638, Nov. 2021.
- [2] D. Floreano and R. J. Wood, "Science, technology and the future of small autonomous drones," *Nature*, vol. 521, no. 7553, pp. 460–466, May 2015.
- [3] M. Ritchie, F. Fioranelli, and H. Borrión, "Micro UAV crime prevention: Can we help Princess Leia?" in *Crime Prevention in the 21st Century*. Cham, Switzerland: Springer, 2017, pp. 359–376.
- [4] X. Shi, C. Yang, W. Xie, C. Liang, Z. Shi, and J. Chen, "Anti-drone system with multiple surveillance technologies: Architecture, implementation, and challenges," *IEEE Commun. Mag.*, vol. 56, no. 4, pp. 68–74, Apr. 2018.
- [5] J. Noh et al., "Tractor beam: Safe-hijacking of consumer drones with adaptive GPS spoofing," *ACM Trans. Privacy Secur.*, vol. 22, no. 2, pp. 1–26, 2019.
- [6] K. Pärilä, M. M. Alam, and Y. Le Moullec, "Jamming of UAV remote control systems using software defined radio," in *Proc. Int. Conf. Mil. Commun. Inf. Syst. (ICMCIS)*, May 2018, pp. 1–6.
- [7] D. Dynamics. (2021). *Dronecatcher*. [Online]. Available: <https://www.dronecatcher.nl>
- [8] M. Z. Chaari and S. Al-Maadeed, "Testing the efficiency of laser technology to destroy the rogue drones," *Secur. Defence Quart.*, vol. 32, no. 5, pp. 31–38, 2020.
- [9] Y. Chen and N. O. Pérez-Arancibia, "Controller synthesis and performance optimization for aerobatic quadrotor flight," *IEEE Trans. Control Syst. Technol.*, vol. 28, no. 6, pp. 2204–2219, Nov. 2020.
- [10] P. Foehn et al., "AlphaPilot: Autonomous drone racing," *Auton. Robots*, vol. 46, no. 1, pp. 307–320, 2022.
- [11] K. Yang and Q. Quan, "An autonomous intercept drone with image-based visual servo," in *Proc. IEEE Int. Conf. Robot. Autom. (ICRA)*, May 2020, pp. 2230–2236.
- [12] Y. Stasinchuk et al., "A multi-UAV system for detection and elimination of multiple targets," in *Proc. IEEE Int. Conf. Robot. Autom. (ICRA)*, May 2021, pp. 555–561.
- [13] M. Vrba et al., "Autonomous capture of agile flying objects using UAVs: The MBZIRC 2020 challenge," *Robot. Auto. Syst.*, vol. 149, Mar. 2022, Art. no. 103970.
- [14] H. Tao, D. Lin, S. He, T. Song, and R. Jin, "Optimal terminal-velocity-control guidance for intercepting non-cooperative maneuvering quadcopter," *J. Field Robot.*, vol. 39, no. 4, pp. 457–472, Jun. 2022.

- [15] A. Loquercio, E. Kaufmann, R. Ranftl, A. Dosovitskiy, V. Koltun, and D. Scaramuzza, "Deep drone racing: From simulation to reality with domain randomization," *IEEE Trans. Robot.*, vol. 36, no. 1, pp. 1–14, Feb. 2020.
- [16] J. Fu, Y. Song, Y. Wu, F. Yu, and D. Scaramuzza, "Learning deep sensorimotor policies for vision-based autonomous drone racing," 2022, *arXiv:2210.14985*.
- [17] J. Li, Z. Ning, S. He, C.-H. Lee, and S. Zhao, "Three-dimensional bearing-only target following via observability-enhanced helical guidance," *IEEE Trans. Robot.*, vol. 39, no. 2, pp. 1509–1526, Apr. 2023.
- [18] D. Hanover et al., "Autonomous drone racing: A survey," 2023, *arXiv:2301.01755*.
- [19] W. Zhao, H. Liu, F. L. Lewis, K. P. Valavanis, and X. Wang, "Robust visual servoing control for ground target tracking of quadrotors," *IEEE Trans. Control Syst. Technol.*, vol. 28, no. 5, pp. 1980–1987, Sep. 2020.
- [20] H. Xie, A. F. Lynch, K. H. Low, and S. Mao, "Adaptive output-feedback image-based visual servoing for quadrotor unmanned aerial vehicles," *IEEE Trans. Control Syst. Technol.*, vol. 28, no. 3, pp. 1034–1041, May 2020.
- [21] G. Wang, J. Qin, Q. Liu, Q. Ma, and C. Zhang, "Image-based visual servoing of quadrotors to arbitrary flight targets," *IEEE Robot. Autom. Lett.*, vol. 8, no. 4, pp. 2022–2029, Apr. 2023.
- [22] J. M. Pak, C. K. Ahn, P. Shi, Y. S. Shmaliy, and M. T. Lim, "Distributed hybrid particle/FIR filtering for mitigating NLOS effects in TOA-based localization using wireless sensor networks," *IEEE Trans. Ind. Electron.*, vol. 64, no. 6, pp. 5182–5191, Jun. 2017.
- [23] R. P. Guan, B. Ristic, L. Wang, and R. Evans, "Monte Carlo localisation of a mobile robot using a Doppler–Azimuth radar," *Automatica*, vol. 97, pp. 161–166, Nov. 2018.
- [24] H. Zhu, J. Mi, Y. Li, K.-V. Yuen, and H. Leung, "VB-Kalman based localization for connected vehicles with delayed and lost measurements: Theory and experiments," *IEEE/ASME Trans. Mechatronics*, vol. 27, no. 3, pp. 1370–1378, Jun. 2022.
- [25] K. Gamagedara, T. Lee, and M. Snyder, "Quadrotor state estimation with IMU and delayed real-time kinematic GPS," *IEEE Trans. Aerosp. Electron. Syst.*, vol. 57, no. 5, pp. 2661–2673, Oct. 2021.
- [26] J.-M. Kai, G. Allibert, M.-D. Hua, and T. Hamel, "Nonlinear feedback control of quadrotors exploiting first-order drag effects," *IFAC-PapersOnLine*, vol. 50, no. 1, pp. 8189–8195, Jul. 2017.
- [27] Y. Song, A. Romero, M. Müller, V. Koltun, and D. Scaramuzza, "Reaching the limit in autonomous racing: Optimal control versus reinforcement learning," *Sci. Robot.*, vol. 8, no. 82, 2023, Art. no. eadg1462.
- [28] P. I. Corke and O. Khatib, *Vision and Control Fundamental Algorithms in MATLAB*, vol. 73. Berlin, Germany: Springer, 2011.
- [29] F. Chaumette and S. Hutchinson, "Visual servo control. I. Basic approaches," *IEEE Robot. Automat. Mag.*, vol. 13, no. 4, pp. 82–90, Dec. 2006.
- [30] Y. Yu, S. Yang, M. Wang, C. Li, and Z. Li, "High performance full attitude control of a quadrotor on $SO(3)$," in *Proc. IEEE Int. Conf. Robot. Autom. (ICRA)*, Jul. 2015, pp. 1698–1703.
- [31] R. M. Murray, Z. Li, and S. S. Sastry, *A Mathematical Introduction to Robotic Manipulation*. Boca Raton, FL, USA: CRC Press, 2017.
- [32] T. Lee, M. Leok, and N. H. McClamroch, "Geometric tracking control of a quadrotor UAV on $SE(3)$," in *Proc. IEEE Conf. Decis. Control*, Dec. 2010, pp. 5420–5425.
- [33] R. Fu, Q. Quan, M. Li, and K.-Y. Cai, "Practical distributed control for cooperative multicopters in structured free flight concepts," *IEEE Trans. Intell. Transp. Syst.*, vol. 24, no. 4, pp. 4203–4216, Apr. 2023.
- [34] X. Dai, C. Ke, Q. Quan, and K.-Y. Cai, "RFlySim: Automatic test platform for UAV autopilot systems with FPGA-based hardware-in-the-loop simulations," *Aerosp. Sci. Technol.*, vol. 114, Jul. 2021, Art. no. 106727.
- [35] D. Shnidman, "Efficient computation of the circular error probability (CEP) integral," *IEEE Trans. Autom. Control*, vol. 40, no. 8, pp. 1472–1474, Aug. 1995.
- [36] K. P. Tee, S. S. Ge, and E. H. Tay, "Barrier Lyapunov functions for the control of output-constrained nonlinear systems," *Automatica*, vol. 45, no. 4, pp. 918–927, Apr. 2009.
- [37] K. M. Roscoe, "Equivalency between strapdown inertial navigation coning and sculling integrals/algorithms," *J. Guid., Control, Dyn.*, vol. 24, no. 2, pp. 201–205, Mar. 2001.



Kun Yang received the B.S. degree from North China Electric Power University, Beijing, China, in 2018, and the M.S. degree from Beihang University (formerly Beijing University of Aeronautics and Astronautics), Beijing, in 2021, where he is currently pursuing the Ph.D. degree with the School of Automation Science and Electrical Engineering.

His main research interests include vision-based navigation and swarm confrontation.



Chenggang Bai received the M.Sc. degree in statistics from Nanjing University of Aeronautics and Astronautics, Nanjing, China, in 1990, and the Ph.D. degree in control theory and control engineering from Zhejiang University, Hangzhou, China, in 1999.

In November 2001, he joined the faculty of the School of Automation Science and Electrical Engineering, Beihang University, Beijing, China, where he has been a Professor since July 2009. His research interests include reliable flight control, software reliability, and software testing.



Zhikun She received the B.Sc. degree in computational mathematics and the Ph.D. degree in mathematics from Peking University, Beijing, China, in 1999 and 2005, respectively.

From 2004 to 2006, he was a Post-Doctoral Researcher with Max-Planck-Institut für Informatik, Saarbrücken, Germany. He is currently a Professor with the School of Mathematical Sciences, Beihang University, Beijing. He has been the Principal Investigator of more than ten research projects and published more than 100 research articles. His

research interests include theory, methodologies, and applications of safety verification and stability analysis of hybrid systems.

Prof. She received the First Class of Natural Science Prize of the Ministry of Education of China in 2013 and the National Science Fund for Excellent Young Scholars of China in 2014.



Quan Quan (Senior Member, IEEE) received the B.S. and Ph.D. degrees in control science and engineering from Beihang University, Beijing, China, in 2004 and 2010, respectively.

Since 2022, he has been a Professor of control science and engineering with Beihang University, where he is currently with the School of Automation Science and Electrical Engineering. His research interests include reliable flight control, swarm intelligence, vision-based navigation, and health assessment.