

DA-IICT, CT 303, Autumn 2024-2025
Lab Exercise 2 and Tutorial
Date: 12/08/2024, Expected by: 23/08/2024
Prepared by: Dr. Abhishek Jindal & Dr. Manish Kumar

References for perusal:

- [1] *Manual, kit 2804: 4-Channel TDM-PCM Modulator and Demodulator*, Scientech.
 - [2] *Modern Digital and Analog Communication Systems*, B. P. Lathi, and Zhi Ding, International 4th edition, Oxford University press.
-

- In the exercise sheet, there are 2 lab problems and 1 tutorial problem.
 - Among the two lab problems, one needs to be done on hardware, while the other one in MATLAB.
 - The hardware experiment is to be done in groups of 4, while the coding in MATLAB should be done in groups of 2.
 - **It is required for a group of 4 to occupy two consecutive desks and share the kit among themselves. Once the hardware-based experiments are done, they should split in groups of 2 and occupy the adjacent PCs on the desks.**
 - All the required soft copies of the texts referred to in the exercises are available in the lecture folder of the instructor for section A.
-

1. **(Tutorial Exercise)** Determine the Nyquist sampling rate and the Nyquist sampling interval for the following signals.
 - $x(t) = \text{sinc}(100\pi t) + 3 \text{sinc}^2(60\pi t)$
 - $x(t) = 1 + \cos(2000\pi t) + \sin(4000\pi t)$.
2. From section 6.9 in [2], study the M-files “Exsample.m”, “uniquan.m”, “sampanquant.m”, and “ExPCM.m”. Based on the knowledge gained, write your own code for sampling and reconstructing sum of two cosine functions of duration 2 seconds and frequency 5 Hz and 8 Hz, respectively. You need to choose the sampling rate yourself, considering all the aspects of sampling theory studied in the lectures. In your implementation, it is important for you to understand the implementation of ideal-low-pass-filtering operation.
3. From [1], read sections “TDM-PCM Modulation and Demodulation” and “2-Channel TDM PCM” on pages 7 to 10. Then perform experiments 1 to 7. You need to understand the block level description of the circuit diagram of the kit. You need to follow the procedures given in the manual and observe the output as suggested in the observations.

Instructions for Preparing Lab Report:

- The tutorial problem needs to be solved during the lab and no submission is required for the same.
- For experiments done on kit, you need to take a snap shot of each output on the oscilloscope. This can be done either by connecting a USB stick to the oscilloscope, or connecting the oscilloscope to the PC. Your lab report must contain these snapshots.
- You need to verify and subsequently mention in the report that the outputs given in the manual corresponding to the experiments are indeed correct.
- For MATLAB based experiments, your lab report must contain the code and all the figures. Further, you need to explain the results in the graphs.

General Instructions:

- The lab is intentionally made from the references given above so that you have ample resources to refer to and learn.
- For the final evaluation, we may have a quiz/lab test which will test if you have gone through the codes and tweaked them in Matlab.
- For learning Matlab functions used in the codes, refer to the help section which pops up as you press F1 in Matlab.