

Precaution

Keep the rheostat in maximum position

Switch on the 30 V dc supply, adjusting different values of rheostat for different values of current note down different ammeter, voltmeter readings.

TABULATION

SLIP TEST

Sl.No.	V_{max}	V_{min}	I_{max}	I_{min}	Z_{sd}	Z_{sq}	X_d	X_q

STATOR RESISTANCE MEASUREMENT

S. No.	V(Volts)	I(amps)	$R_{dc}(\Omega)$
R_{dc}			

SAMPLE CALCULATION (SET NO. ____)

Armature resistance, $R_a = 1.2 \times R_{dc} = 1.2 \times$ ______ = ______ Ω

V_{max} = ______V, V_{min} = ______V, I_{max} = ______A, I_{min} = ______A

$Z_{sd} = \frac{V_{max}}{I_{min}}$ = ______ Ω

$Z_{sq} = \frac{V_{min}}{I_{max}}$ = ______ Ω