LOGICAL INPUTS TO MAIN		
LS address	Function	Owner
M01000	Safety auxiliary	SIM_IO
M01001	Field START	Operator / optional CIMON
M01002	Field STOP	Operator / optional CIMON
M01003	Field RESET	Operator / optional CIMON
M01004	Infeed present	SIM_IO
M01005	Test position	SIM_IO
M01006	Outfeed present	SIM_IO
M01007	Door closed	SIM_IO
M01008	Clamp closed	SIM_IO
M01009	PASS gate feedback	SIM_IO
M0100A	FAIL gate feedback	SIM_IO
M0100B	RETEST gate feedback	SIM_IO
M0100C	Environment start permit	LS MAIN environment block

MAIN COMMAND OUTPUTS		
LS address	Command / display	Owner
M01100	Conveyor run	LS MAIN
M01101	Reverse reserved / always0	LS MAIN
M01102	Clamp close	LS MAIN
M01103	PASS gate	LS MAIN
M01104	FAIL gate	LS MAIN
M01105	RETEST gate	LS MAIN
M01106	Start ready	LS MAIN
M01107	Cycle running	LS MAIN
M01108	Alarm active	LS MAIN
M01109	Buzzer command	LS MAIN

MAIN HMI COMMAND MAP		
Command	LS address	Meaning
START	M00200	Fresh rising edge
STOP	M00201	Abort level
RESET	M00202	Recovery, no start
ACK	M00203	Mute current buzzer
COUNT RESET	M00204	Idle + Manual only

M01100–M01105 are logical actuator commands; no field output wiring is implemented.

M01000 and position/door inputs are produced by SIM_IO. M0100C is computed by the LS environment receiver, never written by SIM_IO.

D00020 / D00021 / D00025 have one application writer: ATE through CIMON. Echo / accepted registers are read-only PLC-owned values.

Physical P input/output allocation is a separate proposal in drawing 020. Do not copy M0100C to/from a similarly numbered spare P input.

NO.	DATE	REVISION
R0	2026-10-22	FUNCTION RECORD

DWG. TITLE

SEMICON SORTER PROJECT
Final Test and Multi-Bin Sorting Cell

LOGICAL I/O AND WRITE OWNERS

DRAWN BY	DATE
J. H. KO	2026-10-14

DWG. NO
004

SHEET NO
1 OF 1