

VMB2BLE

2 channel blind module

Binary format:

<SOF-SID10...SID0-RTR-IDE-r0-DLC3...0-DATABYTE1...DATABYTE_n-CRC14...CRC1-CRCDEL-ACK-ACKDEL-EOF7...EOF1-IFS3...IFS1>

| <i>bits</i> | <i>Description</i> |
|--------------|--|
| SOF | Start Of Frame (always 0) |
| SID10 & SID9 | Priority (00: highest ... 11: lowest priority) |
| SID8...SID1 | Address |
| SID0 | Always 0 |
| RTR | Remote Transmit Request |
| IDE | Identifier Extension (always 0) |
| R0 | reserved (always 0) |
| DLC3...DLC0 | Data Length Code (0...8) |
| Databyte1 | Command |
| Databyte2 | Parameter |
| Databyte3 | Parameter |
| Databyte4 | Parameter |
| Databyte5 | Parameter |
| Databyte6 | Parameter |
| Databyte7 | Parameter |
| Databyte8 | Parameter |
| CRC14...CRC1 | Cyclic Redundancy Checksum |
| CRCDEL | CRC Delimiter (always 1) |
| ACK | Acknowledge slot (transmit 1 readback 0 if received correctly) |
| ACKDEL | Acknowledge Delimiter (always 1) |
| EOF7...EOF1 | End Of Frame (always 1111111) |
| IFS3...IFS1 | InterFrame Space (always 111) |

The blind module can transmit the following commands:

- Clears LEDs on a push button module
- Sets LEDs on a push button module
- Blinks LEDs fast on a push button module

The blind module can transmit the following messages:

- Blind status
- Blind switch status
- Module type
- Bus error counter status
- First, second and third part of the blind name
- Memory data
- Memory data block (4 bytes)
- Real-time clock status
- Date status
- Daylight savings status (Build1235 or higher)
- Real-time clock status request

The blind module can receive the following messages:

- Linked push button status

The blind module can receive the following commands:

- Switch blind off
- Switch blind up
- Switch blind down
- Set blind position
- Forced up
- Cancel forced up
- Forced down
- Cancel forced down
- Inhibit

- Inhibit preset up
- Inhibit preset down
- Cancel inhibit
- Lock
- Unlock
- Blind status request
- Clear Push button Led
- Module type request
- Bus error counter status request
- Blind name request
- Read memory data
- Read memory data block (4 bytes)
- Memory dump request
- Write memory data
- Write memory data block (4 bytes)
- Write module address and serial number
- Real-time clock status request
- Set real-time clock
- Set date
- Set daylight savings (Build 1235 or higher)
- Enable/disable global sunrise/sunset related actions (Build1235 or higher)
- Enable/disable local sunrise/sunset related actions (Build1235 or higher)
- Set local alarm clock
- Set global alarm clock
- Select auto mode

Transmits real time clock status request:

SID10-SID9 = 11 (lowest priority)

SID8...SID1 = H'00'

RTR = 0

DLC3...DLC0 = 1 databyte to send

DATABYTE1 = COMMAND_REALTIME_CLOCK_STATUS_REQUEST (H'D7')

Transmits the real time clock status:

SID10-SID9 = 11 (lowest priority)

SID8...SID1 = Module address

RTR = 0

DLC3...DLC0 = 4 databytes to send

DATABYTE1 = COMMAND_REALTIME_CLOCK_STATUS (H'D8')

DATABYTE2 = Day

| Contents | Day |
|----------|-----------|
| 0 | Monday |
| 1 | Tuesday |
| 2 | Wednesday |
| 3 | Thursday |
| 4 | Friday |
| 5 | Saturday |
| 6 | Sunday |

DATABYTE3 = Hour (0...23)

DATABYTE4 = Minute (0...59)

Transmits the date status:

SID10-SID9 = 11 (lowest priority)

SID8...SID1 = Module address

RTR = 0

DLC3...DLC0 = 5 databytes to send

DATABYTE1 = COMMAND_DATE_STATUS (H'B7')

DATABYTE2 = Day (1...31)

DATABYTE3 = Month (1...12)

DATABYTE4 = High byte of Year

DATABYTE5 = Low byte of Year

Transmits the daylight savings status (Build1235 or higher):

SID10-SID9 = 11 (lowest priority)

SID8...SID1 = Module address

RTR = 0

DLC3...DLC0 = 2 databytes to send

DATABYTE1 = COMMAND_DAYLIGHT_SAVING_STATUS (H'AF')

DATABYTE2 = 0 =disabled / 1 = enabled

Transmits the blind relays switch status:

SID10-SID9 = 00 (highest priority)

SID8...SID1 = Module address

RTR = 0

DLC3...DLC0 = 4 databytes to send

DATABYTE1 = COMMAND_PUSH_BUTTON_STATUS (H'00')

DATABYTE2 = Blind relays just switched on (1 = just pressed/switched on)

DATABYTE3 = Blind relays just switched off (1 = just released/switched off)

DATABYTE4 = 0x00

| | Databyte2 | Databyte3 | Databyte4 |
|--|-------------|-------------|-------------|
| Channel 1 blind up relay just switched on | B'xxxxxx01' | B'xxxxxx00' | B'00000000' |
| Channel 1 blind up relay just switched off | B'xxxxxx00' | B'xxxxxx01' | B'00000000' |
| Channel 1 blind down relay just switched on | B'xxxxxx10' | B'xxxxxx00' | B'00000000' |
| Channel 1 blind down relay just switched off | B'xxxxxx00' | B'xxxxxx10' | B'00000000' |
| Channel 2blind up relay just switched on | B'xxxx01xx' | B'xxxx00xx' | B'00000000' |
| Channel 2blind up relay just switched off | B'xxxx00xx' | B'xxxx01xx' | B'00000000' |
| Channel 2 blind down relay just switched on | B'xxxx10xx' | B'xxxx00xx' | B'00000000' |

| | | | |
|--|-------------|-------------|-------------|
| Channel 2 blind down relay just switched off | B'xxxx00xx' | B'xxxx10xx' | B'00000000' |
|--|-------------|-------------|-------------|

Transmit: Clears LEDs on a push button module:

SID10-SID9 = 11 (lowest priority)
SID8...SID1 = Address of the push button module for clearing LEDs
RTR = 0
DLC3...DLC0 = 2 databytes to send
DATABYTE1 = COMMAND_CLEAR_LED (H'F5')
DATABYTE2 = LED bit numbers (1 = clear LED)

Transmit: Sets LEDs on a push button module:

SID10-SID9 = 11 (lowest priority)
SID8...SID1 = Address of the push button module for setting LEDs on
RTR = 0
DLC3...DLC0 = 2 databytes to send
DATABYTE1 = COMMAND_SET_LED (H'F6')
DATABYTE2 = LED bit numbers (1 = set LED)

Transmit: Blinks LEDs fast on a push button module:

SID10-SID9 = 11 (lowest priority)
SID8...SID1 = Address of the push button module for fast blinking LEDs
RTR = 0
DLC3...DLC0 = 2 databytes to send
DATABYTE1 = COMMAND_FAST_BLINKING_LED (H'F8')
DATABYTE2 = LED bit numbers (1 = fast blink LED)

Transmit: Bus error counter status:

SID10-SID9 = 11 (lowest priority)
SID8...SID1 = Module address
RTR = 0
DLC3...DLC0 = 4 databytes to send
DATABYTE1 = COMMAND_BUSERROR_COUNTER_STATUS (H'DA')
DATABYTE2 = Transmit error counter
DATABYTE3 = Receive error counter
DATABYTE4 = Bus off counter

Transmits the module type:

SID10-SID9 = 11 (lowest priority)
SID8...SID1 = Module address
RTR = 0
DLC3...DLC0 = 7 databytes to send
DATABYTE1 = COMMAND_MODULE_TYPE (H'FF')
DATABYTE2 = VMB2BLE_TYPE (H'1D')
DATABYTE3 = High byte of serial number
DATABYTE4 = Low byte of serial number
DATABYTE5 = Memorymap version
DATABYTE6 = Build year
DATABYTE7 = Build week

Transmits the memory data:

SID10-SID9 = 11 (lowest priority)
SID8...SID1 = Module address
RTR = 0
DLC3...DLC0 = 4 databytes to send
DATABYTE1 = COMMAND_MEMORY_DATA (H'FE')
DATABYTE2 = High memory address (H'00'...H'01')
DATABYTE3 = LOW memory address (H'00'...H'FF')
DATABYTE4 = memory data

Transmits memory data block (4 bytes):

SID10-SID9 = 11 (lowest priority)
SID8...SID1 = Module address
RTR = 0
DLC3...DLC0 = 4 databytes to send
DATABYTE1 = COMMAND_MEMORY_DATA_BLOCK (H'CC')
DATABYTE2 = High start address of memory block
DATABYTE3 = LOW start address of memory block
DATABYTE4 = memory data1
DATABYTE5 = memory data2
DATABYTE6 = memory data3
DATABYTE7 = memory data4

Remark: address range: H'0000' to H'01FC'

Transmits the first part of the blind name:

SID10-SID9 = 11 (lowest priority)
SID8...SID1 = Module address
RTR = 0
DLC3...DLC0 = 8 databytes to send
DATABYTE1 = COMMAND_BLIND_NAME_PART1 (H'F0')
DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind</i> |
|-----------------|--------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

DATABYTE3 = Character 1 of the blind name
DATABYTE4 = Character 2 of the blind name
DATABYTE5 = Character 3 of the blind name
DATABYTE6 = Character 4 of the blind name
DATABYTE7 = Character 5 of the blind name
DATABYTE8 = Character 6 of the blind name

Transmits the second part of the blind name:

SID10-SID9 = 11 (lowest priority)
SID8...SID1 = Module address
RTR = 0
DLC3...DLC0 = 8 databytes to send
DATABYTE1 = COMMAND_BLIND_NAME_PART2 (H'F1')
DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind</i> |
|-----------------|--------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

DATABYTE3 = Character 7 of the blind name
DATABYTE4 = Character 8 of the blind name
DATABYTE5 = Character 9 of the blind name
DATABYTE6 = Character 10 of the blind name
DATABYTE7 = Character 11 of the blind name
DATABYTE8 = Character 12 of the blind name

Transmits the third part of the blind name:

SID10-SID9 = 11 (lowest priority)
SID8...SID1 = Module address
RTR = 0
DLC3...DLC0 = 6 databytes to send
DATABYTE1 = COMMAND_BLIND_NAME_PART3 (H'F2')
DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind</i> |
|-----------------|--------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

DATABYTE3 = Character 13 of the blind name
DATABYTE4 = Character 14 of the blind name
DATABYTE5 = Character 14 of the blind name

DATABYTE6 = Character 16 of the blind name
Remarks: Unused characters contain H'FF'.

Transmits the blind status:

SID10-SID9 = 11 (lowest priority)

SID8...SID1 = Module address

RTR = 0

DLC3...DLC0 = 8 databytes to send

DATABYTE1 = COMMAND_BLIND_STATUS (H'EC')

DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Relay number</i> |
|-----------------|---------------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

DATABYTE3 = Default time out setting in seconds (0=no time out)

DATABYTE4 = Blind status

| <i>Contents</i> | <i>Blind status</i> |
|-----------------|---------------------|
| B'00000000' | Blinds off |
| B'00000001' | Blind up |
| B'00000010' | Blind down |

DATABYTE5 = Led status

| <i>Contents</i> | <i>Mode</i> |
|-----------------|-------------------------------|
| B'00000000' | LEDs off |
| B'10000000' | 'Down' LED on |
| B'01000000' | 'Down' LED slow blinking |
| B'00100000' | 'Down' LED fast blinking |
| B'00010000' | 'Down' LED very fast blinking |
| B'00001000' | 'Up' LED on |
| B'00000100' | 'Up' LED slow blinking |
| B'00000010' | 'Up' LED fast blinking |
| B'00000001' | 'Up' LED very fast blinking |

DATABYTE6 = blind position (0% = up...100%=down)

DATABYTE7 = Locked/inhibit/Forced up/ Forced down on setting

| <i>Contents</i> | <i>Setting</i> |
|-----------------|-----------------------------|
| B'xxxxx000' | Channel normal |
| B'xxxxx001' | Channel inhibited |
| B'xxxxx010' | Channel inhibit preset down |
| B'xxxxx011' | Channel inhibit preset up |
| B'xxxxx100' | Channel forced down |
| B'xxxxx101' | Channel forced up |
| B'xxxxx110' | Channel locked |

DATABYTE8 = alarm & auto mode selection

| <i>Contents</i> | <i>Selected program1</i> |
|-----------------|--------------------------|
| B'xxxxxx00' | Auto mode disabled |
| B'xxxxxx01' | Auto mode 1 |
| B'xxxxxx10' | Auto mode 2 |
| B'xxxxxx11' | Auto mode 3 |
| B'xxxxx0xx' | Alarm 1 off |
| B'xxxxx1xx' | Alarm 1 on |
| B'xxx0xxx' | Local alarm 1 |
| B'xxx1xxx' | Global alarm 1 |
| B'xx0xxxx' | Alarm 2 off |
| B'xx1xxxx' | Alarm 2 on |
| B'xx0xxxxx' | Local alarm 2 |
| B'xx1xxxxx' | Global alarm 2 |
| B'x0xxxxxx' | Sunrise disabled |
| B'x1xxxxxx' | Sunrise enabled |
| B'0xxxxxxx' | Sunset disabled |
| B'1xxxxxxx' | Sunset enabled |

‘Linked push button status’ received:

SID10-SID9 = 00 (highest priority)
SID8...SID1 = Address of linked push button module
RTR = 0
DLC3...DLC0 = 4 databytes received
DATABYTE1 = COMMAND_PUSH_BUTTON_STATUS (H'00')
DATABYTE2 = Linked push buttons just pressed (1 = just pressed)
DATABYTE3 = Linked push buttons just released (1 = just released)
DATABYTE4 = Linked push buttons long pressed (1 = longer than 0.85s pressed)

‘Clear linked button LED’ command received:

SID10-SID9 = 11 (lowest priority)
SID8...SID1 = Address of linked push button module
RTR = 0
DLC3...DLC0 = 2 databytes received
DATABYTE1 = COMMAND_CLEAR_LED (H'F5')
DATABYTE2 = LEDs to clear (a one clears the corresponding LED)

‘Set real time clock’ command received:

SID10-SID9 = 11 (lowest priority)
SID8...SID1 = H'00'
RTR = 0
DLC3...DLC0 = 4 databytes to send
DATABYTE1 = COMMAND_SET_REALTIME_CLOCK (H'D8')
DATABYTE2 = Day of week

| <i>Contents day of week'</i> | <i>Description</i> |
|------------------------------|--------------------|
| H'00' | Monday |
| H'01' | Tuesday |
| H'02' | Wednesday |
| H'03' | Thursday |
| H'04' | Friday |
| H'05' | Saturday |
| H'06' | Sunday |

DATABYTE3 = Hours (0...23)
DATABYTE4 = Minutes (0...59)

‘Set date’ command received:

SID10-SID9 = 11 (lowest priority)
SID8...SID1 = H'00'
RTR = 0
DLC3...DLC0 = 5 databytes to send
DATABYTE1 = COMMAND_SET_REALTIME_DATE (H'B7')
DATABYTE2 = Day (1...31)
DATABYTE3 = Month (1...12)
DATABYTE4 = High byte of Year
DATABYTE5 = Low byte of Year

‘Set daylight savings’ command received (Build1235 or higher):

SID10-SID9 = 11 (lowest priority)
SID8...SID1 = H'00'
RTR = 0
DLC3...DLC0 = 2 databytes to send
DATABYTE1 = COMMAND_SET_DAYLIGHT_SAVING (H'AF')
DATABYTE2 = 0 =disabled / 1 = enabled

‘Enable/disable global sunrise/sunset related actions’ command received (Build1235 or higher):

SID10-SID9 = 11 (lowest priority)

SID8...SID1 = H'00'

RTR = 0

DLC3...DLC0 = 3 databytes to send

DATABYTE1 = COMMAND_ENA_DIS_SUNRISE_SUNSET (H'AE')

DATABYTE2 = Channel

| <i>Contents</i> | <i>Description</i> |
|------------------------|---------------------------|
| B'xxxxxxx1' | Channel 1 |
| B'xxxxxxx1x' | Channel 2 |

DATABYTE3 = enable/disable flags

| <i>Contents</i> | <i>Description</i> |
|------------------------|---------------------------------|
| B'xxxxxxx0' | Disable sunrise related actions |
| B'xxxxxxx1' | Enable sunrise related actions |
| B'xxxxxxx0x' | Disable sunset related actions |
| B'xxxxxxx1x' | Enable sunset related actions |

‘Enable/disable local sunrise/sunset related actions’ command received (Build1235 or higher):

SID10-SID9 = 11 (lowest priority)

SID8...SID1 = Module address

RTR = 0

DLC3...DLC0 = 3 databytes to send

DATABYTE1 = COMMAND_ENA_DIS_SUNRISE_SUNSET (H'AE')

DATABYTE2 = Channel

| <i>Contents</i> | <i>Description</i> |
|------------------------|---------------------------|
| B'xxxxxxx1' | Channel 1 |
| B'xxxxxxx1x' | Channel 2 |

DATABYTE3 = enable/disable flags

| <i>Contents</i> | <i>Description</i> |
|------------------------|---------------------------------|
| B'xxxxxxx0' | Disable sunrise related actions |
| B'xxxxxxx1' | Enable sunrise related actions |
| B'xxxxxxx0x' | Disable sunset related actions |
| B'xxxxxxx1x' | Enable sunset related actions |

‘Set global clock alarm’ command received:

SID10-SID9 = 11 (lowest priority)

SID8...SID1 = H'00'

RTR = 0

DLC3...DLC0 = 7 databytes to send

DATABYTE1 = COMMAND_SET_ALARM_CLOCK (H'C3')

DATABYTE2 = Alarm number (1 or 2)

DATABYTE3 = Wake up hour (0...23)

DATABYTE4 = Wake up minute (0...59)

DATABYTE5 = Go to bed hour (0...23)

DATABYTE6 = Go to bed minute (0...59)

DATABYTE7 = Clock alarm enable flag (0 = disabled / 1 = enabled)

‘Real time clock status request’ command received:

SID10-SID9 = 11 (lowest priority)

SID8...SID1 = Module address

RTR = 0

DLC3...DLC0 = 1 databyte to send

DATABYTE1 = COMMAND_REALTIME_CLOCK_STATUS_REQUEST (H'D7')

‘Set local clock alarm’ command received:

SID10-SID9 = 11 (lowest priority)
 SID8...SID1 = Module address
 RTR = 0
 DLC3...DLC0 = 7 databytes to send
 DATABYTE1 = COMMAND_SET_ALARM_CLOCK (H'C3')
 DATABYTE2 = Alarm number (1 or 2)
 DATABYTE3 = Wake up hour (0...23)
 DATABYTE4 = Wake up minute (0...59)
 DATABYTE5 = Go to bed hour (0...23)
 DATABYTE6 = Go to bed minute (0...59)
 DATABYTE7 = Clock alarm enable flag (0 = disabled / 1 = enabled)

‘Switch blind off’ command received:

SID10-SID9 = 00 (highest priority)
 SID8...SID1 = Module address
 RTR = 0
 DLC3...DLC0 = 2 databytes received
 DATABYTE1 = COMMAND_SWITCH_BLIND_OFF (H'04')
 DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind channel</i> |
|-----------------|----------------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

‘Switch blind up’ command received:

SID10-SID9 = 00 (highest priority)
 SID8...SID1 = Module address
 RTR = 0
 DLC3...DLC0 = 5 databytes received
 DATABYTE1 = COMMAND_BLIND_UP (H'05')
 DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind channel</i> |
|-----------------|----------------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

DATABYTE3 = high byte of time out
 DATABYTE4 = mid byte of time out
 DATABYTE5 = low byte of time out

Remark:

[DATABYTE3][DATABYTE4][DATABYTE5] contain a 24-bit time out in seconds
 If the time parameter contains zero then the default time out is selected.
 If the time parameter contains H'FFFFFF' then the blind up output switches permanently on.

‘Switch blind down’ command received:

SID10-SID9 = 00 (highest priority)
 SID8...SID1 = Module address
 RTR = 0
 DLC3...DLC0 = 5 databytes received
 DATABYTE1 = COMMAND_BLIND_DOWN (H'06')
 DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind channel</i> |
|-----------------|----------------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

DATABYTE3 = high byte of time out
 DATABYTE4 = mid byte of time out
 DATABYTE5 = low byte of time out

Remark:

[DATABYTE3][DATABYTE4][DATABYTE5] contain a 24-bit time out in seconds
 If the time parameter contains zero then the default time out is selected.
 If the time parameter contains H'FFFFFF' then the blind down output switches permanently on.

‘Set blind position’ command received:

SID10-SID9 = 00 (highest priority)

SID8...SID1 = Module address

RTR = 0

DLC3...DLC0 = 3 databytes received

DATABYTE1 = COMMAND_BLIND_POS (H'1C')

DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind channel</i> |
|-----------------|----------------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

DATABYTE3 = Blind position (0...100%)

‘Lock channel’ command received:

SID10-SID9 = 00 (highest priority)

SID8...SID1 = Module address

RTR = 0

DLC3...DLC0 = 5 databytes received

DATABYTE1 = COMMAND_LOCK (H'1A')

DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind channel</i> |
|-----------------|----------------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

DATABYTE3 = high byte of delay time

DATABYTE4 = mid byte of delay time

DATABYTE5 = low byte of delay time

Remark:

[DATABYTE3][DATABYTE4][DATABYTE5] contain a 24-bit time in seconds

The command will be skipped when the time parameter contains zero.

When the time parameter contains H'FFFFFF' then the channel will be permanently locked.

‘Unlock channel’ command received:

SID10-SID9 = 00 (highest priority)

SID8...SID1 = Module address

RTR = 0

DLC3...DLC0 = 2 databytes received

DATABYTE1 = COMMAND_UNLOCK (H'1B')

DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind channel</i> |
|-----------------|----------------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

‘Forced up’ command received:

SID10-SID9 = 00 (highest priority)

SID8...SID1 = Module address

RTR = 0

DLC3...DLC0 = 5 databytes received

DATABYTE1 = COMMAND_FORCED_OFF (H'12')

DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind channel</i> |
|-----------------|----------------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

DATABYTE3 = high byte of delay time

DATABYTE4 = mid byte of delay time

DATABYTE5 = low byte of delay time

Remark:

[DATABYTE3][DATABYTE4][DATABYTE5] contain a 24-bit time in seconds

The command will be skipped when the time parameter contains zero or the channel is already locked.

When the time parameter contains H'FFFFFF' then the channel is permanently forced up.

‘Cancel forced up’ command received:

SID10-SID9 = 00 (highest priority)
 SID8...SID1 = Module address
 RTR = 0
 DLC3...DLC0 = 2 databytes received
 DATABYTE1 = COMMAND_CANCEL_FORCED_OFF (H'13')
 DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind channel</i> |
|-----------------|----------------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

‘Forced down’ command received:

SID10-SID9 = 00 (highest priority)
 SID8...SID1 = Module address
 RTR = 0
 DLC3...DLC0 = 5 databytes received
 DATABYTE1 = COMMAND_FORCED_ON (H'14')
 DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind channel</i> |
|-----------------|----------------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

DATABYTE3 = high byte of delay time
 DATABYTE4 = mid byte of delay time
 DATABYTE5 = low byte of delay time

Remark:

[DATABYTE3][DATABYTE4][DATABYTE5] contain a 24-bit time in seconds

The command will be skipped when the time parameter contains zero or the channel is already locked or forced up.

When the time parameter contains H'FFFFFF' then the channel is permanently forced down.

‘Cancel forced down’ command received:

SID10-SID9 = 00 (highest priority)
 SID8...SID1 = Module address
 RTR = 0
 DLC3...DLC0 = 2 databytes received
 DATABYTE1 = COMMAND_CANCEL_FORCED_ON (H'15')
 DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind channel</i> |
|-----------------|----------------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

‘Inhibit’ command received:

SID10-SID9 = 00 (highest priority)
 SID8...SID1 = Module address
 RTR = 0
 DLC3...DLC0 = 5 databytes received
 DATABYTE1 = COMMAND_INHIBIT (H'16')
 DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind channel</i> |
|-----------------|----------------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

DATABYTE3 = high byte of delay time
 DATABYTE4 = mid byte of delay time
 DATABYTE5 = low byte of delay time

Remark:

[DATABYTE3][DATABYTE4][DATABYTE5] contain a 24-bit time in seconds

The command will be skipped when the time parameter contains zero or the channels is already locked, forced up or forced down.

When the time parameter contains H'FFFFFF' then the channel is permanently inhibited.

‘Inhibit preset up’ command received:

SID10-SID9 = 00 (highest priority)

SID8...SID1 = Module address

RTR = 0

DLC3...DLC0 = 5 databytes received

DATABYTE1 = COMMAND_INHIBIT_PRESET_UP (H'18')

DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind channel</i> |
|-----------------|----------------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

DATABYTE3 = high byte of delay time

DATABYTE4 = mid byte of delay time

DATABYTE5 = low byte of delay time

Remark:

[DATABYTE3][DATABYTE4][DATABYTE5] contain a 24-bit time in seconds

The command will be skipped when the time parameter contains zero or the channel is already locked, forced up, forced down or inhibited.

When the time parameter contains H'FFFFFF' then the channel is permanently inhibited with preset up.

‘Inhibit preset down’ command received:

SID10-SID9 = 00 (highest priority)

SID8...SID1 = Module address

RTR = 0

DLC3...DLC0 = 5 databytes received

DATABYTE1 = COMMAND_INHIBIT_PRESET_DOWN (H'19')

DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind channel</i> |
|-----------------|----------------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

DATABYTE3 = high byte of delay time

DATABYTE4 = mid byte of delay time

DATABYTE5 = low byte of delay time

Remark:

[DATABYTE3][DATABYTE4][DATABYTE5] contain a 24-bit time in seconds

The command will be skipped when the time parameter contains zero or the channel is already locked, forced up, forced down, inhibited or inhibited with preset up.

When the time parameter contains H'FFFFFF' then the channel is permanently inhibited with preset down.

‘Cancel inhibit’ command received:

SID10-SID9 = 00 (highest priority)

SID8...SID1 = Module address

RTR = 0

DLC3...DLC0 = 2 databytes received

DATABYTE1 = COMMAND_CANCEL_INHIBIT (H'17')

DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind channel</i> |
|-----------------|----------------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

‘Blind status request’ command received:

SID10-SID9 = 11 (lowest priority)

SID8...SID1 = Module address

RTR = 0

DLC3...DLC0 = 2 databytes received

DATABYTE1 = COMMAND_RELAY_STATUS_REQUEST (H'FA')

DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind channel</i> |
|-----------------|----------------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

‘Module type request’ command received:

SID10-SID9 = 11 (lowest priority)
 SID8...SID1 = Module address
 RTR = 1
 DLC3...DLC0 = 0 databytes received

‘Blind name request’ command received:

SID10-SID9 = 11 (lowest priority)
 SID8...SID1 = Module address
 RTR = 0
 DLC3...DLC0 = 2 databytes received
 DATABYTE1 = COMMAND_BLIND_NAME_REQUEST (H'EF')
 DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind channel</i> |
|-----------------|----------------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

‘Read data from memory’ command received:

SID10-SID9 = 11 (lowest priority)
 SID8...SID1 = Module address
 RTR = 0
 DLC3...DLC0 = 3 databytes received
 DATABYTE1 = COMMAND_READ_DATA_FROM_MEMORY (H'FD')
 DATABYTE2 = High memory address (H'00'...H'01')
 DATABYTE3 = LOW memory address (H'00'...H'FF')

‘Read data block from memory’ command received:

SID10-SID9 = 11 (lowest priority)
 SID8...SID1 = Module address
 RTR = 0
 DLC3...DLC0 = 3 databytes received
 DATABYTE1 = COMMAND_READ_MEMORY_BLOCK (H'C9')
 DATABYTE2 = High memory address
 DATABYTE3 = LOW memory address

Remark: Valid address range: H'0000' to H'01FC'

‘Memory dump request’ command received:

SID10-SID9 = 11 (lowest priority)
 SID8...SID1 = Module address
 RTR = 0
 DLC3...DLC0 = 1 databytes received
 DATABYTE1 = COMMAND_MEMORY_DUMP_REQUEST (H'CB')

‘Write data to memory’ command received:

SID10-SID9 = 11 (lowest priority)
 SID8...SID1 = Module address
 RTR = 0
 DLC3...DLC0 = 4 databytes received
 DATABYTE1 = COMMAND_WRITE_DATA_TO_MEMORY (H'FC')
 DATABYTE2 = High memory address (H'00'...H'01')
 DATABYTE3 = LOW memory address (H'00'...H'FF')
 DATABYTE4 = memory data to write

Remark: Wait at least 10ms or wait for ‘memory data block’ feedback before sending a next command on the velbus.

‘Write memory block’ command received:

SID10-SID9 = 11 (lowest priority)
SID8...SID1 = Module address
RTR = 0
DLC3...DLC0 = 7 databytes received
DATABYTE1 = COMMAND_WRITE_MEMORY_BLOCK (H'CA')
DATABYTE2 = High memory address
DATABYTE3 = LOW memory address
DATABYTE4 = memory databyte1 to write
DATABYTE5 = memory databyte2 to write
DATABYTE6 = memory databyte3 to write
DATABYTE7 = memory databyte4 to write

Remark:

Valid address range: H'0000' to H'01FC'

Wait for 'memory data block' feedback before sending a next command on the velbus.

‘Bus error counter status request’ command received:

SID10-SID9 = 11 (lowest priority)
SID8...SID1 = Module address
RTR = 0
DLC3...DLC0 = 1 databytes to send
DATABYTE1 = COMMAND_BUS_ERROR_COUNTER_STATUS_REQUEST (H'D9')

‘Select Auto Mode’ command received:

SID10-SID9 = 11 (lowest priority)
SID8...SID1 = Module address
RTR = 0
DLC3...DLC0 = 3 databytes received
DATABYTE1 = COMMAND_SELECT_PROGRAM (H'B3')
DATABYTE2 = Blind channel

| <i>Contents</i> | <i>Blind channel</i> |
|-----------------|----------------------|
| B'00000001' | Blind 1 |
| B'00000010' | Blind 2 |

DATABYTE3 = Auto mode

| <i>Contents</i> | <i>Selected auto mode</i> |
|-----------------|---------------------------|
| 0 | All auto modes disabled |
| 1 | Auto mode 1 |
| 2 | Auto mode 2 |
| 3 | Auto mode 3 |

‘Write module address & serial number’ command received:

SID10-SID9 = 01 (firmware priority)
SID8...SID1 = Current module address
RTR = 0
DLC3...DLC0 = 7 databytes received
DATABYTE1 = COMMAND_WRITE_ADDR_SERIALNR (H'6A')
DATABYTE2 = VMB2BLE_MODULE_TYPE (H'1D')
DATABYTE3 = current high byte SERIAL NUMBER
DATABYTE4 = current low byte SERIAL NUMBER
DATABYTE5 = new module address
DATABYTE6 = new high byte SERIAL NUMBER
DATABYTE7 = new low byte SERIAL NUMBER

Memory map:

| Address | Contents | Address | Contents |
|---------|--|---------|--|
| H'0000' | Blind 1 name character 1 | H'0001' | Blind 1 name character 2 |
| ... | ... | ... | ... |
| H'000E' | Blind 1 name character 15 | H'000F' | Blind 1 name character 16 |
| H'0010' | Blind 2 name character 1 | H'0011' | Blind 2 name character 2 |
| ... | ... | ... | ... |
| H'001E' | Blind 2 name character 15 | H'001F' | Blind 2 name character 16 |
| H'0020' | Blind 1 time out | H'0021' | Low byte 256/(Blind 1 timeout*0.0131072) |
| H'0022' | High byte 256/(Blind 1 timeout*0.0131072) | H'0023' | Blind 2 time out |
| H'0024' | Low byte 256/(Blind 2 timeout*0.0131072) | H'0025' | High byte 256/(Blind 2 timeout*0.0131072) |
| H'0026' | Not used | H'0027' | Not used |
| ... | ... | ... | ... |
| H'008A' | Not used | H'008B' | Not used |
| H'008C' | Blind 1 Sunrise offset (-128'...127') | H'008D' | Blind 1 Sunset offset (-128'...127') |
| H'008E' | Blind 2 Sunrise offset (-128'...127') | H'008F' | Blind 2 Sunset offset (-128'...127') |
| H'0090' | Blind 1 Wake up 1 offset (-128'...127') | H'0091' | Not used |
| H'0092' | Blind 1 Go to bed 1 offset (-128'...127') | H'0093' | Not used |
| H'0094' | Blind 1 Wake up 2 offset (-128'...127') | H'0095' | Not used |
| H'0096' | Blind 1 Go to bed 2 offset (-128'...127') | H'0097' | Not used |
| H'0098' | Blind 2 Wake up 1 offset (-128'...127') | H'0099' | Not used |
| H'009A' | Blind 2 Go to bed 1 offset (-128'...127') | H'009B' | Not used |
| H'009C' | Blind 2 Wake up 2 offset (-128'...127') | H'009D' | Not used |
| H'009E' | Blind 2 Go to bed 2 offset (-128'...127') | H'009F' | Not used |
| H'00A0' | Blind 1 Wake up 1 hour (0...23) | H'00A1' | Blind 1 Wake up 1 minutes (0...59) |
| H'00A2' | Blind 1 Go to bed 1 hour (0...23) | H'00A3' | Blind 1 Go to bed 1 minutes (0...59) |
| H'00A4' | Blind 1 Wake up 2 hour (0...23) | H'00A5' | Blind 1 Wake up 2 minutes (0...59) |
| H'00A6' | Blind 1 Go to bed 2 hour (0...23) | H'00A7' | Blind 1 Go to bed 2 minutes (0...59) |
| H'00A8' | Blind 2 Wake up 1 hour (0...23) | H'00A9' | Blind 2 Wake up 1 minutes (0...59) |
| H'00AA' | Blind 2 Go to bed 1 hour (0...23) | H'00AB' | Blind 2 Go to bed 1 minutes (0...59) |
| H'00AC' | Blind 2 Wake up 2 hour (0...23) | H'00AD' | Blind 2 Wake up 2 minutes (0...59) |
| H'00AE' | Blind 2 Go to bed 2 hour (0...23) | H'00AF' | Blind 2 Go to bed 2 minutes (0...59) |
| H'00B0' | Sunrise hour at 21 December (0...23) | H'00B1' | Sunrise minutes at 21 December (0...59) |
| H'00B2' | Sunrise 21 January – sunrise 5 January (-128'..127') | H'00B3' | Sunrise 5 February – sunrise 21 January (-128'..127') |
| H'00B4' | Sunrise 21 February – sunrise 5 February (-128'..127') | H'00B5' | Sunrise 5 March – sunrise 21 February (-128'..127') |
| H'00B6' | Sunrise 21 March – sunrise 5 March (-128'..127') | H'00B7' | Sunrise 5 April – sunrise 21 March (-128'..127') |
| H'00B8' | Sunrise 21 April – sunrise 5 April (-128'..127') | H'00B9' | Sunrise 5 May – sunrise 21 April (-128'..127') |
| H'00BA' | Sunrise 21 May – sunrise 5 May (-128'..127') | H'00BB' | Sunrise 5 June – sunrise 21 May (-128'..127') |
| H'00BC' | Sunrise 21 June – sunrise 5 June (-128'..127') | H'00BD' | Sunrise 5 July – sunrise 21 June (-128'..127') |
| H'00BE' | Sunrise 21 July – sunrise 5 July (-128'..127') | H'00BF' | Sunrise 5 August – sunrise 21 July (-128'..127') |
| H'00C0' | Sunrise 21 August – sunrise 5 August (-128'..127') | H'00C1' | Sunrise 5 September – sunrise 21 August (-128'..127') |
| H'00C2' | Sunrise 21 September – sunrise 5 September (-128'..127') | H'00C3' | Sunrise 5 October – sunrise 21 September (-128'..127') |
| H'00C4' | Sunrise 21 October – sunrise 5 October (-128'..127') | H'00C5' | Sunrise 5 November – sunrise 21 October (-128'..127') |
| H'00C6' | Sunrise 21 November – sunrise 5 November (-128'..127') | H'00C7' | Sunrise 5 December – sunrise 21 November (-128'..127') |
| H'00C8' | Sunrise 21 December – sunrise 5 December (-128'..127') | H'00C9' | Sunrise 5 January – sunrise 21 December (-128'..127') |
| H'00CA' | Sunset hour at 21 December (0...23) | H'00CB' | Sunset minutes at 21 December (0...59) |
| H'00CC' | Sunset 21 January – sunrise 5 January (-128'..127') | H'00CD' | Sunset 5 February – sunrise 21 January (-128'..127') |
| H'00CE' | Sunset 21 February – sunrise 5 February (-128'..127') | H'00CF' | Sunset 5 March – sunrise 21 February (-128'..127') |
| H'00D0' | Sunset 21 March – sunrise 5 March (-128'..127') | H'00D1' | Sunset 5 April – sunrise 21 March (-128'..127') |
| H'00D2' | Sunset 21 April – sunrise 5 April (-128'..127') | H'00D3' | Sunset 5 May – sunrise 21 April (-128'..127') |
| H'00D4' | Sunset 21 May – sunrise 5 May (-128'..127') | H'00D5' | Sunset 5 June – sunrise 21 May (-128'..127') |
| H'00D6' | Sunset 21 June – sunrise 5 June (-128'..127') | H'00D7' | Sunset 5 July – sunrise 21 June (-128'..127') |
| H'00D8' | Sunset 21 July – sunrise 5 July (-128'..127') | H'00D9' | Sunset 5 August – sunrise 21 July (-128'..127') |
| H'00DA' | Sunset 21 August – sunrise 5 August (-128'..127') | H'00DA' | Sunset 5 September – sunrise 21 August (-128'..127') |
| H'00DC' | Sunset 21 September – sunrise 5 September (-128'..127') | H'00DC' | Sunset 5 October – sunrise 21 September (-128'..127') |
| H'00DE' | Sunset 21 October – sunrise 5 October (-128'..127') | H'00DF' | Sunset 5 November – sunrise 21 October (-128'..127') |
| H'00E0' | Sunset 21 November – sunrise 5 November (-128'..127') | H'00E1' | Sunset 5 December – sunrise 21 November (-128'..127') |
| H'00E2' | Sunset 21 December – sunrise 5 December (-128'..127') | H'00E3' | Sunset 5 January – sunrise 21 December (-128'..127') |
| H'00E4' | Not used | H'00E5' | Not used |
| ... | ... | ... | ... |
| H'00EC' | Not used | H'00ED' | Not used |
| H'00EE' | Channels Forced up | H'00EF' | Channels Forced down |
| H'00F0' | Channels Inhibited | H'00F1' | Channels Inhibited preset up |
| H'00F2' | Channels Inhibited preset down | H'00F3' | Channels Locked/Unlocked |

| | | | |
|---------|--------------------------------------|---------|-----------------------------------|
| H'00F4' | Blind 1 Auto mode (none , 1, 2 or 3) | H'00F5' | Blind 1 Alarm clock configuration |
| H'00F6' | Blind 2 Auto mode (none , 1, 2 or 3) | H'00F7' | Blind 2 Alarm clock configuration |
| H'00F8' | Current day (1...31) | H'00F9' | Current month (1...12) |
| H'00FA' | Current year high byte | H'00FB' | Current year low byte |
| H'00FC' | Module Zone Address | H'00FD' | Module Address |
| H'00FE' | Serial number high | H'00FF' | Serial number low |

Remark:

Unused locations contain H'FF'

Do not overwrite the following address location:

| | |
|-------------------|-------------------------------------|
| H'00EE' | Channels Forced up |
| H'00EF' | Channels Forced down |
| H'00F0' | Channels Inhibited |
| H'00F1' | Channels Inhibited preset up |
| H'00F2' | Channels Inhibited preset down |
| H'00F3' | Channel locked/unlocked |
| H'00F4' | Blind 1 Auto mode (none, 1, 2 or 3) |
| H'00F5' | Blind 1 Alarm clock configuration |
| H'00F6' | Blind 2 Auto mode (none, 1, 2 or 3) |
| H'00F7' | Blind 2 Alarm clock configuration |
| H'00F8' | Current day of month |
| H'00F9' | Current month |
| H'00FA' & H'00FB' | Current year |
| H'00FC' | Module zone address |
| H'00FD' | Module address |
| H'00FE' & H'00FF' | Module serial number |

Blind timeout

| <i>Contents</i> | <i>Time out</i> |
|-----------------|-----------------------------|
| 0 | No timeout (continuous) |
| 1 | 1.3 sec (1 *1.31072s) |
| 2 | 2.6 sec (2 *1.31072s) |
| ... | ... |
| 255 | 5min 34 sec (255 *1.31072s) |

Channel forced up

| <i>Contents</i> | <i>Channel forced up</i> |
|-----------------|-----------------------------|
| B'xxxxxxxx0' | Blind 1 forced up cancelled |
| B'xxxxxxxx1' | Blind 1 forced up |
| B'xxxxxxxx0x' | Blind 2 forced up cancelled |
| B'xxxxxxxx1x' | Blind 2 forced up |

Channel forced down

| <i>Contents</i> | <i>Channel forced down</i> |
|-----------------|-------------------------------|
| B'xxxxxxxx0' | Blind 1 forced down cancelled |
| B'xxxxxxxx1' | Blind 1 forced down |
| B'xxxxxxxx0x' | Blind 2 forced down cancelled |
| B'xxxxxxxx1x' | Blind 2 forced down |

Channel inhibited

| <i>Contents</i> | <i>Channel inhibited</i> |
|-----------------|---------------------------|
| B'xxxxxxxx0' | Blind 1 inhibit cancelled |
| B'xxxxxxxx1' | Blind 1 inhibit |
| B'xxxxxxxx0x' | Blind 2 inhibit cancelled |
| B'xxxxxxxx1x' | Blind 2 inhibit |

Channel inhibited preset up

| <i>Contents</i> | <i>Channel inhibited but preset up</i> |
|-----------------|--|
| B'xxxxxxxx0' | Blind 1 inhibit preset up cancelled |

| | |
|--------------|-------------------------------------|
| B'xxxxxxx1' | Blind 1 inhibit preset up |
| B'xxxxxxx0x' | Blind 2 inhibit preset up cancelled |
| B'xxxxxxx1x' | Blind 2 inhibit preset up |

Channel inhibited preset down

| <i>Contents</i> | <i>Channel inhibited but preset down</i> |
|------------------------|---|
| B'xxxxxxx0' | Blind 1 inhibit preset down cancelled |
| B'xxxxxxx1' | Blind 1 inhibit preset down |
| B'xxxxxxx0x' | Blind 2 inhibit preset down cancelled |
| B'xxxxxxx1x' | Blind 2 inhibit preset down |

Channel locked/unlocked

| <i>Contents</i> | <i>Channel locked/unlocked</i> |
|------------------------|---------------------------------------|
| B'xxxxxxx0' | Blind 1 unlocked |
| B'xxxxxxx1' | Blind 1 locked |
| B'xxxxxxx0x' | Blind 2 unlocked |
| B'xxxxxxx1x' | Blind 2 locked |

Blind Auto mode selection

| <i>Contents</i> | <i>Selected auto mode</i> |
|------------------------|----------------------------------|
| 0 | No auto mode activated |
| 1 | Auto mode 1 activated |
| 2 | Auto mode 2 activated |
| 3 | Auto mode 3 activated |

Blind Alarm clock configuration

| <i>Contents</i> | <i>Alarm clock configuration</i> |
|------------------------|---|
| B'xxxxxxx0' | Alarm 1 disabled |
| B'xxxxxxx1' | Alarm 1 enabled |
| B'xxxxxx0x' | Local alarm 1 |
| B'xxxxxx1x' | Global alarm 1 |
| B'xxxxx0xx' | Alarm 2 disabled |
| B'xxxxx1xx' | Alarm 2 enabled |
| B'xxxx0xxx' | Local alarm 2 |
| B'xxxx1xxx' | Global alarm 2 |
| B'xxx0xxxx' | Sunrise disabled |
| B'xxx1xxxx' | Sunrise enabled |
| B'xx0xxxxx' | Sunset disabled |
| B'xx1xxxxx' | Sunset enabled |
| B'x0xxxxxx' | Summer time disabled |
| B'x1xxxxxx' | Summer time enabled |

| Address | Contents | Address | Contents |
|----------------|--------------------------------------|----------------|-------------------------------------|
| H'0100' | Push button 1 module address | H'0101' | Push button 1 bit number |
| H'0102' | Push button 1 action for channel 1 | H'0103' | Push button 1 first time parameter |
| H'0104' | Push button 1 second time parameter | H'0105' | Push button 2 module address |
| H'0106' | Push button 2 bit number | H'0107' | Push button 2 action for channel 1 |
| H'0108' | Push button 2 first parameter | H'0109' | Push button 2 second parameter |
| ... | ... | ... | ... |
| H'0178' | Push button 25 module address | H'0179' | Push button 25 bit number |
| H'017A' | Push button 25 action for channel 1 | H'017B' | Push button 25 first time parameter |
| H'017C' | Push button 25 second time parameter | H'017D' | Not used |
| H'017E' | Not used | H'017F' | Not used |

| Address | Contents | Address | Contents |
|----------------|--------------------------------------|----------------|-------------------------------------|
| H'0180' | Push button 1 module address | H'0181' | Push button 1 bit number |
| H'0182' | Push button 1 action for channel 2 | H'0183' | Push button 1 first time parameter |
| H'0184' | Push button 1 second time parameter | H'0185' | Push button 2 module address |
| H'0186' | Push button 2 bit number | H'0187' | Push button 2 action for channel 2 |
| H'0188' | Push button 2 first time parameter | H'0189' | Push button 2 second time parameter |
| ... | ... | ... | ... |
| H'01F8' | Push button 25 module address | H'01F9' | Push button 25 bit number |
| H'01FA' | Push button 25 action for channel 2 | H'01FB' | Push button 25 first time parameter |
| H'01FC' | Push button 25 second time parameter | H'01FD' | Not used |
| H'01FE' | Not used | H'01FF' | Not used |

Remark:

Unused locations contain H'FF'

| Action | Description | First time parameter | Second time parameter |
|--------|--|----------------------|-----------------------|
| H'00' | Up | H'FF' | H'FF' |
| H'01' | Direct up | Delayed on time | H'FF' |
| H'02' | Direct up at release | Delayed on time | H'FF' |
| H'03' | Down | H'FF' | H'FF' |
| H'04' | Direct down | Delayed on time | H'FF' |
| H'05' | Direct down at release | Delayed on time | H'FF' |
| H'06' | Up/down | H'FF' | H'FF' |
| H'07' | Go to position | Delayed on time | Position (0 to 100%) |
| H'08' | Go to position at release | Delayed on time | Position (0 to 100%) |
| H'09' | Up in auto mode 1 | H'FF' | H'FF' |
| H'0A' | Direct up in auto mode 1 | Delayed on time | H'FF' |
| H'0B' | Direct up at release in auto mode 1 | Delayed on time | H'FF' |
| H'0C' | Down in auto mode 1 | H'FF' | H'FF' |
| H'0D' | Direct down in auto mode 1 | Delayed on time | H'FF' |
| H'0E' | Direct down at release in auto mode 1 | Delayed on time | H'FF' |
| H'0F' | Up/down in auto mode 1 | H'FF' | H'FF' |
| H'10' | Go to position in auto mode 1 | Delayed on time | Position (0 to 100%) |
| H'11' | Go to position at release in auto mode 1 | Delayed on time | Position (0 to 100%) |
| H'12' | Select auto mode 1 | H'FF' | H'FF' |
| H'13' | Select auto mode 1 at release | H'FF' | H'FF' |
| H'14' | Select/deselect auto mode 1 | H'FF' | H'FF' |
| H'15' | Deselect auto mode | H'FF' | H'FF' |
| H'16' | Deselect auto mode at release | H'FF' | H'FF' |
| H'17' | Up in auto mode 2 | H'FF' | H'FF' |
| H'18' | Direct up in auto mode 2 | Delayed on time | H'FF' |
| H'19' | Direct up at release in auto mode 2 | Delayed on time | H'FF' |
| H'1A' | Down in auto mode 2 | H'FF' | H'FF' |
| H'1B' | Direct down in auto mode 2 | Delayed on time | H'FF' |
| H'1C' | Direct down at release in auto mode 2 | Delayed on time | H'FF' |
| H'1D' | Up/down in auto mode 2 | H'FF' | H'FF' |
| H'1E' | Position in auto mode 2 | Delayed on time | Position (0 to 100%) |
| H'1F' | Go to position at release in auto mode 2 | Delayed on time | Position (0 to 100%) |
| H'20' | Select auto mode 2 | H'FF' | H'FF' |
| H'21' | Select auto mode 2 at release | H'FF' | H'FF' |
| H'22' | Select/deselect auto mode 2 | H'FF' | H'FF' |
| H'23' | Up in auto mode 3 | H'FF' | H'FF' |
| H'24' | Direct up in auto mode 3 | Delayed on time | H'FF' |
| H'25' | Direct up at release in auto mode 3 | Delayed on time | H'FF' |
| H'26' | Down in auto mode 3 | H'FF' | H'FF' |
| H'27' | Direct down in auto mode 3 | Delayed on time | H'FF' |
| H'28' | Direct down at release in auto mode 3 | Delayed on time | H'FF' |
| H'29' | Up/down in auto mode 3 | H'FF' | H'FF' |
| H'2A' | Position in auto mode 3 | Delayed on time | Position (0 to 100%) |
| H'2B' | Go to position at release in auto mode 3 | Delayed on time | Position (0 to 100%) |
| H'2C' | Select auto mode 3 | H'FF' | H'FF' |
| H'2D' | Select auto mode 3 at release | H'FF' | H'FF' |
| H'2E' | Select/deselect auto mode 3 | H'FF' | H'FF' |
| H'2F' | Lock at closed switch | H'FF' | H'FF' |
| H'30' | Lock at open switch | H'FF' | H'FF' |
| H'31' | Lock | Timeout | H'FF' |
| H'32' | Lock/unlock | Timeout | H'FF' |
| H'33' | Unlock | H'FF' | H'FF' |
| H'34' | Forced up at closed switch | H'FF' | H'FF' |
| H'35' | Forced up at open switch | H'FF' | H'FF' |
| H'36' | Forced up | Timeout | H'FF' |
| H'37' | Forced up/cancel forced up | Timeout | H'FF' |
| H'38' | Cancel forced up | H'FF' | H'FF' |
| H'39' | Forced down at closed switch | H'FF' | H'FF' |
| H'3A' | Forced down at open switch | H'FF' | H'FF' |
| H'3B' | Forced down | Timeout | H'FF' |
| H'3C' | Forced down/cancel forced down | Timeout | H'FF' |
| H'3D' | Cancel forced down | H'FF' | H'FF' |
| H'3E' | Inhibit at closed switch | H'FF' | H'FF' |
| H'3F' | Inhibit at open switch | H'FF' | H'FF' |
| H'40' | Inhibit | Timeout | H'FF' |

| | | | |
|-------|--|---------|-------|
| H'41' | Inhibit /cancel inhibit | Timeout | H'FF' |
| H'42' | Cancel inhibit | H'FF' | H'FF' |
| H'43' | Inhibit but preset up at closed switch | H'FF' | H'FF' |
| H'44' | Inhibit but preset up at open switch | H'FF' | H'FF' |
| H'45' | Inhibit but preset up | Timeout | H'FF' |
| H'46' | Inhibit but preset up/cancel inhibit preset up | Timeout | H'FF' |
| H'47' | Cancel inhibit but preset up | H'FF' | H'FF' |
| H'48' | Inhibit but preset down at closed switch | H'FF' | H'FF' |
| H'49' | Inhibit but preset down at closed switch | H'FF' | H'FF' |
| H'4A' | Inhibit but preset down | Timeout | H'FF' |
| H'4B' | Inhibit but preset down/cancel inhibit preset down | Timeout | H'FF' |
| H'4C' | Cancel but inhibit preset down | H'FF' | H'FF' |
| H'4D' | Enable Alarm 1 at closed switch | H'FF' | H'FF' |
| H'4E' | Enable Alarm 1 at open switch | H'FF' | H'FF' |
| H'4F' | Disable Alarm 1 at closed switch | H'FF' | H'FF' |
| H'50' | Disable Alarm 1 at open switch | H'FF' | H'FF' |
| H'51' | Enable Alarm 1 | H'FF' | H'FF' |
| H'52' | Enable/disable Alarm 1 | H'FF' | H'FF' |
| H'53' | Disable Alarm 1 | H'FF' | H'FF' |
| H'54' | Enable Alarm 2 at closed switch | H'FF' | H'FF' |
| H'55' | Enable Alarm 2 at open switch | H'FF' | H'FF' |
| H'56' | Disable Alarm 2 at closed switch | H'FF' | H'FF' |
| H'57' | Disable Alarm 2 at open switch | H'FF' | H'FF' |
| H'58' | Enable Alarm 2 | H'FF' | H'FF' |
| H'59' | Enable/disable Alarm 2 | H'FF' | H'FF' |
| H'5A' | Disable Alarm 2 | H'FF' | H'FF' |
| H'5B' | Enable sunrise at closed switch | H'FF' | H'FF' |
| H'5C' | Enable sunrise at open switch | H'FF' | H'FF' |
| H'5D' | Disable sunrise at closed switch | H'FF' | H'FF' |
| H'5E' | Disable sunrise at open switch | H'FF' | H'FF' |
| H'5F' | Enable sunrise | H'FF' | H'FF' |
| H'60' | Enable/disable sunrise | H'FF' | H'FF' |
| H'61' | Disable sunrise | H'FF' | H'FF' |
| H'62' | Enable sunset at closed switch | H'FF' | H'FF' |
| H'63' | Enable sunset at open switch | H'FF' | H'FF' |
| H'64' | Disable sunset at closed switch | H'FF' | H'FF' |
| H'65' | Disable sunset at open switch | H'FF' | H'FF' |
| H'66' | Enable sunset | H'FF' | H'FF' |
| H'67' | Enable/disable sunset | H'FF' | H'FF' |
| H'68' | Disable sunset | H'FF' | H'FF' |

| Time parameter | Time |
|----------------|----------------|
| 0 | 0s or No timer |
| 1 | 1s |
| 2 | 2s |
| ... | |
| 119 | 1min59s |
| 120 | 2min |
| 121 | 2min15s |
| ... | |
| 131 | 4min45s |
| 132 | 5min |
| 133 | 5min30s |
| ... | |
| 181 | 29min30s |
| 182 | 30min |
| 183 | 31min |
| ... | |
| 211 | 59min |
| 212 | 1h |
| 213 | 1h15min |
| ... | |
| 227 | 4h45min |
| 228 | 5h |
| 229 | 5h30min |
| ... | |
| 237 | 9h30min |
| 238 | 10h |
| 239 | 11h |
| ... | |
| 251 | 23h |
| 252 | 1d |
| 253 | 2d |
| 254 | 3d |
| 255 | infinite |

Memory map version 1 (Build 1409 or higher, but lower than 1809):

| Address | Contents | Address | Contents |
|---------|--|---------|--|
| H'0000' | Blind 1 name character 1 | H'0001' | Blind 1 name character 2 |
| ... | ... | ... | ... |
| H'000E' | Blind 1 name character 15 | H'000F' | Blind 1 name character 16 |
| H'0010' | Blind 2 name character 1 | H'0011' | Blind 2 name character 2 |
| ... | ... | ... | ... |
| H'001E' | Blind 2 name character 15 | H'001F' | Blind 2 name character 16 |
| H'0020' | Blind 1 time out | H'0021' | Low byte 256/(Blind 1 timeout*0.0131072) |
| H'0022' | High byte 256/(Blind 1 timeout*0.0131072) | H'0023' | Blind 2 time out |
| H'0024' | Low byte 256/(Blind 2 timeout*0.0131072) | H'0025' | High byte 256/(Blind 2 timeout*0.0131072) |
| H'0026' | Blind1 unwind delay (s) | H'0027' | Blind2 unwind delay (s) |
| H'0028' | Blind1 collapse delay (s) | H'0029' | Blind2 collapse delay (s) |
| H'002A' | Not used | H'002B' | Not used |
| ... | ... | ... | ... |
| H'003A' | Not used | H'003B' | Not used |
| H'003C' | Blind 1 location id low byte (Build 1409 or higher) | H'003D' | Blind 1 location id high byte (Build 1409 or higher) |
| H'003E' | Blind 1 group id low byte (Build 1409 or higher) | H'003F' | Blind 1 group id high byte (Build 1409 or higher) |
| H'0040' | Blind 1 circuit id low byte (Build 1409 or higher) | H'0041' | Blind 1 circuit id high byte (Build 1409 or higher) |
| H'0042' | Blind 1 load id low byte (Build 1409 or higher) | H'0043' | Blind 1 load id high byte (Build 1409 or higher) |
| H'0044' | Blind 2 location id low byte (Build 1409 or higher) | H'0045' | Blind 2 location id high byte (Build 1409 or higher) |
| H'0046' | Blind 2 group id low byte (Build 1409 or higher) | H'0047' | Blind 2 group id high byte (Build 1409 or higher) |
| H'0048' | Blind 2 circuit id low byte (Build 1409 or higher) | H'0049' | Blind 2 circuit id high byte (Build 1409 or higher) |
| H'004A' | Blind 2 load id low byte (Build 1409 or higher) | H'004B' | Blind 2 load id high byte (Build 1409 or higher) |
| H'004C' | Module name character 1 (Build 1409 or higher) | H'004D' | Module name character 2 (Build 1409 or higher) |
| ... | ... | ... | ... |
| H'008A' | Module name character 63 (Build 1409 or higher) | H'008B' | Module name character 64 (Build 1409 or higher) |
| H'008C' | Blind 1 Sunrise offset (-128'...127') | H'008D' | Blind 1 Sunset offset (-128'...127') |
| H'008E' | Blind 2 Sunrise offset (-128'...127') | H'008F' | Blind 2 Sunset offset (-128'...127') |
| H'0090' | Blind 1 Wake up 1 offset (-128'...127') | H'0091' | Not used |
| H'0092' | Blind 1 Go to bed 1 offset (-128'...127') | H'0093' | Not used |
| H'0094' | Blind 1 Wake up 2 offset (-128'...127') | H'0095' | Not used |
| H'0096' | Blind 1 Go to bed 2 offset (-128'...127') | H'0097' | Not used |
| H'0098' | Blind 2 Wake up 1 offset (-128'...127') | H'0099' | Not used |
| H'009A' | Blind 2 Go to bed 1 offset (-128'...127') | H'009B' | Not used |
| H'009C' | Blind 2 Wake up 2 offset (-128'...127') | H'009D' | Not used |
| H'009E' | Blind 2 Go to bed 2 offset (-128'...127') | H'009F' | Not used |
| H'00A0' | Blind 1 Wake up 1 hour (0...23) | H'00A1' | Blind 1 Wake up 1 minutes (0...59) |
| H'00A2' | Blind 1 Go to bed 1 hour (0...23) | H'00A3' | Blind 1 Go to bed 1 minutes (0...59) |
| H'00A4' | Blind 1 Wake up 2 hour (0...23) | H'00A5' | Blind 1 Wake up 2 minutes (0...59) |
| H'00A6' | Blind 1 Go to bed 2 hour (0...23) | H'00A7' | Blind 1 Go to bed 2 minutes (0...59) |
| H'00A8' | Blind 2 Wake up 1 hour (0...23) | H'00A9' | Blind 2 Wake up 1 minutes (0...59) |
| H'00AA' | Blind 2 Go to bed 1 hour (0...23) | H'00AB' | Blind 2 Go to bed 1 minutes (0...59) |
| H'00AC' | Blind 2 Wake up 2 hour (0...23) | H'00AD' | Blind 2 Wake up 2 minutes (0...59) |
| H'00AE' | Blind 2 Go to bed 2 hour (0...23) | H'00AF' | Blind 2 Go to bed 2 minutes (0...59) |
| H'00B0' | Sunrise hour at 21 December (0...23) | H'00B1' | Sunrise minutes at 21 December (0...59) |
| H'00B2' | Sunrise 21 January – sunrise 5 January (-128'..127') | H'00B3' | Sunrise 5 February – sunrise 21 January (-128'..127') |
| H'00B4' | Sunrise 21 February – sunrise 5 February (-128'..127') | H'00B5' | Sunrise 5 March – sunrise 21 February (-128'..127') |
| H'00B6' | Sunrise 21 March – sunrise 5 March (-128'..127') | H'00B7' | Sunrise 5 April – sunrise 21 March (-128'..127') |
| H'00B8' | Sunrise 21 April – sunrise 5 April (-128'..127') | H'00B9' | Sunrise 5 May – sunrise 21 April (-128'..127') |
| H'00BA' | Sunrise 21 May – sunrise 5 May (-128'..127') | H'00BB' | Sunrise 5 June – sunrise 21 May (-128'..127') |
| H'00BC' | Sunrise 21 June – sunrise 5 June (-128'..127') | H'00BD' | Sunrise 5 July – sunrise 21 June (-128'..127') |
| H'00BE' | Sunrise 21 July – sunrise 5 July (-128'..127') | H'00BF' | Sunrise 5 August – sunrise 21 July (-128'..127') |
| H'00C0' | Sunrise 21 August – sunrise 5 August (-128'..127') | H'00C1' | Sunrise 5 September – sunrise 21 August (-128'..127') |
| H'00C2' | Sunrise 21 September – sunrise 5 September (-128'..127') | H'00C3' | Sunrise 5 October – sunrise 21 September (-128'..127') |
| H'00C4' | Sunrise 21 October – sunrise 5 October (-128'..127') | H'00C5' | Sunrise 5 November – sunrise 21 October (-128'..127') |
| H'00C6' | Sunrise 21 November – sunrise 5 November (-128'..127') | H'00C7' | Sunrise 5 December – sunrise 21 November (-128'..127') |
| H'00C8' | Sunrise 21 December – sunrise 5 December (-128'..127') | H'00C9' | Sunrise 5 January – sunrise 21 December (-128'..127') |
| H'00CA' | Sunset hour at 21 December (0...23) | H'00CB' | Sunset minutes at 21 December (0...59) |
| H'00CC' | Sunset 21 January – sunrise 5 January (-128'..127') | H'00CD' | Sunset 5 February – sunrise 21 January (-128'..127') |
| H'00CE' | Sunset 21 February – sunrise 5 February (-128'..127') | H'00CF' | Sunset 5 March – sunrise 21 February (-128'..127') |
| H'00D0' | Sunset 21 March – sunrise 5 March (-128'..127') | H'00D1' | Sunset 5 April – sunrise 21 March (-128'..127') |
| H'00D2' | Sunset 21 April – sunrise 5 April (-128'..127') | H'00D3' | Sunset 5 May – sunrise 21 April (-128'..127') |
| H'00D4' | Sunset 21 May – sunrise 5 May (-128'..127') | H'00D5' | Sunset 5 June – sunrise 21 May (-128'..127') |

| | | | |
|---------|---|---------|---|
| H'00D6' | Sunset 21 June – sunrise 5 June (-128'..127') | H'00D7' | Sunset 5 July – sunrise 21 June (-128'..127') |
| H'00D8' | Sunset 21 July – sunrise 5 July (-128'..127') | H'00D9' | Sunset 5 August – sunrise 21 July (-128'..127') |
| H'00DA' | Sunset 21 August – sunrise 5 August (-128'..127') | H'00DA' | Sunset 5 September – sunrise 21 August (-128'..127') |
| H'00DC' | Sunset 21 September – sunrise 5 September (-128'..127') | H'00DC' | Sunset 5 October – sunrise 21 September (-128'..127') |
| H'00DE' | Sunset 21 October – sunrise 5 October (-128'..127') | H'00DF' | Sunset 5 November – sunrise 21 October (-128'..127') |
| H'00E0' | Sunset 21 November – sunrise 5 November (-128'..127') | H'00E1' | Sunset 5 December – sunrise 21 November (-128'..127') |
| H'00E2' | Sunset 21 December – sunrise 5 December (-128'..127') | H'00E3' | Sunset 5 January – sunrise 21 December (-128'..127') |
| H'00E4' | Not used | H'00E5' | Terminator (Build 1409 or higher) |
| H'00E6' | Module location id low byte (Build 1409 or higher) | H'00E7' | Module location id high byte (Build 1409 or higher) |
| H'00E8' | Module group id low byte (Build 1409 or higher) | H'00E9' | Module group id high byte (Build 1409 or higher) |
| H'00EA' | Module circuit id low byte (Build 1409 or higher) | H'00EB' | Module circuit id high byte (Build 1409 or higher) |
| H'00EC' | Module load id low byte (Build 1409 or higher) | H'00ED' | Module load id high byte (Build 1409 or higher) |
| H'00EE' | Channels Forced up | H'00EF' | Channels Forced down |
| H'00F0' | Channels Inhibited | H'00F1' | Channels Inhibited preset up |
| H'00F2' | Channels Inhibited preset down | H'00F3' | Channels Locked/Unlocked |
| H'00F4' | Blind 1 Auto mode (none , 1, 2 or 3) | H'00F5' | Blind 1 Alarm clock configuration |
| H'00F6' | Blind 2 Auto mode (none , 1, 2 or 3) | H'00F7' | Blind 2 Alarm clock configuration |
| H'00F8' | Current day (1...31) | H'00F9' | Current month (1...12) |
| H'00FA' | Current year high byte | H'00FB' | Current year low byte |
| H'00FC' | Module Zone Address | H'00FD' | Module Address |
| H'00FE' | Serial number high | H'00FF' | Serial number low |

Remark:

Unused locations contain H'FF'

Do not overwrite the following address location:

| | |
|-------------------|-------------------------------------|
| H'00EE' | Channels Forced up |
| H'00EF' | Channels Forced down |
| H'00F0' | Channels Inhibited |
| H'00F1' | Channels Inhibited preset up |
| H'00F2' | Channels Inhibited preset down |
| H'00F3' | Channel locked/unlocked |
| H'00F4' | Blind 1 Auto mode (none, 1, 2 or 3) |
| H'00F5' | Blind 1 Alarm clock configuration |
| H'00F6' | Blind 2 Auto mode (none, 1, 2 or 3) |
| H'00F7' | Blind 2 Alarm clock configuration |
| H'00F8' | Current day of month |
| H'00F9' | Current month |
| H'00FA' & H'00FB' | Current year |
| H'00FC' | Module zone address |
| H'00FD' | Module address |
| H'00FE' & H'00FF' | Module serial number |

Blind timeout

| Contents | Time out |
|----------|-----------------------------|
| 0 | No timeout (continuous) |
| 1 | 1.3 sec (1 *1.31072s) |
| 2 | 2.6 sec (2 *1.31072s) |
| ... | ... |
| 255 | 5min 34 sec (255 *1.31072s) |

Channel forced up

| Contents | Channel forced up |
|--------------|-----------------------------|
| B'xxxxxxx0' | Blind 1 forced up cancelled |
| B'xxxxxxx1' | Blind 1 forced up |
| B'xxxxxxx0x' | Blind 2 forced up cancelled |
| B'xxxxxxx1x' | Blind 2 forced up |

Channel forced down

| Contents | Channel forced down |
|-------------|-------------------------------|
| B'xxxxxxx0' | Blind 1 forced down cancelled |

| | |
|--------------|-------------------------------|
| B'xxxxxxx1' | Blind 1 forced down |
| B'xxxxxxx0x' | Blind 2 forced down cancelled |
| B'xxxxxxx1x' | Blind 2 forced down |

Channel inhibited

| <i>Contents</i> | <i>Channel inhibited</i> |
|------------------------|---------------------------------|
| B'xxxxxxx0' | Blind 1 inhibit cancelled |
| B'xxxxxxx1' | Blind 1 inhibit |
| B'xxxxxxx0x' | Blind 2 inhibit cancelled |
| B'xxxxxxx1x' | Blind 2 inhibit |

Channel inhibited preset up

| <i>Contents</i> | <i>Channel inhibited but preset up</i> |
|------------------------|---|
| B'xxxxxxx0' | Blind 1 inhibit preset up cancelled |
| B'xxxxxxx1' | Blind 1 inhibit preset up |
| B'xxxxxxx0x' | Blind 2 inhibit preset up cancelled |
| B'xxxxxxx1x' | Blind 2 inhibit preset up |

Channel inhibited preset down

| <i>Contents</i> | <i>Channel inhibited but preset down</i> |
|------------------------|---|
| B'xxxxxxx0' | Blind 1 inhibit preset down cancelled |
| B'xxxxxxx1' | Blind 1 inhibit preset down |
| B'xxxxxxx0x' | Blind 2 inhibit preset down cancelled |
| B'xxxxxxx1x' | Blind 2 inhibit preset down |

Channel locked/unlocked

| <i>Contents</i> | <i>Channel locked/unlocked</i> |
|------------------------|---------------------------------------|
| B'xxxxxxx0' | Blind 1 unlocked |
| B'xxxxxxx1' | Blind 1 locked |
| B'xxxxxxx0x' | Blind 2 unlocked |
| B'xxxxxxx1x' | Blind 2 locked |

Blind Auto mode selection

| <i>Contents</i> | <i>Selected auto mode</i> |
|------------------------|----------------------------------|
| 0 | No auto mode activated |
| 1 | Auto mode 1 activated |
| 2 | Auto mode 2 activated |
| 3 | Auto mode 3 activated |

Blind Alarm clock configuration

| <i>Contents</i> | <i>Alarm clock configuration</i> |
|------------------------|---|
| B'xxxxxxx0' | Alarm 1 disabled |
| B'xxxxxxx1' | Alarm 1 enabled |
| B'xxxxxxx0x' | Local alarm 1 |
| B'xxxxxxx1x' | Global alarm 1 |
| B'xxxxx0xx' | Alarm 2 disabled |
| B'xxxxx1xx' | Alarm 2 enabled |
| B'xxxx0xxx' | Local alarm 2 |
| B'xxxx1xxx' | Global alarm 2 |
| B'xxx0xxxx' | Sunrise disabled |
| B'xxx1xxxx' | Sunrise enabled |
| B'xx0xxxxx' | Sunset disabled |
| B'xx1xxxxx' | Sunset enabled |
| B'x0xxxxxx' | Summer time disabled |
| B'x1xxxxxx' | Summer time enabled |

| Address | Contents | Address | Contents |
|----------------|--------------------------------------|----------------|-------------------------------------|
| H'0100' | Push button 1 module address | H'0101' | Push button 1 bit number |
| H'0102' | Push button 1 action for channel 1 | H'0103' | Push button 1 first time parameter |
| H'0104' | Push button 1 second time parameter | H'0105' | Push button 2 module address |
| H'0106' | Push button 2 bit number | H'0107' | Push button 2 action for channel 1 |
| H'0108' | Push button 2 first parameter | H'0109' | Push button 2 second parameter |
| ... | ... | ... | ... |
| H'0178' | Push button 25 module address | H'0179' | Push button 25 bit number |
| H'017A' | Push button 25 action for channel 1 | H'017B' | Push button 25 first time parameter |
| H'017C' | Push button 25 second time parameter | H'017D' | Not used |
| H'017E' | Not used | H'017F' | Not used |

| Address | Contents | Address | Contents |
|----------------|--------------------------------------|----------------|-------------------------------------|
| H'0180' | Push button 1 module address | H'0181' | Push button 1 bit number |
| H'0182' | Push button 1 action for channel 2 | H'0183' | Push button 1 first time parameter |
| H'0184' | Push button 1 second time parameter | H'0185' | Push button 2 module address |
| H'0186' | Push button 2 bit number | H'0187' | Push button 2 action for channel 2 |
| H'0188' | Push button 2 first time parameter | H'0189' | Push button 2 second time parameter |
| ... | ... | ... | ... |
| H'01F8' | Push button 25 module address | H'01F9' | Push button 25 bit number |
| H'01FA' | Push button 25 action for channel 2 | H'01FB' | Push button 25 first time parameter |
| H'01FC' | Push button 25 second time parameter | H'01FD' | Not used |
| H'01FE' | Not used | H'01FF' | Not used |

Remark:

Unused locations contain H'FF'

| Action | Description | First time parameter | Second time parameter |
|--------|--|----------------------|-----------------------|
| H'00' | Up | H'FF' | H'FF' |
| H'01' | Direct up | Delayed on time | H'FF' |
| H'02' | Direct up at release | Delayed on time | H'FF' |
| H'03' | Down | H'FF' | H'FF' |
| H'04' | Direct down | Delayed on time | H'FF' |
| H'05' | Direct down at release | Delayed on time | H'FF' |
| H'06' | Up/down | H'FF' | H'FF' |
| H'07' | Go to position | Delayed on time | Position (0 to 100%) |
| H'08' | Go to position at release | Delayed on time | Position (0 to 100%) |
| H'09' | Up in auto mode 1 | H'FF' | H'FF' |
| H'0A' | Direct up in auto mode 1 | Delayed on time | H'FF' |
| H'0B' | Direct up at release in auto mode 1 | Delayed on time | H'FF' |
| H'0C' | Down in auto mode 1 | H'FF' | H'FF' |
| H'0D' | Direct down in auto mode 1 | Delayed on time | H'FF' |
| H'0E' | Direct down at release in auto mode 1 | Delayed on time | H'FF' |
| H'0F' | Up/down in auto mode 1 | H'FF' | H'FF' |
| H'10' | Go to position in auto mode 1 | Delayed on time | Position (0 to 100%) |
| H'11' | Go to position at release in auto mode 1 | Delayed on time | Position (0 to 100%) |
| H'12' | Select auto mode 1 | H'FF' | H'FF' |
| H'13' | Select auto mode 1 at release | H'FF' | H'FF' |
| H'14' | Select/deselect auto mode 1 | H'FF' | H'FF' |
| H'15' | Deselect auto mode | H'FF' | H'FF' |
| H'16' | Deselect auto mode at release | H'FF' | H'FF' |
| H'17' | Up in auto mode 2 | H'FF' | H'FF' |
| H'18' | Direct up in auto mode 2 | Delayed on time | H'FF' |
| H'19' | Direct up at release in auto mode 2 | Delayed on time | H'FF' |
| H'1A' | Down in auto mode 2 | H'FF' | H'FF' |
| H'1B' | Direct down in auto mode 2 | Delayed on time | H'FF' |
| H'1C' | Direct down at release in auto mode 2 | Delayed on time | H'FF' |
| H'1D' | Up/down in auto mode 2 | H'FF' | H'FF' |
| H'1E' | Position in auto mode 2 | Delayed on time | Position (0 to 100%) |
| H'1F' | Go to position at release in auto mode 2 | Delayed on time | Position (0 to 100%) |
| H'20' | Select auto mode 2 | H'FF' | H'FF' |
| H'21' | Select auto mode 2 at release | H'FF' | H'FF' |
| H'22' | Select/deselect auto mode 2 | H'FF' | H'FF' |
| H'23' | Up in auto mode 3 | H'FF' | H'FF' |
| H'24' | Direct up in auto mode 3 | Delayed on time | H'FF' |
| H'25' | Direct up at release in auto mode 3 | Delayed on time | H'FF' |
| H'26' | Down in auto mode 3 | H'FF' | H'FF' |
| H'27' | Direct down in auto mode 3 | Delayed on time | H'FF' |
| H'28' | Direct down at release in auto mode 3 | Delayed on time | H'FF' |
| H'29' | Up/down in auto mode 3 | H'FF' | H'FF' |
| H'2A' | Position in auto mode 3 | Delayed on time | Position (0 to 100%) |
| H'2B' | Go to position at release in auto mode 3 | Delayed on time | Position (0 to 100%) |
| H'2C' | Select auto mode 3 | H'FF' | H'FF' |
| H'2D' | Select auto mode 3 at release | H'FF' | H'FF' |
| H'2E' | Select/deselect auto mode 3 | H'FF' | H'FF' |
| H'2F' | Lock at closed switch | H'FF' | H'FF' |
| H'30' | Lock at open switch | H'FF' | H'FF' |
| H'31' | Lock | Timeout | H'FF' |
| H'32' | Lock/unlock | Timeout | H'FF' |
| H'33' | Unlock | H'FF' | H'FF' |
| H'34' | Forced up at closed switch | H'FF' | H'FF' |
| H'35' | Forced up at open switch | H'FF' | H'FF' |
| H'36' | Forced up | Timeout | H'FF' |
| H'37' | Forced up/cancel forced up | Timeout | H'FF' |
| H'38' | Cancel forced up | H'FF' | H'FF' |
| H'39' | Forced down at closed switch | H'FF' | H'FF' |
| H'3A' | Forced down at open switch | H'FF' | H'FF' |
| H'3B' | Forced down | Timeout | H'FF' |
| H'3C' | Forced down/cancel forced down | Timeout | H'FF' |
| H'3D' | Cancel forced down | H'FF' | H'FF' |
| H'3E' | Inhibit at closed switch | H'FF' | H'FF' |
| H'3F' | Inhibit at open switch | H'FF' | H'FF' |
| H'40' | Inhibit | Timeout | H'FF' |

| | | | |
|-------|--|---------|-------|
| H'41' | Inhibit /cancel inhibit | Timeout | H'FF' |
| H'42' | Cancel inhibit | H'FF' | H'FF' |
| H'43' | Inhibit but preset up at closed switch | H'FF' | H'FF' |
| H'44' | Inhibit but preset up at open switch | H'FF' | H'FF' |
| H'45' | Inhibit but preset up | Timeout | H'FF' |
| H'46' | Inhibit but preset up/cancel inhibit preset up | Timeout | H'FF' |
| H'47' | Cancel inhibit but preset up | H'FF' | H'FF' |
| H'48' | Inhibit but preset down at closed switch | H'FF' | H'FF' |
| H'49' | Inhibit but preset down at closed switch | H'FF' | H'FF' |
| H'4A' | Inhibit but preset down | Timeout | H'FF' |
| H'4B' | Inhibit but preset down/cancel inhibit preset down | Timeout | H'FF' |
| H'4C' | Cancel but inhibit preset down | H'FF' | H'FF' |
| H'4D' | Enable Alarm 1 at closed switch | H'FF' | H'FF' |
| H'4E' | Enable Alarm 1 at open switch | H'FF' | H'FF' |
| H'4F' | Disable Alarm 1 at closed switch | H'FF' | H'FF' |
| H'50' | Disable Alarm 1 at open switch | H'FF' | H'FF' |
| H'51' | Enable Alarm 1 | H'FF' | H'FF' |
| H'52' | Enable/disable Alarm 1 | H'FF' | H'FF' |
| H'53' | Disable Alarm 1 | H'FF' | H'FF' |
| H'54' | Enable Alarm 2 at closed switch | H'FF' | H'FF' |
| H'55' | Enable Alarm 2 at open switch | H'FF' | H'FF' |
| H'56' | Disable Alarm 2 at closed switch | H'FF' | H'FF' |
| H'57' | Disable Alarm 2 at open switch | H'FF' | H'FF' |
| H'58' | Enable Alarm 2 | H'FF' | H'FF' |
| H'59' | Enable/disable Alarm 2 | H'FF' | H'FF' |
| H'5A' | Disable Alarm 2 | H'FF' | H'FF' |
| H'5B' | Enable sunrise at closed switch | H'FF' | H'FF' |
| H'5C' | Enable sunrise at open switch | H'FF' | H'FF' |
| H'5D' | Disable sunrise at closed switch | H'FF' | H'FF' |
| H'5E' | Disable sunrise at open switch | H'FF' | H'FF' |
| H'5F' | Enable sunrise | H'FF' | H'FF' |
| H'60' | Enable/disable sunrise | H'FF' | H'FF' |
| H'61' | Disable sunrise | H'FF' | H'FF' |
| H'62' | Enable sunset at closed switch | H'FF' | H'FF' |
| H'63' | Enable sunset at open switch | H'FF' | H'FF' |
| H'64' | Disable sunset at closed switch | H'FF' | H'FF' |
| H'65' | Disable sunset at open switch | H'FF' | H'FF' |
| H'66' | Enable sunset | H'FF' | H'FF' |
| H'67' | Enable/disable sunset | H'FF' | H'FF' |
| H'68' | Disable sunset | H'FF' | H'FF' |

| Time parameter | Time |
|----------------|----------------|
| 0 | 0s or No timer |
| 1 | 1s |
| 2 | 2s |
| ... | |
| 119 | 1min59s |
| 120 | 2min |
| 121 | 2min15s |
| ... | |
| 131 | 4min45s |
| 132 | 5min |
| 133 | 5min30s |
| ... | |
| 181 | 29min30s |
| 182 | 30min |
| 183 | 31min |
| ... | |
| 211 | 59min |
| 212 | 1h |
| 213 | 1h15min |
| ... | |
| 227 | 4h45min |
| 228 | 5h |
| 229 | 5h30min |
| ... | |
| 237 | 9h30min |
| 238 | 10h |
| 239 | 11h |
| ... | |
| 251 | 23h |
| 252 | 1d |
| 253 | 2d |
| 254 | 3d |
| 255 | infinite |

Memory map version 2 (Build 1809 or higher):

| Address | Contents | Address | Contents |
|---------|--|---------|--|
| H'0000' | Blind 1 name character 1 | H'0001' | Blind 1 name character 2 |
| ... | ... | ... | ... |
| H'000E' | Blind 1 name character 15 | H'000F' | Blind 1 name character 16 |
| H'0010' | Blind 2 name character 1 | H'0011' | Blind 2 name character 2 |
| ... | ... | ... | ... |
| H'001E' | Blind 2 name character 15 | H'001F' | Blind 2 name character 16 |
| H'0020' | Blind 1 time out | H'0021' | Low byte 256/(Blind 1 timeout*0.0131072) |
| H'0022' | High byte 256/(Blind 1 timeout*0.0131072) | H'0023' | Blind 2 time out |
| H'0024' | Low byte 256/(Blind 2 timeout*0.0131072) | H'0025' | High byte 256/(Blind 2 timeout*0.0131072) |
| H'0026' | Blind1 unwind delay (s) | H'0027' | Blind2 unwind delay (s) |
| H'0028' | Blind1 collapse delay (s) | H'0029' | Blind2 collapse delay (s) |
| H'002A' | Blind1 slats rotate time | H'002B' | Blind2 slats rotate time |
| H'002C' | Not used | H'002D' | Not used |
| ... | ... | ... | ... |
| H'003A' | Not used | H'003B' | Not used |
| H'003C' | Blind 1 location id low byte (Build 1409 or higher) | H'003D' | Blind 1 location id high byte (Build 1409 or higher) |
| H'003E' | Blind 1 group id low byte (Build 1409 or higher) | H'003F' | Blind 1 group id high byte (Build 1409 or higher) |
| H'0040' | Blind 1 circuit id low byte (Build 1409 or higher) | H'0041' | Blind 1 circuit id high byte (Build 1409 or higher) |
| H'0042' | Blind 1 load id low byte (Build 1409 or higher) | H'0043' | Blind 1 load id high byte (Build 1409 or higher) |
| H'0044' | Blind 2 location id low byte (Build 1409 or higher) | H'0045' | Blind 2 location id high byte (Build 1409 or higher) |
| H'0046' | Blind 2 group id low byte (Build 1409 or higher) | H'0047' | Blind 2 group id high byte (Build 1409 or higher) |
| H'0048' | Blind 2 circuit id low byte (Build 1409 or higher) | H'0049' | Blind 2 circuit id high byte (Build 1409 or higher) |
| H'004A' | Blind 2 load id low byte (Build 1409 or higher) | H'004B' | Blind 2 load id high byte (Build 1409 or higher) |
| H'004C' | Module name character 1 (Build 1409 or higher) | H'004D' | Module name character 2 (Build 1409 or higher) |
| ... | .. | .. | .. |
| H'008A' | Module name character 63 (Build 1409 or higher) | H'008B' | Module name character 64 (Build 1409 or higher) |
| H'008C' | Blind 1 Sunrise offset (-128'...127') | H'008D' | Blind 1 Sunset offset (-128'...127') |
| H'008E' | Blind 2 Sunrise offset (-128'...127') | H'008F' | Blind 2 Sunset offset (-128'...127') |
| H'0090' | Blind 1 Wake up 1 offset (-128'...127') | H'0091' | Not used |
| H'0092' | Blind 1 Go to bed 1 offset (-128'...127') | H'0093' | Not used |
| H'0094' | Blind 1 Wake up 2 offset (-128'...127') | H'0095' | Not used |
| H'0096' | Blind 1 Go to bed 2 offset (-128'...127') | H'0097' | Not used |
| H'0098' | Blind 2 Wake up 1 offset (-128'...127') | H'0099' | Not used |
| H'009A' | Blind 2 Go to bed 1 offset (-128'...127') | H'009B' | Not used |
| H'009C' | Blind 2 Wake up 2 offset (-128'...127') | H'009D' | Not used |
| H'009E' | Blind 2 Go to bed 2 offset (-128'...127') | H'009F' | Not used |
| H'00A0' | Blind 1 Wake up 1 hour (0...23) | H'00A1' | Blind 1 Wake up 1 minutes (0...59) |
| H'00A2' | Blind 1 Go to bed 1 hour (0...23) | H'00A3' | Blind 1 Go to bed 1 minutes (0...59) |
| H'00A4' | Blind 1 Wake up 2 hour (0...23) | H'00A5' | Blind 1 Wake up 2 minutes (0...59) |
| H'00A6' | Blind 1 Go to bed 2 hour (0...23) | H'00A7' | Blind 1 Go to bed 2 minutes (0...59) |
| H'00A8' | Blind 2 Wake up 1 hour (0...23) | H'00A9' | Blind 2 Wake up 1 minutes (0...59) |
| H'00AA' | Blind 2 Go to bed 1 hour (0...23) | H'00AB' | Blind 2 Go to bed 1 minutes (0...59) |
| H'00AC' | Blind 2 Wake up 2 hour (0...23) | H'00AD' | Blind 2 Wake up 2 minutes (0...59) |
| H'00AE' | Blind 2 Go to bed 2 hour (0...23) | H'00AF' | Blind 2 Go to bed 2 minutes (0...59) |
| H'00B0' | Sunrise hour at 21 December (0...23) | H'00B1' | Sunrise minutes at 21 December (0...59) |
| H'00B2' | Sunrise 21 January – sunrise 5 January (-128'..127') | H'00B3' | Sunrise 5 February – sunrise 21 January (-128'..127') |
| H'00B4' | Sunrise 21 February – sunrise 5 February (-128'..127') | H'00B5' | Sunrise 5 March – sunrise 21 February (-128'..127') |
| H'00B6' | Sunrise 21 March – sunrise 5 March (-128'..127') | H'00B7' | Sunrise 5 April – sunrise 21 March (-128'..127') |
| H'00B8' | Sunrise 21 April – sunrise 5 April (-128'..127') | H'00B9' | Sunrise 5 May – sunrise 21 April (-128'..127') |
| H'00BA' | Sunrise 21 May – sunrise 5 May (-128'..127') | H'00BB' | Sunrise 5 June – sunrise 21 May (-128'..127') |
| H'00BC' | Sunrise 21 June – sunrise 5 June (-128'..127') | H'00BD' | Sunrise 5 July – sunrise 21 June (-128'..127') |
| H'00BE' | Sunrise 21 July – sunrise 5 July (-128'..127') | H'00BF' | Sunrise 5 August – sunrise 21 July (-128'..127') |
| H'00C0' | Sunrise 21 August – sunrise 5 August (-128'..127') | H'00C1' | Sunrise 5 September – sunrise 21 August (-128'..127') |
| H'00C2' | Sunrise 21 September – sunrise 5 September (-128'..127') | H'00C3' | Sunrise 5 October – sunrise 21 September (-128'..127') |
| H'00C4' | Sunrise 21 October – sunrise 5 October (-128'..127') | H'00C5' | Sunrise 5 November – sunrise 21 October (-128'..127') |
| H'00C6' | Sunrise 21 November – sunrise 5 November (-128'..127') | H'00C7' | Sunrise 5 December – sunrise 21 November (-128'..127') |
| H'00C8' | Sunrise 21 December – sunrise 5 December (-128'..127') | H'00C9' | Sunrise 5 January – sunrise 21 December (-128'..127') |
| H'00CA' | Sunset hour at 21 December (0...23) | H'00CB' | Sunset minutes at 21 December (0...59) |
| H'00CC' | Sunset 21 January – sunrise 5 January (-128'..127') | H'00CD' | Sunset 5 February – sunrise 21 January (-128'..127') |
| H'00CE' | Sunset 21 February – sunrise 5 February (-128'..127') | H'00CF' | Sunset 5 March – sunrise 21 February (-128'..127') |
| H'00D0' | Sunset 21 March – sunrise 5 March (-128'..127') | H'00D1' | Sunset 5 April – sunrise 21 March (-128'..127') |
| H'00D2' | Sunset 21 April – sunrise 5 April (-128'..127') | H'00D3' | Sunset 5 May – sunrise 21 April (-128'..127') |

| | | | |
|---------|---|---------|---|
| H'00D4' | Sunset 21 May – sunrise 5 May (-128'..127') | H'00D5' | Sunset 5 June – sunrise 21 May (-128'..127') |
| H'00D6' | Sunset 21 June – sunrise 5 June (-128'..127') | H'00D7' | Sunset 5 July – sunrise 21 June (-128'..127') |
| H'00D8' | Sunset 21 July – sunrise 5 July (-128'..127') | H'00D9' | Sunset 5 August – sunrise 21 July (-128'..127') |
| H'00DA' | Sunset 21 August – sunrise 5 August (-128'..127') | H'00DA' | Sunset 5 September – sunrise 21 August (-128'..127') |
| H'00DC' | Sunset 21 September – sunrise 5 September (-128'..127') | H'00DC' | Sunset 5 October – sunrise 21 September (-128'..127') |
| H'00DE' | Sunset 21 October – sunrise 5 October (-128'..127') | H'00DF' | Sunset 5 November – sunrise 21 October (-128'..127') |
| H'00E0' | Sunset 21 November – sunrise 5 November (-128'..127') | H'00E1' | Sunset 5 December – sunrise 21 November (-128'..127') |
| H'00E2' | Sunset 21 December – sunrise 5 December (-128'..127') | H'00E3' | Sunset 5 January – sunrise 21 December (-128'..127') |
| H'00E4' | Not used | H'00E5' | Terminator (Build 1409 or higher) |
| H'00E6' | Module location id low byte (Build 1409 or higher) | H'00E7' | Module location id high byte (Build 1409 or higher) |
| H'00E8' | Module group id low byte (Build 1409 or higher) | H'00E9' | Module group id high byte (Build 1409 or higher) |
| H'00EA' | Module circuit id low byte (Build 1409 or higher) | H'00EB' | Module circuit id high byte (Build 1409 or higher) |
| H'00EC' | Module load id low byte (Build 1409 or higher) | H'00ED' | Module load id high byte (Build 1409 or higher) |
| H'00EE' | Channels Forced up | H'00EF' | Channels Forced down |
| H'00F0' | Channels Inhibited | H'00F1' | Channels Inhibited preset up |
| H'00F2' | Channels Inhibited preset down | H'00F3' | Channels Locked/Unlocked |
| H'00F4' | Blind 1 Auto mode (none , 1, 2 or 3) | H'00F5' | Blind 1 Alarm clock configuration |
| H'00F6' | Blind 2 Auto mode (none , 1, 2 or 3) | H'00F7' | Blind 2 Alarm clock configuration |
| H'00F8' | Current day (1...31) | H'00F9' | Current month (1...12) |
| H'00FA' | Current year high byte | H'00FB' | Current year low byte |
| H'00FC' | Module Zone Address | H'00FD' | Module Address |
| H'00FE' | Serial number high | H'00FF' | Serial number low |

Remark:

Unused locations contain H'FF'

Do not overwrite the following address location:

| | |
|-------------------|-------------------------------------|
| H'00EE' | Channels Forced up |
| H'00EF' | Channels Forced down |
| H'00F0' | Channels Inhibited |
| H'00F1' | Channels Inhibited preset up |
| H'00F2' | Channels Inhibited preset down |
| H'00F3' | Channel locked/unlocked |
| H'00F4' | Blind 1 Auto mode (none, 1, 2 or 3) |
| H'00F5' | Blind 1 Alarm clock configuration |
| H'00F6' | Blind 2 Auto mode (none, 1, 2 or 3) |
| H'00F7' | Blind 2 Alarm clock configuration |
| H'00F8' | Current day of month |
| H'00F9' | Current month |
| H'00FA' & H'00FB' | Current year |
| H'00FC' | Module zone address |
| H'00FD' | Module address |
| H'00FE' & H'00FF' | Module serial number |

Blind timeout

| Contents | Time out |
|----------|-----------------------------|
| 0 | No timeout (continuous) |
| 1 | 1.3 sec (1 *1.31072s) |
| 2 | 2.6 sec (2 *1.31072s) |
| ... | ... |
| 255 | 5min 34 sec (255 *1.31072s) |

Blind slats rotate time

| Contents | Rotate time |
|----------|-----------------------------------|
| 0 | No rotating slats blind (default) |
| 1 | 1 sec |
| 2 | 2 sec |
| ... | ... |
| 255 | 255 sec |

Channel forced up

| <i>Contents</i> | <i>Channel forced up</i> |
|-----------------|-----------------------------|
| B'xxxxxxx0' | Blind 1 forced up cancelled |
| B'xxxxxxx1' | Blind 1 forced up |
| B'xxxxxxx0x' | Blind 2 forced up cancelled |
| B'xxxxxxx1x' | Blind 2 forced up |

Channel forced down

| <i>Contents</i> | <i>Channel forced down</i> |
|-----------------|-------------------------------|
| B'xxxxxxx0' | Blind 1 forced down cancelled |
| B'xxxxxxx1' | Blind 1 forced down |
| B'xxxxxxx0x' | Blind 2 forced down cancelled |
| B'xxxxxxx1x' | Blind 2 forced down |

Channel inhibited

| <i>Contents</i> | <i>Channel inhibited</i> |
|-----------------|---------------------------|
| B'xxxxxxx0' | Blind 1 inhibit cancelled |
| B'xxxxxxx1' | Blind 1 inhibit |
| B'xxxxxxx0x' | Blind 2 inhibit cancelled |
| B'xxxxxxx1x' | Blind 2 inhibit |

Channel inhibited preset up

| <i>Contents</i> | <i>Channel inhibited but preset up</i> |
|-----------------|--|
| B'xxxxxxx0' | Blind 1 inhibit preset up cancelled |
| B'xxxxxxx1' | Blind 1 inhibit preset up |
| B'xxxxxxx0x' | Blind 2 inhibit preset up cancelled |
| B'xxxxxxx1x' | Blind 2 inhibit preset up |

Channel inhibited preset down

| <i>Contents</i> | <i>Channel inhibited but preset down</i> |
|-----------------|--|
| B'xxxxxxx0' | Blind 1 inhibit preset down cancelled |
| B'xxxxxxx1' | Blind 1 inhibit preset down |
| B'xxxxxxx0x' | Blind 2 inhibit preset down cancelled |
| B'xxxxxxx1x' | Blind 2 inhibit preset down |

Channel locked/unlocked

| <i>Contents</i> | <i>Channel locked/unlocked</i> |
|-----------------|--------------------------------|
| B'xxxxxxx0' | Blind 1 unlocked |
| B'xxxxxxx1' | Blind 1 locked |
| B'xxxxxxx0x' | Blind 2 unlocked |
| B'xxxxxxx1x' | Blind 2 locked |

Blind Auto mode selection

| <i>Contents</i> | <i>Selected auto mode</i> |
|-----------------|---------------------------|
| 0 | No auto mode activated |
| 1 | Auto mode 1 activated |
| 2 | Auto mode 2 activated |
| 3 | Auto mode 3 activated |

Blind Alarm clock configuration

| <i>Contents</i> | <i>Alarm clock configuration</i> |
|-----------------|----------------------------------|
| B'xxxxxxx0' | Alarm 1 disabled |
| B'xxxxxxx1' | Alarm 1 enabled |
| B'xxxxxxx0x' | Local alarm 1 |
| B'xxxxxxx1x' | Global alarm 1 |
| B'xxxxx0xx' | Alarm 2 disabled |
| B'xxxxx1xx' | Alarm 2 enabled |
| B'xxxx0xxx' | Local alarm 2 |
| B'xxxx1xxx' | Global alarm 2 |
| B'xxx0xxxx' | Sunrise disabled |

| | |
|-------------|----------------------|
| B'xxx1xxxx' | Sunrise enabled |
| B'xx0xxxxx' | Sunset disabled |
| B'xx1xxxxx' | Sunset enabled |
| B'x0xxxxxx' | Summer time disabled |
| B'x1xxxxxx' | Summer time enabled |

| Address | Contents | Address | Contents |
|----------------|--------------------------------------|----------------|-------------------------------------|
| H'0100' | Push button 1 module address | H'0101' | Push button 1 bit number |
| H'0102' | Push button 1 action for channel 1 | H'0103' | Push button 1 first time parameter |
| H'0104' | Push button 1 second time parameter | H'0105' | Push button 2 module address |
| H'0106' | Push button 2 bit number | H'0107' | Push button 2 action for channel 1 |
| H'0108' | Push button 2 first parameter | H'0109' | Push button 2 second parameter |
| ... | ... | ... | ... |
| H'0178' | Push button 25 module address | H'0179' | Push button 25 bit number |
| H'017A' | Push button 25 action for channel 1 | H'017B' | Push button 25 first time parameter |
| H'017C' | Push button 25 second time parameter | H'017D' | Not used |
| H'017E' | Not used | H'017F' | Not used |

| Address | Contents | Address | Contents |
|----------------|--------------------------------------|----------------|-------------------------------------|
| H'0180' | Push button 1 module address | H'0181' | Push button 1 bit number |
| H'0182' | Push button 1 action for channel 2 | H'0183' | Push button 1 first time parameter |
| H'0184' | Push button 1 second time parameter | H'0185' | Push button 2 module address |
| H'0186' | Push button 2 bit number | H'0187' | Push button 2 action for channel 2 |
| H'0188' | Push button 2 first time parameter | H'0189' | Push button 2 second time parameter |
| ... | ... | ... | ... |
| H'01F8' | Push button 25 module address | H'01F9' | Push button 25 bit number |
| H'01FA' | Push button 25 action for channel 2 | H'01FB' | Push button 25 first time parameter |
| H'01FC' | Push button 25 second time parameter | H'01FD' | Not used |
| H'01FE' | Not used | H'01FF' | Not used |

Remark:

Unused locations contain H'FF'

| Action | Description | First time parameter | Second time parameter |
|--------|--|----------------------|-----------------------|
| H'00' | Up | H'FF' | H'FF' |
| H'01' | Direct up | Delayed on time | H'FF' |
| H'02' | Direct up at release | Delayed on time | H'FF' |
| H'03' | Down | H'FF' | H'FF' |
| H'04' | Direct down | Delayed on time | H'FF' |
| H'05' | Direct down at release | Delayed on time | H'FF' |
| H'06' | Up/down | H'FF' | H'FF' |
| H'07' | Go to position | Delayed on time | Position (0 to 100%) |
| H'08' | Go to position at release | Delayed on time | Position (0 to 100%) |
| H'09' | Up in auto mode 1 | H'FF' | H'FF' |
| H'0A' | Direct up in auto mode 1 | Delayed on time | H'FF' |
| H'0B' | Direct up at release in auto mode 1 | Delayed on time | H'FF' |
| H'0C' | Down in auto mode 1 | H'FF' | H'FF' |
| H'0D' | Direct down in auto mode 1 | Delayed on time | H'FF' |
| H'0E' | Direct down at release in auto mode 1 | Delayed on time | H'FF' |
| H'0F' | Up/down in auto mode 1 | H'FF' | H'FF' |
| H'10' | Go to position in auto mode 1 | Delayed on time | Position (0 to 100%) |
| H'11' | Go to position at release in auto mode 1 | Delayed on time | Position (0 to 100%) |
| H'12' | Select auto mode 1 | H'FF' | H'FF' |
| H'13' | Select auto mode 1 at release | H'FF' | H'FF' |
| H'14' | Select/deselect auto mode 1 | H'FF' | H'FF' |
| H'15' | Deselect auto mode | H'FF' | H'FF' |
| H'16' | Deselect auto mode at release | H'FF' | H'FF' |
| H'17' | Up in auto mode 2 | H'FF' | H'FF' |
| H'18' | Direct up in auto mode 2 | Delayed on time | H'FF' |
| H'19' | Direct up at release in auto mode 2 | Delayed on time | H'FF' |
| H'1A' | Down in auto mode 2 | H'FF' | H'FF' |
| H'1B' | Direct down in auto mode 2 | Delayed on time | H'FF' |
| H'1C' | Direct down at release in auto mode 2 | Delayed on time | H'FF' |
| H'1D' | Up/down in auto mode 2 | H'FF' | H'FF' |
| H'1E' | Position in auto mode 2 | Delayed on time | Position (0 to 100%) |
| H'1F' | Go to position at release in auto mode 2 | Delayed on time | Position (0 to 100%) |
| H'20' | Select auto mode 2 | H'FF' | H'FF' |
| H'21' | Select auto mode 2 at release | H'FF' | H'FF' |
| H'22' | Select/deselect auto mode 2 | H'FF' | H'FF' |
| H'23' | Up in auto mode 3 | H'FF' | H'FF' |
| H'24' | Direct up in auto mode 3 | Delayed on time | H'FF' |
| H'25' | Direct up at release in auto mode 3 | Delayed on time | H'FF' |
| H'26' | Down in auto mode 3 | H'FF' | H'FF' |
| H'27' | Direct down in auto mode 3 | Delayed on time | H'FF' |
| H'28' | Direct down at release in auto mode 3 | Delayed on time | H'FF' |
| H'29' | Up/down in auto mode 3 | H'FF' | H'FF' |
| H'2A' | Position in auto mode 3 | Delayed on time | Position (0 to 100%) |
| H'2B' | Go to position at release in auto mode 3 | Delayed on time | Position (0 to 100%) |
| H'2C' | Select auto mode 3 | H'FF' | H'FF' |
| H'2D' | Select auto mode 3 at release | H'FF' | H'FF' |
| H'2E' | Select/deselect auto mode 3 | H'FF' | H'FF' |
| H'2F' | Lock at closed switch | H'FF' | H'FF' |
| H'30' | Lock at open switch | H'FF' | H'FF' |
| H'31' | Lock | Timeout | H'FF' |
| H'32' | Lock/unlock | Timeout | H'FF' |
| H'33' | Unlock | H'FF' | H'FF' |
| H'34' | Forced up at closed switch | H'FF' | H'FF' |
| H'35' | Forced up at open switch | H'FF' | H'FF' |
| H'36' | Forced up | Timeout | H'FF' |
| H'37' | Forced up/cancel forced up | Timeout | H'FF' |
| H'38' | Cancel forced up | H'FF' | H'FF' |
| H'39' | Forced down at closed switch | H'FF' | H'FF' |
| H'3A' | Forced down at open switch | H'FF' | H'FF' |
| H'3B' | Forced down | Timeout | H'FF' |
| H'3C' | Forced down/cancel forced down | Timeout | H'FF' |
| H'3D' | Cancel forced down | H'FF' | H'FF' |
| H'3E' | Inhibit at closed switch | H'FF' | H'FF' |
| H'3F' | Inhibit at open switch | H'FF' | H'FF' |
| H'40' | Inhibit | Timeout | H'FF' |

| | | | |
|-------|--|---------|-------|
| H'41' | Inhibit /cancel inhibit | Timeout | H'FF' |
| H'42' | Cancel inhibit | H'FF' | H'FF' |
| H'43' | Inhibit but preset up at closed switch | H'FF' | H'FF' |
| H'44' | Inhibit but preset up at open switch | H'FF' | H'FF' |
| H'45' | Inhibit but preset up | Timeout | H'FF' |
| H'46' | Inhibit but preset up/cancel inhibit preset up | Timeout | H'FF' |
| H'47' | Cancel inhibit but preset up | H'FF' | H'FF' |
| H'48' | Inhibit but preset down at closed switch | H'FF' | H'FF' |
| H'49' | Inhibit but preset down at closed switch | H'FF' | H'FF' |
| H'4A' | Inhibit but preset down | Timeout | H'FF' |
| H'4B' | Inhibit but preset down/cancel inhibit preset down | Timeout | H'FF' |
| H'4C' | Cancel but inhibit preset down | H'FF' | H'FF' |
| H'4D' | Enable Alarm 1 at closed switch | H'FF' | H'FF' |
| H'4E' | Enable Alarm 1 at open switch | H'FF' | H'FF' |
| H'4F' | Disable Alarm 1 at closed switch | H'FF' | H'FF' |
| H'50' | Disable Alarm 1 at open switch | H'FF' | H'FF' |
| H'51' | Enable Alarm 1 | H'FF' | H'FF' |
| H'52' | Enable/disable Alarm 1 | H'FF' | H'FF' |
| H'53' | Disable Alarm 1 | H'FF' | H'FF' |
| H'54' | Enable Alarm 2 at closed switch | H'FF' | H'FF' |
| H'55' | Enable Alarm 2 at open switch | H'FF' | H'FF' |
| H'56' | Disable Alarm 2 at closed switch | H'FF' | H'FF' |
| H'57' | Disable Alarm 2 at open switch | H'FF' | H'FF' |
| H'58' | Enable Alarm 2 | H'FF' | H'FF' |
| H'59' | Enable/disable Alarm 2 | H'FF' | H'FF' |
| H'5A' | Disable Alarm 2 | H'FF' | H'FF' |
| H'5B' | Enable sunrise at closed switch | H'FF' | H'FF' |
| H'5C' | Enable sunrise at open switch | H'FF' | H'FF' |
| H'5D' | Disable sunrise at closed switch | H'FF' | H'FF' |
| H'5E' | Disable sunrise at open switch | H'FF' | H'FF' |
| H'5F' | Enable sunrise | H'FF' | H'FF' |
| H'60' | Enable/disable sunrise | H'FF' | H'FF' |
| H'61' | Disable sunrise | H'FF' | H'FF' |
| H'62' | Enable sunset at closed switch | H'FF' | H'FF' |
| H'63' | Enable sunset at open switch | H'FF' | H'FF' |
| H'64' | Disable sunset at closed switch | H'FF' | H'FF' |
| H'65' | Disable sunset at open switch | H'FF' | H'FF' |
| H'66' | Enable sunset | H'FF' | H'FF' |
| H'67' | Enable/disable sunset | H'FF' | H'FF' |
| H'68' | Disable sunset | H'FF' | H'FF' |

| Time parameter | Time |
|----------------|----------------|
| 0 | 0s or No timer |
| 1 | 1s |
| 2 | 2s |
| ... | |
| 119 | 1min59s |
| 120 | 2min |
| 121 | 2min15s |
| ... | |
| 131 | 4min45s |
| 132 | 5min |
| 133 | 5min30s |
| ... | |
| 181 | 29min30s |
| 182 | 30min |
| 183 | 31min |
| ... | |
| 211 | 59min |
| 212 | 1h |
| 213 | 1h15min |
| ... | |
| 227 | 4h45min |
| 228 | 5h |
| 229 | 5h30min |
| ... | |
| 237 | 9h30min |
| 238 | 10h |
| 239 | 11h |
| ... | |
| 251 | 23h |
| 252 | 1d |
| 253 | 2d |
| 254 | 3d |
| 255 | infinite |