



CW2015CHBD

Fuel Gauge IC with Low-SOC Alert

Features

- System-Side or Pack-Side Fuel Gauging
- 3% Maximum Total SOC Measurement Error
- 14-bit Sigma-Delta ADC for Temperature and Cell Voltage Measurement
- Precision Voltage Measurement
- No Offset Accumulation During Life Time
- No Full-to-Empty Battery Learning Cycles Necessary
- No Sense Resistor Required
- SOC and RRT available
- External Alarm/Interrupt for Low-Battery Warning Available
- Patented “FastCali” gas gauging algorithm
- Calibration After Quick Soft-Reset
- Ultra Low Power Consumption
 - Active mode 15 μ A
 - Sleep mode <1 μ A
- General I²C interface
- Tiny, Lead(Pb)-Free, TDFN-8 Package

Applications

- Smartphone
- Tablet PCs
- Handheld and Portable Applications

General Description

The CW2015 is an ultra-compact, host-side/pack-side, sensing resistor free, fuel gauging system IC for Lithium-ion(Li+) based batteries in handheld and portable devices.

The CW2015 tracks Li+ battery’s operational condition and uses state-of-art algorithm to report the relative State-of-Charge (SOC) of very different battery chemistry systems (LiCoOx, polymer Li-ion, LiMnOx etc.).

The CW2015 includes a 14-bit Sigma-Delta ADC, a precision voltage reference and build-in accurate temperature sensor. The IC allows the end-user to eliminate the expensive sensing resistor which occupies large board area. And the IC also sends out the alarm signal if the battery SOC level reaches pre-programmed threshold.

Quick start function offers the possibility to make an initial estimation of the battery’s SOC, which also enables the IC to be located on system side or pack side, giving the flexibility to system maker on pack selection.

The CW2015 uses a 2-wire I²C compatible serial interface that operates in standard (100 kHz) or fast (400 kHz) mode.

Typical Applications




Figure 1. Typical Application for 1-Cell and System Side




Figure 2. Typical Application for 1-Cell and Pack Side

The CW2015 can be also used in 2 or more cells connected in series, or several cells connected in parallel. Please refers to the application note or contacts support@cellwise-semi.com for details.


Ordering Information

PART	OPERATING TEMPERATURE	PACKAGE	TOP MARK
CW2015CHBD	-20°C to 70°C	TDFN8	2015CH BDXXXX

Note: XXXX stands for the manufacture info. Contact Cellwise for details.

Pin Configuration

TDFN Package Top view
2mm*3mm – 8pin
(Pad Side Down)




Pin Description

TDFN PIN	NAME	DESCRIPTION
1	CTG	Connect to ground
2	CELL	Battery voltage monitor I/O
3	VDD	System power supply
4	GND	General purpose ground connection
5	ALRT	Low SOC alarm signal for MCU interrupt controller
6	QSTRT	Quick start, allows to do a quick SOC estimate
7	SCL	Serial clock input
8	SDA	Serial data Input/output
9	EP	Exposed pad, connect to GND or let floating

Type Number

CW2015XXXX



D: TDFN8;

B: Standard firmware and parameter, B version

H: Standard Li-Polymer profile type*

C: C generation product

*This only means the embedded profile for test is Li-polymer, not means the CW2015 is only used for Li-polymer battery. The CW2015 is compatible with Li-ion, Li-polymer and other type Li batteries.

Absolute Maximum Ratings

		VALUE		UNITS
		MIN	MAX	
PIN voltage range respect to GND	CTG, CELL, VDD, $\overline{\text{ALRT}}$, QSTRT, SCL, SDA to GND	-0.3	6	V
Operation Temperature	T _A	-20	70	°C
Junction Temperature	T _J	-40	150	°C
Storage Temperature	T _{STG}	-50	150	°C
ESD	All pins. HBM model.		±2	KV
Moisture Sensitivity Level	MSL	Level 3		

Caution:

Stresses beyond "Absolute Maximum Ratings" condition may cause permanent damage to the device. These are stress ratings only and functional operation of the device at these or any other beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

Recommended DC Operating Conditions

$2.5 \leq V_{DD} \leq 4.7$, $T_A = -20$ to 70°C , unless otherwise specified.


PARAMETER	SYMBOL	CONDITIONS	MIN.	TYP.	MAX.	UNITS
Supply Voltage	V_{DD}		+2.5		+4.7	V
Data I/O Pins	SCL, SDA, QSTRT, ALRT		-0.3		+5.5	V
Analog I/O	CELL, CTG		-0.3		+5.5	V

Electrical Characteristics

$2.5 \leq V_{DD} \leq 4.7$, $T_A = -20$ to 70°C , unless otherwise specified

PARAMETER	SYMBOL	CONDITIONS	Min.	Typ.	Max.	UNITS
Active Current	I_{ACTIVE}	Normal Operation		15	20	μA
Sleep-Mode Current	I_{SLEEP}			0.5	1	μA
Time-Based Accuracy	t_{ERR}	$V_{DD}=3.7\text{V}$	-3		3	%
ADC input resistor	R_{ADIN}	$V_{DD}=V_{CELL}=3.7\text{V}$	10			$\text{M}\Omega$
ADC resolution				14		bits
ADC conversion time	t_{ADCON}	$V_{DD}=V_{CELL}=3.7\text{V}$		10		ms
Battery Voltage update time	$t_{VUPDATE}$	$V_{DD}=V_{CELL}=3.7\text{V}$		250		ms
Input Logic-High	V_{IH}	$V_{DD}=3.7\text{V}$	1.4			V
SCL, SDA, QSTRT						
Input Logic-Low	V_{IL}	$V_{DD}=3.7\text{V}$			0.6	V
SCL, SDA, QSTRT						
Input Hysteresis	V_{IHYS}		0.2			V
Output Logic-Low: SDA, $\overline{\text{ALRT}}$	V_{OL}	$I_{OL}=4\text{mA}$		0.2	0.4	V
Pull down current: SDA, $\overline{\text{ALRT}}$				4		mA

Function Block Diagram



Detailed Description

Function

The CW2015 is an ultra-compact, high precise gas gauging IC that embed new generational battery SOC estimate algorithm.

The CW2015 provide the battery voltage, SOC and RRT estimate to user by measuring the cell voltage and temperature.

FastCali algorithm

From battery OCV (open circuits voltage), we deduce the SOC (state of charge) of this battery. Obtains OCV from two ways: idle battery voltage that has been relaxed at least half an hour; battery voltage adds the internal resistor voltage drop when charging or discharging.

Creative “equipment current track” technology precisely calculates the present voltage drop of the internal resistor, combine with the FastCali algorithm, the CW2015 promptly infer the OCV value no matter the battery is in charging, relaxing or discharging state.

First SOC Estimate after Power Up

The CW2015 considers the battery as a free one that has been relaxed more than 0.5 hours when power up. It treats the battery voltage measured by the 14bits ADC as an OCV voltage. According to this voltage, the device deduces the first SOC value.

Error in the first SOC value will be calibrated during the normal use.

RRT

RRT offers the system remaining run time to user for reference. RRT is determined by the present SOC and battery discharging current, i.e. total system power dissipation. Battery remaining capacitor divide the current is the run time. Base on the “equipment current track” technology, the CW2015 obtains the discharging current only through measure the battery voltage.

RRT updates all the time and vary according to the present current. Minimum scale of the RRT is 1min.

Quick Start

Quick start allows the device to restart fuel gauge calculations in the same manner as an initial power-up by pull up the quick start pin or set the MODE register [0x0A].

This action used to reduce the large error in the SOC value.

Low SOC Alert

When battery SOC lower than or equal to the setting threshold [0x08], low SOC alert triggered. The CW2015 set the ALRT flag to 1, and pull down the ALRT pin to inform the external host. The ALRT pin remains logic-low until the host reset the ALRT flag to logic 0 by I²C bus.

Cleared ALRT don't generate another alert signal while the SOC remains below the alert threshold. The SOC must rise above and then fall below or equal to the alert threshold value before another interrupt is generated.

Sleep Mode

All the function will be halt in the sleep mode, power consumption of the device reduced to the lowest level. Set the MODE register bit Sleep to 11 to enter into the sleep mode and all data update stop. When exit from sleep mode, the chip will reset and the newly reported SOC may be different with that when just entering into sleep mode. When the battery voltage is lower than 2.5V, it enters into the sleep mode

automatically.

POR

Power on reset. Set the MODE register bit POR to 1111 to reset the device, all the registers will reset to default value.

Battery Profile

The battery profile of the CW2015 is programmable to match batteries with constant charging voltages of 4.20V, 4.35V, 4.40V or other voltages. User's battery is recommended to have battery characterization to get its exclusive profile for more accurate SOC. Please contact Cellwise for details.

Register Map

Below table shows the I²C register map for the CW2015.

Table 1. Register Map

REGISTER NAME	ADDRESS	DESCRIPTION	READ/WRITE	DEFAULT VALUE
VERSION	0x00	Returns IC version, software version	R	0x73
VCELL	0x02-0x03	Reports 14-bit A/D measurement of battery voltage	R	0x00
SOC	0x04-0x05	Reports 16-bit SOC result calculated	R	0x00
RRT_Alert	0x06-0x07	13 bits remaining run time and low SOC alert bit	W/R	0x00
CONFIG	0x08	Configure register, alert threshold set	W/R	0x18
MODE	0x0A	Special command for IC state	W/R	0xC0

VCELL Register(0x02~0x03)

The VCELL register is a read-only register that updates continuously the battery terminal voltage. Battery voltage is measured at the CELL pin with GND pin as a ground reference. A 14bit sigma-delta A/D converter is used and the voltage resolution is 305uV for the CW2015. This A/D converter updates the cell voltage for a period of <10ms after IC POR and then four times a second afterwards.




Figure 3. VCELL Register Format

SOC Register(0x04~0x05)

The SOC register is also a read-only register that indicates the State-of-Charge of the battery cell. SOC value is a relative concept which display as a percentage of the cell's total capacity. This register intrinsically adjusts itself to the change of battery cell's parameter due to aging, poor cell parameter distribution control or rapid change in total capacity.

In this register, the high 8bit part contains the SOC information in % units which can be directly used by end user if this accuracy is already good enough for application. The low 8bit part provides more accurate

part of the SOC information until 1/256%.




Figure 4. SOC Register Format

RRT_ALRT Register(0x06~0x07)

ALRT, Flag register bit. This bit is set by the IC when the SOC register value falls below or equal to the alert threshold setting and an interrupt is generated. This bit can only be cleared by the host through I²C bus. The power-up default value for ALRT is logic 0.

The read-only register RRT indicates the remaining run time (RRT) of the battery according to the present SOC and the discharge current. RRT is not a linear variation value, and updates once per second.

Register RRT provides 13 bits to record the remaining time, and 1 LSB represents one minute.




Figure 5. RRT_ALRT Register Format

CONFIG Register(0x08)

ATHD is low SOC alert threshold setting register. The alert threshold is a 5-bit value that sets the state of charge level where an interrupt is generated on the ALRT pin. The alert threshold has an LSB weight of 1% and can be programmed from 0% up to 31%. The power-up default value for ATHD is 3%.

UFG is a flag bit used to indicator the battery information update state.




Figure 6. CONFIG Register Format

MODE Register(0x0A)

Mode register is used for Master to control the IC.

Sleep mode, two bits to control. Default value 11, write 11 to force the CW2015 enter the sleep mode; write 00 to wake up.

QSTRT, quick start, two bits to control. Default value 00, write 11 to start.

Quick-start allows the IC to restart fuel-gauge calculations in the same manner as initial power-up of the IC. For example, if an application's power-up sequence is exceedingly noisy such that excess error is

introduced into the IC's "first guess" of SOC, the host can issue a quick-start to reduce the error. A quick-start is also initiated by a rising edge on the QSTRT pin.

POR, power of reset, four bits to control. Default value 0000, write 1111 to completely restart the IC as if power removed.




Figure 7. MODE Register Format

I²C Interface

The CW2015 communicates through an I²C interface. I²C is a two-wire open-drain interface supporting multiple devices and masters on a single bus. Some I²C devices can act as masters or slaves, but the CW2015 can only act as a slave device that only pull the bus wires LOW and never drive the bus HIGH. Data on the I²C-bus can be transferred at rates of up to 100kbps in standard mode. I2C fast mode (400kbps) are also supported.

Device Address

I²C device address is consisted of 7bits slave address and 1 read/write control bit.




Figure 8. I2C address structure

Address of the CW2015 is fixed on 0b1100010. Combine with de R/W bit:

Read command of CW2015 is 0xC5;

Write command of CW2015 is 0xC4.


START and STOP Conditions

When the bus is idle, both SCL and SDA must be HIGH. A bus master signals the beginning of a transmission with a START condition by transitioning SDA from HIGH to LOW while SCL is HIGH. When the master has finished communicating with the slave, it issues a STOP condition by transitioning SDA from LOW to HIGH while SCL is HIGH. The bus is then free for another transmission. When the bus is in use, it stays busy if a repeated START (Sr) is generated instead of a STOP condition. The repeated START (Sr) conditions are functionally identical to the START (S).


Read and Write Command

Figure 9 shows an overview of the read and write command on the I²C bus.

Read



Write




☐ From Master to Slave S Start


☒ From Slave Master A Acknowledge

Figure 9. Read and Write Command


Typical Operation Parameter




**C/2 RATE ZIGZAG PATTERN SOC
ACCURACY 1**




**C/2 RATE ZIGZAG PATTERN SOC
ACCURACY 2**




**REAL APPLICATION/DISCHARGE SOC
ACCURACY 1**




**REAL APPLICATION/DISCHARGE SOC
ACCURACY 2**



**REAL APPLICATION UNDER CV MODE
SOC ACCURACY 1**



**REAL APPLICATION UNDER CV MODE
SOC ACCURACY 2**



Typical Applications (Continued.)




Figure 10. Typical Application for 2-Cell and System Side





Figure 11. Typical Application for 2-Cell and Pack side

Tape and Reel Information


TDFN Package Reel Information



Color: Blue

All DIM in mm

TDFN Package Tape Information



Carrier Tape Color: Black

Cover Tape Width: 5.30 ± 0.10


Cover Tape Color: Transparent

All DIM in mm

All the package materials are Pb free and Halogen free.

Package Information

TDFN 2x3-8L(P0.50T0.75/0.85) PACKAGE OUTLINE DIMENSIONS



SYMBOL	DIMENSIONS IN MILLIMETERS		DIMENSIONS IN INCHES	
	MIN.	MAX.	MIN.	MAX.
A	0.700/0.800	0.800/0.900	0.028/0.031	0.031/0.035
A1	0.000	0.050	0.000	0.002
A3	0.203REF.		0.008REF.	
D	1.924	2.076	0.076	0.082
E	2.924	3.076	0.115	0.121
D1	1.400	1.600	0.055	0.063
E1	1.400	1.600	0.055	0.063
K	0.200MIN		0.008MIN	
b	0.200	0.300	0.008	0.012
e	0.500TYP.		0.020TYP.	
L	0.224	0.376	0.009	0.015

Revision History

Release No.	Date	Revision Description
1.0	2017-08-01	Initial Release
1.1	2018-01-19	Add MSL rating on page 4
1.2	2018-06-29	Update register default value
1.3	2019-05-13	Add 2-cell application diagrams and update sleep mode description

DISCLAIMER

CELLWISE reserves the right to make changes without further notices to any products herein to improve reliability, function or design. CELLWISE does not assume any liability arising out of the application or use of any product or circuit described herein; neither does it convey any license under its patent rights, nor the rights of others.

CELLWISE's products are not authorized for use as critical components in life support devices or systems without the express written approval of the president of CELLWISE corporation.

As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
2. A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.