



DC – AI – Routing – Switching – Security – Wireless – Automation

ZR/ZR+ Coherent Optics in ACX7100-32C

An HPE Juniper Networking Techpost

Antu Chatterjee

2022-08-23

HPE



Contents

1	ZR/ZR+ Coherent Optics in ACX7100-32C	3
1.1	Introduction	3
1.2	400GE Optics choices and challenges	3
1.3	Deployment Models with 400GE ZR/ZR+	3
1.3.1	Extended reach P2P packet	4
1.3.2	Multi-span Metro	4
1.4	ACX7100 Series Routers	4
1.4.1	Juniper's Approach for 400GE ZR/ZR+	5
1.5	Thermal & Power Analysis	6
1.5.1	Topology	6
1.5.2	KPIs to monitor	8
1.5.3	Without Optics	8
1.5.4	ZR optics on all (x36) Ports, no Traffic	9
1.5.5	ZR Optics on all (x36) Ports, Full Meshed Line Rate Traffic	11
1.6	Summary View	13
1.6.1	100GE Interfaces	14
1.6.2	400GE Interfaces	19
1.7	Telemetry configuration integrated with Paragon Insights	20
1.8	Summary	21
1.9	Glossary	21
1.10	Acknowledgments	21

List of Figures

1	Typical Power: Measured power is 486 W by the router at normal fan speed.	9
2	Typical Power Measured is 706 W	10
3	Maximum Power Measured is 832 W	11
4	Typical Power Measured is 791 W	12
5	Maximum Power Measured is 920 W	13

1 ZR/ZR+ Coherent Optics in ACX7100-32C

Antu Chatterjee - 08/23/2022

How does the Juniper ACX7100-32C router handle a fully loaded 400GE ZR and 100GE ZR4, long reach, high power coherent optics configuration?

1.1 Introduction

In this article, I want to talk about long reach, high power coherent optics challenges on 1RU fixed form-factor routers and how Juniper's ACX7100-32C (Cloud Metro ACX platforms) handles these challenges with design choices to optimize the thermals.

To answer the question with data-points "Will ACX7100-32C handle ZR4/ZR optics across all ports (x36) and stay stable under 4.8Tbps of traffic load and ambient and higher temperature?", the article is divided into three sections:

- System design & choices
- Test topology & KPIs
- Reporting of metrics presented via Grafana dashboard

1.2 400GE Optics choices and challenges

Metro and Data Center architectures are evolving to accommodate ever-growing traffic and performance-based applications that demand high bandwidth and low latency.

With the appropriate choice of optic cages, Juniper's Cloud Metro ACX7100-32C router supports coherent optical solutions like 400GE ZR/ZR+ and 100GE ZR4 on all ports.

While the new standards of optics substantially increase bandwidth capacity between the Cloud Metro and Data Centers reducing operating costs, footprint, and power consumption; parameters like optical power (influencing the reach and architectural capabilities) and operating temperature (influencing module packaging) becomes critical vis-e-vis heat dissipation in a 1RU fixed port configuration.

Let's double click on the 400GE deployment requirements and associated challenges in the Access, Metro, and Backbone.


- Operators require off-the-shelf optical modules to build and scale their networks quickly and efficiently. Power at ambient and higher temperature is one of the prime decision-making factors, especially with long-reach coherent optics along with optics cage configurations like stacked caging or belly-to-belly.
- High-performance network environments need to cool pluggable optical modules efficiently. High power modules must dissipate this heat effectively to ensure the operational performance of the modules. Prudent module, cage, heat sink and overall system design for optics modules help to optimize thermals.

1.3 Deployment Models with 400GE ZR/ZR+

There are a couple of ways the 400GE ZR/ZR+ are deployed based on the application.


1.3.1 Extended reach P2P packet

In this case, 400GE ZR modules are used as single carrier 400Gbps optical line rate and transporting 400GE, 2x 200GE, or 4x 100GE client signals for point-to-point reach.



1.3.2 Multi-span Metro

In this case, 400GE ZR provides solutions with higher performance to address a much wider range using amplifiers for metro/regional packet networking requirements.




1.4 ACX7100 Series Routers

ACX7100 routers exist in two versions—ACX7100-32C and ACX7100-48L—and detailed specifications are mentioned in ACX7100 Deepdive (<https://juniper.github.io/techposts/acx7100-deepdive/article>), here we will focus on the ACX7100-32C router with 400GE ZR and 100GE ZR4 optics.

ACX7100-32C offers:

- Connectivity for 32x 100GE and 4x 400GE (via QSFP-DD connectors)
- Six fan trays, front to back, with 5+1 redundancy

- Two power supply modules (1200W-1600W), with 1+1 redundancy



1.4.1 Juniper's Approach for 400GE ZR/ZR+

Let's double-click on the design consideration and the metrics to highlight the value proposition of the ACX7100-32C router:

- Optics cage and connector layout
- System design to optimize thermals with heat sinks.


The architecture choices of optical cage, connector and its layout have a direct impact on optics' thermal performance. The goal is to exhaust the heat from the module case and ensure the internal components stay within a certain temperature range. It guarantees reliability and optimal performance.

Details on optics design can be found at <http://www.qsfp-dd.com/wp-content/uploads/2021/01/2021-QSFP-DD-MSA-Thermal-Whitepaper-Final.pdf>

ACX7100-32C router uses QSFP-DD connector for all 32 QSFP28 ports (backward compatible with regular QSFP28 connectors) to accommodate higher power requirements. The system has an optimized design of optics cage for belly-to-belly configuration as show in the figure 4 below:



- 1x4 cages are used for the 32x QSFP28 ports
- 1x2 cages (with the smallest heatsinks) are used for the 4x QSFP-DD ports



The power dissipation ranges of 400GE client and line (ZR, ZR+) optical modules are 10-14W and 16-20W, respectively.

The router is designed for complete voltage range (High Line and Low Line) and supports front-to-back air flow.

Type	Voltage	Power	Air Flow
AC	103 to 140V (LL) 180 to 264V (HL)	1200W 1600W	AFO
DC	-40 to 48V (LL) 48 to 72V (HL)	1200W 1600W	AFO

1.5 Thermal & Power Analysis

Completely inhabited ACX7100-32C router with high-power digital coherent optics on all ports, has power rating within 1000 W, at an ambient temperature (25deg C). At higher temperature (55deg C), the power rating increases slightly and is well within 1200 W.

1.5.1 Topology

The router ACX7100-32C is populated with ZR optics connected to the traffic generator. The topology is built with fully meshed traffic (and not with snake) configuration.





```
1 regress@rtme-acx7100-32C>
```

show chassis hardware detail

```
1
2 Hardware inventory:
3 Item Version Part number Serial number Description
4 Chassis YX0221120001 JNP7100-32C [ACX7100-32C]
5 PSM 0 REV 04 740-085431 1ED7A140225 PSU 1600W AC, Front to Back Airflow
6 PSM 1 REV 04 740-085431 1ED7A140217 PSU 1600W AC, Front to Back Airflow
7 Routing Engine 0 REV 09 611-112446 YY0221120021 RE-JNP-7100
8   sda 100030 MB SFSA100GM2AK4T0- 00006018575697000031 Solid State Disk
9   sdb 100030 MB SFSA100GM2AK4T0- 00006018575697000007 Solid State Disk
10  CB 0 REV 13 650-113148 YX0221120001 Control Board
11  FPC 0 BUILTIN BUILTIN ACX7100-32C
12    PIC 0 BUILTIN BUILTIN MRATE- 32xQSFP-DD + 4xQSFP56-DD
13      Xcvr 0 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
14      Xcvr 1 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
15      Xcvr 2 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
16      Xcvr 3 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
17      Xcvr 4 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
18      Xcvr 5 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
19      Xcvr 6 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
20      Xcvr 7 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
21      Xcvr 8 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
22      Xcvr 9 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
23      Xcvr 10 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
24      Xcvr 11 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
25      Xcvr 12 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
26      Xcvr 13 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
27      Xcvr 14 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
28      Xcvr 15 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
29      Xcvr 16 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
30      Xcvr 17 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
31      Xcvr 18 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
32      Xcvr 19 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
33      Xcvr 20 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
34      Xcvr 21 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
35      Xcvr 22 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
36      Xcvr 23 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
37      Xcvr 24 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
38      Xcvr 25 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
39      Xcvr 26 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
40      Xcvr 27 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
41      Xcvr 28 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
42      Xcvr 29 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
43      Xcvr 30 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
44      Xcvr 31 REV 01 740-120240 1W1CQVA7xxxxx QSFP28-100G-ZR4
45      Xcvr 32 XXXX NON-JNPR L2131D0xxx QSFP56-DD-400G-ZR
46      Xcvr 33 REV 01 740-114884 1T1TZFA6xxxxx QSFP56-DD-400G-ZR
47      Xcvr 34 XXXX NON-JNPR L2129D0xxx QSFP56-DD-400G-ZR
48      Xcvr 35 REV 01 740-114884 1T1TZFA6xxxxx QSFP56-DD-400G-ZR
49  Fan Tray 0 JNP7100 Fan Tray, Front to Back Airflow - AFO
50  Fan Tray 1 JNP7100 Fan Tray, Front to Back Airflow - AFO
51  Fan Tray 2 JNP7100 Fan Tray, Front to Back Airflow - AFO
52  Fan Tray 3 JNP7100 Fan Tray, Front to Back Airflow - AFO
53  Fan Tray 4 JNP7100 Fan Tray, Front to Back Airflow - AFO
54  Fan Tray 5 JNP7100 Fan Tray, Front to Back Airflow - AFO
55
56 regress@rtme-acx7100-32C>
```

1.5.2 KPIs to monitor

Power rating: observes the power consumption (typical and maximum) by ACX7100-32C router under ambient and higher temperature. The higher temperature is mimicked by setting the fan speed to maximum.

Power rating are noted at multiple stages:

- Default router configuration without any optics,
- With ZR (-10 dB) optics on all ports and,
- With line rate traffic including random patterns across all ports in a fully meshed configuration.

Router and optics temperature: without and with traffic.

- Ambient temperature of the router
- Temperature of optics (100GE and 400GE) across (x36) ports

We built Grafana dashboards to monitor the KPIs, using REST APIs.

- One dashboard displays power rating of the router, number of optics plugged in, temperature of the optics and ambient temperature of the router
- Another displays attributes of the optics when device is under test.

Note: To reproduce higher temperature conditions, we set up fan speed to maximum with “request chassis fan speed full-speed tray 0”

```
1 regress@rtme-acx7100-32C>
```

show chassis fan

```
1
2 Item Status % RPM Measurement
3 Fan Tray 0 Fan 1 OK 99% 29600 RPM
4 Fan Tray 0 Fan 2 OK 100% 24800 RPM
5 Fan Tray 1 Fan 1 OK 100% 30000 RPM
6 Fan Tray 1 Fan 2 OK 100% 25000 RPM
7 Fan Tray 2 Fan 1 OK 99% 29600 RPM
8 Fan Tray 2 Fan 2 OK 100% 24800 RPM
9 Fan Tray 3 Fan 1 OK 99% 29600 RPM
10 Fan Tray 3 Fan 2 OK 100% 24800 RPM
11 Fan Tray 4 Fan 1 OK 100% 30000 RPM
12 Fan Tray 4 Fan 2 OK 100% 24800 RPM
13 Fan Tray 5 Fan 1 OK 98% 29400 RPM
14 Fan Tray 5 Fan 2 OK 100% 24800 RPM
```

1.5.3 Without Optics

Router power consumption at normal and max fan speed:

Test Conditions	Environment	Power
Typical Power (without optics)	Normal Fan Speed	486W
Max Power (without optics)	Maximum Fan Speed	616W





Figure 1: Typical Power: Measured power is 486 W by the router at normal fan speed.



1.5.4 ZR optics on all (x36) Ports, no Traffic

Router power consumption and temperature at normal and max fan speed:

Test Conditions	Environment	Power
Typical Power with4x 400GE ZR + 32x 100GE ZR4optics plugged-in, no traffic	Normal Fan Speed	706W
Maximum Power with4x 400G ZR + 32x 100GE ZR4optics plugged-in, no traffic	Maximum Fan Speed	832W

Power Consumption	Average Fan Speed	400G-FR4 Count	100G-LR4 Count	400G-ZR Count	100G-ZR4 Count	BGP Routes	
706 W	61.8%	0	0	4	32	0	
Average 400G Port Input Throughput		Average 400G Port Output Throughput		Average 100G Port Input Throughput		Average 100G Port Output Throughput	
118 b/s		144 b/s		14.8 b/s		18 b/s	
						ENV - Temp	
27 °C							

et-0/0/0 - Temp	et-0/0/1 - Temp	et-0/0/2 - Temp	et-0/0/3 - Temp	et-0/0/4 - Temp	et-0/0/5 - Temp	et-0/0/6 - Temp	et-0/0/7 - Temp
31 °C	33 °C	31 °C	33 °C	31 °C	33 °C	30 °C	32 °C
et-0/0/8 - Temp	et-0/0/9 - Temp	et-0/0/10 - Temp	et-0/0/11 - Temp	et-0/0/12 - Temp	et-0/0/13 - Temp	et-0/0/14 - Temp	et-0/0/15 - Temp
31 °C	32 °C	30 °C	33 °C	30 °C	33 °C	30 °C	32 °C
et-0/0/16 - Temp	et-0/0/17 - Temp	et-0/0/18 - Temp	et-0/0/19 - Temp	et-0/0/20 - Temp	et-0/0/21 - Temp	et-0/0/22 - Temp	et-0/0/23 - Temp
30 °C	33 °C	30 °C	33 °C	30 °C	33 °C	30 °C	33 °C
et-0/0/24 - Temp	et-0/0/25 - Temp	et-0/0/26 - Temp	et-0/0/27 - Temp	et-0/0/28 - Temp	et-0/0/29 - Temp	et-0/0/30 - Temp	et-0/0/31 - Temp
30 °C	33 °C	32 °C	34 °C	33 °C	35 °C	33 °C	36 °C
et-0/0/32 - Temp	et-0/0/33 - Temp	et-0/0/34 - Temp	et-0/0/35 - Temp				
64 °C	61 °C	68 °C	61 °C				

Figure 2: Typical Power Measured is 706 W

Typical power measured is 706 W by the router at normal fan speed with ZR optics plugged into 4x 400GE and 32x 100GE ports. Temperature of the 100GE optics are in the range of 31-33 degC, while 400GE optics are in the range of 61-68 degC.

Power Consumption	Average Fan Speed	4000-FRM Count	1000-LRM Count	4000-ZR Count	1000-ZRM Count	BGP Routes	
832 W	99.2%	0	0	4	32	0	
Average 4000 Port Input Throughput		Average 4000 Port Output Throughput		Average 1000 Port Input Throughput		Average 1000 Port Output Throughput	
0 b/s		0 b/s		15 b/s		18.3 b/s	
ENV - Temp							
et-0/0/0 - Temp	et-0/0/1 - Temp	et-0/0/2 - Temp	et-0/0/3 - Temp	et-0/0/4 - Temp	et-0/0/5 - Temp	et-0/0/6 - Temp	et-0/0/7 - Temp
29 °C	31 °C	29 °C	31 °C	29 °C	31 °C	28 °C	30 °C
et-0/0/8 - Temp	et-0/0/9 - Temp	et-0/0/10 - Temp	et-0/0/11 - Temp	et-0/0/12 - Temp	et-0/0/13 - Temp	et-0/0/14 - Temp	et-0/0/15 - Temp
29 °C	30 °C	28 °C	31 °C	29 °C	31 °C	28 °C	30 °C
et-0/0/16 - Temp	et-0/0/17 - Temp	et-0/0/18 - Temp	et-0/0/19 - Temp	et-0/0/20 - Temp	et-0/0/21 - Temp	et-0/0/22 - Temp	et-0/0/23 - Temp
28 °C	31 °C	29 °C	32 °C	28 °C	31 °C	28 °C	31 °C
et-0/0/24 - Temp	et-0/0/25 - Temp	et-0/0/26 - Temp	et-0/0/27 - Temp	et-0/0/28 - Temp	et-0/0/29 - Temp	et-0/0/30 - Temp	et-0/0/31 - Temp
29 °C	31 °C	31 °C	32 °C	32 °C	33 °C	32 °C	34 °C
et-0/0/32 - Temp	et-0/0/33 - Temp	et-0/0/34 - Temp	et-0/0/35 - Temp				
55 °C	52 °C	60 °C	52 °C				

Figure 3: Maximum Power Measured is 832 W

Maximum Power measured is 832 W by the router at maximum fan speed with ZR optics plugged into 4x 400GE and 32x 100GE ports only. Temperature of the 100GE optics are in the range of 28-31 degC, while 400GE optics are in the range of 52-60 degC.

1.5.5 ZR Optics on all (x36) Ports, Full Meshed Line Rate Traffic

Router power consumption and temperature at normal and max fan speed

Traffic profile (IMIX): the traffic generator is configured with fully meshed traffic pattern and following packet sizes, line rate on all ports.

- 64 bytes
- 78 bytes
- 100 bytes
- 373 bytes
- 570 bytes
- 1300 bytes
- 1518 bytes
- 9000 bytes

Test Conditions	Environment	Power
Typical Power with 4x 400GE ZR + 32x 100GE ZR4 optics plugged-in, with traffic	Normal Fan Speed	791W
Maximum Power with 4x 400GE ZR + 32x 100GE ZR4 optics plugged-in, with traffic	Maximum Fan Speed	920W

Power Consumption	Average Fan Speed	400G-FRM Count	100G-LRM Count	400G-ZR Count	100G-ZR4 Count	BGP Routes	
791 W	62.1%	0	0	4	32	1000000	
Average 400G Port Input Throughput	Average 400G Port Output Throughput	Average 100G Port Input Throughput	Average 100G Port Output Throughput	ENV - Temp			
347 Gb/s	347 Gb/s	86.7 Gb/s	86.5 Gb/s	28 °C			
et-0/0/0 - Temp	et-0/0/1 - Temp	et-0/0/2 - Temp	et-0/0/3 - Temp	et-0/0/4 - Temp	et-0/0/5 - Temp	et-0/0/6 - Temp	et-0/0/7 - Temp
31 °C	34 °C	32 °C	34 °C	31 °C	34 °C	31 °C	33 °C
et-0/0/8 - Temp	et-0/0/9 - Temp	et-0/0/10 - Temp	et-0/0/11 - Temp	et-0/0/12 - Temp	et-0/0/13 - Temp	et-0/0/14 - Temp	et-0/0/15 - Temp
31 °C	33 °C	31 °C	34 °C	31 °C	34 °C	30 °C	33 °C
et-0/0/16 - Temp	et-0/0/17 - Temp	et-0/0/18 - Temp	et-0/0/19 - Temp	et-0/0/20 - Temp	et-0/0/21 - Temp	et-0/0/22 - Temp	et-0/0/23 - Temp
30 °C	34 °C	31 °C	34 °C	31 °C	34 °C	31 °C	34 °C
et-0/0/24 - Temp	et-0/0/25 - Temp	et-0/0/26 - Temp	et-0/0/27 - Temp	et-0/0/28 - Temp	et-0/0/29 - Temp	et-0/0/30 - Temp	et-0/0/31 - Temp
31 °C	34 °C	33 °C	35 °C	34 °C	36 °C	34 °C	37 °C
et-0/0/32 - Temp	et-0/0/33 - Temp	et-0/0/34 - Temp	et-0/0/35 - Temp				
67 °C	64 °C	71 °C	64 °C				

Figure 4: Typical Power Measured is 791 W

Typical Power measured is 791 W by the router when line rate traffic is sent across 4x 400GE + 32x 100GE ports and fan speed set to normal. Temperature of the 100GE optics is in the range of 31-34 degC, while 400GE optics are in the range of 64-71 degC.




Figure 5: Maximum Power Measured is 920 W

Maximum Power measured is 920 W by the router when line rate traffic is sent across 4x 400GE & 32x 100GE ports and fan speed is set to max. Temperature of the 100GE optics are in the range of 30-37 degC, while 400GE optics are in the range of 62-68 degC.

1.6 Summary View

In the following dashboard, we display multiple optic attributes including:

- Chromatic dispersion: arises from the variation in propagation velocity with wavelength
- Optical Signal to Noise Ratio (OSNR): provides a measure of optical noise interference on optical signals. The OSNR values are most critical at the receiving end of the network since if this ratio reduces, then the probability of the receiver recovering the signal is reduced
- Pre-FEC BER: The 400G ZR Optics first transforms the optical signal into a digital bit stream and then applies a forward error correction (FEC), which automatically corrects failed bits, if any. As long as the pre-FEC is below the threshold level, the system ensures that all bit errors are successfully identified and corrected, and therefore, no packet loss occurs
- Input power: If the input power of the optics goes lower than the desired value, indicates that there could be a problem with the receiver itself, or as in most cases, could be in the fiber (can be a bad fiber, or the connector is dirty and requires cleaning).
- Output power: The highest power the optics can deliver and pumps it out. It's not configurable since it's the output power that is pumped out by the optics. You can distinguish good and bad module based on the output power.


1.6.1 100GE Interfaces
















1.6.2 400GE Interfaces





1.7 Telemetry configuration integrated with Paragon Insights

Streaming Telemetry and monitoring of high-power coherent optics is outside the scope of this article and will be taken up as part of another article where Juniper's Paragon Insight monitors the attributes and raises alarm when the values are abnormal or found to be out of bounds. Following attributes are monitored by Paragon Insight:

Input-power	/components/component/optical-channel/state/input-power
OSNR	/components/component/optical-channel/state/osnr
Pre-FEC-BER	/components/component/optical-channel/state/pre-fec-ber/instant
Output-power	/components/component/optical-channel/state/output-power
Laser-bias-current	/components/component/optical-channel/state/laser-bias-current
Chromatic dispersion	/components/component/optical-channel/state/chromatic-dispersion
Second order polarization mode dispersion	/components/component/optical-channel/state/second-order-polarization-mode-dispersion
Polarization dependent loss	/components/component/optical-channel/state/polarization-dependent-loss
Carrier frequency offset	/components/component/optical-channel/state/carrier-frequency-offset/instant

1.8 Summary

The key takeaways for ACX7100-32C, regardless of configuration: ACX7100-32C can support 4x 400GE and 32x 100GE ZR4s in all ports with a power budget of <1000W at ambient and higher temperatures. This is achieved by a single row of QSFP-DD connectors with the smallest heatsink for 1RU in belly-to-belly configuration.

1.9 Glossary

- KPI : Key Performance Indicator
- IMIX : Internet Mix
- AFO : Air Flow Out
- AFI : Air Flow In
- LL : Low line input voltage
- HL : High line input voltage
- QSFP-DD : 400GE optics type

1.10 Acknowledgments

I would like to express my gratitude to my mentor Nicolas Fevrier, Sr. Director, PLM, for the detailed reviews of the article. I would also thank the Lab Engineers, TME team (Suneesh Babu, Jose Dimabuyu & Jose Miguel) and Hardware Engineering team (Kapil Jain, Rajeshwar Sable) for the timely support and help.



DC – AI – Routing – Switching – Security – Wireless – Automation

© Copyright 2026 Hewlett Packard Enterprise Development LP. The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty.

Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.

Trademark acknowledgments, if needed. All third-party marks are the property of their respective owners.

HEWLETT PACKARD ENTERPRISE

HPE.com

HPE

