

Sunburn device: the whole program

every block of the program that runs on the wrist, explained in plain English · printed 2026-09-14

The Sunburn device is a wearable built on a BBC micro:bit, a small computer with 25 lights and two buttons. It measures the sun's UV with a sensor, checks the online UV index for where you are through a phone, and then flashes, beeps or taps your arm until you put sunscreen on. Two hours later it reminds you to reapply. The program that does all this is built from 74 coloured blocks. Every one of them is on these sheets, with a note saying what it does.

Each picture is one block of the program, exactly as it looks in the MakeCode editor where the program is built by snapping coloured pieces together. A block is read from top to bottom. Under each picture: the block's name, what kind of block it is, what it does, which other blocks use it (Used by) and which blocks it calls on (Uses). This sheet is the whole program at a glance: nine numbered sections. Sections 1 and 2 are the plan the device follows; sections 3 to 9 are the parts that plan calls on.



- 1

Start here: settings · 1 block · sheet 2
This block runs first, the moment the device is switched on. It holds every setting: which UV sensor is fitted, how the sound and the tapping arm are wired, the UV levels that count as low, moderate, very high and extreme, and how long each wait is. Then it starts everything up. To change how the device behaves, this is the only place to look.
- 2

The flowchart · 20 blocks · sheet 3
The plan the device follows all day, taken straight from the Sunburn Flowchart. Every box and every question on the flowchart is one block here, with the same name, in the same order: read the UV sensor, check the reading makes sense, ask the phone for the online UV index, decide how strong the sun is, then react. The forever block keeps the plan running round and round.
- 3

Buttons · 3 blocks · sheet 7
The micro:bit has two buttons. A means done: sunscreen is on, or I am going inside. B wakes the device up. Pressing both together turns it off, or on again.
- 4

Alerts · 4 blocks · sheet 8
The ways the device gets your attention: flashing and beeping, tapping your arm with the small motor, and going to sleep when nobody answers. Each one keeps going until you press A or its time limit runs out. No answer for a long time means the device is probably not being worn, so it sleeps until a button is pressed.
- 5


Screen and lights · 8 blocks · sheet 9
What you see. The 5 by 5 grid of lights shows the UV number, a happy face or a warning, and messages one word at a time. If a small screen is fitted, it shows the number large, the level, the message and the countdowns.
- 6

Sound and the tapping arm · 5 blocks · sheet 11
The beeps, and the small motor (a servo) whose arm taps your wrist when the sun is extreme.
- 7

Talking to the phone · 11 blocks · sheet 11
How the wearable and the phone app talk over Bluetooth. The phone sends the online UV index for where you are; the wearable sends back what it is doing every two seconds and reports each event, such as sunscreen applied. The same messages also go down the USB cable, so everything can be tested on a laptop.
- 8

Helpers · 10 blocks · sheet 14
Small jobs the other blocks share: the maths for each type of sensor, turning minutes into the milliseconds the program counts in, sorting numbers, and tidying up numbers, times and text.
- 9

The optional screen · 12 blocks · sheet 16
Only used if a small screen is added to the wearable. These blocks draw letters and numbers on it dot by dot. The device works exactly the same without a screen.



The Sunburn Flowchart the device follows. Every box on it is a block in section 2 with the same name.

What the block colours mean

- | | |
|-------------------------------|-----------------------------|
| Variables: remember a value | Text |
| Functions: a step with a name | Arrays: lists |
| Basic: the lights, pauses | Music: beeps |
| Input: buttons and time | Pins: sensor, motor, screen |
| Loops: repeat | Bluetooth: the phone |
| Logic: if, compare | Serial: the USB cable |
| Maths | Control: timing |

Reading the other sheets

Every picture is one block from the editor at 60% of its size on screen. Under it: the block's name, what kind of block it is, what it does, which blocks use it (Used by) and which blocks it calls on (Uses).

UV index How strong the sun's burning rays are, from 0 (none) to 11 and above (extreme). Protection is needed from 3 upwards, even on cool or cloudy days.

micro:bit The small computer the program runs on. It has a 5 by 5 grid of lights, buttons A and B, and sockets called pins (P0, P1, P2) that other parts plug into.

Block One instruction of the program. Blocks snap together and run in order from top to bottom. A block with a name at the top (function) is a step that other blocks can call on.

Sensor The part that measures UV. It gives a voltage, which the program turns into a UV index number.

Servo A small motor with an arm. Here it taps the wearer's wrist when the sun is extreme.

Bluetooth and USB The two ways the wearable talks to a phone or a laptop. The phone app sends the online UV index; the wearable sends back what it is doing.

OLED An optional small screen. Without one, the grid of lights does the job.

ms and Hz ms are milliseconds, thousandths of a second. Hz sets how high a beep sounds.

Demo timings Much shorter waits (seconds instead of minutes and hours) so the whole day can be shown in a few minutes at a demo.

Names in the blocks Words like uvSampleCount are the program's own names for its settings and memory. Read them as English: uv sample count is how many readings to take.

1

Start here: settings

1 block

This block runs first, the moment the device is switched on. It holds every setting: which UV sensor is fitted, how the sound and the tapping arm are wired, the UV levels that count as low, moderate, very high and extreme, and how long each wait is. Then it starts everything up. To change how the device behaves, this is the only place to look.

on start

set uvSensorType to 1

set uvSampleCount to 15

set soundOutput to 1

set servoType to 1

set servoRestAngle to 90

set servoTapAngle to 30

set oledMode to 1

set oledType to 1

set oledAddress to 60

set uvLowMax to 2

set uvHighMax to 7

set uvVeryHighMax to 10

set waitMinutes to 5

set reapplyHours to 2

set tapMaxMinutes to 2

set alertGiveUpMinutes to 10

set onLineUvMaxAgeMinutes to 30

set sensorRetrySeconds to 5

set firmwareVersion to "3.1"

call applySensorPreset

call applyTimings

call setupSound

call setupOled

call advertiseOverBluetooth

if button B is pressed then

set demoMode to true

call applyTimings

+

call deviceTurnsOn

on start Runs once, when the device is switched on

The first thing that runs when the device is switched on. All the settings are listed here, then the start-up steps: work out the sensor maths, set the timings, get the sound, the screen and Bluetooth ready, and show that the device is on. Holding B while switching on uses the fast demo timings.

Uses: deviceTurnsOn, setupSound, advertiseOverBluetooth, applySensorPreset, applyTimings, setupOled

2 The flowchart

20 blocks


The plan the device follows all day, taken straight from the Sunburn Flowchart. Every box and every question on the flowchart is one block here, with the same name, in the same order: read the UV sensor, check the reading makes sense, ask the phone for the online UV index, decide how strong the sun is, then react. The forever block keeps the plan running round and round.



forever Runs again and again, all day

Runs the flowchart once, then goes straight back to the top and runs it again, all day long.


Uses: runFlowchart



runFlowchart A step of the program

The whole flowchart from top to bottom. Read the sensor. If the reading makes sense, pick the UV value, show it, decide the level and react: a happy face, or an alert until A is pressed. Then wait 5 minutes and check whether it is time for more sunscreen. If the reading does not make sense, show CHECK SENSOR instead. Pressing A and B together at any moment turns the device off and stops every wait.


Used by: forever · **Uses:** readUvSensor, sensorReadingInRange, showCheckSensor, chooseUvValue, uvBand, showHappyFace, moderateOrHighUv, veryHighUv, extremeUv, wait5Minutes, reapplyTimerExpired, showReapplySunscreen, showUvReading



phoneSendingOnlineUv A yes-or-no question the program asks

Asks: has the phone app sent an online UV index in the last 30 minutes?

Used by: chooseUvValue, showUvReading, sendStatus



chooseUvValue A step of the program

Picks the UV number the device will act on: the higher of the sensor's reading and the phone's online value, or just the sensor's reading when the phone is not sending.

Used by: runFlowchart · **Uses:** phoneSendingOnlineUv

2 The flowchart (continued)

20 blocks

The plan the device follows all day, taken straight from the Sunburn Flowchart. Every box and every question on the flowchart is one block here, with the same name, in the same order: read the UV sensor, check the reading makes sense, ask the phone for the online UV index, decide how strong the sun is, then react. The forever block keeps the plan running round and round.

```
function readUvSensor
  set stateName to "reading"
  repeat uvSampleCount times
    do
      samples add value analog read pin analog pin P1 to end
      pause (ms) 2
  call sortNumbers samples
  set sensorRaw to samples get value at floor uvSampleCount / 2
  set sensorNoise to samples get value at uvSampleCount - 1 - samples get value at 0
  set sensorVolts to sensorRaw x 3.3 / 1023
  set sensorUv to sensorVolts - uvZeroVolts / uvVoltsPerIndex
  call debugLog join "raw" sensorRaw "noise" sensorNoise
```

readUvSensor A step of the program

Reads the UV sensor plugged into pin P1. It takes 15 quick readings and uses the middle one, so a single odd reading cannot set off a false alarm. Then it turns the sensor's voltage into a UV index number.

Used by: runFlowchart, handleCommand, calibrateToKnownUv · **Uses:** sortNumbers, debugLog

```
function sensorReadingInRange
  set inRange to true
  if sensorRaw ≥ 1020 then
    set inRange to false
  if sensorNoise > 200 then
    set inRange to false
  if sensorUv < -1.5 or sensorUv > 20 then
    set inRange to false
  if inRange then
    set sensorErrorReported to false
  return inRange
```

sensorReadingInRange A yes-or-no question the program asks

Asks: is this reading believable? The answer is no if the sensor is missing or shorted, if the readings jump about (a loose wire), or if the number could not be real.

Used by: runFlowchart

```
function start2HourReapplyTimer
  set reapplyTimerRunning to true
  set reapplyDueTime to running time (ms) + reapplyMs
```

start2HourReapplyTimer A step of the program

Starts the 2 hour countdown to the next sunscreen.

Used by: sunscreenApplied

```
function showCheckSensor
  set stateName to "error"
  if not sensorErrorReported then
    call sendLine "ev=error;msg=CHECK SENSOR"
    set sensorErrorReported to true
  show icon
  call showMessage "CHECK SENSOR"
  call oledFooter join "pin" call formatNumber sensorVolts " V"
  call beep 440 200
  call beep 440 200
  pause (ms) sensorRetrySeconds x 1000
```

showCheckSensor A step of the program

When the reading is not believable: shows a cross and the words CHECK SENSOR, beeps twice, tells the app there is a problem, and tries again in 5 seconds. A faulty sensor is never treated as safe.

Used by: runFlowchart · **Uses:** showMessage, oledFooter, beep, sendLine, formatNumber

```
function showHappyFace
  set stateName to "safe"
  show icon
  call oledShowMessage "Low UV. No sunscreen needed"
```

showHappyFace A step of the program


UV 0 to 2: shows a happy face. No sunscreen needed right now.

Used by: runFlowchart · **Uses:** oledShowMessage

2 The flowchart (continued)

20 blocks

The plan the device follows all day, taken straight from the Sunburn Flowchart. Every box and every question on the flowchart is one block here, with the same name, in the same order: read the UV sensor, check the reading makes sense, ask the phone for the online UV index, decide how strong the sun is, then react. The forever block keeps the plan running round and round.



uvBand Works out a piece of text · needs: uv

Turns a UV index into one of the four levels on the flowchart: low (0 to 2), moderate or high (3 to 7), very high (8 to 10) or extreme (11 and above).


Used by: runFlowchart, sendStatus



moderateOrHighUv A step of the program

UV 3 to 7: flashes and beeps slowly until A is pressed, then shows how much sunscreen to put on and starts the 2 hour timer. If sunscreen is already on, it just shows a tick and the time left. If nobody presses A within 10 minutes, the device assumes it is not being worn and goes to sleep.


Used by: runFlowchart · **Uses:** sunscreenApplied, alreadyProtected, flashAndBeepUntilA, standbyUntilButton, showMessage



veryHighUv A step of the program

UV 8 to 10: flashes and beeps quickly until A is pressed, then shows the sunscreen advice plus hat and shade, and starts the 2 hour timer. It alerts again if the wearer so far only had the moderate advice.


Used by: runFlowchart · **Uses:** sunscreenApplied, alreadyProtected, flashAndBeepUntilA, standbyUntilButton, showMessage



extremeUv A step of the program

UV 11 or more: taps the arm until A is pressed (after 2 minutes it beeps instead), shows Go inside now, then sleeps until a button is pressed.

Used by: runFlowchart · **Uses:** tapArmUntilA, standbyUntilButton, showMessage, sendEvent



sunscreenApplied A step of the program · needs: level


A was pressed after a sunscreen alert: remembers which advice was given, counts one more application, tells the app, and starts the timer.

Used by: moderateOrHighUv, veryHighUv · **Uses:** start2HourReapplyTimer, sendEvent


2 The flowchart (continued)

20 blocks

The plan the device follows all day, taken straight from the Sunburn Flowchart. Every box and every question on the flowchart is one block here, with the same name, in the same order: read the UV sensor, check the reading makes sense, ask the phone for the online UV index, decide how strong the sun is, then react. The forever block keeps the plan running round and round.




alreadyProtected A step of the program
Sunscreen is already on, so there is no alert: just a tick and the time until it needs reapplying.
Used by: moderateOrHighUv, veryHighUv · **Uses:** oledShowMessage, formatTime




wait5Minutes A step of the program
Waits 5 minutes before the next check. The wait ends early if the device is turned off or the sunscreen timer runs out. Pressing A during the wait shows the UV number and the countdown.
Used by: runFlowchart · **Uses:** reapplyTimerExpired, showLedStatus, oledFooter, formatTime, reapplyCountdownText




reapplyTimerExpired A yes-or-no question the program asks
Asks: have the 2 hours since the last sunscreen passed?
Used by: runFlowchart, wait5Minutes



showReapplySunscreen A step of the program
Shows Reapply sunscreen and clears the timer, so the next trip round the flowchart alerts again if the sun is still strong.
Used by: runFlowchart · **Uses:** showMessage, sendEvent



deviceTurnsOn A step of the program
Switching on: shows a tick, says Device on on the screen, tells the app, and marks the device as on.
Used by: on button A+B pressed, handleCommand, on start · **Uses:** oledHeader, oledShowMessage, oledFooter, servoOff, sendEvent




deviceTurnsOff A step of the program
Switching off: everything stops and the screen shows OFF. Bluetooth stays on so the app can switch it back on.
Used by: on button A+B pressed, handleCommand · **Uses:** servoOff, sendEvent, oledClear, oledWriteRow


3 Buttons

3 blocks

The micro:bit has two buttons. A means done: sunscreen is on, or I am going inside. B wakes the device up. Pressing both together turns it off, or on again.



on button A pressed Runs each time button A is pressed
Pressing A means done: sunscreen is on, or I am going inside. It also wakes the device, skips a long message, and during a wait shows the UV number and the countdown.



on button B pressed Runs each time button B is pressed
Pressing B wakes the device from sleep. Holding B while switching on gives the fast demo timings.



on button A+B pressed Runs when A and B are pressed together
Pressing A and B together turns the device off, or on again.
Uses: deviceTurnsOn, deviceTurnsOff

The ways the device gets your attention: flashing and beeping, tapping your arm with the small motor, and going to sleep when nobody answers. Each one keeps going until you press A or its time limit runs out. No answer for a long time means the device is probably not being worn, so it sleeps until a button is pressed.

```
function flashAndBeepUntilA fast
  set ackPressed to false
  set beatMs to 500
  set tone to 523
  if fast then
    set beatMs to 150
    set tone to 659
  +
  set giveUpTime to running time (ms) + alertGiveUpMs
  while call stillWaitingForA giveUpTime
  do
    call ledsAllOn
    call beep tone beatMs
    clear screen
    pause (ms) beatMs
```

flashAndBeepUntilA A step of the program · needs: fast
Flashes all 25 lights and beeps until A is pressed or the app says done. The fast setting is the quicker, higher beep for very high UV. It gives up after 10 minutes so a device left on a table does not beep all day.
Used by: moderateOrHighUv, veryHighUv, tapArmUntilA · **Uses:** stillWaitingForA, ledsAllOn, beep

```
function stillWaitingForA untilTime
  return not ackPressed and deviceOn and running time (ms) < untilTime
```

stillWaitingForA A yes-or-no question the program asks · needs: untilTime
Asks: should the alert carry on? Yes while A has not been pressed, the device is still on, and the time limit has not been reached.
Used by: flashAndBeepUntilA, tapArmUntilA

```
function tapArmUntilA
  set ackPressed to false
  show icon
  set stopTappingTime to running time (ms) + tapMaxMs
  while call stillWaitingForA stopTappingTime
  do
    call servoTapOnce
  call servoOff
  if not ackPressed and deviceOn then
    call flashAndBeepUntilA true
  +
```

tapArmUntilA A step of the program
Taps the wearer's arm with the motor until A is pressed. After 2 minutes it beeps instead, so a device that is not being worn does not run the motor flat.
Used by: extremeUv · **Uses:** flashAndBeepUntilA, stillWaitingForA, servoOff, servoTapOnce


```
function standbyUntilButton
  set wentToStandby to true
  set stateName to "standby"
  call sendEvent "standby"
  set anyButtonPressed to false
  show icon
  call oledShowMessage "Standby. Press a button to check again"
  call oledFooter ""
  while deviceOn and not anyButtonPressed
  do
    pause (ms) 200
```

standbyUntilButton A step of the program
Sleep: waits for any button, or done from the app. Pressing A and B together still turns the device off. Afterwards it goes straight back to reading the sensor.
Used by: moderateOrHighUv, veryHighUv, extremeUv · **Uses:** oledShowMessage, oledFooter, sendEvent

5 Screen and lights

8 blocks

What you see. The 5 by 5 grid of lights shows the UV number, a happy face or a warning, and messages one word at a time. If a small screen is fitted, it shows the number large, the level, the message and the countdowns.



showUvReading A step of the program

Shows the UV number: rounded on the grid of lights, and exact, with the level and where it came from, on the screen.


Used by: runFlowchart · **Uses:** phoneSendingOnlineUv, uvBandName, oledHeader, formatNumber, oledWriteRow, oledWriteBig



uvBandName Works out a piece of text · needs: uv

The words for the screen: LOW, MODERATE, HIGH, VERY HIGH or EXTREME.

Used by: showUvReading



showLedStatus A step of the program

When A is pressed during a wait: the UV number and the time until reapply scroll across the lights, then the usual icon comes back.


Used by: wait5Minutes · **Uses:** reapplyCountdownText



oledFooter A step of the program · needs: text

The bottom line of the screen: the countdowns.


Used by: showCheckSensor, wait5Minutes, deviceTurnsOn, standbyUntilButton · **Uses:** oledWriteRow



ledsAllOn A step of the program

Turns all 25 lights on: the flash of an alert.

Used by: flashAndBeepUntilA



oledHeader A step of the program


The top line of the screen: the title, and a star while a phone is connected.

Used by: deviceTurnsOn, showUvReading, on bluetooth connected, on bluetooth disconnected · **Uses:** oledWriteRow

5 Screen and lights (continued)

8 blocks

What you see. The 5 by 5 grid of lights shows the UV number, a happy face or a warning, and messages one word at a time. If a small screen is fitted, it shows the number large, the level, the message and the countdowns.



showMessage A step of the program · needs: text

Shows a message: on the screen if there is one, otherwise scrolled across the lights one word at a time. Pressing A skips the rest.

Used by: showCheckSensor, moderateOrHighUv, veryHighUv, extremeUv, showReapplySunscreen · **Uses:** oledShowMessage



oledShowMessage A step of the program · needs: text


The middle of the screen: a message, split over three lines of 21 letters.

Used by: showHappyFace, alreadyProtected, deviceTurnsOn, standbyUntilButton, showMessage · **Uses:** oledWriteRow

6 Sound and the tapping arm

5 blocks


The beeps, and the small motor (a servo) whose arm taps your wrist when the sun is extreme.



setupSound A step of the program

Gets the sound ready: the micro:bit's built-in speaker, or a buzzer on pin P0.


Used by: on start



beep A step of the program · needs: frequency, ms

One beep. It needs how high the beep should sound (the frequency) and how long it lasts (in milliseconds).

Used by: showCheckSensor, flashAndBeepUntilA




servoAngle A step of the program ·

needs: angle

Turns the motor's arm to an angle. The motor's signal wire is on pin P2.

Used by: servoOff, servoTapOnce



servoTapOnce A step of the program

One tap of the arm, about half a second long.

Used by: tapArmUntilA · **Uses:** servoAngle



servoOff A step of the program

Moves the arm back to rest, then stops sending it signals so it is silent and uses no power.

Used by: deviceTurnsOn, deviceTurnsOff, tapArmUntilA · **Uses:** servoAngle

7 Talking to the phone

11 blocks


How the wearable and the phone app talk over Bluetooth. The phone sends the online UV index for where you are; the wearable sends back what it is doing every two seconds and reports each event, such as sunscreen applied. The same messages also go down the USB cable, so everything can be tested on a laptop.



advertiseOverBluetooth A step of the program

Makes the wearable visible over Bluetooth so a phone can connect, and sends the same messages down the USB cable so a laptop can test everything.


Used by: on start



on bluetooth connected Runs when a phone connects

A phone has connected: say hello and send it the current status straight away.


Uses: oledHeader, sendLine, sendStatus



on bluetooth disconnected Runs when the phone goes away

The phone has gone: remember that, and update the screen.


Uses: oledHeader



on bluetooth data received Runs when a line of text arrives from the phone

A line of text arrived from the phone: pass it to the block that reads commands.


Uses: handleCommand



every 2000 ms Runs every 2 seconds in the background

Every 2 seconds, send the app a status line.

Uses: sendStatus



on serial data received Runs when a line of text arrives over the USB cable


A line of text arrived over the USB cable: pass it to the block that reads commands.

Uses: handleCommand

7 Talking to the phone (continued)

11 blocks


How the wearable and the phone app talk over Bluetooth. The phone sends the online UV index for where you are; the wearable sends back what it is doing every two seconds and reports each event, such as sunscreen applied. The same messages also go down the USB cable, so everything can be tested on a laptop.



sendLine A step of the program · needs: text

Sends one line of text down the USB cable, and to the phone when one is connected.


Used by: showCheckSensor, on bluetooth connected, sendEvent, sendStatus, handleCommand, calibrateToKnownUv



sendEvent A step of the program · needs: name

Tells the app something happened: sunscreen applied, a reminder, went inside, sleep, a sensor problem, on or off.

Used by: extremeUv, sunscreenApplied, showReapplySunscreen, deviceTurnsOn, deviceTurnsOff, standbyUntilButton · **Uses:** sendLine



sendStatus A step of the program

Builds the status line the app shows: what the device is doing, the UV values, the level, the seconds until sunscreen is due, how many applications so far, the program version, and whether demo timings are on.

Used by: on bluetooth connected, every 2000 ms, handleCommand · **Uses:** phoneSendingOnlineUv, uvBand, sendLine, formatNumber

7

Talking to the phone (continued)

11 blocks

How the wearable and the phone app talk over Bluetooth. The phone sends the online UV index for where you are; the wearable sends back what it is doing every two seconds and reports each event, such as sunscreen applied. The same messages also go down the USB cable, so everything can be tested on a laptop.

```
function handleCommand command
  set parts to split call cleanText command at "="
  set key to parts get value at 0
  if length of array parts > 1 then
    set value to parts get value at 1
    call debugLog join "cmd" key " " value
    if key == "uv" then
      set newUv to parse to number value
      if newUv ≥ 0 and newUv ≤ 20 then
        set onlineUv to newUv
        set onlineUvTime to running time (ms)
        call sendLine "ok=uv"
      else
        call sendLine "err=uv"
    else if key == "ack" then
      set ackPressed to true
      set anyButtonPressed to true
      call sendLine "ok=ack"
    else if key == "zero" then
      call readUvSensor
      set uvZeroVolts to sensorVolts
      call sendLine join "ok=zero;v=" call formatNumber uvZeroVolts
    else if key == "cal" then
      call calibrateToKnownUv parse to number value
    else if key == "demo" then
      set demoMode to value == 1
      call applyTimings
      call sendLine "ok=demo"
    else if key == "power" then
      if value == 0 and deviceOn then
        call deviceTurnsOff
      else if value == 1 and not deviceOn then
        call deviceTurnsOn
    else if key == "debug" then
      set debugMode to value == 1
      call sendLine "ok=debug"
    else if key == "ping" then
      set oledText to 0
      if oledPresent then
        set oledText to 1
    call sendLine join "pong;fw=" firmwareVersion ";oled=" oledText
  else if key == "read" then
    call sendStatus
  else if length of key > 0 then
    call sendLine "err=unknown"
```

handleCommand A step of the program · needs: command
Reads a command from the app or a laptop and acts on it: a new online UV value, done, calibrate the sensor, demo timings on or off, switch off or on, extra detail on or off, ping, or send the status now.
Used by: on bluetooth data received, on serial data received · **Uses:** readUvSensor, deviceTurnsOn, deviceTurnsOff, sendLine, sendStatus, calibrateToKnownUv, applyTimings, formatNumber, cleanText, debugLog


```
function calibrateToKnownUv knownUv
  call readUvSensor
  if knownUv > 0 and sensorVolts > uvZeroVolts then
    set uvVoltsPerIndex to sensorVolts - uvZeroVolts / knownUv
    call sendLine "ok=cal"
  else
    call sendLine "err=cal"
```

calibrateToKnownUv A step of the program · needs: knownUv
Corrects the sensor's scale. With the sensor in the sun, the app sends today's real UV index and the wearable adjusts its maths so it reads the same.
Used by: handleCommand · **Uses:** readUvSensor, sendLine

8 Helpers


10 blocks

Small jobs the other blocks share: the maths for each type of sensor, turning minutes into the milliseconds the program counts in, sorting numbers, and tidying up numbers, times and text.




applySensorPreset A step of the program
The maths for each type of UV sensor: which voltage means zero, and how many volts make one point of UV index.

Used by: on start




applyTimings A step of the program
Turns the minutes and hours from the settings into the milliseconds the program counts in. Demo timings are much shorter, so the whole flowchart can be shown in a few minutes.


Used by: handleCommand, on start




twoDigits Works out a piece of text · needs: n
Adds a leading zero: 7 becomes 07.
Used by: formatTime



debugLog A step of the program · needs: text
Extra detail lines for a laptop, sent only after the command debug=1.
Used by: readUvSensor, handleCommand



sortNumbers A step of the program · needs: list
Puts a list of numbers in order from smallest to largest. It is used to find the middle sensor reading.
Used by: readUvSensor




formatNumber Works out a piece of text · needs: n
Writes a number with one decimal place: 7.25 becomes 7.3.
Used by: showCheckSensor, showUvReading, sendStatus, handleCommand

8

Helpers (continued)


10 blocks

Small jobs the other blocks share: the maths for each type of sensor, turning minutes into the milliseconds the program counts in, sorting numbers, and tidying up numbers, times and text.




```
function formatTime ms
  set totalSeconds to floor max of 0 and ms / 1000
  set hours to floor totalSeconds / 3600
  set minutes to remainder of floor totalSeconds / 60 / 60
  set seconds to remainder of totalSeconds / 60
  if hours = 0 then
    set timeText to join minutes ":" call twoDigits seconds
  else
    set timeText to join hours "h" call twoDigits minutes
  return timeText
```

formatTime Works out a piece of text · needs: ms
Writes a time the way a clock would: 1:30, or 2h00.
Used by: alreadyProtected, wait5Minutes, reapplyCountdownText · **Uses:** twoDigits




```
function reapplyCountdownText
  if reapplyTimerRunning then
    set timeLeft3 to reapplyDueTime - running time ms
    set countdown to join " SPF " call formatTime timeLeft3
  return countdown
```

reapplyCountdownText Works out a piece of text
The short SPF 1h23 text for the bottom of the screen while the sunscreen timer is running.
Used by: wait5Minutes, showLedStatus · **Uses:** formatTime



```
function cleanText text
  set cleaned to text
  set lastCode to char code from cleaned at length of cleaned - 1
  while length of cleaned > 0 and call isBlank lastCode
    do
      set cleaned to substring of cleaned from 0 of length length of cleaned - 1
      set lastCode to char code from cleaned at length of cleaned - 1
  while length of cleaned > 0 and call isBlank char code from cleaned at 0
    do
      set cleaned to substring of cleaned from 1 of length length of cleaned - 1
  return cleaned
```

cleanText Works out a piece of text · needs: text
Removes stray spaces and line endings from a command before it is read.
Used by: handleCommand · **Uses:** isBlank



```
function isBlank code
  return code = 32 or code = 13 or code = 10
```

isBlank A yes-or-no question the program asks · needs: code
Asks: is this character a space or the end of a line?
Used by: cleanText

9 The optional screen

12 blocks

Only used if a small screen is added to the wearable. These blocks draw letters and numbers on it dot by dot. The device works exactly the same without a screen.

```
function setupOled
  set oledPresent to false
  if oledMode > 0 then
    call loadFont
    call buildNibbleTable
    call oledCommand 174
    set screenStatus to i2c read number at address oledAddress of format UInt8LE repeated false
    if oledMode = 2 or screenStatus = 64 then
      call oledInitCommands
      set oledPresent to true
      call oledClear
```

setupOled A step of the program
Looks for a screen on pins 19 and 20 and gets it ready. If there is no screen, everything else works the same.
Used by: on start · **Uses:** oledInitCommands, loadFont, buildNibbleTable, oledCommand, oledClear

```
function loadFont
  set hex to join hex "000000000000005f00000007000700147f147f14242a7f2a..."
  set hex to join hex "21c0014083e081408083e0808005030000008080808006..."
  set hex to join hex "2141454b311814127f1027454545393c4a49493001710905..."
  set hex to join hex "24100141414141400412214080201510906324979413e7e1..."
  set hex to join hex "7f090909013e4149497a7f0808087f00417f41002040413f..."
  set hex to join hex "1413e7f090909063e4151215e7f0919294646494931010..."
  set hex to join hex "07087008076151494543007f41410002040810200041417f..."
  set hex to join hex "444383844444420384444487f3854545418087e0901020c5..."
  set hex to join hex "00417f40007c041804787c0804047838444444387c141414..."
  set hex to join hex "0207c1c2040201c3c4030403c44281028440c5050503c446..."
  set hexDigits to "0123456789abcdef"
  set fontBytes to empty array
  for fontIndex from 0 to 474
    do
      set highDigit to hexDigits find index of char from hex at fontIndex x 2
      set lowDigit to hexDigits find index of char from hex at fontIndex x 2 + 1
      fontBytes add value highDigit x 16 + lowDigit to end
```

loadFont A step of the program
The shape of every letter, number and symbol, 5 dots wide by 7 tall, stored as text and unpacked when the device starts.
Used by: setupOled

```
function oledInitCommands
  call oledCommand 213
  call oledCommand 128
  call oledCommand 168
  call oledCommand 63
  call oledCommand 211
  call oledCommand 0
  call oledCommand 64
  if oledType = 2 then
    call oledCommand 173
    call oledCommand 139
  else
    call oledCommand 141
    call oledCommand 20
    call oledCommand 32
    call oledCommand 2
  call oledCommand 161
  call oledCommand 200
  call oledCommand 218
  call oledCommand 18
  call oledCommand 129
  call oledCommand 207
  call oledCommand 217
  call oledCommand 241
  call oledCommand 219
  call oledCommand 64
  call oledCommand 164
  call oledCommand 166
  call oledCommand 175
```

oledInitCommands A step of the program
The standard list of instructions that wakes up a 128 by 64 dot screen.
Used by: setupOled · **Uses:** oledCommand

```
function oledCommand command
  i2c write number
  at address oledAddress
  with value command
  of format UInt16BE
  repeated false
```

oledCommand A step of the program
· needs: command
Sends the screen one instruction.
Used by: setupOled, oledInitCommands, oledSetPosition

9 The optional screen (continued)

12 blocks

Only used if a small screen is added to the wearable. These blocks draw letters and numbers on it dot by dot. The device works exactly the same without a screen.

```
function buildNibbleTable
  set nibbleStretch to empty array
  for nibble from 0 to 15
    do
      set remaining to nibble
      set weight to 3
      repeat 4 times
        do
          if remainder of remaining / 2 = 1 then
            change stretched by weight
          set remaining to floor remaining / 2
          set weight to weight x 4
        nibbleStretch add value stretched to end
```

buildNibbleTable A step of the program

A lookup table for double-size letters: every dot is doubled sideways.

Used by: setupOled

```
function oledSetPosition page col
  set pixelColumn to col
  if oledType = 2 then
    change pixelColumn by 2
  call oledCommand 176 + page
  call oledCommand remainder of pixelColumn / 16
  call oledCommand 16 + floor pixelColumn / 16
```

oledSetPosition A step of the program · needs: page, col

Moves to a place on the screen: a row from 0 to 7 and a column from 0 to 127.

Used by: oledClear, oledWriteText, oledWriteBig · **Uses:** oledCommand

```
function oledWriteRow row text
  set rowText to text
  while length of rowText < 21
    do
      set rowText to join rowText " "
  call oledWriteText row 0 rowText
```

oledWriteRow A step of the program · needs: row, text

Writes a whole row, filling the rest with spaces so old text is wiped.

Used by: deviceTurnsOff, showUvReading, oledHeader, oledShowMessage, oledFooter · **Uses:** oledWriteText

```
function fontByte code column
  set safeCode to code
  if safeCode < 32 or safeCode > 126 then
    set safeCode to 63
  return fontBytes get value at safeCode - 32 x 5 + column
```

fontByte Works out a number · needs: code, column

One column of dots, out of five, of one character.

Used by: oledWriteText, oledWriteBig

```
function oledData byte1 byte2 byte3
  set packet to byte1 x 65536
  change packet by byte2 x 256
  change packet by byte3
  i2c write number
  at address oledAddress
  with value 1073741824 + packet
  of format UInt32BE
  repeated false
```

oledData A step of the program · needs: byte1,

byte2, byte3

Sends the screen three columns of dots.

Used by: oledClear, oledWriteText, oledWriteBig

```
function oledClear
  if oledPresent then
    for clearPage from 0 to 7
      do
        call oledSetPosition clearPage 0
        repeat 43 times
          do
            call oledData 0 0 0
```

oledClear A step of the program

Blanks the whole screen.

Used by: deviceTurnsOff, setupOled · **Uses:** oledData, oledSetPosition

9

The optional screen (continued)

12 blocks

Only used if a small screen is added to the wearable. These blocks draw letters and numbers on it dot by dot. The device works exactly the same without a screen.

functionoledWriteTextrowcoltext

ifoledPresentthen

set smallText to text

iflength of smallText > 21 - colthen

set smallText to substring of smallText from 0 of length 21 - col

call oledSetPositionrowcolx6

forcharIndex from 0 to length of smallText - 1

do

set charCode to char code from smallText at charIndex

call oledData

call fontBytecharCode0

call fontBytecharCode1

call fontBytecharCode2

call oledData

call fontBytecharCode3

call fontBytecharCode4

0

oledWriteText A step of the program · needs: row, col, text

Writes small text: up to 21 characters on each of 8 rows.

Used by: oledWriteRow · **Uses:** fontByte, oledData, oledSetPosition

Sunburn device · sheet 18 of 19 · section 9 of 9 · A3

9 The optional screen (continued)

12 blocks

Only used if a small screen is added to the wearable. These blocks draw letters and numbers on it dot by dot. The device works exactly the same without a screen.

```
function oledWriteBig row col text
  if oledPresent then
    set bigText to text
    if length of bigText > 10 then
      set bigText to substring of bigText from 0 of length 10
    for half from 0 to 1
      do
        call oledSetPosition row + half col x 6
        for bigCharIndex from 0 to length of bigText - 1
          do
            set bigCharCode to char code from bigText at bigCharIndex
            for columnIndex from 0 to 5
              do
                if columnIndex < 5 then
                  set glyphColumn to call fontByte bigCharCode columnIndex
                if half = 0 then
                  stretchedColumns add value nibbleStretch get value at remainder of glyphColumn / 16 to end
                else
                  stretchedColumns add value nibbleStretch get value at floor glyphColumn / 16 to end
            call oledData stretchedColumns get value at 0 stretchedColumns get value at 0 stretchedColumns get value at 1
            call oledData stretchedColumns get value at 1 stretchedColumns get value at 2 stretchedColumns get value at 2
            call oledData stretchedColumns get value at 3 stretchedColumns get value at 3 stretchedColumns get value at 4
            call oledData stretchedColumns get value at 4 stretchedColumns get value at 5 stretchedColumns get value at 5
```

oledWriteBig A step of the program · needs: row, col, text
Writes double-size text, two rows tall and up to 10 characters. It is used for the big UV number.
Used by: showUvReading · **Uses:** fontByte, oledData, oledSetPosition