```
#include <Arduino.h>

#include <WiFi.h>
#include <WiFiMulti.h>
#include <HTTPClient.h>

// PIN configuration
const int fsrPin = 34;        // Analog pin for FSR
(ensure it's an analog pin like GPIO 34, 35, 32, 33)
const int reedPin = 14;       // Digital pin for reed
switch

// Thresholds
const int fsrThreshold = 200; // Adjust this depending
on your FSR readings

WiFiMulti wifiMulti;

void setup() {
  Serial.begin(115200);
  while (!Serial) {
     // wait for serial port to connect. Needed for
native USB port only
     delay(500);
  }

  pinMode(reedPin, INPUT);
  // No need to define analog pin mode for fsrPin

  Serial.println("Connecting WIFI...");
    wifiMulti.addAP("RAMSO", "876543210");
    while ((wifiMulti.run() != WL_CONNECTED)) {
      delay(500);
```

```
    }
   Serial.println("WIFI Connected!");
}

void loop() {
  int fsrValue = analogRead(fsrPin);     // Soma
thamani ya FSR
  int reedState = digitalRead(reedPin);  // Soma reed
switch (LOW = closed)

  Serial.print("FSR Value: ");
   Serial.print(fsrValue);
  Serial.print(" | Reed: ");
  Serial.println(reedState == LOW ? "FUNGWA" :
"HAIJAFUNGWA");

  // Logic ya kuamua
  if (fsrValue > fsrThreshold) { // Kiti kimekaliwa
    if (reedState == HIGH) { // Mkanda HAUJAFUNGWA
      Serial.println("⚠ Abiria ameketi bila kufunga
mkanda!");
      sendData("P01", "0");
      // Hapa unaweza kuongeza vibration motor au LED
au buzzer
    } else {
      Serial.println("✅ Mkanda umefungwa vizuri.");
      sendData("P01", "1");
    }
  } else {
    Serial.println("🪑 Hakuna abiria kwenye kiti.");
    sendData("P01", "N/A");
  }
```

```
  delay(1000); // Subiri kidogo kabla ya kusoma tena
}

void sendData(String seatNo, String seatStatus){
  Serial.println("Sending Data for Seat No: " +
(String)seatNo + ", with Status: " +
(String)seatStatus);
  if ((wifiMulti.run() == WL_CONNECTED)) {
    HTTPClient http;
    String url = "http://172.18.8.56/recordSeatStatus.
php?seatNo=" + (String)seatNo + "&seatState=" +
(String)seatStatus;
    if (http.begin(url)) {
      // start connection and send HTTP header
      int httpCode = http.GET();
      // httpCode will be negative on error
      if (httpCode > 0) {
        // HTTP header has been send and Server
response header has been handled
        Serial.println("DATA IS SENT!");
        // file found at server
        if (httpCode == HTTP_CODE_OK) {
          String payload = http.getString();
          Serial.println(payload);
        }
      }
      http.end();
    } else {
      Serial.println("CONNECTION ERROR");
    }
  }else{
    Serial.println("WIFI DISCONNECTED");
  }
```

```
  delay(5000);
}
```