Basic Introduction
Accessing Documents
General Information
STREAM
DELTA PRO
DELTA 2
DELTA 2 MAX
Smart Home Panel
Smart Plug
PowerStream Micro-inverter
Wave Air Conditioner
Glacier
Power Kits
PowerOcean
DELTA Pro Ultra
DELTA Pro 3
Smart Home Panel II
River 2 Pro
Code package download
Support

ModuleType definition

Field	Field Type	Description

HTTP communication mode

Set & Get Quota

How to transfer request parameters using these two HTTP APIs.

PUT: /iot-open/sign/device/quota: SetCmdRequest

GET: /iot-open/sign/device/quota: GetCmdRequest, GetCmdResponse

Set Command	SetCmdRequest	GetCmdRequest	GetCmdResponse

RTC time update	<pre>{
	"sn": "SP10ZAW5ZE9E0052",
	"operateType": "TCP",
	"params": {
	"cmdSet": 11,
	"id": 3,
	"week": 2,
	"sec": 17,
	"min": 38,
	"hour": 18,
	"day": 16,
	"month": 11,
	"year": 2022
	}
	}</pre>
		<pre>{
		"sn": "SP10ZAW5ZE9E0052",
		"params": {
		"quotas": [
		"heartbeat.time"
		]
		}
		}</pre>	

Load channel control	<pre>{
	"sn": "SP10ZAW5ZE9E0052",
	"operateType": "TCP",
	"params": {
	"cmdSet": 11,
	"id": 16,
	"ch": 1,
	"ctrlMode": 1,</pre>
		<pre>{
		"sn": "SP10ZAW5ZE9E0052",
		"params": {
		"quotas": [
		"loadChInfo"
		]
		}
		}</pre>	

Set Command	SetCmdRequest	GetCmdRequest	GetCmdResponse
	<pre>"sta": 1 } }</pre>		

Standby channel control	<pre>{
	"sn": "SP10ZAW5ZE9E0052",
	"operateType": "TCP",
	"params": {
	"cmdSet": 11,
	"id": 17,
	"ch": 10,
	"ctrlMode": 1,
	"sta": 1
	}
	}</pre>		

Split-phase information configuration	<pre>{
	"sn": "SP10ZAW5ZE9E0052",
	"operateType": "TCP",
	"params": {
	"cmdSet": 11,
	"id": 18,
	"cfgList": [
	{
	"linkMark": 1,
	"linkCh": 0
	},
	{
	"linkMark": 0,
	"linkCh": 0
	},
	{
	"linkMark": 0,
	"linkCh": 0
	},
	{</pre>
		<pre>{
		"sn": "SP10ZAW5ZE9E0052",
		"params": {
		"quotas": [
		"splitPhaseInfo.cur",
		"splitPhaseInfo.cfgList",
		"splitPhaseInfo.cmdSet",
		"splitPhaseInfo.id"
		]
		}
		}</pre>
			<pre>{
			"code": "0",
			"message": "Success",
			"data": {
			"splitPhaseInfo.id": 19,
			"splitPhaseInfo.cmdSet": 11,
			"splitPhaseInfo.cfgList": [
			{
			"linkMark": 1,
			"linkCh": 0
			},
			{
			"linkMark": 0,
			"linkCh": 0
			},
			{
			"linkMark": 0,
			"linkCh": 0</pre>

Set Command	SetCmdRequest	GetCmdRequest	GetCmdResponse
	"linkMark": 0, "linkCh": 0 }, { "linkMark": 0, "linkCh": 0 }, { "linkMark": 0, "linkCh": 0 }, { "linkMark": 0, "linkCh": 0 }, { "linkMark": 0, "linkCh": 0 }, { "linkMark": 0, "linkCh": 0 }, { "linkMark": 0, "linkCh": 0 }] } }		}, { "linkMark": 0, "linkCh": 0 }, { "linkMark": 0, "linkCh": 0 }, { "linkMark": 0, "linkCh": 0 }, { "linkMark": 0, "linkCh": 0 }, { "linkMark": 0, "linkCh": 0 }, { "linkMark": 0, "linkCh": 0 }, { "linkMark": 0, "linkCh": 0 }] }, "eagleEyeTraceId": "", "tid": "" }
Channel current configuration (cur: 6, 13, 16, 20, 30)	{ "sn": "SP10ZAW5ZE9E0052", "operateType": "TCP", "params": {	{ "sn": "SP10ZAW5ZE9E0052", "params": { "quotas": [	{ "code": "0", "message": "Success", "data": {

Set Command	SetCmdRequest	GetCmdRequest	GetCmdResponse
	"cmdSet": 11, "id": 20, "chNum": 0, "cur": 6 } }	"loadChCurInfo.cur", "loadChCurInfo.cmdSet", "loadChCurInfo.id"] } }	"loadChCurInfo.cur": [6, 15, 20, 30, 20, 20, 20, 20, 20, 20, 16, 16], "loadChCurInfo.cmdSet": 11, "loadChCurInfo.id": 21 }, "eagleEyeTraceId": "", "tid": "" }
Grid power parameter configuration (gridVol: 220 230 240)	{ "sn": "SP10ZAW5ZE9E0052", "operateType": "TCP", "params": { "gridVol": 230, "gridFreq": 50, "cmdSet": 11, "id": 22 } }	{ "sn": "SP10ZAW5ZE9E0052", "params": { "quotas": ["gridInfo.gridVol", "gridInfo.gridFreq", "gridInfo.cmdSet", "gridInfo.id"] } }	{ "code": "0", "message": "Success", "data": { "gridInfo.cmdSet": 11, "gridInfo.gridFreq": 60, "gridInfo.gridVol": 120, "gridInfo.id": 23 }, "eagleEyeTraceId": "", "tid": "" }
EPS mode configuration (eps: 0:	{ "sn":	{ "sn":	{ "code":

Set Command	SetCmdRequest	GetCmdRequest	GetCmdResponse

off, 1: on)	"SP10ZAW5ZE9E0052",
	"operateType": "TCP",
	"params": {
	"cmdSet": 11,
	"id": 24,
	"eps": 1
	}
	}
		"SP10ZAW5ZE9E0052",
		"params": {
		"quotas": [
		"epsModeInfo.eps",
		"epsModeInfo.cmdSet",
		"epsModeInfo.id"
		]
		}
		}
			"0",
			"message": "Success",
			"data": {
			"epsModeInfo.cmdSet": 11,
			"epsModeInfo.id": 25,
			"epsModeInfo.eps": true
			},
			"eagleEyeTraceId": "",
			"tid": ""
			}

Channel enable status configuration (chNum: 0–9, isEnable, 0: off, 1: on)	{
	"sn": "SP10ZAW5ZE9E0052",
	"operateType": "TCP",
	"params": {
	"isEnable": 1,
	"chNum": 1,
	"cmdSet": 11,
	"id": 26
	}
	}
		{
		"sn": "SP10ZAW5ZE9E0052",
		"params": {
		"quotas": [
		"emergencyStrategy.chSta"
		]
		}
		}
			{
			"code": "0",
			"message": "Success",
			"data": {
			"emergencyStrategy.chSta": [
			{
			"priority": 0,
			"isEnable": 1
			},
			{
			"priority": 1,
			"isEnable": 1
			},
			{
			"priority": 2,
			"isEnable": 1
			},
			{
			"priority": 3,
			"isEnable": 1
			},
			{
			"priority": 4,

Set Command	SetCmdRequest	GetCmdRequest	GetCmdResponse

			"isEnable": 1
			},
			{
			"priority": 5,
			"isEnable": 1
			},
			{
			"priority": 6,
			"isEnable": 1
			},
			{
			"priority": 7,
			"isEnable": 1
			},
			{
			"priority": 8,
			"isEnable": 1
			},
			{
			"priority": 9,
			"isEnable": 1
			}
			]
			},
			"eagleEyeTraceId": "",
			"tid": ""
			}

Load channel information configuration(chNum 0~9)	{
	"sn": "SP10ZAW5ZE9E0052",
	"operateType": "TCP",
	"params": {
	"cmdSet": 11,
	"id": 32,
	"chNum": 1,
	"info": {
		{
		"sn": "SP10ZAW5ZE9E0052",
		"params": {
		"quotas": [
		"loadChInfo"
		]
		}
		}
			{
			"code": "0",
			"message": "Success",
			"data": {
			"loadChInfo": {
			"info": [
			{
			"iconNum": 0,

Set Command	SetCmdRequest	GetCmdRequest	GetCmdResponse
	<pre>"chName": "test", "iconInfo": 10 } } }</pre>		<pre>"chName": "test" }, { "iconNum": 27, "chName": "Line 2" }, { "iconNum": 27, "chName": "Line 3" }, { "iconNum": 27, "chName": "Line 4" }, { "iconNum": 0, "chName": "Line 5" }, { "iconNum": 27, "chName": "Line 6" }, { "iconNum": 27, "chName": "Line 7" }, { "iconNum": 27, "chName": "Line 8" }, { "iconNum": 27, "chName": "Line 9" }, { "iconNum": 27,</pre>

Set Command	SetCmdRequest	GetCmdRequest	GetCmdResponse
			"chName": "Line 10" }] } }, "eagleEyeTraceId": "", "tid": "" }

Region information configuration	{
	"sn": "SP10ZAW5ZE9E0052",
	"operateType": "TCP",
	"params": {
	"cmdSet": 11,
	"id": 34,
	"area": "US, China"
	}
	}
		{
		"sn": "SP10ZAW5ZE9E0052",
		"params": {
		"quotas": [
		"areaInfo.area",
		"areaInfo.cmdSet",
		"areaInfo.id"
		]
		}
		}
			{
			"code": "0",
			"message": "Success",
			"data": {
			"areaInfo.id": 35,
			"areaInfo.cmdSet": 11,
			"areaInfo.area": "United States,Alabama"
			},
			"eagleEyeTraceId": "",
			"tid": ""
			}

Setting the emergency mode	{
	"sn": "SP10ZAW5ZE9E0052",
	"operateType": "TCP",
	"params": {
	"cmdSet": 11,
	"id": 64,
	"isCfg": 1,
	"backupMode": 1,
	"overloadMode": 1,
	"chSta": [
	{
	"priority": 1,
	"isEnable":
		{
		"sn": "SP10ZAW5ZE9E0052",
		"params": {
		"quotas": [
		"emergencyStrategy.isCfg",
		"emergencyStrategy.backupMode",
		"emergencyStrategy.cmdSet",
		"emergencyStrategy.chSta",
		"emergencyStrategy.id",
		"emergencyStrategy.ove
			{
			"code": "0",
			"message": "Success",
			"data": {
			"emergencyStrategy.backupMode": 1,
			"emergencyStrategy.overloadMode": 1,
			"emergencyStrategy.chSta": [
			{
			"priority": 1,
			"isEnable": 1

Set Command	SetCmdRequest	GetCmdRequest	GetCmdResponse
	1 }, { "priority": 1, "isEnable": 1 }, { "priority": 2, "isEnable": 1 }, { "priority": 3, "isEnable": 1 }, { "priority": 4, "isEnable": 1 }, { "priority": 5, "isEnable": 1 }, { "priority": 6, "isEnable": 1 }, { "priority": 7, "isEnable": 1 }, { "priority": 8, "isEnable": 1 }, { "priority": 9, "isEnable":	rloadMode"] } }	}, { "priority": 1, "isEnable": 1 }, { "priority": 2, "isEnable": 1 }, { "priority": 3, "isEnable": 1 }, { "priority": 4, "isEnable": 1 }, { "priority": 5, "isEnable": 1 }, { "priority": 6, "isEnable": 1 }, { "priority": 7, "isEnable": 1 }, { "priority": 8, "isEnable": 1 }, { "priority": 9, "isEnable": 1

Set Command	SetCmdRequest	GetCmdRequest	GetCmdResponse
	1 }] } }		}], "emergencyStrategy.id": 65, "emergencyStrategy.isCfg": 1, "emergencyStrategy.cmdSet": 11 }, "eagleEyeTraceId": "", "tid": "" }

Setting the scheduled charging job	{
	"sn": "SP10ZAW5ZE9E0052",
	"operateType": "TCP",
	"params": {
	"cfg": {
	"param": {
	"lowBattery": 95,
	"chChargeWatt": 2000,
	"chSta": [
	1,
	0
	],
	"hightBattery": 100
	},
	"comCfg": {
	"timeScale": [
	255,
	255,
	255,
	255,
	255,
	255,
	255,
	255,
	255,
	255,
		{
		"sn": "SP10ZAW5ZE9E0052",
		"params": {
		"quotas": [
		"timeTask"
		]
		}
		}
			{
			"code": "0",
			"message": "Success",
			"data": {
			"timeTask": [
			{
			"cfg": {
			"param": {
			"lowBattery": 0,
			"chChargeWatt": 0,
			"chSta": [
			0,
			0,
			0,
			0,
			0,
			0,
			0,
			0,
			0,
			0
			],
			"hightBattery": 0
			},
			"comCfg": {
			"timeScale": [
			0,

Set Command	SetCmdRequest	GetCmdRequest	GetCmdResponse

	255,
	255,
	255,
	255,
	255,
	255,
	127
	],
	"isCfg": 1,
	"type": 1,
	"timeRange": {
	"isCfg": 1,
	"startTime": {
	"sec": 0,
	"min": 0,
	"week": 4,
	"hour": 0,
	"month": 1,
	"year": 2023,
	"day": 11
	},
	"timeMode": 0,
	"endTime": {
	"sec": 59,
	"min": 59,
	"week": 7,
	"hour": 23,
	"month": 1,
	"year": 2023,
	"day": 22
	},
	"mode1": {
	"thur": 0,
	"sat": 0,
	"wed": 0,
	"tues": 0,
	"fri": 0,
	"sun": 0,
	"mon": 0
	},
	"isEnable": 1
	},
			0,
			0,
			0,
			0,
			0,
			0,
			0,
			0,
			0,
			0,
			0,
			0,
			0,
			0,
			0
			],
			"isCfg": 0,
			"type": 0,
			"isEnable": 0,
			"setTime": {
			"sec": 0,
			"week": 0,
			"min": 0,
			"hour": 0,
			"month": 0,
			"year": 0,
			"day": 0
			},
			"timeRange": {
			"isCfg": 0,
			"timeMode": 0,
			"startTime": {
			"sec": 0,
			"week": 0,
			"min": 0,
			"hour": 0,
			"month": 0,
			"year": 0,
			"day": 0
			},
			"endTime":

Set Command	SetCmdRequest	GetCmdRequest	GetCmdResponse
	"isEnable": 1, "setTime": { "sec": 35, "min": 53, "week": 4, "hour": 15, "month": 1, "year": 2023, "day": 11 } } }, "cfgIndex": 1, "cmdSet": 11, "id": 81 } }		{ "sec": 59, "week": 0, "min": 59, "hour": 23, "month": 0, "year": 0, "day": 0 }, "isEnable": 0 } } }, "index": 16 }] }, "eagleEyeTraceId": "", "tid": "" }
Setting the scheduled discharging job	{ "sn": "SP10ZAW5ZE9E0052", "operateType": "TCP", "params": { "cfg": { "chSta": [1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1], "comCfg": { "timeScale": [1,	{ "sn": "SP10ZAW5ZE9E0052", "params": { "quotas": ["timeTask"] } }	

Set Command	SetCmdRequest	GetCmdRequest	GetCmdResponse


```
0,
0,
0,
0,
0,
0,
0,
0,
0,
0,
0,
0,
0,
0,
0,
0,
0,
0
],
"isCfg": 1,
"type": 2,
"timeRange": {
"isCfg": 1,
"timeMode": 0,
"startTime": {
"sec": 0,
"min": 0,
"week": 2,
"hour": 0,
"month": 10,
"year": 2022,
"day": 24
},
"endTime": {
"sec": 59,
"min": 59,
"week": 2,
"hour": 23,
"month": 10,
"year": 2022,
"day": 25
},
```

Set Command	SetCmdRequest	GetCmdRequest	GetCmdResponse

	"isEnable": 1
	},
	"isEnable": 1,
	"setTime": {
	"sec": 61,
	"min": 9,
	"week": 7,
	"hour": 16,
	"month": 11,
	"year": 2022,
	"day": 15
	}
	}
	},
	"cfgIndex": 0,
	"cmdSet": 11,
	"id": 82
	}
	}		

Setting the configuration status	{
	"sn": "SP10ZAW5ZE9E0052",
	"operateType": "TCP",
	"params": {
	"cmdSet": 11,
	"id": 7,
	"cfgSta": 1
	}
	}
		{
		"sn": "SP10ZAW5ZE9E0052",
		"params": {
		"quotas": [
		"cfgSta.sta",
		"cfgSta.cmdSet",
		"cfgSta.id"
		]
		}
		}
			{
			"code": "0",
			"message": "Success",
			"data": {
			"cfgSta.cmdSet": 11,
			"cfgSta.sta": 0,
			"cfgSta.id": 8
			},
			"eagleEyeTraceId": "",
			"tid": ""
			}

Getting the configuration status	{ "sn": "SP10ZAW5ZE9E0052", "operateType": "TCP",		

Set Command	SetCmdRequest	GetCmdRequest	GetCmdResponse

	"params": {
	"cmdSet": 11,
	"id": 8
	}
	}		

Start self-check information pushing	{
	"sn": "SP10ZAW5ZE9E0052",
	"operateType": "TCP",
	"params": {
	"cmdSet": 11,
	"id": 112,
	"selfCheckType": 1
	}
	}
		{
		"sn": "SP10ZAW5ZE9E0052",
		"params": {
		"quotas": [
		"selfCheck.flag",
		"selfCheck.cmsSet",
		"selfCheck.id"
		]
		}
		}
			{
			"code": "0",
			"message": "Success",
			"data": {
			"selfCheck.id": 113,
			"selfCheck.flag": 1
			},
			"eagleEyeTraceId": "",
			"tid": ""
			}

Pushing standby charging/discharging parameters	{
	"sn": "SP10ZAW5ZE9E0052",
	"operateType": "TCP",
	"params": {
	"cmdSet": 11,
	"id": 29,
	"forceChargeHigh": 0,
	"discLower": 0
	}
	}
		{
		"sn": "SP10ZAW5ZE9E0052",
		"params": {
		"quotas": [
		"backupChaDiscCfg.forceChargeHigh",
		"backupChaDiscCfg.discLower",
		"backupChaDiscCfg.cmdSet",
		"backupChaDiscCfg.id"
		]
		}
		}
			{
			"code": "0",
			"message": "Success",
			"data": {
			"backupChaDiscCfg.cmdSet": 11,
			"backupChaDiscCfg.discLower": 0,
			"backupChaDiscCfg.forceChargeHigh": 100,
			"backupChaDiscCfg.id": 30
			},
			"eagleEyeTraceId": "",
			"tid": ""
			}

GetAllQuotaResponse

heartbeat

Field	Field's Type	Description
workTime	long	Device work time /min
backupFullCap	int	Backup full capacity
backupBatPer	int	Backup battery percentage
gridDayWatth	float	Grid electricity consumption per day
backupDayWatth	float	Backup electricity consumption per day
backupChaTime	int	Backup discharge time
gridSta	int	Grid electricity status0 off, 1 on

heartbeat.time

Field	Field's Type	Description
year	int	Year
month	int	Month
day	int	Day
hour	int	Hour
min	int	Minute
sec	int	Second
week	int	Week

heartbeat.loadCmdChCtrlInfos

Field	Field's Type	Description
powCh	int	Channel number 0~9
ctrlSta	short	Power supply type0 Grid supply, 1 storage power supply, 2 close
ctrlMode	short	Contol mode0 Auto, 1 Manual
priority	short	Channel priority

heartbeat.backupCmdChCtrlInfos

Field	Field's Type	Description
pwoCh	int	Channel number 10~11
ctrlSta	short	Power supply type0 Grid supply, 1 storage power supply, 2 close
ctrlMode	short	Contol mode0 Auto, 1 Manual
priority	short	Channel priority

splitPhaseInfo

Field	Field's Type	Description
cfgList	CfgInfo[10]	Split phase info listcfgList.length must be 10

CfgInfo

Field	Field's Type	Description
linkMark	short	0 Not be split1 Should be split
linkCh	int	Spilt channel number

loadChCurInfo

Field	Field's Type	Description
cur	int[10]	Channel currentcur[0] represent channel1's current

gridInfo

Field	Field's Type	Description
gridVol	int	Grid voltageRange: 100 ~ 250
gridFreq	int	Grid FrequencyRange: 50 ~ 60

epsModeInfo

Field	Field's Type	Description
eps	bool	EPS mode status0 off, 1 on

chUseInfo

Field	Field's Type	Description
isEnable	bool[]	Channel use or notisEnable[0]=false, represent channel1 off

loadChInfo

Field	Field's Type	Description
chName	string	Channel nick name
iconNum	int	Channel icon number

timeTask

Field	Field's Type	Description
index	int	Task index
cfg	CfgInfo	Task config info

CfgInfo

Field	Field's Type	Description
param	param	Parameter
comCfg	ComCfg	Job configuration

param

Field	Field's Type	Description
hightBattery	int	Charge high power percentage
lowBattery	int	Charge low power percentage
chChargeWatt	int	Channel charge power
chSta	int[]	Channel status0 off, 1 on

ComCfg

Field	Field's Type	Description
timeScale	int[]	Time scale
isCfg	short	Config or not0 No, 1 Yes

Field	Field's Type	Description
type	short	Power type1 charge, 2 discharge
isEnable	short	Config enable or not0 No, 1 Yes
setTime	TimeInfo	Setting time
timeRange	TimeRangeInfo	Strategy effective time range

TimeRangeInfo

Field	Field's Type	Description
isCfg	short	Config or not0 No, 1 Yes
isEnable	short	Config enable or not0 No, 1 Yes
timeMode	short	Time mode0 every day, 1 every week, 2 every month, 3 year month day
startTime	TimeInfo	Start time
endTime	TimeInfo	End time
model	——	timeMode = 0 "model": { "data": 12212121212122 }timeMode = 1 "model" : { "mon":1, "tues":1, "wed":1, "thur":1, "fri": 1, "sat": 1, "sun": 1, } timeMode = 2 "model": [1,2,3,4,5,6] timeMode = 3 "model":{ "day":1, "month":4, "year":2022 }

TimeInfo

Field	Field's Type	Description
year	int	Year
month	int	Month
day	int	Day
hour	int	Hour
min	int	Minute
sec	int	Second
week	int	Week

cfgSta

Field	Field's Type	Description
sta	int	Config or not 0 No, 1 Yes

backupChaDiscCfg

Field	Field's Type	Description
forceChargeHigh	int	Charge upper threshold percentage
discLower	int	Discharge lower threshold percentage

MQTT communication mode

Set & Set Reply

Usage of Topic	Topic	From	To
Set device function	/open/${certificateAccount}/${sn}/set	app	device
Reply to the set result	/open/${certificateAccount}/${sn}/set_reply	device	app

Full Format Example

Set Data Format

```
{
    "id": 123456789,
    "moduleType": 1,
    "operateType": "TCP",
    "version": "1.0",
    "sn": "SP10ZAW5ZE9E0052",
    "params": {
        "cmdSet": 11,
        "id": 16,
        "ch": 1,
        "ctrlMode": 1,
        "sta": 1
    }
}
```

Set Reply Data Format

```
{
    "id": 123,
    "version": "1.0",
    "moduleType": 1,
    "time": 2557051,
    "code": 0,
    "operateType": "standbyTime",
    "data": {
        "ack": 0
    }
}
```

ParamInfo Message Format

Set Command	SetTopic's ParamInfo	SetReplyTopic's ParamInfo

RTC time update	<pre>{
	"id": 123456789,
	"moduleType": 1,
	"operateType": "TCP",
	"version": "1.0",
	"sn": "SP10ZAW5ZE9E0052",
	"params": {
	"cmdSet": 11,
	"id": 3,
	"week": 2,
	"sec": 17,
	"min": 38,
	"hour": 18,
	"day": 16,
	"month": 11,
	"year": 2022
	}
	}</pre>
		<pre>{
		"version": "1.0",
		"cmdId": 0,
		"cmdFunc": 0,
		"id": 438661101,
		"addr": 0,
		"timestamp": 1711452104016,
		"operateType": "TCP",
		"params": {
		"ack": 0,
		"cmdSet": 11,
		"id": 3
		}
		}</pre>

Load channel control	<pre>{
	"id": 123456789,
	"moduleType": 1,
	"operateType": "TCP",
	"version": "1.0",
	"sn": "SP10ZAW5ZE9E0052",
	"params": {
	"cmdSet": 11,
	"id": 16,
	"ch": 1,
	"ctrlMode": 1,
	"sta": 1
	}
	}</pre>
		<pre>{
		"version": "1.0",
		"cmdId": 0,
		"cmdFunc": 0,
		"id": 123456789,
		"addr": 0,
		"timestamp": 1711452160038,
		"operateType": "TCP",
		"params": {
		"sta": 0,
		"ack": 0,
		"cmdSet": 11,
		"id": 16
		}
		}</pre>

Standby channel control	<pre>{
	"id": 123456789,
	"moduleType": 1,
	"operateType": "TCP",
	"version": "1.0",
	"sn": "SP10ZAW5ZE9E0052",
	"params": {
	"cmdSet": 11,
	"id": 17,
	"ch": 10,
	"ctrlMode": 1,
	"sta": 1
	}
	}</pre>
		<pre>{
		"id": 123456789,
		"moduleType": 1,
		"operateType": "TCP",
		"version": "1.0",
		"sn": "SP10ZAW5ZE9E0052",
		"params": {
		"cmdSet": 11,
		"id": 17,
		"ch": 10,
		"ctrlMode": 1,
		"sta": 1
		}
		}</pre>

Set Command	SetTopic's ParamInfo	SetReplyTopic's ParamInfo

Split-phase information configuration	<pre>{
	"id": 123456789,
	"moduleType": 1,
	"operateType": "TCP",
	"version": "1.0",
	"sn": "SP10ZAW5ZE9E0052",
	"params": {
	"cmdSet": 11,
	"id": 18,
	"cfgList": [
	{
	"linkMark": 1,
	"linkCh": 0
	},
	{
	"linkMark": 0,
	"linkCh": 0
	},
	{
	"linkMark": 0,
	"linkCh": 0
	},
	{
	"linkMark": 0,
	"linkCh": 0
	},
	{
	"linkMark": 0,
	"linkCh": 0
	},
	{
	"linkMark": 0,
	"linkCh": 0
	},
	{
	"linkMark": 0,
	"linkCh": 0
	},
	{
	"linkMark": 0,
	"linkCh": 0
	}
	]
	}
	}</pre>
		<pre>{
		"version": "1.0",
		"cmdId": 0,
		"cmdFunc": 0,
		"id": 123456789,
		"addr": 0,
		"timestamp": 1711452195163,
		"operateType": "TCP",
		"params": {
		"sta": 0,
		"ack": 0,
		"cmdSet": 11,
		"id": 18
		}
		}</pre>

Set Command	SetTopic's ParamInfo	SetReplyTopic's ParamInfo

Channel current configuration (cur: 6, 13, 16, 20, 30)	<pre>{
	"id": 123456789,
	"moduleType": 1,
	"operateType": "TCP",
	"version": "1.0",
	"sn": "SP10ZAW5ZE9E0052",
	"params": {
	"cmdSet": 11,
	"id": 20,
	"chNum": 0,
	"cur": 6
	}
	}</pre>
		<pre>{
		"version": "1.0",
		"cmdId": 0,
		"cmdFunc": 0,
		"id": 123456789,
		"addr": 0,
		"timestamp": 1711452228967,
		"operateType": "TCP",
		"params": {
		"sta": 0,
		"ack": 0,
		"cmdSet": 11,
		"id": 20
		}
		}</pre>

Grid power parameter configuration (gridVol: 220 230 240)	<pre>{
	"id": 123456789,
	"moduleType": 1,
	"operateType": "TCP",
	"version": "1.0",
	"sn": "SP10ZAW5ZE9E0052",
	"params": {
	"gridVol": 230,
	"gridFreq": 50,
	"cmdSet": 11,
	"id": 22
	}
	}</pre>
		<pre>{
		"version": "1.0",
		"cmdId": 0,
		"cmdFunc": 0,
		"id": 123456789,
		"addr": 0,
		"timestamp": 1711452256182,
		"operateType": "TCP",
		"params": {
		"sta": 0,
		"reconGridFreq": 5632,
		"ack": 0,
		"cmdSet": 11,
		"id": 22,
		"reconGridVol": 0
		}
		}</pre>

EPS mode configuration (eps: 0: off, 1: on)	<pre>{
	"id": 123456789,
	"moduleType": 1,
	"operateType": "TCP",
	"version": "1.0",
	"sn": "SP10ZAW5ZE9E0052",
	"params": {
	"cmdSet": 11,
	"id": 24,
	"eps": 0
	}
	}</pre>
		<pre>{
		"version": "1.0",
		"cmdId": 0,
		"cmdFunc": 0,
		"id": 123456789,
		"addr": 0,
		"timestamp": 1711452767766,
		"operateType": "TCP",
		"params": {
		"sta": 0,
		"ack": 0,
		"cmdSet": 11,
		"id": 24
		}
		}</pre>

Set Command	SetTopic's ParamInfo	SetReplyTopic's ParamInfo

Channel enable status configuration (chNum: 0–9, isEnable, 0: off, 1: on)	<pre>{
	    "id": 123456789,
	    "moduleType": 1,
	    "operateType": "TCP",
	    "version": "1.0",
	    "sn": "SP10ZAW5ZE9E0052",
	    "params": {
	        "isEnable": 1,
	        "chNum": 1,
	        "cmdSet": 11,
	        "id": 26
	    }
	}</pre>
		<pre>{
		    "version": "1.0",
		    "cmdId": 0,
		    "cmdFunc": 0,
		    "id": 123456789,
		    "addr": 0,
		    "timestamp": 1711452787483,
		    "operateType": "TCP",
		    "params": {
		        "sta": 0,
		        "chNum": 1,
		        "ack": 0,
		        "cmdSet": 11,
		        "id": 26
		    }
		}</pre>

Load channel information configuration (chNum 0~9)	<pre>{
	    "id": 123456789,
	    "moduleType": 1,
	    "operateType": "TCP",
	    "version": "1.0",
	    "sn": "SP10ZAW5ZE9E0052",
	    "params": {
	        "chNum": 1,
	        "cmdSet": 11,
	        "id": 32,
	        "info": {
	            "iconInfo": 10,
	            "chName": "test223111"
	        }
	    }
	}</pre>
		<pre>{
		    "version": "1.0",
		    "cmdId": 0,
		    "cmdFunc": 0,
		    "id": 123456789,
		    "addr": 0,
		    "timestamp": 1711452805878,
		    "operateType": "TCP",
		    "params": {
		        "sta": 0,
		        "chNum": 1,
		        "ack": 0,
		        "cmdSet": 11,
		        "id": 32
		    }
		}</pre>

Region information configuration	<pre>{
	    "id": 123456789,
	    "moduleType": 1,
	    "operateType": "TCP",
	    "version": "1.0",
	    "sn": "SP10ZAW5ZE9E0052",
	    "params": {
	        "cmdSet": 11,
	        "id": 34,
	        "area": "US, China 1"
	    }
	}</pre>
		<pre>{
		    "version": "1.0",
		    "cmdId": 0,
		    "cmdFunc": 0,
		    "id": 123456789,
		    "addr": 0,
		    "timestamp": 1711452043883,
		    "operateType": "TCP",
		    "params": {
		        "sta": 0,
		        "ack": 0,
		        "cmdSet": 11,
		        "id": 34
		    }
		}</pre>

Set Command	SetTopic's ParamInfo	SetReplyTopic's ParamInfo

Setting the emergency mode	<pre>{
	"id": 123456789,
	"moduleType": 1,
	"operateType": "TCP",
	"version": "1.0",
	"sn": "SP10ZAW5ZE9E0052",
	"params": {
	"cmdSet": 11,
	"id": 64,
	"isCfg": 1,
	"backupMode": 1,
	"overloadMode": 1,
	"chSta": [
	{
	"priority": 1,
	"isEnable": 1
	},
	{
	"priority": 1,
	"isEnable": 1
	},
	{
	"priority": 2,
	"isEnable": 1
	},
	{
	"priority": 3,
	"isEnable": 1
	},
	{
	"priority": 4,
	"isEnable": 1
	},
	{
	"priority": 5,
	"isEnable": 1
	},
	{
	"priority": 6,
	"isEnable": 1
	},
	{
	"priority": 7,
	"isEnable": 1
	},
	{
	"priority": 8,
	"isEnable": 1
	},
	{
	"priority": 9,
	"isEnable": 1
	}
	]</pre>
		<pre>{
		"version": "1.0",
		"cmdId": 0,
		"cmdFunc": 0,
		"id": 123456789,
		"addr": 0,
		"timestamp": 1711452841815,
		"operateType": "TCP",
		"params": {
		"sta": 0,
		"ack": 0,
		"cmdSet": 11,
		"id": 64
		}
		}</pre>

Set Command	SetTopic's ParamInfo	SetReplyTopic's ParamInfo
	<pre> } }</pre>	

Reset	<pre>{
	    "id": 123456789,
	    "moduleType": 1,
	    "operateType": "TCP",
	    "version": "1.0",
	    "sn": "SP10ZAW5ZE9E0052",
	    "params": {
	        "cmdSet": 1,
	        "id": 20
	    }
	}</pre>
		<pre>{
		    "version": "1.0",
		    "cmdId": 0,
		    "cmdFunc": 0,
		    "id": 123456789,
		    "addr": 0,
		    "timestamp": 1711452878830,
		    "operateType": "TCP",
		    "params": {
		        "ack": 0,
		        "cmdSet": 1,
		        "id": 20
		    }
		}</pre>

Setting the scheduled charging job	<pre>{
	    "id": 123456789,
	    "moduleType": 1,
	    "operateType": "TCP",
	    "version": "1.0",
	    "sn": "SP10ZAW5ZE9E0052",
	    "params": {
	        "cfg": {
	"param": {
	"lowBattery": 95,
	"chChargeWatt": 2000,
	"chSta": [
	1,
	0
	],
	"hightBattery": 100
	},
	"comCfg": {
	"timeScale": [
	255,
	255,
	255,
	255,
	255,
	255,
	255,
	255,
	255,</pre>
		<pre>{
		    "version": "1.0",
		    "cmdId": 0,
		    "cmdFunc": 0,
		    "id": 123456789,
		    "addr": 0,
		    "timestamp": 1711452905589,
		    "operateType": "TCP",
		    "params": {
		        "sta": 0,
		"cfgIndex": 1,
		        "ack": 0,
		        "cmdSet": 11,
		        "id": 81
		    }
		}</pre>

Set Command	SetTopic's ParamInfo	SetReplyTopic's ParamInfo


```
255,
255,
255,
255,
255,
255,
255,
255,
127
                ],
"isCfg": 1,
"type": 1,
"timeRange": {
"isCfg": 1,
"startTime": {
"sec": 0,
"min": 0,
"week": 4,
"hour": 0,
"month": 1,
"year": 2023,
"day": 11
},
"timeMode": 0,
"endTime": {
"sec": 59,
"min": 59,
"week": 7,
"hour": 23,
"month": 1,
"year": 2023,
"day": 22
},
"mode1": {
"thur": 0,
"sat": 0,
"wed": 0,
"tues": 0,
"fri": 0,
"sun": 0,
"mon": 0
},
"isEnable": 1
                },
"isEnable": 1,
"setTime": {
```

Set Command	SetTopic's ParamInfo	SetReplyTopic's ParamInfo
	"sec": 35, "min": 53, "week": 4, "hour": 15, "month": 1, "year": 2023, "day": 11 } } }, "cfgIndex": 1, "cmdSet": 11, "id": 81 } }	

Setting the scheduled discharging job	{
	"id": 123456789,
	"moduleType": 1,
	"operateType": "TCP",
	"version": "1.0",
	"sn": "SP10ZAW5ZE9E0052",
	"params": {
	"cfg": {
	"chSta": [
	1,
	1,
	1,
	1,
	1,
	1,
	1,
	1,
	1,
	1
	],
	"comCfg": {
	"timeScale": [
	1,
	0,
	0,
	0,
	0,
	0,
	0,
	0,
	0,
	0,
	0,
	0,
		{
		"version": "1.0",
		"cmdId": 0,
		"cmdFunc": 0,
		"id": 123456789,
		"addr": 0,
		"timestamp": 1711452933095,
		"operateType": "TCP",
		"params": {
		"sta": 0,
		"cfgIndex": 0,
		"ack": 0,
		"cmdSet": 11,
		"id": 82
		}
		}

Set Command	SetTopic's ParamInfo	SetReplyTopic's ParamInfo


```
0,
0,
0,
0,
0
                ],
"isCfg": 1,
"type": 2,
"timeRange": {
"isCfg": 1,
"timeMode": 0,
"startTime": {
"sec": 0,
"min": 0,
"week": 2,
"hour": 0,
"month": 10,
"year": 2022,
"day": 24
},
"endTime": {
"sec": 59,
"min": 59,
"week": 2,
"hour": 23,
"month": 10,
"year": 2022,
"day": 25
},
"isEnable": 1
                },
"isEnable": 1,
"setTime": {
"sec": 61,
"min": 9,
"week": 7,
"hour": 16,
"month": 11,
"year": 2022,
"day": 15
                }
            }
        },
        "cfgIndex":
0,
        "cmdSet":
11,
        "id": 82
    }
}
```

Set Command	SetTopic's ParamInfo	SetReplyTopic's ParamInfo

Setting the configuration status	<pre>{
	"id": 123456789,
	"moduleType": 1,
	"operateType": "TCP",
	"version": "1.0",
	"sn": "SP10ZAW5ZE9E0052",
	"params": {
	"cmdSet": 11,
	"id": 7,
	"cfgSta": 1
	}
	}</pre>
		<pre>{
		"version": "1.0",
		"cmdId": 0,
		"cmdFunc": 0,
		"id": 123456789,
		"addr": 0,
		"timestamp": 1711452958649,
		"operateType": "TCP",
		"params": {
		"sta": 0,
		"ack": 0,
		"cmdSet": 11,
		"id": 7
		}
		}</pre>

Getting the configuration status	<pre>{
	"id": 123456789,
	"moduleType": 1,
	"operateType": "TCP",
	"version": "1.0",
	"sn": "SP10ZAW5ZE9E0052",
	"params": {
	"cmdSet": 11,
	"id": 8
	}
	}</pre>
		<pre>{
		"version": "1.0",
		"cmdId": 0,
		"cmdFunc": 0,
		"id": 123456789,
		"addr": 0,
		"timestamp": 1711452958649,
		"operateType": "TCP",
		"params": {
		"sta": 0,
		"ack": 0,
		"cmdSet": 11,
		"id": 7
		}
		}</pre>

Start self-check information pushing	<pre>{
	"id": 123456789,
	"moduleType": 1,
	"operateType": "TCP",
	"version": "1.0",
	"sn": "SP10ZAW5ZE9E0052",
	"params": {
	"cmdSet": 11,
	"id": 112,
	"selfCheckType": 1
	}
	}</pre>
		<pre>{
		"version": "1.0",
		"cmdId": 0,
		"cmdFunc": 0,
		"id": 123456789,
		"addr": 0,
		"timestamp": 1711453003786,
		"operateType": "TCP",
		"params": {
		"ack": 0,
		"result": 0,
		"cmdSet": 11,
		"id": 112
		}
		}</pre>

Set Command	SetTopic's ParamInfo	SetReplyTopic's ParamInfo

Pushing standby charging/discharging parameters	<pre>{
	"id": 123456789,
	"moduleType": 1,
	"operateType": "TCP",
	"version": "1.0",
	"sn": "SP10ZAW5ZE9E0052",
	"params": {
	"cmdSet": 11,
	"id": 29,
	"forceChargeHigh": 60,
	"discLower": 30
	}
	}</pre>
		<pre>{
		"version": "1.0",
		"cmdId": 0,
		"cmdFunc": 0,
		"id": 123456789,
		"addr": 0,
		"timestamp": 1711453031712,
		"operateType": "TCP",
		"params": {
		"sta": 0,
		"ack": 0,
		"cmdSet": 11,
		"id": 29
		}
		}</pre>

Report Device Quota

Usage of Topic	Topic	From	To
Report device quota	/open/${certificateAccount}/${sn}/quota	device	app

Please see HTTP GetAllQuotaResponse and Set & Set Reply for the fields definition.

Example

<pre>{
"id": 1479773,
"version": "1.0",
"time": 871405684,
"moduleType": 1,
"needAck": 1,
"typeCode": "pdStatus",
"params": {
"fsmState": 5,
"iceMkMode": 1,
"flagTwoZone": 1,
"tmpR": 845,
"tmpL": -85,
"tmpAver": 335,
"iceTm": 0,
"iceTmTag": 0,
"err": 0,
"doorStat": 0,
"icePercent": 0,
"batFlag": 0,
...
}
}</pre>

Report Device status

Usage of Topic	Topic	From	To
Report Device status	/open/${certificateAccount}/${sn}/status	device	app

Message Format

```
{
    "id": "123456789",
    "version": "1.0",
    "timestamp": 1634841971000,
    "params": {
        "status": 0
    }
}
```

Field

Field	Field Type	Description
status	int	Device online or not0: No, 1: Yes

Was this page helpful?

YES NO

Was this page helpful?

We'd like to hear from you.Click here to give your feedback or suggestions.