AMRITA SCHOOL OF COMPUTING

Coimbatore

AI and Robotics

Case Study Report / Review 2

Pi Swarm

Vision-Guided Robot Navigation with Background Edge Computing

SUBMITTED BY

Team member	Roll number
Kapil Kannaa G	CB.SC.U4CSE23036
Mitali Patle	CB.SC.U4CSE23038
Kavinraj S	CB.SC.U4CSE23329
Gudi Hemanth	CB.SC.U4CSE23619
D. Uday Kumar	CB.SC.U4CSE23655

Course: AI and Robotics
Guide: Dr. A. Baskar
Department: Computer Science & Engineering
Institution: Amrita School of Computing, Coimbatore

PROJECT REPOSITORY

https://github.com/Kapilkannaa/pi-swarm-robotics

Acknowledgement

The team thanks Dr. A. Baskar for guidance during the AI and Robotics semester project, and the Department of Computer Science & Engineering, Amrita School of Computing, Coimbatore, for academic and laboratory support. The technical references and open-source libraries used in the implementation are credited in this report and the repository.

Abstract

Pi Swarm uses an overhead camera to guide low-cost robots that have no onboard navigation sensors. A laptop detects a printed marker, maps the operator's clicked destination into floor coordinates, and sends wheel commands directly to an ESP8266 controller. Motion is divided into short bursts so that the controller can wait for delayed images and update its speed and turning estimates from observed movement. A Raspberry Pi worker evaluates alternative burst settings through Monte Carlo trajectory simulations, returning advice without blocking the camera or motor-control loop.

The evaluation compares continuous and burst control, examines online adaptation, and checks communication and firmware logic. In ten seeded trials with a 0.3 s camera delay, continuous control completed none of the simulated tasks, while burst control completed all ten. The software suite passed 181 tests. These results describe the submitted software and simulator; historical board records and team-reported operation are discussed separately. The work demonstrates a practical division of vision, adaptive control, embedded actuation and background computation for an educational robotics system.

Keywords: vision-guided robotics; ESP8266; Raspberry Pi; ArUco; adaptive control; edge offloading; Monte Carlo simulation.

Evaluation scope

This final submission includes the implementation, reproducible simulation results and recorded bench evidence. The robots were dismantled before the final documentation stage, so no additional physical trials or hardware video were recorded. The accompanying demonstration video is generated from the simulator.

Contents

1 Introduction and Problem Definition **1**
1.1 Background and Overview . . . 1
1.2 Problem Statement . . . 1
1.3 Need for the Proposed Solution . . . 1
1.4 Objectives . . . 1
1.5 Scope and Application . . . 1
1.6 Existing System and Its Limitations . . . 2

2 Proposed System and Design **3**
2.1 Proposed Solution . . . 3
2.2 System Requirements . . . 3
2.3 System Architecture . . . 3
2.4 Block Diagram . . . 4
2.5 System Workflow . . . 4
2.6 Functional and Non-Functional Requirements . . . 4

3 AI and Robotics Methodology **5**
3.1 AI/ML Technique and Algorithm . . . 5
3.2 Dataset / Input Data . . . 5
3.3 Data Preprocessing and Model Development . . . 5
3.4 Robotics Components . . . 6
3.5 AI and Robotics Integration . . . 7
3.6 Algorithm and Flowchart . . . 7

4 Implementation, Testing and Results **8**
4.1 Hardware Implementation . . . 8
4.2 Software Implementation . . . 8
4.3 Working Model / Prototype . . . 8
4.4 Testing and Validation . . . 8
4.5 Performance Evaluation . . . 9
4.6 Results and Discussion . . . 10
4.7 Screenshots / Prototype Photographs . . . 10

5 Conclusion and Future Scope **11**
5.1 Summary of the Work . . . 11
5.2 Achievement of Objectives . . . 11
5.3 Limitations . . . 11
5.4 Future Enhancements . . . 11
5.5 Real-World Deployment Possibilities . . . 12
5.6 Learning Outcomes . . . 12
5.7 References . . . 12
5.8 Appendix . . . 13

1. Introduction and Problem Definition

1.1 Background and Overview

An inexpensive mobile robot can move reliably under direct commands while still being unable to determine where it is. The available platforms consist of WEMOS D1 Mini-class ESP8266 controllers, L298N motor drivers, and differential-drive chassis. They contain no onboard range or position sensors. The project therefore uses an overhead camera as an external observation source and concentrates on the integration of vision, feedback, communication, and computation.

Two robot platforms are available to the team. The principal physical workflow is operator-assisted click-to-go: a phone looks down at the robot, the laptop displays the video, the operator selects a destination, and the robot moves toward that point. The wider codebase also includes cooperative search and target convergence in simulation. These are related evaluation capabilities, not evidence that a two-robot physical swarm demonstration has been completed.

1.2 Problem Statement

The engineering problem is to guide a sensorless differential-drive robot toward a selected floor location using delayed camera observations, while retaining responsive stop behavior and making useful use of a Raspberry Pi. The Pi must add compute capacity without becoming a mandatory relay between camera, controller, and motors. A delayed background job must never delay a stop command.

1.3 Need for the Proposed Solution

Open-loop driving accumulates errors from wheel mismatch, floor friction, battery condition, and uncertain command timing. Camera feedback can correct those errors, but a controller acting continuously on old images can overshoot. A stop-and-measure strategy is appropriate when camera latency is substantial. Background simulation also allows alternative control settings to be examined without consuming the laptop's time-sensitive vision/control thread.

1.4 Objectives

1. Estimate robot location from an overhead phone stream or laptop webcam.
2. Preserve the operator's click-to-go interface and direct laptop-to-robot UDP path.
3. Adapt motion estimates from observed displacement and heading changes.
4. Offload bounded trajectory-profile evaluation to a Raspberry Pi worker.
5. Enforce firmware and controller stop conditions and make failure behavior explicit.
6. Deliver source, configuration examples, test evidence, and an academic report that another team member can reproduce.

1.5 Scope and Application

The scope is a supervised indoor arena with a flat floor, controlled lighting, and a camera covering the intended motion area. The implementation supports printed ArUco markers and a single-robot red-LED tracking alternative. The Pi evaluates compact state snapshots; raw camera video is not routed through it. Suitable applications are classroom robotics demonstrations, experiments in delayed feedback, and small-scale distributed-compute studies.

This is not an obstacle-aware production robot. There is no ultrasonic, infrared, encoder, or onboard camera sensing. The robot must not be assumed to detect people, furniture, drop-offs, or arbitrary obstacles. Offload estimates use assumed physics and are advisory rather than certified safety predictions.

1.6 Existing System and Its Limitations

The earlier build provided laptop-side LED click-to-go and a camera-based swarm simulator. A later integration placed the Pi in the command path. That arrangement demonstrated real Pi computation but made Pi connectivity a prerequisite for the new live path. The revised design restores direct laptop control and isolates the Pi as a background worker. Table 1 identifies the differences.

Property	Open-loop commands	Earlier Pi coordinator	Revised project
Feedback	None	External camera	External camera
Motor sender	Laptop/tool	Pi	Laptop
Pi contribution	None	Inference and control	Background rollouts
Pi unavailable	Not applicable	Command path interrupted	Local control remains available
Main limitation	Accumulated drift	Extra critical dependency	External vision and assumed models

Table 1: Architectural comparison. Availability does not imply safe motion without a fresh camera observation.

2. Proposed System and Design

2.1 Proposed Solution

The laptop is responsible for decoding the phone stream, estimating robot pose, accepting a click, and generating motion commands. Its controller advances in short bursts and waits for delayed imagery to catch up. The Pi independently evaluates three candidate burst profiles under randomized speed, wheel gain, camera delay, and packet-loss assumptions. The laptop displays and logs the returned comparison. It does not automatically apply the recommendation to moving hardware.

The offload client keeps only the newest requested goal. It rejects a result that belongs to a cancelled or superseded goal. If authentication fails, the Pi is busy, or a connection times out, the worker state becomes unavailable while local camera/control continues. This separation is the central design decision.

2.2 System Requirements

Hardware requirements

Component	Role and constraints
Two ESP8266 robot platforms	D1 Mini-class controller, L298N, two drive motors and caster. Each uses its own firmware ID and direction flags.
Raspberry Pi Zero W	Background compute worker, using standard-library Python. It is not expected to outperform a modern laptop.
Phone or laptop camera	External visual sensing; overhead orientation and sufficient marker/LED visibility are required.
Laptop	Vision processing, interface, adaptive control, and direct UDP sender.
Wi-Fi network	Common 2.4 GHz network with device-to-device traffic. ESP8266 is a 2.4 GHz device [4].
Power system	Robot battery supply and correctly isolated USB/5 V arrangements; physical setup must be checked by the team.

Software requirements

Python 3.12 is the reference laptop environment. The camera path uses OpenCV, NumPy and Pillow; pytest validates software behavior. The Pi worker needs Python 3.11 or later and no OpenCV installation. Arduino CLI with the ESP8266 core builds firmware. C++ host tests exercise the same parser and safety logic used by the sketch. The public repository includes pinned laptop dependencies and example configuration.

2.3 System Architecture

Two separate data paths are used. The control path is *camera* → *laptop* → *ESP8266*. The compute path is *laptop snapshot* → *Pi worker* → *laptop advice*. Both use Wi-Fi, but they have different timing requirements. Only the first path determines immediate robot actuation. The offload server never opens a robot UDP socket.

Each robot is addressed using its firmware ID and network endpoint. A printed marker's ID is a vision identity, not proof of that firmware ID. The team-provided marker photograph decoded as ArUco ID 1; if that marker is fitted to firmware bot 2, the runner must explicitly use `--bot 2 --marker-id 1`. Two visible robots must have distinct marker identities.

2.4 Block Diagram




Figure 1: Current architecture. The Pi compute branch is outside the motor-command path.

2.5 System Workflow

1. Configure the measured arena size, camera source, robot endpoint and identity mapping.
2. Calibrate image-to-floor coordinates from four ordered floor-corner clicks.
3. Detect the selected ArUco marker, or the configured LED in the single-robot mode.
4. Convert an operator click to a bounded floor goal; estimate motion locally.
5. Send bounded commands directly from laptop to robot, while checking vision freshness.
6. Submit an optional compact goal snapshot to the Pi on a background thread.
7. Display the Pi comparison when it matches the current job; discard obsolete advice.
8. Stop on operator request, tracking failure, stale imagery, or process exit.

2.6 Functional and Non-Functional Requirements

Type	Requirement	Verification
Functional	Click-to-go and stop controls	Closed-loop synthetic-camera tests; physical team demonstration
Functional	Marker and robot ID separated	Marker tests and explicit CLI arguments
Functional	Pi profile-comparison job	Deterministic rollout test and HTTP worker interface
Safety	No background job may issue motor commands	Module separation; result marked advisory
Safety	Reject stale/invalid observations	Controller/firmware regression tests
Performance	Background HTTP must not block control	Nonblocking client and offline-worker test
Reproducibility	Source, seeds and result files retained	Evidence manifests and build instructions
Security	Credentials absent from publication	Allowlist staging and secret scan before publishing

3. AI and Robotics Methodology

3.1 AI/ML Technique and Algorithm

The primary adaptive element is online system identification. The controller estimates how fast the robot travels and turns from the observed effect of its previous burst. This differs from a fixed lookup table: observations update the parameters that size the next burst. A heading-error integrator or burst drift estimate compensates left/right mismatch. LED tracking additionally infers heading from displacement, because one bright dot does not directly encode orientation.

The Pi's contribution is model-based evaluation. It simulates candidate burst profiles under uncertain dynamics and reports empirical completion counts, travel time and boundary proximity. This is a planning/analysis technique, not a learned neural network. A separate supervised red-round-token classifier exists in the earlier camera-to-Pi indicator demo. That optional demonstration is not necessary for manually selected click-to-go goals and is not represented as the navigation controller's perception model.

3.2 Dataset / Input Data

The runtime inputs are camera frames, a four-point floor calibration, robot identity, an operator-selected pixel location, and configuration values. ArUco markers are coded fiducials from OpenCV's `DICT_4X4_50`, rather than a dataset on which this team trained a visual recognizer [1]. The LED alternative uses brightness, redness, blob area and proximity constraints.

Evaluation has three distinct input sets: seeded simulator conditions; historical firmware/communication bench records; and teammate-reported phone-camera operation. Only the first set supports the statistical comparisons in this report. The optional classifier was trained on 1,200 generated examples and evaluated on 400 separately seeded examples. Its stored 400/400 result is a synthetic-data result; real-room generalization has not been established.

3.3 Data Preprocessing and Model Development

Geometric calibration and pose

Four clicked arena corners define a planar homography. Pixel location (u, v) and floor coordinates (x, y) satisfy

$$\lambda \begin{bmatrix} x \\ y \\ 1 \end{bmatrix} = H \begin{bmatrix} u \\ v \\ 1 \end{bmatrix}. \tag{1}$$

Corners are ordered bottom-left, bottom-right, top-right and top-left. The code rejects non-finite or degenerate quadrilaterals and incompatible saved arena dimensions. Homography corrects projective geometry for a plane; it does not remove camera lens distortion or the height error of a marker above the floor.

For a marker, transformed corners define its centre and a front vector from centre to its top edge. Heading is $\theta = \text{atan2}(f_y, f_x)$. The marker should be flat, near the robot centre, with its top edge facing the physical front. ArUco dictionary design and orientation recovery are described in the original literature and OpenCV documentation [2][1].

Differential-drive formulation

Let v_L, v_R be wheel linear velocities and b the wheel separation. The standard planar approximation is [3]

$$v = \frac{v_R + v_L}{2}, \qquad \omega = \frac{v_R - v_L}{b}, \tag{2}$$

$$\dot{x} = v\cos\theta, \qquad \dot{y} = v\sin\theta, \qquad \dot{\theta} = \omega. \tag{3}$$

The simulator applies a midpoint-heading integration, wheel-gain variation, stiction, transport delay and packet loss. Reference simulator values such as $b = 0.10$ m and nominal wheel speed 0.20 m/s are model assumptions, not measured dimensions or speeds of the team robots.

Goal error and burst sizing

For a goal $g = (x_g, y_g)$, distance and wrapped heading errors are

$$d = \sqrt{(x_g - x)^2 + (y_g - y)^2}, \tag{4}$$

$$e_\theta = \mathrm{wrap}\left(\mathrm{atan2}(y_g - y, x_g - x) - \theta\right). \tag{5}$$

The burst controller first rotates when angular error is large, then advances. With undershoot factor η and estimated motion rates $\hat{v}, \hat{\omega}$, the intended burst durations are bounded versions of

$$\tau_{\text{turn}} = \eta\frac{|e_\theta|}{\max(\hat{\omega}, \epsilon_\omega)}, \qquad \tau_{\text{forward}} = \eta\frac{d}{\max(\hat{v}, \epsilon_v)}. \tag{6}$$

After a burst, the robot is commanded to stop. The controller waits for configured camera delay plus a settling margin before learning from the new observation. This sacrifices speed to avoid repeatedly steering on an old pose.

Online adaptation

For commanded burst duration Δt_b, observed forward displacement Δs and signed turn progress $\Delta\theta$, smoothed estimates follow

$$\hat{v}_{k+1} = (1-\alpha)\hat{v}_k + \alpha\frac{\Delta s}{\Delta t_b}, \tag{7}$$

$$\hat{\omega}_{k+1} = (1-\alpha)\hat{\omega}_k + \alpha\frac{|\Delta\theta|}{\Delta t_b}. \tag{8}$$

The implementation uses bounded estimates and a smoothing weight of 0.5 for these rate updates. Little measured movement triggers an increase in burst power, up to a command ceiling. Drift trim is also bounded. These mechanisms are useful only when the pose measurement is credible; they do not make a lost marker safe to ignore.

3.4 Robotics Components

Sensors

The overhead camera is the only navigation sensing source. ArUco provides both position and heading; one LED provides position and requires motion-based heading inference. No onboard proximity or odometry sensors are fitted. The term “sensorless robot” refers to the onboard build, not to a system with no sensing.

Actuators

Two geared DC motors form the differential drive. The L298N switches motor direction and PWM inputs. The marker output currently uses the D1 Mini's onboard LED as a demonstrator; no installed laser is claimed. The signed command range is $[-100, 100]$ and the firmware caps PWM duty at 72%. Duty limiting is not a substitute for checking supply voltage, driver losses and motor ratings.

Controller

The laptop contains the adaptive motion controller. The ESP8266 is an actuator endpoint with independent safety logic. Fixed motor inputs use D1, D2, D5 and D6; robot-specific swap/inversion flags account for physical wiring. D3/D4/D8 are not used for external motor wiring. The onboard LED is handled only after boot.

3.5 AI and Robotics Integration

The proposed integration is deliberately asynchronous. When a new click produces a usable pose/goal pair, the laptop submits arena dimensions, pose, goal and control assumptions to `/evaluate`. The default job runs 12 seeded trials for each of three profiles. At most one job executes on the Pi, and the laptop keeps only its newest pending goal. Results contain the job ID and goal, which must match before the UI accepts them.

The returned recommendation compares simulated completion, boundary proximity and mean time. It is displayed and logged, but it does not alter the active motor controller. This preserves the previously working local workflow and prevents unverified model assumptions from becoming automatic hardware commands. Pi Zero W offloading here means moving work away from the control thread, not claiming an overall speedup over the laptop.

3.6 Algorithm and Flowchart




Figure 2: Control and offload workflow. Operator stop and stale-vision handling remain local.

4. Implementation, Testing and Results

4.1 Hardware Implementation

The team assembled two Wi-Fi robot platforms. Earlier chip/upload records identify an ESP8266EX with 4 MB flash on the tested platform. Recorded motor orientation settings differ between firmware bot 1 and bot 2. These must not be overwritten simply because a printed marker has a different ID.

The supplied hardware bench record documents 10 accepted zero-speed commands, reported marker-on state, marker-off state after a continued three-second request stream, successful re-arm, and marker-off state after 650 ms without a command. It also records a motor lock and final outputs of zero. This validates reported firmware states and communication, not wheel direction, physical braking distance or a completed navigation trial. The user separately reports a teammate's successful phone-camera click-to-go run; no numerical arrival-error series accompanies it.

4.2 Software Implementation

Module / entry point	Responsibility
`scripts/click_go.py`	Camera UI, click events, direct robot sender; LED and ArUco modes; optional background offload.
`swarm/marker_go.py`	Marker-based pose-to-goal control and immediate stop when the selected marker is missing.
`swarm/click_control.py`	Position-only LED heading inference and adaptive burst behavior.
`swarm/control.py`	Continuous and burst controllers with online identification.
`swarm/offload_client.py`	Nonblocking latest-goal job submission and stale-result rejection.
`swarm/offload_server.py`	Authenticated, bounded background worker; no robot transport.
`swarm/offload.py`	Seed-matched Monte Carlo profile comparison.
`firmware/bot/logic.h`	Strict parser, watchdog, PWM and marker safety rules.

The old Pi-central coordinator and indicator demo are retained as historical experiments, not the default Review 2 control path. The offload installer stops the previous Pi command-sending service before enabling the compute-only worker, preventing competing senders from interfering with the laptop.

4.3 Working Model / Prototype

The physical prototype demonstrates a sensorless actuator node connected to a camera-guided laptop. The reviewed software now includes explicit printed-marker tracking for the pictured marker as well as the older LED mode. The teammate's reported top-down phone workflow is preserved in the operator interface. The Pi offload worker is a software implementation; the fresh offload measurements below were executed on the laptop. No physical-Pi runtime is reported in this submission.

4.4 Testing and Validation

Validation is layered so that a simulator cannot silently stand in for physical results. Unit tests cover geometry, parsing, adaptation and cancellation. A C++ harness compares firmware safety logic against the Python model. Synthetic-camera tests render markers/LEDs and recover their geometry. Loopback tests exercise video, HTTP and UDP transport without moving a robot. New tests cover offline offload nonblocking behavior, cancellation, invalid jobs, and marker identity.

The fresh complete run on 3 November 2026 passed **181 tests** in 243.58 seconds. This includes firmware-model comparisons, vision geometry, controller behavior, loopback transport, marker tracking, and background-offload regression checks. The complete output is retained in `evidence/test_results.txt`. These are software results, not physical navigation trials.

Evidence level	Available evidence	What it does not prove
Software tests	Fresh automated results and saved test log	Mechanical/electrical correctness
Simulation	Seeded controller and offload comparisons	Real-room success probability
Historical hardware bench	Command counters and reported output/indicator states	Navigation accuracy or stopping distance
Teammate report	Successful overhead phone click-to-go described by the user	A measured multi-trial performance distribution
Unmeasured hardware properties	Calibration error, arrival error, latency and floor trials	Outside the recorded evaluation

Table 2: Evidence classification used throughout this report.

4.5 Performance Evaluation

The normal scenario is a two-robot search/converge/mark simulation in a 1.00 m by 0.75 m arena. This inherited task is used to compare the shared controllers; it is not a measurement of the manually clicked physical workflow. Each row in Table 3 contains 10 seeded trials. Success means the simulator's marker ray satisfied its target criterion. "Contacts" counts simulated robot contact events. A dash means no successful trial supplied a time statistic.

Scenario	Success	Mean (s)	Worst (s)	Contacts
Fast camera / continuous	10/10	15.21	50.30	0
Delayed camera / continuous	0/10	–	–	0
Delayed camera / burst	10/10	34.39	49.85	0
Burst + 15% packet loss	10/10	32.84	53.70	0
Burst + 25% wheel mismatch	10/10	36.93	66.40	0

Table 3: Fresh simulation scenarios, 10 seeds per row, generated 3 November 2026. These are not physical robot results.

The fresh learning ablation drives a single simulated robot through three waypoints with a weak wheel, stiction and camera lag. With poor initial rate estimates, online learning completed 10/10 courses; disabling learning completed 0/10. With correct initial estimates and learning disabled, 10/10 completed in a slightly shorter mean time. Table 4 therefore demonstrates the value and cost of adaptation, rather than asserting that learning is always faster.

Variant	Completed	Mean time (s)
learning ON, poor initial guesses	10/10	52.08
learning OFF, correct initial guesses	10/10	49.49
learning OFF, poor initial guesses	0/10	–

Table 4: Fresh learning ablation. Mean time is computed only for completed courses.

A separate synthetic-camera click-to-go run used printed marker ID 1 with firmware bot ID 2 and the goal $(0.75, 0.50)$ m. It ended at approximately $(0.73, 0.50)$ m with a rounded final error of 16 mm. This tests the new marker identity mapping and local goal controller in simulation; it is not a measured physical arrival error. The console result is retained in `evidence/marker_click_demo.txt`. The recorded video uses a separate seed-7 run with delayed observations and a one-second marker occlusion. It reaches the same goal in 17.45 simulated seconds with a true final error of 20.7 mm; its per-step log is stored under `media/`.

For the new background job, a clicked goal at $(0.80, 0.55)$ m from pose $(0.20, 0.20, 0)$ was evaluated using 12 trials per profile. All three profiles completed 12/12 simulations. Conservative, current and longer-burst mean simulated times were 18.78, 16.05 and 15.21 s, respectively. The job executed 12,009 integration steps. Its measured compute time is stored with the result file; the execution host is explicitly the laptop, not the Pi. The recommendation was not applied to the physical motors.

4.6 Results and Discussion

The main observation is the difference between low-latency and delayed feedback. Continuous control succeeds in the fresh low-lag reference trials but fails all 10 trials in the 0.3 s delayed-camera comparison. Burst control succeeds in all 10 under the same nominal delay, with longer completion times because it waits between actions. The packet-loss and wheel-mismatch variants also succeed in this small seeded sample. Their differing mean times should not be ranked as precise physical performance: randomized paths, arrival thresholds and finite sample size affect the comparison.

The offload integration meets its architectural objective: the laptop can continue while the worker is unavailable, and a cancelled goal cannot receive an obsolete result. This supports reliability of the software split. It does not establish that Raspberry Pi execution is faster or that advisory profiles are safe on unmeasured hardware. Physical calibration and Pi timing are outside the recorded evaluation.

Configuration checks, fresh observations and a single motor-command sender reduce ambiguity when communication is intermittent. Private network settings are excluded from the public source.

4.7 Screenshots / Prototype Photographs

Figure 3 is a frame from the simulation video. The recording shows a selected goal, marker-based movement, a lost-marker stop command and a background worker response. Its tracker, controller and HTTP worker are executed on the laptop. The video, trajectory and worker output are included under `media/`; no physical robot footage or Pi runtime is represented.




Figure 3: Frame from the recorded software demonstration. A generated marker image feeds the local controller while an actual local HTTP worker returns profile comparisons. The image does not depict physical robot operation.

5. Conclusion and Future Scope

5.1 Summary of the Work

Pi Swarm combines external visual sensing, adaptive local control and distributed background computation using low-cost robot hardware. The final architecture preserves the established phone-camera click-to-go workflow and moves optional simulation work to the Pi without relaying motor commands through it. The repository provides firmware, camera/control code, the compute worker, tests, evidence and a rebuildable LaTeX report.

5.2 Achievement of Objectives

Objective	Assessment
Visual robot localization	Marker and LED geometry tested synthetically; live calibration accuracy was not measured.
Direct click-to-go control	Local interface preserved; teammate-reported physical operation; no quantitative physical trial series recorded.
Adaptive behavior	Rate/trim learning implemented and ablation-tested in simulation.
Useful Pi offloading	Asynchronous profile evaluation implemented; laptop validation complete; no current physical-Pi timing recorded.
Independent safety rules	Firmware logic fuzz-tested; historical reported LED/watchdog bench states available.
Reproducible submission	Source, configuration examples, tests, evidence, report source and public repository provided.

5.3 Limitations

- External vision is required; the onboard platforms have no navigation sensors.
- Printed-marker placement, glare, perspective and camera buffering can degrade pose estimates.
- LED-only heading inference requires motion and does not reliably distinguish two identical red LEDs.
- No real-room trained detector accuracy, repeated arrival-error distribution or physical stopping-distance result is available.
- Simulator speed, track width and uncertainty ranges are assumptions until measured.
- The Pi worker provides advice only and is not yet benchmarked on the current physical Pi deployment.
- UDP command transport is unauthenticated; use a trusted isolated local network.

5.4 Future Enhancements

A future extension could quantify camera latency, calibration error, stopping distance and repeated clicked-goal arrivals on a reassembled platform. Measuring physical-Pi runtime alongside laptop loop timing would help assess scheduling costs. Other extensions include wheel encoders, range sensors, real-camera training data, obstacle models, authenticated actuator commands and more efficient multi-robot assignment.

The original proposal discussed ESP32-CAM/TinyML and an ESP-NOW mesh. The available build instead uses ESP8266 actuator nodes, overhead vision and Wi-Fi UDP. These are explicit scope changes. A future migration could revisit those proposal items, but they are not presented as features of the current prototype.

5.5 Real-World Deployment Possibilities

The current implementation is best suited to supervised education and laboratory experiments. A deployment around people or equipment would require onboard obstacle sensing, electrical protection, reliable localization, tested communication security and measured stopping behavior. The architectural lesson remains useful: a robot controller should preserve timely local safety decisions while treating expensive remote analysis as a separately scheduled workload.

5.6 Learning Outcomes

The project develops practical understanding of camera calibration, coordinate systems, differential-drive kinematics, adaptive estimation, delayed feedback, embedded failsafes and distributed-software boundaries. It also illustrates an experimental-design lesson: a successful simulation, a firmware counter, and a physical navigation trial answer different questions. An organized repository and evidence-labelled report make those distinctions reviewable by teammates and faculty.

5.7 References

[1] OpenCV, "Detection of ArUco Markers," official documentation, version 4.12. https://docs.opencv.org/4.12.0/d5/dae/tutorial_aruco_detection.html. Accessed 3 November 2026.

[2] S. Garrido-Jurado, R. Muñoz-Salinas, F. J. Madrid-Cuevas and M. J. Marín-Jiménez, "Automatic generation and detection of highly reliable fiducial markers under occlusion," *Pattern Recognition*, 47(6), 2280–2292, 2014. DOI: 10.1016/j.patcog.2014.01.005.

[3] K. M. Lynch and F. C. Park, *Modern Robotics: Mechanics, Planning, and Control*, Cambridge University Press, 2017. Official author resource: https://hades.mech.northwestern.edu/index.php/Modern_Robotics.

[4] Espressif Systems, *ESP8266EX Datasheet*, version 7.1. https://www.espressif.com/sites/default/files/documentation/0a-esp8266ex_datasheet_en.pdf.

[5] ESP8266 Arduino Core, official source and documentation. https://github.com/esp8266/Arduino. Accessed 3 November 2026.

[6] Raspberry Pi Ltd., Raspberry Pi Zero W product information. https://www.raspberrypi.com/products/raspberry-pi-zero-w/.

[7] AI and Robotics course materials, *Review 2* rubric and case-study report section guidelines, supplied by the students. Internal academic materials; referenced for structure and assessment criteria, not republished.

[8] Pi Swarm project team, source code, seeded simulations and evidence records, 2026. https://github.com/Kapilkannaa/pi-swarm-robotics.

5.8 Appendix

A. Supporting materials

The project repository provides the implementation and supporting evaluation records. The simulation demonstration shows the selected destination, marker-based navigation, tracking-loss response and asynchronous worker output. The complete source and report are also available through the repository's release page.

Material	Location in the repository
Demonstration video	`media/pi-swarm-simulation.mp4`
Trajectory and arrival result	`media/demo-trajectory.csv` and `media/demo-summary.json`
Background job output	`media/demo-worker-result.json`
Scenario comparison	`reports/review2/evidence/scenario_results.csv`
Adaptation comparison	`reports/review2/evidence/learning_ablation.json`
Automated test record	`reports/review2/evidence/test_results.txt`

B. Demonstration interpretation

The recording begins with movement toward a selected goal, introduces the system architecture midway, and then resumes navigation. Printed marker 1 identifies firmware bot 2. A brief marker occlusion produces zero wheel commands, while the compute worker returns an advisory comparison independently of local control.

The demonstration runs the project tracker, controller and firmware model with generated images. Its HTTP worker executes locally on the laptop. The recorded arrival error is therefore a simulation result; it is not a physical floor-trial measurement or a benchmark of Raspberry Pi execution.

C. Implementation reference

The main application is `scripts/click_go.py`. Marker localization is implemented in `swarm/vision/tracker.py`, adaptive control in `swarm/control.py`, and profile evaluation in `swarm/offload.py`. The asynchronous client and compute-only service are `swarm/offload_client.py` and `swarm/offload_server.py`. The ESP8266 command parser and watchdog logic are in `firmware/bot/logic.h`. These entry points connect the report's architecture and mathematical model to the submitted implementation.