Electromagnetic Field Propagation in Optical Fiber: A Rigorous Treatment of Modal Theory and Retarded Potentials

Corrected Research Framework

January 11, 2026

Abstract

We present a mathematically rigorous treatment of electromagnetic field propagation in optical fibers, carefully distinguishing between the retarded potential formulation and modal decomposition approaches. We address common inconsistencies in the literature regarding wave equations in inhomogeneous media, proper Green's functions for stratified structures, and the transition to quantum field theory. All derivations are provided in detail with explicit assumptions.

Contents

1 Maxwell's Equations in Optical Fibers **3**
- 1.1 Fundamental Equations . . . 3
- 1.2 Constitutive Relations . . . 3
- 1.3 Electromagnetic Potentials . . . 3

2 Gauge Freedom and Wave Equations **3**
- 2.1 Gauge Transformation . . . 3
- 2.2 Lorenz Gauge in Homogeneous Media . . . 4
- 2.3 Wave Equations in Inhomogeneous Media . . . 4
- 2.4 Why Modal Analysis is Preferred . . . 4

3 Step-Index Fiber Structure **5**
- 3.1 Cylindrical Geometry . . . 5
- 3.2 Fiber Parameters . . . 5

4 Modal Decomposition in Fibers **5**
- 4.1 Helmholtz Equation . . . 5
- 4.2 Modal Expansion . . . 5
- 4.3 Fundamental Mode (LP_{01}) . . . 6
- 4.4 Effective Refractive Index . . . 6

5 Dispersion in Optical Fibers **6**
5.1 Frequency-Dependent Propagation Constant . . . 6
5.2 Dispersion Parameter . . . 6
5.3 Propagation Equation in Frequency Domain . . . 7
5.4 Time-Domain Propagation . . . 7

6 Attenuation in Optical Fibers **7**
6.1 Power vs. Amplitude Attenuation . . . 7
6.2 Conversion Formula . . . 7

7 Gaussian Pulse Propagation: Complete Derivation **7**
7.1 Input Pulse . . . 7
7.2 Fourier Transform . . . 8
7.3 Propagation with Second-Order Dispersion . . . 8
7.4 Inverse Fourier Transform . . . 8
7.5 Gaussian Integral . . . 8
7.6 Pulse Width Evolution . . . 8
7.7 Physical Interpretation . . . 9

8 Retarded Potentials: Proper Treatment **9**
8.1 Free-Space Green's Function (Reference) . . . 9
8.2 Fiber Green's Function . . . 9
8.3 Modal vs. Retarded Approaches . . . 9

9 Complete Worked Example **10**
9.1 Problem Statement . . . 10
9.2 Solution . . . 10

10 Quantum Field Theory in Fibers **11**
10.1 Quantization Procedure . . . 11
10.2 Coherent States in Fibers . . . 11
10.3 Propagation of Coherent States . . . 11
10.4 Hamiltonian Formulation . . . 11

11 Parameter Space and Classical-Quantum Interface **12**
11.1 Complete Parameter Set . . . 12
11.2 Classical-to-Quantum Encoding . . . 12
11.3 Atom-Field Interaction . . . 13

12 Summary of Corrections **13**
12.1 Mathematical Issues Resolved . . . 13
12.2 Common Pitfalls to Avoid . . . 13

13 Further Topics **14**

A Bessel Function Properties **14**

B Fourier Transform Conventions **15**

C Units and Constants **15**

1 Maxwell's Equations in Optical Fibers

1.1 Fundamental Equations

In a dielectric medium such as an optical fiber, Maxwell's equations in SI units are:

$$\nabla \cdot \mathbf{D} = \rho_{\text{free}} \qquad \text{(Gauss's Law)}$$
$$\nabla \cdot \mathbf{B} = 0 \qquad \text{(No magnetic monopoles)}$$
$$\nabla \times \mathbf{E} = -\frac{\partial \mathbf{B}}{\partial t} \qquad \text{(Faraday's Law)}$$
$$\nabla \times \mathbf{H} = \mathbf{J}_{\text{free}} + \frac{\partial \mathbf{D}}{\partial t} \qquad \text{(Ampère-Maxwell Law)}$$

1.2 Constitutive Relations

For a linear, isotropic, non-magnetic, and non-dispersive (in space) dielectric:

$$\mathbf{D}(\mathbf{r}, t) = \varepsilon_0 \varepsilon_r(\mathbf{r}) \mathbf{E}(\mathbf{r}, t) = \varepsilon(\mathbf{r}) \mathbf{E}(\mathbf{r}, t) \tag{1}$$
$$\mathbf{B}(\mathbf{r}, t) = \mu_0 \mathbf{H}(\mathbf{r}, t) \tag{2}$$

where $\mu_r \approx 1$ for silica-based optical fibers (non-magnetic material).

Assumption 1 (Refractive Index)**.** *The position-dependent refractive index is defined by:*

$$n(\mathbf{r}) = \sqrt{\varepsilon_r(\mathbf{r})} \tag{3}$$

with $\varepsilon(\mathbf{r}) = \varepsilon_0 n^2(\mathbf{r})$.

1.3 Electromagnetic Potentials

To reduce the complexity of solving six coupled equations for $\mathbf{E}$ and $\mathbf{B}$, we introduce the vector potential $\mathbf{A}$ and scalar potential Φ:

$$\mathbf{B} = \nabla \times \mathbf{A} \tag{4}$$
$$\mathbf{E} = -\nabla \Phi - \frac{\partial \mathbf{A}}{\partial t} \tag{5}$$

These definitions automatically satisfy Eqs. (No magnetic monopoles) and (Faraday's Law).

2 Gauge Freedom and Wave Equations

2.1 Gauge Transformation

The potentials $(\mathbf{A}, \Phi)$ are not unique. For any scalar function $\lambda(\mathbf{r}, t)$, the gauge transformation:

$$\mathbf{A}' = \mathbf{A} + \nabla \lambda \tag{6}$$
$$\Phi' = \Phi - \frac{\partial \lambda}{\partial t} \tag{7}$$

leaves the physical fields $\mathbf{E}$ and $\mathbf{B}$ unchanged.

2.2 Lorenz Gauge in Homogeneous Media

For a *homogeneous* medium with constant ε, we impose the Lorenz gauge condition:

$$\nabla \cdot \mathbf{A} + \frac{\varepsilon\mu_0}{1}\frac{\partial \Phi}{\partial t} = 0 \tag{8}$$

Using $c = 1/\sqrt{\varepsilon_0\mu_0}$ and $v = c/n$ where $n^2 = \varepsilon/\varepsilon_0$:

$$\nabla \cdot \mathbf{A} + \frac{n^2}{c^2}\frac{\partial \Phi}{\partial t} = 0 \tag{9}$$

Substituting into Maxwell's equations yields the wave equations:

$$\Box \mathbf{A} = -\mu_0 \mathbf{J}_{\text{free}} \tag{10}$$

$$\Box \Phi = -\frac{\rho_{\text{free}}}{\varepsilon} \tag{11}$$

where the d'Alembertian operator for a homogeneous medium is:

$$\Box \equiv \nabla^2 - \frac{n^2}{c^2}\frac{\partial^2}{\partial t^2} \tag{12}$$

2.3 Wave Equations in Inhomogeneous Media

Remark 1 (Critical Issue)**.** *For inhomogeneous media where $\varepsilon(\mathbf{r})$ varies with position, the wave equation derivation is more complex.*

Starting from Ampère's law (Ampère-Maxwell Law) and using $\mathbf{B} = \nabla \times \mathbf{A}$:

$$\nabla \times (\nabla \times \mathbf{A}) = \mu_0 \mathbf{J}_{\text{free}} + \mu_0 \varepsilon(\mathbf{r})\frac{\partial \mathbf{E}}{\partial t} \tag{13}$$

Using the vector identity $\nabla \times (\nabla \times \mathbf{A}) = \nabla(\nabla \cdot \mathbf{A}) - \nabla^2 \mathbf{A}$:

$$-\nabla^2 \mathbf{A} + \nabla(\nabla \cdot \mathbf{A}) = \mu_0 \mathbf{J}_{\text{free}} - \mu_0 \varepsilon(\mathbf{r})\frac{\partial^2 \mathbf{A}}{\partial t^2} - \mu_0 \varepsilon(\mathbf{r})\frac{\partial}{\partial t}(\nabla \Phi) \tag{14}$$

If we attempt to use a Lorenz-like gauge $\nabla \cdot \mathbf{A} = -\varepsilon(\mathbf{r})\mu_0 \partial\Phi/\partial t$:

$$\nabla(\nabla \cdot \mathbf{A}) = -\nabla\left[\varepsilon(\mathbf{r})\mu_0 \frac{\partial \Phi}{\partial t}\right] = -\nabla\varepsilon(\mathbf{r}) \cdot \mu_0 \frac{\partial \Phi}{\partial t} - \varepsilon(\mathbf{r})\mu_0 \frac{\partial}{\partial t}(\nabla \Phi) \tag{15}$$

This produces the wave equation:

$$\nabla^2 \mathbf{A} - \mu_0 \varepsilon(\mathbf{r})\frac{\partial^2 \mathbf{A}}{\partial t^2} = -\mu_0 \mathbf{J}_{\text{free}} + \mu_0 \frac{\partial \Phi}{\partial t}\nabla\varepsilon(\mathbf{r}) \tag{16}$$

Remark 2 (Boundary Terms)**.** *The term $\nabla\varepsilon(\mathbf{r})$ is zero in the bulk core and cladding but produces a* ***delta function*** *at the core-cladding interface. These boundary terms are essential for matching boundary conditions.*

2.4 Why Modal Analysis is Preferred

For step-index fibers with sharp boundaries, the retarded potential approach with inhomogeneous Green's functions becomes intractable. Instead, we use **modal decomposition**, which naturally incorporates boundary conditions.

3 Step-Index Fiber Structure

3.1 Cylindrical Geometry

Using cylindrical coordinates (ρ, ϕ, z), a step-index fiber has:

$$n(\rho) = \begin{cases} n_{\text{core}} & \rho < a \quad \text{(core)} \\ n_{\text{clad}} & \rho > a \quad \text{(cladding)} \end{cases} \tag{17}$$

where a is the core radius.

3.2 Fiber Parameters

- **Numerical Aperture (NA):**

$$\text{NA} = \sqrt{n_{\text{core}}^2 - n_{\text{clad}}^2} \approx n_{\text{core}}\sqrt{2\Delta} \tag{18}$$

where $\Delta = (n_{\text{core}} - n_{\text{clad}})/n_{\text{core}} \approx 0.01$ is the fractional index difference.

- **V-number (normalized frequency):**

$$V = k_0 a \cdot \text{NA} = \frac{2\pi a}{\lambda_0}\sqrt{n_{\text{core}}^2 - n_{\text{clad}}^2} \tag{19}$$

where $k_0 = 2\pi/\lambda_0$ is the free-space wavenumber.

- **Single-mode condition:** $V < 2.405$

4 Modal Decomposition in Fibers

4.1 Helmholtz Equation

For monochromatic fields with time dependence $e^{-i\omega t}$, Maxwell's equations reduce to:

$$\nabla^2 \mathbf{E} + k_0^2 n^2(\rho)\mathbf{E} = 0 \tag{20}$$

4.2 Modal Expansion

The general solution is a sum over guided modes:

$$\mathbf{E}(\rho, \phi, z, t) = \sum_m a_m \mathbf{E}_m(\rho, \phi) e^{i(\beta_m z - \omega t)} + \text{c.c.} \tag{21}$$

where:

- $\mathbf{E}_m(\rho, \phi)$ is the transverse mode profile
- β_m is the propagation constant (eigenvalue)
- a_m is the complex mode amplitude

4.3 Fundamental Mode (LP_{01})

For the linearly polarized LP_{01} mode (azimuthally symmetric, $m = 0$):

$$E_{01}(\rho) \propto \begin{cases} J_0(u\rho/a) & \rho < a \\ \frac{J_0(u)}{K_0(w)} K_0(w\rho/a) & \rho > a \end{cases} \tag{22}$$

where J_0 and K_0 are Bessel functions, and the eigenvalue equation is:

$$\frac{uJ_1(u)}{J_0(u)} = \frac{wK_1(w)}{K_0(w)} \tag{23}$$

with $u^2 + w^2 = V^2$.

4.4 Effective Refractive Index

Each mode has an effective index:

$$n_{\text{eff},m} = \frac{\beta_m}{k_0}, \quad n_{\text{clad}} < n_{\text{eff},m} < n_{\text{core}} \tag{24}$$

5 Dispersion in Optical Fibers

5.1 Frequency-Dependent Propagation Constant

For a given mode, β depends on frequency ω (or wavelength λ). The Taylor expansion around carrier frequency ω_0 is:

$$\beta(\omega) = \beta_0 + \beta_1(\omega - \omega_0) + \frac{1}{2}\beta_2(\omega - \omega_0)^2 + \frac{1}{6}\beta_3(\omega - \omega_0)^3 + \cdots \tag{25}$$

where:

$$\beta_0 = \beta(\omega_0) \tag{26}$$

$$\beta_1 = \left.\frac{d\beta}{d\omega}\right|_{\omega_0} = \frac{1}{v_g} \quad \text{(inverse group velocity)} \tag{27}$$

$$\beta_2 = \left.\frac{d^2\beta}{d\omega^2}\right|_{\omega_0} \quad \text{(group velocity dispersion, GVD)} \tag{28}$$

$$\beta_3 = \left.\frac{d^3\beta}{d\omega^3}\right|_{\omega_0} \quad \text{(third-order dispersion)} \tag{29}$$

5.2 Dispersion Parameter

The dispersion parameter D (in ps/(nm·km)) is related to β_2 by:

$$D = -\frac{2\pi c}{\lambda_0^2}\beta_2 \tag{30}$$

Typical values: $D \approx 17$ ps/(nm·km) at $\lambda_0 = 1550$ nm for standard single-mode fiber (SMF-28).

ps Picoseconds - amount of time delay or "spread" introduced to the pulse
nm nanometers - he spectral width of the light source
km kilometers - he length of the optical fiber

5.3 Propagation Equation in Frequency Domain

For a pulse propagating in a single mode:

$$\tilde{A}(\omega, z) = \tilde{A}(\omega, 0) \exp[i\beta(\omega)z - \alpha(\omega)z/2] \tag{31}$$

where $\alpha(\omega)$ is the frequency-dependent attenuation coefficient.

5.4 Time-Domain Propagation

The inverse Fourier transform gives:

$$A(t, z) = \int_{-\infty}^{\infty} \tilde{A}(\omega, 0) \exp[i\beta(\omega)z - i\omega t - \alpha z/2] \frac{d\omega}{2\pi} \tag{32}$$

6 Attenuation in Optical Fibers

6.1 Power vs. Amplitude Attenuation

Fiber loss is typically specified in dB/km for *power*:

$$\text{Loss (dB)} = 10 \log_{10} \left(\frac{P_{\text{in}}}{P_{\text{out}}} \right) = \alpha_{\text{dB}} L \tag{33}$$

For *field amplitude*:

$$A(z) = A(0) e^{-\alpha_{\text{Np}} z} \tag{34}$$

where α_{Np} is in Nepers/km.

6.2 Conversion Formula

$$\alpha_{\text{Np}} = \frac{\ln(10)}{20} \alpha_{\text{dB}} = 0.1151 \times \alpha_{\text{dB}} \tag{35}$$

Since power $P \propto |A|^2$:

$$P(z) = P(0) e^{-2\alpha_{\text{Np}} z} = P(0) \times 10^{-\alpha_{\text{dB}} z/10} \tag{36}$$

7 Gaussian Pulse Propagation: Complete Derivation

7.1 Input Pulse

Consider a Gaussian pulse at $z = 0$:

$$A(t, 0) = A_0 \exp \left[-\frac{t^2}{2T_0^2} \right] e^{i\omega_0 t} \tag{37}$$

We use the complex envelope representation:

$$A(t, z) = \mathcal{A}(t, z) e^{i(\beta_0 z - \omega_0 t)} \tag{38}$$

where $\mathcal{A}(t, z)$ is the slowly varying envelope.

7.2 Fourier Transform

$$\tilde{A}(\omega, 0) = A_0 T_0 \sqrt{2\pi} \exp\left[-\frac{(\omega - \omega_0)^2 T_0^2}{2}\right] \tag{39}$$

7.3 Propagation with Second-Order Dispersion

Keeping terms up to β_2 in Eq. (25):

$$\beta(\omega) \approx \beta_0 + \beta_1(\omega - \omega_0) + \frac{\beta_2}{2}(\omega - \omega_0)^2 \tag{40}$$

After propagation distance z:

$$\tilde{A}(\omega, z) = \tilde{A}(\omega, 0) \exp\left[i\beta_0 z + i\beta_1(\omega - \omega_0)z + \frac{i\beta_2}{2}(\omega - \omega_0)^2 z\right] \tag{41}$$

7.4 Inverse Fourier Transform

Defining $\Omega = \omega - \omega_0$:

$$A(t, z) = A_0 e^{i\beta_0 z} \int_{-\infty}^{\infty} \exp\left[-\frac{\Omega^2 T_0^2}{2} + i\Omega(\beta_1 z - t) + \frac{i\beta_2 z}{2}\Omega^2\right] \frac{d\Omega}{\sqrt{2\pi}} \tag{42}$$

Completing the square in the exponent:

$$-\frac{\Omega^2 T_0^2}{2} + \frac{i\beta_2 z}{2}\Omega^2 = -\frac{1}{2}\left(T_0^2 - i\beta_2 z\right)\Omega^2 \tag{43}$$

7.5 Gaussian Integral

Using:

$$\int_{-\infty}^{\infty} \exp\left[-\frac{a}{2}\Omega^2 + b\Omega\right] d\Omega = \sqrt{\frac{2\pi}{a}} \exp\left[\frac{b^2}{2a}\right] \tag{44}$$

with $a = T_0^2 - i\beta_2 z$ and $b = i(\beta_1 z - t)$:

$$A(t, z) = \frac{A_0}{\sqrt{1 - i\beta_2 z/T_0^2}} \exp\left[-\frac{(t - \beta_1 z)^2}{2T_0^2(1 - i\beta_2 z/T_0^2)}\right] e^{i(\beta_0 z - \omega_0 t)} \tag{45}$$

7.6 Pulse Width Evolution

Separating real and imaginary parts:

$$\frac{1}{1 - i\beta_2 z/T_0^2} = \frac{1 + i\beta_2 z/T_0^2}{1 + (\beta_2 z/T_0^2)^2} \tag{46}$$

The pulse intensity $I(t, z) = |A(t, z)|^2$ is:

$$I(t, z) = \frac{I_0}{T(z)/T_0} \exp\left[-\frac{(t - \beta_1 z)^2}{T(z)^2}\right] \tag{47}$$

where the pulse width evolution is:

$$T(z) = T_0 \sqrt{1 + \left(\frac{z}{L_D}\right)^2} \tag{48}$$

and the dispersion length is:

$$L_D = \frac{T_0^2}{|\beta_2|} \tag{49}$$

7.7 Physical Interpretation

- For $z \ll L_D$: negligible broadening, $T(z) \approx T_0$
- For $z = L_D$: $T(L_D) = \sqrt{2}T_0$ (41% broadening)
- For $z \gg L_D$: linear broadening, $T(z) \approx |\beta_2|z/T_0$

8 Retarded Potentials: Proper Treatment

8.1 Free-Space Green's Function (Reference)

For a homogeneous infinite medium, the solution to:

$$\left(\nabla^2 - \frac{n^2}{c^2}\frac{\partial^2}{\partial t^2}\right)\mathbf{A} = -\mu_0\mathbf{J} \tag{50}$$

is given by the retarded potential:

$$\mathbf{A}(t,\mathbf{r}) = \frac{\mu_0}{4\pi}\int \frac{\mathbf{J}(t_{\text{ret}},\mathbf{r}')}{|\mathbf{r}-\mathbf{r}'|}d^3\mathbf{r}' \tag{51}$$

where:

$$t_{\text{ret}} = t - \frac{n|\mathbf{r}-\mathbf{r}'|}{c} \tag{52}$$

8.2 Fiber Green's Function

Remark 3 (Critical Point)**.** *Equation* (51) *is* ***not valid*** *for step-index fibers because:*

1. *The medium is inhomogeneous (n depends on ρ)*
2. *There are boundaries at $\rho = a$*
3. *The geometry is cylindrical, not spherically symmetric*

The proper Green's function for a fiber must be constructed from fiber modes:

$$G(\mathbf{r},\mathbf{r}';\omega) = \sum_m \frac{\mathbf{E}_m(\rho,\phi)\mathbf{E}_m^*(\rho',\phi')}{N_m}\frac{e^{i\beta_m|z-z'|}}{2i\beta_m} \tag{53}$$

where N_m is the mode normalization constant.

8.3 Modal vs. Retarded Approaches

Theorem 1 (Equivalence in Source-Free Regions)**.** *In regions without sources ($\mathbf{J} = 0$), the modal expansion:*

$$\mathbf{A}(\mathbf{r},t) = \sum_m a_m\mathbf{A}_m(\rho,\phi)e^{i(\beta_m z-\omega t)} \tag{54}$$

is equivalent to the retarded potential formulation with fiber Green's functions, provided proper boundary conditions are satisfied.

For fiber propagation problems, the modal approach is standard because:

- Modes automatically satisfy boundary conditions
- Orthogonality simplifies coupled-mode equations
- Experimental excitation naturally produces modal distributions

9 Complete Worked Example

9.1 Problem Statement

A Gaussian pulse propagates through a single-mode fiber with:

$$\begin{aligned} L &= 10 \text{ km} \\ n_{\text{core}} &= 1.45 \\ \beta_2 &= -20 \text{ ps}^2/\text{km} \\ \alpha &= 0.2 \text{ dB/km} \\ T_0 &= 10 \text{ ps} \\ \lambda_0 &= 1550 \text{ nm} \end{aligned}$$

Calculate: (a) propagation delay, (b) pulse broadening, (c) amplitude attenuation.

9.2 Solution

(a) Propagation Delay:

The group velocity is $v_g = c/n_g$ where $n_g \approx n_{\text{core}}$ for fundamental mode. The time delay is:

$$\begin{aligned} \Delta t &= \frac{n_{\text{core}} L}{c} = \frac{1.45 \times 10^4 \text{ m}}{3 \times 10^8 \text{ m/s}} \\ &= 4.833 \times 10^{-5} \text{ s} = \boxed{48.33\ \mu\text{s}} \end{aligned} \tag{55}$$

(b) Pulse Broadening:

Dispersion length:

$$L_D = \frac{T_0^2}{|\beta_2|} = \frac{(10 \text{ ps})^2}{20 \text{ ps}^2/\text{km}} = \boxed{5 \text{ km}} \tag{56}$$

Since $L = 10$ km $= 2L_D$, dispersion is significant. Pulse width at $z = L$:

$$T(L) = T_0 \sqrt{1 + \left(\frac{L}{L_D}\right)^2} = 10\sqrt{1+4} = \boxed{22.36 \text{ ps}} \tag{57}$$

Broadening factor: $T(L)/T_0 = 2.236$ (124% increase).

(c) Amplitude Attenuation:

Convert attenuation to Nepers:

$$\alpha_{\text{Np}} = 0.1151 \times 0.2 = 0.02302 \text{ Np/km} \tag{58}$$

Total attenuation over 10 km:

$$\text{Amplitude} = e^{-\alpha_{\text{Np}} L} = e^{-0.2302} = \boxed{0.794} \tag{59}$$

This represents 79.4% of the original amplitude, or 63.1% of the original power (since $P \propto |A|^2$).

Power Loss Check:

$$\text{Power (dB)} = -\alpha_{\text{dB}} \times L = -0.2 \times 10 = -2 \text{ dB} \tag{60}$$

$$\frac{P_{\text{out}}}{P_{\text{in}}} = 10^{-2/10} = 0.631 = (0.794)^2 \quad \checkmark \tag{61}$$

10 Quantum Field Theory in Fibers

10.1 Quantization Procedure

The classical field $\mathbf{A}(\mathbf{r}, t)$ is promoted to an operator $\hat{\mathbf{A}}(\mathbf{r}, t)$. For a fiber of length L in a periodic box (for normalization):

$$\hat{\mathbf{A}}(\mathbf{r}, t) = \sum_m \sqrt{\frac{\hbar\omega_m}{2\varepsilon_0\varepsilon_m V_m}} \left[\hat{a}_m(t)\mathbf{f}_m(\mathbf{r}) + \hat{a}_m^\dagger(t)\mathbf{f}_m^*(\mathbf{r})\right] \tag{62}$$

where:

- $\hat{a}_m$, $\hat{a}_m^\dagger$ are annihilation/creation operators: $[\hat{a}_m, \hat{a}_n^\dagger] = \delta_{mn}$
- $\mathbf{f}_m(\mathbf{r})$ is the normalized mode function
- V_m is the effective mode volume
- $\varepsilon_m = \langle n^2 \rangle_m$ is the average permittivity weighted by mode intensity

10.2 Coherent States in Fibers

A coherent state $|\alpha\rangle$ for mode m is an eigenstate of the annihilation operator:

$$\hat{a}_m|\alpha_m\rangle = \alpha_m|\alpha_m\rangle \tag{63}$$

The mean photon number is $\langle \hat{n}_m \rangle = |\alpha_m|^2$.

10.3 Propagation of Coherent States

For a single-mode coherent state propagating through fiber of length L:

$$|\alpha(0)\rangle \xrightarrow{\text{propagate}} |\alpha(L)\rangle \tag{64}$$

where:

$$\alpha(L) = \alpha(0)\exp[i\beta(\omega)L]\exp[-\alpha L/2] \tag{65}$$

The density matrix evolves as:

$$\hat{\rho}(L) = |\alpha(L)\rangle\langle\alpha(L)| = \hat{U}(L)\hat{\rho}(0)\hat{U}^\dagger(L) \tag{66}$$

where $\hat{U}(L)$ is the propagation unitary (for lossless fiber) or non-unitary map (with loss).

10.4 Hamiltonian Formulation

The fiber propagation Hamiltonian in the interaction picture is:

$$\hat{H}_{\text{fiber}} = \sum_m \hbar\omega_m \hat{a}_m^\dagger \hat{a}_m + \hat{H}_{\text{disp}} + \hat{H}_{\text{loss}} + \hat{H}_{\text{nonlin}} \tag{67}$$

For linear propagation:

- $\hat{H}_{\text{disp}}$: dispersion (creates correlations between frequency components)
- $\hat{H}_{\text{loss}}$: coupling to reservoir (non-Hermitian, requires Lindblad master equation)
- $\hat{H}_{\text{nonlin}}$: nonlinear effects like self-phase modulation (ignored in this treatment)

11 Parameter Space and Classical-Quantum Interface

11.1 Complete Parameter Set

We define the parameter vector $\boldsymbol{\theta}$ containing:

Fiber Geometry:

- n_{core}, n_{clad}: refractive indices
- a: core radius
- L: fiber length

Material Properties (wavelength-dependent):

- $\alpha(\lambda_0; \boldsymbol{\theta}_{\text{mat}})$: attenuation coefficient
- $\beta_2(\lambda_0; \boldsymbol{\theta}_{\text{mat}})$: group velocity dispersion
- $\beta_3(\lambda_0; \boldsymbol{\theta}_{\text{mat}})$: third-order dispersion

Signal Parameters:

- λ_0: carrier wavelength
- T_0: initial pulse width
- P_0: peak power

Remark 4 (Parameter Dependencies)**.** *Not all parameters are independent:*

$$\beta_2 = \beta_2(n_{core}, n_{clad}, a, \lambda_0) \tag{68}$$

$$\alpha = \alpha(\lambda_0, dopants, impurities) \tag{69}$$

The functional dependencies arise from material dispersion and waveguide geometry.

11.2 Classical-to-Quantum Encoding

For quantum communication applications, classical data $x \in \mathbb{R}$ is encoded into quantum states:

$$x \mapsto \hat{\rho}(x|\boldsymbol{\theta}_{\text{enc}}) = |\psi_x\rangle\langle\psi_x| \tag{70}$$

Common encodings:

1. **Coherent state encoding:** $|\psi_x\rangle = |\alpha_x\rangle$ where $\alpha_x = \sqrt{\bar{n}}e^{i\phi(x)}$
2. **Fock state encoding:** $|\psi_x\rangle = |n_x\rangle$ (photon number states)
3. **Squeezed state encoding:** $|\psi_x\rangle = \hat{S}(\xi_x)|0\rangle$

After propagation through fiber:

$$\hat{\rho}(x, L|\boldsymbol{\theta}) = \mathcal{E}_{\text{fiber}}[\hat{\rho}(x, 0|\boldsymbol{\theta})] \tag{71}$$

where $\mathcal{E}_{\text{fiber}}$ is the quantum channel (completely positive, trace-preserving map).

11.3 Atom-Field Interaction

At the receiver, the field interacts with atoms via the dipole Hamiltonian:

$$\hat{H}_{\text{int}} = -\hat{\mathbf{d}} \cdot \hat{\mathbf{E}}(\mathbf{r}, t|\boldsymbol{\theta}) \tag{72}$$

where $\hat{\mathbf{d}} = q\hat{\mathbf{r}}$ is the atomic dipole operator.
In the rotating wave approximation:

$$\hat{H}_{\text{int}} = \hbar g(\mathbf{r}|\boldsymbol{\theta})(\hat{\sigma}^+\hat{a} + \hat{\sigma}^-\hat{a}^\dagger) \tag{73}$$

where $g(\mathbf{r}|\boldsymbol{\theta})$ is the position-dependent coupling strength, which depends on the fiber mode profile.

12 Summary of Corrections

12.1 Mathematical Issues Resolved

1. **Wave equation in inhomogeneous media:** Explicitly showed boundary terms $\nabla\varepsilon(\mathbf{r})$ that appear at core-cladding interface (Eq. 16).

2. **Green's function approach:** Clarified that free-space retarded potentials (Eq. 51) are invalid for fibers; proper treatment requires mode-expansion Green's function (Eq. 53).

3. **Modal vs. temporal dispersion:** Separated spatial mode index m from temporal frequency dependence $\beta(\omega)$; for single-mode fibers, only temporal dispersion matters.

4. **Gaussian pulse derivation:** Provided complete derivation from Fourier transform through completing the square, showing explicit steps to obtain pulse width evolution (Eqs. 48–49).

5. **Attenuation conversion:** Gave explicit dB-to-Neper conversion (Eq. 35) and distinguished power vs. amplitude loss.

6. **Quantum field theory:** Properly introduced quantization procedure with mode normalization, clarified coherent state propagation (Eq. 65), and connected to Hamiltonian formalism.

7. **Parameter dependencies:** Explicitly noted which parameters are independent vs. derived from other parameters.

12.2 Common Pitfalls to Avoid

- **Don't** use position-dependent d'Alembertian $\nabla^2 - n^2(\mathbf{r})/c^2 \cdot \partial^2/\partial t^2$ without accounting for ∇n^2 terms at boundaries.

- **Don't** apply free-space Green's functions to waveguide problems; always use modal expansions for fibers.

- **Don't** confuse spatial mode index (LP_{01}, LP_{11}, etc.) with temporal frequency components.

- **Don't** forget that β_2 is wavelength-dependent and can change sign (zero-dispersion wavelength $\sim 1.3\ \mu$ m for standard fiber).
- **Don't** neglect dispersion when $L \gtrsim L_D$; pulse broadening becomes significant.
- **Do** verify dimensional consistency: $[\beta_2] = \text{time}^2/\text{length}$, $[\alpha] = 1/\text{length}$.
- **Do** distinguish between phase velocity $v_p = \omega/\beta$ and group velocity $v_g = d\omega/d\beta$.

13 Further Topics

Topics beyond this treatment include:

- Nonlinear fiber optics (self-phase modulation, four-wave mixing)
- Polarization mode dispersion (PMD)
- Multimode fibers and intermodal dispersion
- Fiber Bragg gratings and coupled-mode theory
- Raman and Brillouin scattering
- Soliton propagation
- Quantum noise in optical fibers

References

1. Agrawal, G. P. (2019). *Nonlinear Fiber Optics* (6th ed.). Academic Press.
2. Snyder, A. W., & Love, J. D. (1983). *Optical Waveguide Theory.* Chapman and Hall.
3. Jackson, J. D. (1999). *Classical Electrodynamics* (3rd ed.). Wiley.
4. Louisell, W. H. (1973). *Quantum Statistical Properties of Radiation.* Wiley.
5. Glauber, R. J. (1963). Coherent and incoherent states of the radiation field. *Physical Review*, 131(6), 2766.

A Bessel Function Properties

For the fiber mode solutions, we use:

- $J_\nu(x)$: Bessel function of the first kind, oscillatory for real x
- $K_\nu(x)$: Modified Bessel function of the second kind, exponentially decaying for real $x > 0$
- Recursion: $J_{\nu-1}(x) + J_{\nu+1}(x) = (2\nu/x)J_\nu(x)$
- Derivative: $J'_\nu(x) = [J_{\nu-1}(x) - J_{\nu+1}(x)]/2$

B Fourier Transform Conventions

We use the symmetric convention:

$$\tilde{f}(\omega) = \frac{1}{\sqrt{2\pi}} \int_{-\infty}^{\infty} f(t) e^{i\omega t} dt \tag{74}$$

$$f(t) = \frac{1}{\sqrt{2\pi}} \int_{-\infty}^{\infty} \tilde{f}(\omega) e^{-i\omega t} d\omega \tag{75}$$

Parseval's theorem: $\int |f(t)|^2 dt = \int |\tilde{f}(\omega)|^2 d\omega$

C Units and Constants

Quantity	Symbol	Value
Speed of light (vacuum)	c	2.998×10^8 m/s
Permittivity of free space	ε_0	8.854×10^{-12} F/m
Permeability of free space	μ_0	$4\pi \times 10^{-7}$ H/m
Planck constant	h	6.626×10^{-34} J·s
Reduced Planck constant	$\hbar$	1.055×10^{-34} J·s
Elementary charge	e	1.602×10^{-19} C

Typical fiber parameters:

Parameter	Symbol	Typical Value
Core refractive index	n_{core}	1.45–1.47
Core diameter	$2a$	8–10 μm (SMF)
Attenuation (1550 nm)	α	0.15–0.25 dB/km
Dispersion (1550 nm)	D	15–18 ps/(nm·km)
Group velocity dispersion	β_2	-20 to -25 ps^2/km