

ASSIGNMENT 4

Name: - Kewal Jisaheb

ID NO.: - 21EL078

Division: - 11

Year: - 2023-24

Subject: - Digital System Design (3EL42)

Branch: - Electronics (EL)

Q1. BCD TIMECOUNT


VERILOG CODE:-

```
//////////////////////////////////////////  
module bcd_Count(  
    input clock, reset,  
    output reg [3:0]dout  
);  
    initial dout = 0;  
  
    always @ (posedge (clock))  
    begin  
        if (reset)  
            dout <= 0;  
        else if (dout <= 9)  
            dout <= dout + 1;  
        else if (dout == 9)  
            dout <= 0;  
    end  
endmodule
```

TEST BENCH:-

```
module bcdcounter_testbench();  
    reg clock, reset;  
    wire [3:0] dout;  
  
    bcd_counter dut(clock, reset, dout);  
    initial begin  
        clock=0;  
        forever #5 clock=~clock;  
    end  
    initial begin  
        reset=1;  
        #20;  
        reset=0;  
    end  
endmodule
```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

Start Writing Synthesis Report

Report BlackBoxes:

BlackBox name	Instances

Report Cell Usage:

Cell	Count
BUFG	1
LUT3	1
LUT4	4
FDRE	4
IBUF	2
OBUF	4

Report Instance Areas:

Instance	Module	Cells
top		16

Finished Writing Synthesis Report : Time (s): cpu = 00:00:18 ; elapsed = 00:00:22 . Memory (MB): peak = 1019.316 ; gain = 0.000

POWER REPORT:-


Summary

Power analysis from Implemented netlist. Activity derived from constraints files, simulation files or vectorless analysis.

Total On-Chip Power: 2.855 W
Design Power Budget: Not Specified
Power Budget Margin: N/A
Junction Temperature: 30.4°C
Thermal Margin: 54.6°C (28.8 W)
Effective θ_{JA} : 1.9°C/W
Power supplied to off-chip devices: 0 W
Confidence level: Low

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power



Q2.3-1 MUX


VERILOG CODE:-

```
module mux_2_1(  
    input sel,  
    input i0, i1,  
    output y);  
  
    assign y = sel ? i1 : i0;  
endmodule  
  
module mux_3_1(  
    input sel0, sel1,  
    input i0,i1,i2,i3,  
    output reg y);  
  
    wire y0, y1;  
  
    mux_2_1 m1(sel1, i0, i1, y0);  
    mux_2_1 m2(sel0, y0, i2, y);  
endmodule
```

TESTBENCH:-

```
module tb;  
    reg sel0, sel1;  
    reg i0,i1,i2,i3;  
    wire y;  
  
    mux_3_1 mux(sel0, sel1, i0, i1, i2, i3, y);  
  
    initial begin  
        $monitor("sel0=%b, sel1=%b -> i3 = %0b, i2 = %0b, i1 = %0b, i0 = %0b -> y = %0b", sel0, sel1, i3, i2, i1, i0, y);  
        {i3,i2,i1,i0} = 4'h5;  
  
        repeat(8) begin  
            {sel0, sel1} = $random;  
            #5;  
        end  
    end  
endmodule
```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

```
-----
Start Writing Synthesis Report
-----

Report BlackBoxes:
+-----+
| BlackBox name |Instances |
+-----+
+-----+

Report Cell Usage:
+-----+
| Cell |Count |
+-----+
|1| LUT5 | 1|
|2| IBUF | 5|
|3| OBUF | 1|
+-----+

Report Instance Areas:
+-----+
| Instance |Module |Cells |
+-----+
|1| top | | 7|
+-----+

-----
Finished Writing Synthesis Report : Time (s): cpu = 00:00:18 ; elapsed = 00:00:25 . Memory (MB): peak = 1014.996 ; gain = 0.000
-----
```

POWER REPORT:-


Summary

Power estimation from Synthesized netlist. Activity derived from constraints files, simulation files or vectorless analysis. Note: these early estimates can change after implementation.

Total On-Chip Power: 0.49 W
Design Power Budget: Not Specified
Power Budget Margin: N/A
Junction Temperature: 25.9°C
Thermal Margin: 59.1°C (31.2 W)
Effective θ_{JA} : 1.9°C/W
Power supplied to off-chip devices: 0 W
Confidence level: Low

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power



Q3. BCD TO SEVEN SEGMENT DISPLAY


VERILOG CODE:-

```
///////////////////////////////////////////////////  
module segment7(  
    bcd,  
    seg  
);  
  
    //Declare inputs,outputs and internal variables.  
    input [3:0] bcd;  
    output [6:0] seg;  
    reg [6:0] seg;  
  
    //always block for converting bcd digit into 7 segment format  
    always @(bcd)  
    begin  
        case (bcd) //case statement  
            0 : seg = 7'b0000001;  
            1 : seg = 7'b1001111;  
            2 : seg = 7'b0010010;  
            3 : seg = 7'b0000110;  
            4 : seg = 7'b1001100;  
            5 : seg = 7'b0100100;  
            6 : seg = 7'b0100000;  
            7 : seg = 7'b0001111;  
            8 : seg = 7'b0000000;  
            9 : seg = 7'b0000100;  
            //switch off 7 segment character when the bcd digit is not a decimal number.  
            default : seg = 7'b1111111;  
        endcase  
    end  
endmodule
```

TESTBENCH:-

```
module tb_segment7;  
  
    reg [3:0] bcd;  
    wire [6:0] seg;  
    integer i;  
  
    // Instantiate the Unit Under Test (UUT)  
    segment7 uut (  
        .bcd(bcd),  
        .seg(seg)  
    );  
  
    //Apply inputs  
    initial begin  
        for(i = 0;i < 16;i = i+1) //run loop for 0 to 15.  
        begin  
            bcd = i;  
            #10; //wait for 10 ns  
        end  
    end  
endmodule
```


RTL SCHEMATIC:-



SYNTHESIS REPORT:-

```
-----
Start Writing Synthesis Report
-----

Report BlackBoxes:
+-----+-----+
| BlackBox name | Instances |
+-----+-----+

Report Cell Usage:
+-----+-----+
| Cell | Count |
+-----+-----+
| 1 | LUT4 | 7 |
| 2 | IBUF | 4 |
| 3 | OBUF | 7 |
+-----+-----+

Report Instance Areas:
+-----+-----+
| Instance | Module | Cells |
+-----+-----+
| 1 | top | | 18 |
+-----+-----+

Finished Writing Synthesis Report : Time (s): cpu = 00:00:15 ; elapsed = 00:00:17 . Memory (MB): peak = 1016.211 ; gain = 0.000
-----
```

POWER REPORT:-


Summary

Power estimation from Synthesized netlist. Activity derived from constraints files, simulation files or vectorless analysis. Note: these early estimates can change after implementation.

Total On-Chip Power: 2.767 W
Design Power Budget: Not Specified
Power Budget Margin: N/A
Junction Temperature: 30.2°C
Thermal Margin: 54.8°C (28.9 W)
Effective θ_{JA} : 1.9°C/W
Power supplied to off-chip devices: 0 W
Confidence level: Low

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power



Q4. D LATCH USING 2:1 MUX

VERILOG CODE:-

```
module DFFusingMUX(input d1, d0, sel, clk, rst, output reg q);
    reg d;

    always @ (*)
    begin
        case(sel)
            0 : d = d0;
            1 : d = d1;
        endcase
    end

    always @(posedge clk)
    begin
        if(rst)
            q <= 0;
        else
            q <= d;
        end
    end
endmodule
```

TESTBENCH:-

```
module tb;
    reg d1,d0;
    reg clk;
    reg rst;
    wire q;


    d_latch d3(q,d1,d0,clk,rst);

    initial
    begin
        clk = 1'b0;
        forever #20 clk = ~clk ;
    end

    initial
    begin
        rst = 1'b1;
        #40;
        rst = 1'b0;
        #40;
        d0 = 1'b0;
        d1= 1'b0;
        #40
        d0 = 1'b1;
        d1 = 1'b0;
        #40;

        $finish ;
    end
endmodule
```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

```
-----
Start Writing Synthesis Report
-----

Report BlackBoxes:
+-----+
| BlackBox name | Instances |
+-----+
+-----+

Report Cell Usage:
+-----+
| Cell | Count |
+-----+
|1| BUFG | 1|
|2| LUT3 | 1|
|3| FDRE | 1|
|4| IBUF | 5|
|5| OBUF | 1|
+-----+

Report Instance Areas:
+-----+
| Instance | Module | Cells |
+-----+
|1| top | | 9|
+-----+

Finished Writing Synthesis Report : Time (s): cpu = 00:00:14 ; elapsed = 00:00:20 . Memory (MB): peak = 1019.727 ; gain = 0.000
-----
```

POWER REPORT:-


Summary

Power estimation from Synthesized netlist. Activity derived from constraints files, simulation files or vectorless analysis. Note: these early estimates can change after implementation.

Total On-Chip Power: 0.457 W
Design Power Budget: Not Specified
Power Budget Margin: N/A
Junction Temperature: 25.9°C
Thermal Margin: 59.1°C (31.2 W)
Effective θ_{JA} : 1.9°C/W
Power supplied to off-chip devices: 0 W
Confidence level: Low

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power



Q5. 8-BIT BARREL SHIFTER

VERILOG CODE:-

```
module barrel_shifter_8bit (in, ctrl, out);
    input [7:0] in;
    input [2:0] ctrl;
    output [7:0] out;
    wire [7:0] x,y;

    //4bit shift right
    mux2X1 ins_17 (.in0(in[7]),.in1(1'b0),.sel(ctrl[2]),.out(x[7]));
    mux2X1 ins_16 (.in0(in[6]),.in1(1'b0),.sel(ctrl[2]),.out(x[6]));
    mux2X1 ins_15 (.in0(in[5]),.in1(1'b0),.sel(ctrl[2]),.out(x[5]));
    mux2X1 ins_14 (.in0(in[4]),.in1(1'b0),.sel(ctrl[2]),.out(x[4]));
    mux2X1 ins_13 (.in0(in[3]),.in1(in[7]),.sel(ctrl[2]),.out(x[3]));
    mux2X1 ins_12 (.in0(in[2]),.in1(in[6]),.sel(ctrl[2]),.out(x[2]));
    mux2X1 ins_11 (.in0(in[1]),.in1(in[5]),.sel(ctrl[2]),.out(x[1]));
    mux2X1 ins_10 (.in0(in[0]),.in1(in[4]),.sel(ctrl[2]),.out(x[0]));

    //2 bit shift right

    mux2X1 ins_27 (.in0(x[7]),.in1(1'b0),.sel(ctrl[1]),.out(y[7]));
    mux2X1 ins_26 (.in0(x[6]),.in1(1'b0),.sel(ctrl[1]),.out(y[6]));
    mux2X1 ins_25 (.in0(x[5]),.in1(x[7]),.sel(ctrl[1]),.out(y[5]));
    mux2X1 ins_24 (.in0(x[4]),.in1(x[6]),.sel(ctrl[1]),.out(y[4]));
    mux2X1 ins_23 (.in0(x[3]),.in1(x[5]),.sel(ctrl[1]),.out(y[3]));
    mux2X1 ins_22 (.in0(x[2]),.in1(x[4]),.sel(ctrl[1]),.out(y[2]));
    mux2X1 ins_21 (.in0(x[1]),.in1(x[3]),.sel(ctrl[1]),.out(y[1]));
    mux2X1 ins_20 (.in0(x[0]),.in1(x[2]),.sel(ctrl[1]),.out(y[0]));

    //1 bit shift right
    mux2X1 ins_07 (.in0(y[7]),.in1(1'b0),.sel(ctrl[0]),.out(out[7]));
    mux2X1 ins_06 (.in0(y[6]),.in1(y[7]),.sel(ctrl[0]),.out(out[6]));
    mux2X1 ins_05 (.in0(y[5]),.in1(y[6]),.sel(ctrl[0]),.out(out[5]));
    mux2X1 ins_04 (.in0(y[4]),.in1(y[5]),.sel(ctrl[0]),.out(out[4]));
    mux2X1 ins_03 (.in0(y[3]),.in1(y[4]),.sel(ctrl[0]),.out(out[3]));
    mux2X1 ins_02 (.in0(y[2]),.in1(y[3]),.sel(ctrl[0]),.out(out[2]));

    //2 bit shift right

    mux2X1 ins_27 (.in0(x[7]),.in1(1'b0),.sel(ctrl[1]),.out(y[7]));
    mux2X1 ins_26 (.in0(x[6]),.in1(1'b0),.sel(ctrl[1]),.out(y[6]));
    mux2X1 ins_25 (.in0(x[5]),.in1(x[7]),.sel(ctrl[1]),.out(y[5]));
    mux2X1 ins_24 (.in0(x[4]),.in1(x[6]),.sel(ctrl[1]),.out(y[4]));
    mux2X1 ins_23 (.in0(x[3]),.in1(x[5]),.sel(ctrl[1]),.out(y[3]));
    mux2X1 ins_22 (.in0(x[2]),.in1(x[4]),.sel(ctrl[1]),.out(y[2]));
    mux2X1 ins_21 (.in0(x[1]),.in1(x[3]),.sel(ctrl[1]),.out(y[1]));
    mux2X1 ins_20 (.in0(x[0]),.in1(x[2]),.sel(ctrl[1]),.out(y[0]));

    //1 bit shift right
    mux2X1 ins_07 (.in0(y[7]),.in1(1'b0),.sel(ctrl[0]),.out(out[7]));
    mux2X1 ins_06 (.in0(y[6]),.in1(y[7]),.sel(ctrl[0]),.out(out[6]));
    mux2X1 ins_05 (.in0(y[5]),.in1(y[6]),.sel(ctrl[0]),.out(out[5]));
    mux2X1 ins_04 (.in0(y[4]),.in1(y[5]),.sel(ctrl[0]),.out(out[4]));
    mux2X1 ins_03 (.in0(y[3]),.in1(y[4]),.sel(ctrl[0]),.out(out[3]));
    mux2X1 ins_02 (.in0(y[2]),.in1(y[3]),.sel(ctrl[0]),.out(out[2]));
    mux2X1 ins_01 (.in0(y[1]),.in1(y[2]),.sel(ctrl[0]),.out(out[1]));
    mux2X1 ins_00 (.in0(y[0]),.in1(y[1]),.sel(ctrl[0]),.out(out[0]));

endmodule

////////////////////////
//2X1 Mux
////////////////////////

module mux2X1( in0,in1,sel,out);
    input in0,in1;
    input sel;
    output out;
    assign out=(sel)?in1:in0;
endmodule
```

TESTBENCH:-

```


) module barrel_shifter_8bit_tb;
    reg [7:0] in;
    reg [2:0] ctrl;
    wire [7:0] out;

    barrel_shifter_8bit uut(.in(in), .ctrl(ctrl), .out(out));

) initial
) begin
    $display($time, " << Starting the Simulation >>");
    in= 8'd0; ctrl=3'd0; //no shift
    #10 in=8'd128; ctrl= 3'd4; //shift 4 bit
    #10 in=8'd128; ctrl= 3'd2; //shift 2 bit
    #10 in=8'd128; ctrl= 3'd1; //shift by 1 bit
    #10 in=8'd255; ctrl= 3'd7; //shift by 7bit
) end
) initial begin
    $monitor("Input=%d, Control=%d, Output=%d",in,ctrl,out);
) end
) endmodule

```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

```
-----
Start Writing Synthesis Report
-----

Report BlackBoxes:
+-----+
| BlackBox name |Instances |
+-----+
+-----+

Report Cell Usage:
+-----+
| Cell |Count |
+-----+
|1| LUT3 | 3|
|2| LUT4 | 2|
|3| LUT5 | 3|
|4| LUT6 | 5|
|5| IBUF | 11|
|6| OBUF | 8|
+-----+

Report Instance Areas:
+-----+
| Instance |Module |Cells |
+-----+
|1| top | | 32|
+-----+

-----
Finished Writing Synthesis Report : Time (s): cpu = 00:00:13 ; elapsed = 00:00:16 . Memory (MB): peak = 1020.242 ; gain = 0.000
-----
```

POWER REPORT:-

Summary

Power estimation from Synthesized netlist. Activity derived from constraints files, simulation files or vectorless analysis. Note: these early estimates can change after implementation.

Total On-Chip Power:	2.904 W
Design Power Budget:	Not Specified
Power Budget Margin:	N/A
Junction Temperature:	30.5°C
Thermal Margin:	54.5°C (28.8 W)
Effective θ_{JA} :	1.9°C/W
Power supplied to off-chip devices:	0 W
Confidence level:	Low

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power

Dynamic:	2.817 W	(97%)
Device Static:	0.087 W	(3%)

93%

Signals:	0.132 W	(5%)
Logic:	0.045 W	(2%)
I/O:	2.639 W	(93%)

Q6. 1-BIT COMPARATOR USING 4X1 MUX


VERILOG CODE:-

```
////////////////////////////////////  
module comp_lbit(out, a, b, c, d, s0, s1);  
  
    output out;  
    input a, b, c, d, s0, s1;  
    wire sobar, slbar, T1, T2, T3, T4;  
  
    not (s0bar, s0), (slbar, s1);  
    and (T1, a, s0bar, slbar), (T2, b, s0bar, s1), (T3, c, s0, slbar), (T4, a, s0, s1);  
    or(out, T1, T2, T3, T4);  
  
endmodule
```

TESTBENCH:-

```
.....  
) module tb;  
  
    wire out;  
    reg a;  
    reg b;  
    reg c;  
    reg d;  
    reg s0, s1;  
  
    m41 name(.out(out), .a(a), .b(b), .c(c), .d(d), .s0(s0), .s1(s1));  
) initial  
) begin  
  
    a=1'b0; b=1'b0; c=1'b0;  
    s0=1'b0; s1=1'b0;  
    #500 $finish;  
  
) end  
  
    always #40 a=~a;  
    always #20 b=~b;  
    always #10 c=~c;  
    always #80 s0=~s0;  
    always #160 s1=~s1;  
  
) always@(a or b or c or s0 or s1)  
) $monitor("At time = %t, Output = %d", $time, out);  
  
) endmodule
```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

```
Start Writing Synthesis Report
-----

Report BlackBoxes:
+-----+
| BlackBox name |Instances |
+-----+
+-----+

Report Cell Usage:
+-----+
| Cell |Count |
+-----+
|1| LUT5 | 1|
|2| IBUF | 5|
|3| OBUF | 1|
+-----+

Report Instance Areas:
+-----+
| Instance |Module |Cells |
+-----+
|1| top | | 7|
+-----+

Finished Writing Synthesis Report : Time (s): cpu = 00:00:24 ; elapsed = 00:00:37 . Memory (MB): peak = 1021.613 ; gain = 0.000
-----
```

POWER REPORT:-


Summary

Power estimation from Synthesized netlist. Activity derived from constraints files, simulation files or vectorless analysis. Note: these early estimates can change after implementation.

Total On-Chip Power: 0.531 W
Design Power Budget: Not Specified
Power Budget Margin: N/A
Junction Temperature: 26.0°C
Thermal Margin: 59.0°C (31.1 W)
Effective θ_{JA} : 1.9°C/W
Power supplied to off-chip devices: 0 W
Confidence level: Low

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power



Q7.LOGICAL, ALGEBRAIC, AND ROTATE SHIFT OPERATIONS

VERILOG CODE:-

```
) module shift_rotate (a, opcode, result);
    input [7:0] a;
    input [2:0] opcode;
    output [7:0] result;
    wire [7:0] a;
    wire [2:0] opcode;
    reg [7:0] result;

    parameter sra_op = 3'b000,
               srl_op = 3'b001,
               sla_op = 3'b010,
               sll_op = 3'b011,
               ror_op = 3'b100,
               rol_op = 3'b101;

    always @ (a or opcode)
    begin
        case (opcode)
        ) sra_op : result = {a[7], a[7], a[6], a[5],
        ) a[4], a[3], a[2], a[1]};
        srl_op : result = a >> 1;
        sla_op : result = {a[6], a[5], a[4], a[3],
        ) a[2], a[1], a[0], 1'b0};
        sll_op : result = a << 1;
        ror_op : result = {a[0], a[7], a[6], a[5],
        ) a[4], a[3], a[2], a[1]};
        rol_op : result = {a[6], a[5], a[4], a[3],
        ) a[2], a[1], a[0], a[7]};
        default : result = 0;
        endcase
    end
endmodule
```

TESTBENCH:-

```

module shift_rotate_tb;

    reg [7:0] a;
    reg [2:0] opcode;
    wire [7:0] result;
    integer i;
    shift_rotate uut (
        .a(a),
        .opcode(opcode),
        .result(result)
    );

    initial begin
        a=8'b10110101;
        opcode = 000;

        end


        initial
        begin
            for(i=0;i<6;i=i+1)
            begin
                opcode=i;
                #10;
            end
        end

        initial
        $monitor(" A=%b | Opcode=%b | Result =%b ",a,opcode,result);

    endmodule

```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

Start Writing Synthesis Report

Report BlackBoxes:

```
+-----+
| BlackBox name | Instances |
+-----+
```

Report Cell Usage:

```
+-----+
| Cell | Count |
+-----+
| 1 | LUT5 | 7 |
| 2 | LUT6 | 1 |
| 3 | IBUF | 11 |
| 4 | OBUF | 8 |
+-----+
```

Report Instance Areas:

```
+-----+
| Instance | Module | Cells |
+-----+
| 1 | top | | 27 |
+-----+
```

Finished Writing Synthesis Report : Time (s): cpu = 00:00:23 ; elapsed = 00:00:33 . Memory (MB): peak = 1017.926 ; gain = 0.000

POWER REPORT:-


Summary

Power estimation from Synthesized netlist. Activity derived from constraints files, simulation files or vectorless analysis. Note: these early estimates can change after implementation.

Total On-Chip Power: 3.055 W
Design Power Budget: Not Specified
Power Budget Margin: N/A
Junction Temperature: 30.8°C
Thermal Margin: 54.2°C (28.6 W)
Effective θ_{JA} : 1.9°C/W
Power supplied to off-chip devices: 0 W
Confidence level: Low

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power



Q8. ALU

VERILOG CODE:-

```
.....  
module alu (a, b, opcode, rslt);  
  
input [3:0] a, b;  
input [2:0] opcode;  
output [7:0] rslt;  
  
reg [7:0] rslt;  
  
parameter add_op = 3'b000,  
sub_op = 3'b001,  
mul_op = 3'b010,  
and_op = 3'b011,  
or_op = 3'b100,  
not_op = 3'b101,  
xor_op = 3'b110,  
xnor_op = 3'b111;  
  
always @ (a or b or opcode)  
begin  
case (opcode)  
add_op: rslt = a + b;  
sub_op: rslt = a - b;  
mul_op: rslt = a * b;  
and_op: rslt = a & b; //also ab  
or_op: rslt = a | b;  
not_op: rslt = ~a; //also ~b  
xor_op: rslt = a ^ b;  
xnor_op: rslt = ~(a ^ b);  
endcase  
end  
endmodule
```


TEST BENCH:-

```

`timescale 1ns / 1ps
module alu_tb;
    reg [3:0] a;
    reg [3:0] b;
    reg [2:0] opcode;
    wire [7:0] rslt;
    alu uut (.a(a), .b(b), .opcode(opcode), .rslt(rslt));
    initial
    begin
        #0 a = 4'b0001; b = 4'b0010; opcode = 3'b000;
        #10 a = 4'b0110; b = 4'b0110; opcode = 3'b000;
        #10 a = 4'b1100; b = 4'b0011; opcode = 3'b001;
        #10 a = 4'b1101; b = 4'b1010; opcode = 3'b001;
        #10 a = 4'b1100; b = 4'b0111; opcode = 3'b010;
        #10 a = 4'b1111; b = 4'b0011; opcode = 3'b010;
        #10 a = 4'b1100; b = 4'b0111; opcode = 3'b011;
        #10 a = 4'b1101; b = 4'b1011; opcode = 3'b011;
        #10 a = 4'b0101; b = 4'b1011; opcode = 3'b100;
        #10 a = 4'b1001; b = 4'b1010; opcode = 3'b100;
        #10 a = 4'b1001; opcode = 3'b101;
        #10 a = 4'b0011; opcode = 3'b101;
        #10 a = 4'b0111; b = 4'b1011; opcode = 3'b110;
        #10 a = 4'b1010; b = 4'b0101; opcode = 3'b110;
        #10 a = 4'b0110; b = 4'b0110; opcode = 3'b111;
        #10 a = 4'b0011; b = 4'b1110; opcode = 3'b111;
    end
    initial
    begin
        $monitor(" A=%b | B=%b | Opcode = %b | Result=%b",a,b,opcode,rslt);
        #300 $finish;
    end
endmodule

```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

Start Writing Synthesis Report		
Report BlackBoxes:		
+	+	+
	BlackBox name	Instances
+	+	+
+	+	+
Report Cell Usage:		
+	+	+
	Cell	Count
+	+	+
1	CARRY4	2
2	LUT2	6
3	LUT4	6
4	LUT5	7
5	LUT6	19
6	MUXF7	3
7	IBUF	11
8	OBUF	8
+	+	+
Report Instance Areas:		
+	+	+
	Instance	Module Cells
+	+	+
1	top	62
+	+	+
Finished Writing Synthesis Report : Time (s): cpu = 00:00:17 ; elapsed = 00:00:21 . Memory (MB): peak = 1016.625 ; gain = 0.000		

POWER REPORT:-

Summary	
Power estimation from Synthesized netlist. Activity derived from constraints files, simulation files or vectorless analysis. Note: these early estimates can change after implementation.	
Total On-Chip Power:	4.409 W
Design Power Budget:	Not Specified
Power Budget Margin:	N/A
Junction Temperature:	33.3°C
Thermal Margin:	51.7°C (27.3 W)
Effective θJA:	1.9°C/W
Power supplied to off-chip devices:	0 W
Confidence level:	Low
Launch Power Constraint Advisor to find and fix invalid switching activity	
On-Chip Power	
<div><div>98%</div><div><div>Dynamic: 4.318 W (98%)</div><div><div>93%</div><div><div>Signals: 0.118 W (3%)</div><div>Logic: 0.168 W (4%)</div><div>I/O: 4.032 W (93%)</div></div></div><div>Device Static: 0.091 W (2%)</div></div></div>	

Q9. 4-BIT ASYNCHRONOUS DOWN COUNTER

VERILOG CODE:-

```
module dff(q,qbar,clk,rst,d);
    output reg q;
    output qbar;
    input clk, rst;
    input d;

    assign qbar = ~q;

    always @(posedge clk, posedge rst)
    begin
        if (rst)
            q <= 0;
        else
            q <= d;
    end
endmodule

module async_counter(count,countbar,clk,rst);
    input clk, rst;
    output [3:0] count, countbar;
    dff dff1(count[0],countbar[0],clk,rst,countbar[0]);
    dff dff2(count[1],countbar[1],count[0],rst,countbar[1]);
    dff dff3(count[2],countbar[2],count[1],rst,countbar[2]);
    dff dff4(count[3],countbar[3],count[2],rst,countbar[3]);

endmodule
```

TESTBENCH:-

```
module async_counter_tb;

    // Inputs
    reg clk;
    reg rst;


    // Outputs
    wire [3:0] count;
    wire [3:0] countbar;

    // Instantiate the Unit Under Test (UUT)
    async_counter uut (
        .count(count),
        .countbar(countbar),
        .clk(clk),
        .rst(rst)
    );

    initial
    begin
        clk = 0;
        rst = 1;
        #23; // Just give enough time to reset the design
        rst = 0;
        #200;
        $finish;
    end
    always #5 clk = ~clk;

endmodule
```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

Start Writing Synthesis Report

Report BlackBoxes:

BlackBox name	Instances
---------------	-----------

Report Cell Usage:

Cell	Count
BUFG	1
LUT1	4
FDCE	4
IBUF	2
OBUF	8

Report Instance Areas:

Instance	Module	Cells
top		19
dff1	dff_0	2
dff2	dff_0	2
dff3	dff_1	2
dff4	dff_2	2

Finished Writing Synthesis Report : Time (s): cpu = 00:00:27 ; elapsed = 00:00:37 . Memory (MB): peak = 1017.906 ; gain = 0.000

POWER REPORT:-

Summary

Power estimation from Synthesized netlist. Activity derived from constraints files, simulation files or vectorless analysis. Note: these early estimates can change after implementation.

Total On-Chip Power:16.203 W

Design Power Budget:Not Specified

Power Budget Margin:N/A

Junction Temperature:55.5°C

Thermal Margin:29.5°C (15.5 W)

Effective θJA:1.9°C/W

Power supplied to off-chip devices: 0 W

Confidence level:Low

Launch Power Constraint Advisor to find and fix invalid switching activity

On-Chip Power

99%

Dynamic:16.062 W (99%)

94%

Signals:0.781 W (5%)

Logic:0.074 W (1%)

I/O:15.207 W (94%)

Device Static:0.141 W (1%)

Q10. MOD-N UPDOWN COUNTER

VERILOG CODE:-

```
`timescale 1ns / 1ps
| module modN_counter
|   # (parameter N = 10,
|     parameter WIDTH = 4)
|
|   ( input  clk,
|     input  reset,
|     input  upordown,
|     output reg[WIDTH-1:0] count);
|
|   always @ (posedge clk )
|   begin
|     if (reset==1)
|       count <= 0;
|
|     else
|       if(upordown==1)      //Up Mode is selected
|         if (count == N-1)
|           count <= 0;
|         else
|           count<=count+1; //increment counter
|
|       else                 //Down Mode is selected
|         if(count==0)
|           count<=N-1;
|         else
|           count<=count-1; //Decrement the counter
|
|   end
| endmodule
```


TESTBENCH:-

```

`timescale 1ns / 1ps
module modN_updown_tb;
    reg clk;
    reg reset;
    reg upordown;
    wire [3:0] count;
    modN_counter uut (
        .clk(clk),
        .reset(reset),
        .upordown(upordown),
        .count(count)
    );
    initial begin
        clk = 0;
        reset = 1;
        #50 reset = 0; upordown = 0;
        #200;
        upordown = 1;
        #200;
        reset = 1;
        upordown = 0;
        #100;
        reset = 0;
    end
    always #10 clk=~clk;
    initial
    begin
        $monitor("UporDown=%b | Count=%b",upordown,count);
        #1000 $finish;
    end
endmodule

```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

Start Writing Synthesis Report

Report BlackBoxes:

BlackBox name	Instances

Report Cell Usage:

Cell	Count
1	BUFG 1
2	LUT1 1
3	LUT5 3
4	FDRE 4
5	IBUF 3
6	OBUF 4

Report Instance Areas:

Instance	Module	Cells
1	top	16

Finished Writing Synthesis Report : Time (s): cpu = 00:00:18 ; elapsed = 00:00:22 . Memory (MB): peak = 1015.855 ; gain = 0.000

POWER REPORT:-

Summary

Power estimation from Synthesized netlist. Activity derived from constraints files, simulation files or vectorless analysis. Note: these early estimates can change after implementation.

Total On-Chip Power: 3.805 W

Design Power Budget: Not Specified

Power Budget Margin: N/A

Junction Temperature: 32.2°C


Thermal Margin: 52.8°C (27.9 W)

Effective SJA: 1.9°C/W

Power supplied to off-chip devices: 0 W

Confidence level: Low

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity



Q11. UNIVERSAL BINARY COUNTER

VERILOG CODE:-

```
`timescale 1ns / 1ps
module univ_bin_counter
#(parameter N=8)
(
input wire clk, reset,
input wire syn_clr , load, en, up,
input wire [N-1:0] d,
output wire max, min,
output wire [N-1:0] q
);
reg [N-1:0] r_reg, r_next;
always @(posedge clk, posedge reset)
if (reset)
r_reg <= 0; //
else
r_reg <= r_next;
always @(*)
if (syn_clr)
r_next = 0;
else if (load)
r_next = d;
else if (en & up)
r_next = r_reg + 1;
else if (en & ~up)
r_next = r_reg - 1;
else
r_next = r_reg;
assign q = r_reg;
assign max = (r_reg==2**N-1) ? 1'b1 : 1'b0;
assign min = (r_reg==0) ? 1'b1 : 1'b0;
endmodule
```

TESTBENCH:-

```
`timescale 1ns / 1ps
module univ_bin_counter_tb;
reg clk;
reg reset;
reg syn_clr;
reg load;
reg en;
reg up;
reg [7:0] d;
wire max;
wire min;
wire [7:0] q;
univ_bin_counter uut (.clk(clk), .reset(reset), .syn_clr(syn_clr), .load(load), .en(en), .up(up), .d(d), .max(max), .min(min), .q(q));
initial begin
clk = 0;
reset = 0;
syn_clr = 0;
load = 0;
en = 0;
up = 0;
d = 0;
#10 reset =1; syn_clr=1; load=1; en=1;up=1; d=1;
#10 reset =0; syn_clr=0; load=1; en=1;up=1; d=1;
#10 reset =0; syn_clr=0; load=0; en=1;up=1; d=1;
#400 reset =0;syn_clr=0 ; load=0; en=1;up=0; d=1;
end
always #5 clk=~clk;
initial
begin
$monitor(" Reset=%b | Sync_clr=%b | Load=%b| En=%b | Up=%b| D=%b | Q=%b",reset,syn_clr,load,en,up,d,q);
#1000 $finish;
end
endmodule
```



```

Start Writing Synthesis Report
-----

Report BlackBoxes:
+-----+-----+
| BlackBox name | Instances |
+-----+-----+

Report Cell Usage:
+-----+-----+
| Cell | Count |
+-----+-----+
|1| BUFG | 1|
|2| CARRY4 | 2|
|3| LUT1 | 1|
|4| LUT2 | 6|
|5| LUT3 | 2|
|6| LUT4 | 10|
|7| LUT5 | 2|
|8| FDCE | 8|
|9| IBUF | 14|
|10| OBUF | 10|
+-----+-----+

Report Instance Areas:
+-----+-----+-----+
| Instance | Module | Cells |
+-----+-----+-----+
|1| top | | 56|
+-----+-----+-----+

-----
Finished Writing Synthesis Report : Time (s): cpu = 00:00:26 ; elapsed = 00:00:34 . Memory (MB): peak = 1019.758 ; gain = 0.000

```

POWER REPORT:-


Summary

Power estimation from Synthesized netlist. Activity derived from constraints files, simulation files or vectorless analysis. Note: these early estimates can change after implementation.

Total On-Chip Power: 3.709 W
Design Power Budget: Not Specified
Power Budget Margin: N/A
Junction Temperature: 32.0°C
Thermal Margin: 53.0°C (28.0 W)
Effective θ_{JA} : 1.9°C/W
Power supplied to off-chip devices: 0 W
Confidence level: Low

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power



Q12. UNIVERSAL SHIFT REGISTER

VERILOG CODE:-


```
`timescale 1ns / 1ps
module universal_shiftreg(DATAOUT, clock, reset, MODE, DATAIN);
    output reg [3:0] DATAOUT;
    input clock, reset;
    input [1:0] MODE;
    input [3:0] DATAIN;

    always @(posedge clock)
    begin
        if(reset)
            DATAOUT <= 0;
        else
            begin
                case (MODE)
                    2'b00 : DATAOUT <= DATAOUT;    // locked mode, do nothing
                    2'b01 : DATAOUT <= {DATAIN[0], DATAIN[3:1]}; //DATAOUT >> 1;
                    2'b10 : DATAOUT <= {DATAIN[2:0], DATAIN[3]}; //DATAOUT << 1;
                    2'b11 : DATAOUT <= DATAIN;      // parallel in parallel out
                endcase
            end
        end
    end
endmodule
```

TESTBENCH:-

```
`timescale 1ns / 1ps
module univ_bin_counter_tb;
    reg clk;
    reg reset;
    reg syn_clr;
    reg load;
    reg en;
    reg up;
    reg [7:0] d;
    wire max;
    wire min;
    wire [7:0] q;
    univ_bin_counter uut (.clk(clk), .reset(reset), .syn_clr(syn_clr), .load(load), .en(en), .up(up), .d(d), .max(max), .min(min), .q(q));
    initial begin
        clk = 0;
        reset = 0;
        syn_clr = 0;
        load = 0;
        en = 0;
        up = 0;
        d = 0;
        #10 reset =1; syn_clr=1; load=1; en=1;up=1; d=1;
        #10 reset =0; syn_clr=0; load=1; en=1;up=1; d=1;
        #10 reset =0; syn_clr=0; load=0; en=1;up=1; d=1;
        #400 reset =0;syn_clr=0 ; load=0; en=1;up=0; d=1;
    end
    always #5 clk=~clk;
    initial
    begin
        $monitor(" Reset=%b | Sync_clr=%b | Load=%b| En=%b | Up=%b| D=%b | Q=%b",reset,syn_clr,load,en,up,d,q);
        #1000 $finish;
    end
endmodule
```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

Start Writing Synthesis Report

Report BlackBoxes:

BlackBox name	Instances

Report Cell Usage:

Cell	Count
BUFG	1
LUT2	1
LUT5	4
FDRE	4
IBUF	8
OBUF	4

Report Instance Areas:

Instance	Module	Cells
1	top	22

Finished Writing Synthesis Report : Time (s): cpu = 00:00:25 ; elapsed = 00:00:35 . Memory (MB): peak = 1017.617 ; gain = 0.000


POWER REPORT:-

Summary

Power estimation from Synthesized netlist. Activity derived from constraints files, simulation files or vectorless analysis. Note: these early estimates can change after implementation.

Total On-Chip Power: 1.333 W
Design Power Budget: Not Specified
Power Budget Margin: N/A
Junction Temperature: 27.5°C
Thermal Margin: 57.5°C (30.3 W)
Effective θ_{JA} : 1.9°C/W
Power supplied to off-chip devices: 0 W
Confidence level: Low
[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power



Q13. CN(CHANGE-NO CHANGE FLIPFLOP) USING 2:1 MUX

VERILOG CODE:-

```
module mux2X1(a,b,s,y);
input a,b,s;
output reg y;
always @(a or b or s)
begin
case(s)
0: y=a;
1: y=b;
default: y=1'b0;
endcase
end
endmodule

module d_ff(d,clk,reset,q);
input d,clk,reset;
output reg q;
always @(posedge clk)
begin
if(reset)
q=0;
else
q=d;
end
endmodule

module cn_flipflop(c,n,clk,q,qbar);
input c,n,clk;
output q,qbar;
wire cn,n_bar,d_wire;
mux2X1 mux1(1'b0,c,n,cn);
mux2X1 mux2(1'b1,1'b0,n,n_bar);
mux2X1 mux3(cn,n_bar,q,d_wire);
d_ff dff1(.d(d_wire),.clk(clk),.reset(),.q(q));
assign qbar=~q;
endmodule
```

TESTBENCH:-


```
`timescale 1ns / 1ps
module cn_flipflop_tb;

    reg c;
    reg n;
    reg clk;
    wire q,qbar;

    cn_flipflop uut (.c(c),.n(n),.clk(clk),.q(q),.qbar(qbar));

    initial begin
        c = 0;
        n = 0;
        clk = 0;
        #10 c=0;n=1;
        #10 c=1;n=0;
        #10 c=1;n=1;
    end
    always #5 clk=~clk;
    initial
    begin $monitor("C=%b | N=%b | Q=%b | Qbar=%b",c,n,q,qbar);
        #100 $finish;
    end
endmodule
```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

Start Writing Synthesis Report

Report BlackBoxes:

BlackBox name	Instances

Report Cell Usage:

Cell	Count
BUFG	1
LUT1	1
LUT3	1
FDRE	1
IBUF	3
OBUF	2

Report Instance Areas:

Instance	Module	Cells
top		9
dff1	d_ff	3

Finished Writing Synthesis Report : Time (s): cpu = 00:00:24 ; elapsed = 00:00:34 . Memory (MB): peak = 1014.594 ; gain = 0.000

POWER REPORT:-


Summary

Power estimation from Synthesized netlist. Activity derived from constraints files, simulation files or vectorless analysis. Note: these early estimates can change after implementation.

Total On-Chip Power: 0.856 W
Design Power Budget: Not Specified
Power Budget Margin: N/A
Junction Temperature: 26.6°C
Thermal Margin: 58.4°C (30.8 W)
Effective θ_{JA} : 1.9°C/W
Power supplied to off-chip devices: 0 W
Confidence level: Low

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power



Q14.FREQUENCY DIVIDER BY ODD NUMBERS

VERILOG CODE:-

```
`timescale 1ns / 1ps
module clk_div_odd
#(parameter N=5)
( input  clk_in,output  clk_out);

reg  [3:0] count = 4'b0;
reg    A1 = 0;
reg    B1 = 0;
reg    Tff_A = 0;
reg    Tff_B = 0;
wire    clock_out;
wire    wTff_A;
wire    wTff_B;
assign  wTff_A  = Tff_A;
assign  wTff_B  = Tff_B;

assign  clk_out = wTff_B ^ wTff_A;
always@(posedge clk_in)
begin
    if(count == N-1)
    begin
        count <= 4'b0000;
    end
    else
    begin
        count <= count + 1;
    end
end
always@(posedge clk_in)
begin
    if(count == 4'b0000)
        A1 <= 1;
    else
        A1 <= 0;
end
end
```

```

|   A1 <= 0;
|   end
| always@(posedge clk_in)
|   begin
|       if(count == (N+1)/2)
|           B1 <= 1;
|       else
|           B1 <= 0;
|       end
|   always@(negedge A1)
|   begin
|       Tff_A <= ~Tff_A;
|   end

|   always@(negedge clk_in)
|   begin
|       if(B1)
|           begin
|               Tff_B <= ~Tff_B;
|           end
|       end
|   end
| endmodule

```

TESTBENCH:-

```

`timescale 1ns / 1ps
) module clk_div_odd_tb;
    reg clk_in;
    wire clk_out;
    clk_div_odd uut (
        .clk_in(clk_in),
        .clk_out(clk_out)
    );

    initial begin
        clk_in=1;
    end


    always #10 clk_in= ~clk_in;

    initial
    #200 $finish;

) endmodule

```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

Start Writing Synthesis Report

Report BlackBoxes:

BlackBox name	Instances

Report Cell Usage:

Cell	Count
BUFG	1
LUT1	2
LUT2	3
LUT3	1
LUT4	4
FDRE	8
IBUF	1
OBUF	1

Report Instance Areas:

Instance	Module	Cells
1	top	21

Finished Writing Synthesis Report : Time (s): cpu = 00:00:25 ; elapsed = 00:00:34 . Memory (MB): peak = 1015.637 ; gain = 0.000

POWER REPORT:-

Summary

Power estimation from Synthesized netlist. Activity derived from constraints files, simulation files or vectorless analysis. Note: these early estimates can change after implementation.

Total On-Chip Power:	2.168 W
Design Power Budget:	Not Specified
Power Budget Margin:	N/A
Junction Temperature:	29.1°C
Thermal Margin:	55.9°C (29.5 W)
Effective θ_{JA} :	1.9°C/W
Power supplied to off-chip devices:	0 W
Confidence level:	Low

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power

96%

Dynamic: 2.083 W (96%)

86%

Device Static: 0.085 W (4%)

Signals: 0.175 W (8%)

Logic: 0.120 W (6%)

I/O: 1.788 W (86%)

Q15. GREATEST COMMON DIVISOR USING BEHAVIOURAL MODELLING

VERILOG CODE:-

```
`timescale 1ns / 1ps
> module gcd_beh #( parameter W = 4)
(
    input [W-1:0] A, B,
    input clk,rst,
    output reg [W-1:0] GCD
);
    reg [W-1:0] Ain, Bin;
> always @(posedge clk or negedge rst)
> begin
    Ain = A; Bin = B;
> while( Ain != Bin)
> begin
> if ( Ain < Bin )
    Bin = Bin-Ain;
    else
> Ain = Ain - Bin;
> end
    GCD = Ain;
> end
> endmodule
```

TESTBENCH:-

```
`timescale 1ns / 1ps
> module gcd_beh_tb;
    parameter W=7;
    reg [W-1:0] A;
    reg [W-1:0] B;
    wire [W-1:0] GCD;
    gcd_beh uut ( .A(A) , .B(B) , .GCD(GCD) );
>    initial begin
        A=90;B=86;
        #10 A=48; B=12;
        #10 A=65;B=4;
        #10 A=48;B=7;
        #10 A=8;B=2;
        #10 A=125;B=6;
        #10 A=85;B=76;
        #10 A=54;B=44;
        #10 A=95;B=32;
        #10 A=109;B=91;
        #10 A=75;B=34;
>    end
>    initial
>    begin
        $monitor("A= %d | B=%d | GCD=%d", A,B,GCD);
        #200 $finish;
>    end
> endmodule
```

Q16.SINGLE PORT RAM

VERILOG CODE:-

```
module single_port_ram
#(parameter addr_width = 6,
parameter data_width = 8,
parameter depth = 64)
(
    input [data_width-1:0] data,
    input [addr_width-1:0] addr,
    input we,clk,
    output [data_width-1:0] q
);

    reg [data_width-1:0] ram [depth-1:0];


    reg [addr_width-1:0] addr_reg;

    always @(posedge clk)
    begin
        if (we)
            ram[addr] <=data;
        else
            addr_reg <=addr;
    end
    assign q= ram[addr_reg];
endmodule
```

TESTBENCH:-

```
`timescale 1ns / 1ps
module single_port_ram_tb;
parameter addr_width = 6;
parameter data_width = 8;
parameter depth = 64;
    reg [data_width-1:0] data;
    reg [addr_width:0] addr;
    reg we;
    reg clk;
    wire [data_width-1:0] q;
    single_port_ram uut (.data(data),.addr(addr), .we(we),.clk(clk),.q(q));
    initial begin
        clk=0;
        forever #5 clk=~clk;
    end
    initial begin
        data=8'h01;
        addr=5'd0;
        we=1'b1;
        #10
        data=8'h02;
        addr=5'd1;
        #10;
        data=8'h03;
        addr=5'd2;
        #10;
        addr=5'd0;
        we=1'b0;
        #10;
        addr=5'd1;
        #10;
        addr=5'd2;
        #10;
    end
endmodule
```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

```
-----
Start Writing Synthesis Report
-----

Report BlackBoxes:
+-----+-----+
| BlackBox name | Instances |
+-----+-----+

Report Cell Usage:
+-----+-----+
| Cell          | Count |
+-----+-----+
|1| BUFG         | 1|
|2| LUT1         | 1|
|3| RAM64M       | 2|
|4| RAM64X1D     | 2|
|5| FDRE         | 6|
|6| IBUF         | 16|
|7| OBUF         | 8|
+-----+-----+

Report Instance Areas:
+-----+-----+
| Instance | Module | Cells |
+-----+-----+
|1| top      |        | 36|
+-----+-----+

Finished Writing Synthesis Report : Time (s): cpu = 00:00:13 ; elapsed = 00:00:18 . Memory (MB): peak = 1017.363 ; gain = 0.000
-----
```


POWER REPORT:-


Summary

Power analysis from Implemented netlist. Activity derived from constraints files, simulation files or vectorless analysis.

Total On-Chip Power: 2.194 W
Design Power Budget: Not Specified
Power Budget Margin: N/A
Junction Temperature: 29.1°C
Thermal Margin: 55.9°C (29.5 W)
Effective θ_{JA} : 1.9°C/W
Power supplied to off-chip devices: 0 W
Confidence level: Low

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power



Q17. DUAL PORT RAM

VERILOG CODE:-

```
module dual_port_ram
# (parameter data_width=8,
  parameter addr_width=4,
  parameter depth=16
)
(
  input clk,
  input wr_en,
  input [data_width-1:0] data_in,
  input [addr_width-1:0] addr_in_0,
  input [addr_width-1:0] addr_in_1,
  input port_en_0,
  input port_en_1,
  output [data_width-1:0] data_out_0,
  output [data_width-1:0] data_out_1
);

  reg [data_width-1:0] ram[0:depth-1];

always@(posedge clk)
begin
  if(port_en_0 == 1 && wr_en == 1)
    ram[addr_in_0] <= data_in;
end

assign data_out_0 = port_en_0 ? ram[addr_in_0] : 'dZ;
assign data_out_1 = port_en_1 ? ram[addr_in_1] : 'dZ;

endmodule
```

TESTBENCH:-


```
module dual_port_ram_tb;
parameter addr_width = 4;
parameter data_width = 8;
parameter depth = 16;
integer i;
reg clk;
reg wr_en;
reg [data_width-1:0] data_in;
reg [addr_width-1:0] addr_in_0;
reg [addr_width-1:0] addr_in_1;
reg port_en_0;
reg port_en_1;
wire [data_width-1:0] data_out_0;
wire [data_width-1:0] data_out_1;
dual_port_ram uut (.clk(clk), .wr_en(wr_en), .data_in(data_in), .addr_in_0(addr_in_0), .addr_in_1(addr_in_1), .port_en_0(port_en_0), .port_en_1(port_en_1),
.data_out_0(data_out_0), .data_out_1(data_out_1));
always
#5 clk = ~clk;
initial begin
  clk = 1;
  addr_in_1 = 0;
  port_en_0 = 0;
  port_en_1 = 0;
  wr_en = 0;
  data_in = 0;
  addr_in_0 = 0;
  #20;
  port_en_0 = 1;
  wr_en = 1;
  for(i=1; i <= 16; i = i + 1) begin
    data_in = i;
    addr_in_0 = i-1;
    #10;
  end
  wr_en = 0;
```

```

    wr_en = 0;
    port_en_0 = 0;
    port_en_1 = 1;
    for(i=1; i <= 16; i = i + 1) begin
        addr_in_1 = i-1;
        #10;
    end
    port_en_1 = 0;
end
endmodule

```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

Start Writing Synthesis Report

Report BlackBoxes:

BlackBox name	Instances

Report Cell Usage:

Cell	Count
BUFG	1
LUT1	2
LUT2	1
RAM16X1D	8
IBUF	20
OBUFT	16

Report Instance Areas:

Instance	Module	Cells
top		48

Finished Writing Synthesis Report : Time (s): cpu = 00:00:14 ; elapsed = 00:00:20 . Memory (MB): peak = 1018.852 ; gain = 0.000


POWER REPORT:-

Summary

Power estimation from Synthesized netlist. Activity derived from constraints files, simulation files or vectorless analysis. Note: these early estimates can change after implementation.

Total On-Chip Power: 2.233 W
Design Power Budget: Not Specified
Power Budget Margin: N/A
Junction Temperature: 29.2°C
Thermal Margin: 55.8°C (29.4 W)
Effective θ_{JA} : 1.9°C/W
Power supplied to off-chip devices: 0 W
Confidence level: Low
[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power



Q18. CLOCK BUFFER

VERILOG CODE:-

```
`timescale 1ns / 1ps
module clock_buffer(mclk,bclk);
    input mclk;
    output bclk;
    buf b1(bclk,mclk);
endmodule
```

TESTBENCH:-

```
`timescale 1ns / 1ps
module clock_buffer_tb();
    reg mclk;
    wire bclk;
    realtime t1,t2,t3,t4,t5,t6;
    parameter T=10;
    clock_buffer dut(mclk,bclk);
    initial
    begin
        mclk=1'b0;
        forever #(T/2) mclk=~mclk;
    end
    task master;
    begin
        @(posedge mclk) t1=$realtime;
        @(posedge mclk) t2=$realtime;
        t3=t2-t1;
    end
    endtask
    task bufout;
    begin
        @(posedge bclk) t4=$realtime;
        @(posedge bclk) t5=$realtime;
        t6=t5-t4;
    end
    endtask
    task freq_phase;
    realtime f,p;
    begin
        f=t6-t3;
        p=t4-t1;
        $display("freq_diff=%0t,phase_diff=%0t",f,p);
    end
    endtask
    initial
    begin
        fork master;
        bufout;
        join freq_phase;
    end
endmodule
```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

Start Writing Synthesis Report

Report BlackBoxes:

```
+-----+
| BlackBox name |Instances |
+-----+
+-----+
```

Report Cell Usage:

```
+-----+
| Cell |Count |
+-----+
|1 |IBUF | 1|
|2 |OBUF | 1|
+-----+
```

Report Instance Areas:

```
+-----+
| Instance |Module |Cells |
+-----+
|1 |top | | 2|
+-----+
```

Finished Writing Synthesis Report : Time (s): cpu = 00:00:14 ; elapsed = 00:00:16 . Memory (MB): peak = 1015.395 ; gain = 0.000

POWER REPORT:-


Summary

Power estimation from Synthesized netlist. Activity derived from constraints files, simulation files or vectorless analysis. Note: these early estimates can change after implementation.

Total On-Chip Power: 0.333 W
Design Power Budget: Not Specified
Power Budget Margin: N/A
Junction Temperature: 25.6°C
Thermal Margin: 59.4°C (31.3 W)
Effective θ_{JA} : 1.9°C/W
Power supplied to off-chip devices: 0 W
Confidence level: Low

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power



Q19. SYNCHRONOUS FIFO

VERILOG CODE:-

```
module sync_fifo (input [7:0] data_in, input clk, rst, rd, wr,
output empty, full, output reg [3:0] fifo_cnt,
output reg [7:0] data_out);

    reg [7:0] fifo_ram [0:7];
    reg [2:0] rd_ptr, wr_ptr;
    assign empty= (fifo_cnt==0);
    assign full =(fifo_cnt==8);
    always @(posedge clk) begin: write
    if (wr && ! full)
    fifo_ram [wr_ptr] <= data_in;
    else if (wr && rd)
    fifo_ram [wr_ptr] <= data_in;
    end

    //Read and Write Clock
    always @ (posedge clk) begin: read
    if (rd && !empty)
    data_out <= fifo_ram [rd_ptr];
    else if (rd && wr)
    data_out <= fifo_ram [rd_ptr];
    end

    //pointer block
    always @(posedge clk) begin: pointer
    if (rst) begin
    wr_ptr <= 0;
    rd_ptr <= 0;
    end
    else begin
    wr_ptr <= ((wr && ! full) || (wr && rd)) ? wr_ptr+1 :
    wr_ptr;
    end
    end
```



```

    wr_ptr;
    rd_ptr <= ((rd && !empty) || (wr && rd)) ? rd_ptr+1:
    rd_ptr;
end
end

//counter
always @(posedge clk) begin: count
    if (rst) fifo_cnt <= 0;
    else begin
        case ({wr, rd})
            2'b00: fifo_cnt <= fifo_cnt;
            2'b01: fifo_cnt <= (fifo_cnt==0) ? 0: fifo_cnt-1;
            2'b10: fifo_cnt <= (fifo_cnt==8) ? 8: fifo_cnt+1;
            2'b11 : fifo_cnt <= fifo_cnt;
            default: fifo_cnt <= fifo_cnt;
        endcase
    end
end
endmodule

```

TESTBENCH:-

```
) module sync_fifo_tb();
  reg clk, rst, wr, rd ;
  reg[7:0] data_in;
  reg[7:0] tempdata;
  wire [7:0] data_out;
  wire [3:0] fifo_cnt;

  sync_fifo fifo( .clk(clk), .rst(rst), .data_in(data_in), .data_out(data_out),
    .wr(wr), .rd(rd), .empty(empty),
    .full(full), .fifo_cnt(fifo_cnt) );

) initial
) begin
  clk = 0;
  rst = 1;
  rd = 0;
  wr = 0;
  tempdata = 0;
  data_in = 0;

  #15 rst = 0;

  push(1);
  fork
    push(2);
    pop(tempdata);
  join
  push(10);
  push(20);
  push(30);
  push(40);
  push(50);
  push(60);
  push(70);
```

```
        push(70);
        push(80);
        push(90);
        push(100);
        push(110);
        push(120);
        push(130);

        pop(tempdata);
        push(tempdata);
        pop(tempdata);
        pop(tempdata);
        pop(tempdata);
        pop(tempdata);
        push(140);
        pop(tempdata);
        push(tempdata); //
        pop(tempdata);
        pop(tempdata);
        pop(tempdata);
        pop(tempdata);
        pop(tempdata);
        pop(tempdata);
        pop(tempdata);
        pop(tempdata);
        pop(tempdata);
        push(5);
        pop(tempdata);
    } end

    } always
    #5 clk = ~clk;
```

```

always
    #5 clk = ~clk;

task push;
input[7:0] data;

    if( full )
        $display("---Cannot push: FIFO Full---");
    else
        begin
            $display("Pushed ",data );
            data_in = data;
            wr= 1;
            @(posedge clk);
            #1 wr = 0;
        end

    endtask

task pop;
output [7:0] data;

    if( empty )
        $display("---Cannot Pop: FIFO Empty---");
    else
        begin

            rd = 1;
            @(posedge clk);


            #1 rd = 0;
            data = data_out;
            $display("-----Poped ", data);

        end
    endtask

endmodule

```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

Start Writing Synthesis Report

Report BlackBoxes:

BlackBox name	Instances

Report Cell Usage:

Cell	Count
BUFG	1
LUT2	3
LUT3	2
LUT4	4
LUT5	4
LUT6	4
RAM32M	2
FDRE	18
IBUF	12
OBUF	14

Report Instance Areas:

Instance	Module	Cells
1	top	64

Finished Writing Synthesis Report : Time (s): cpu = 00:00:14 ; elapsed = 00:00:16 . Memory (MB): peak = 1017.957 ; gain = 0.000

POWER REPORT:-


Summary

Power analysis from Implemented netlist. Activity derived from constraints files, simulation files or vectorless analysis.

Total On-Chip Power: 3.239 W
Design Power Budget: Not Specified
Power Budget Margin: N/A
Junction Temperature: 31.1°C
Thermal Margin: 53.9°C (28.4 W)
Effective θ_{JA} : 1.9°C/W
Power supplied to off-chip devices: 0 W
Confidence level: Low

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power



Q20. PRIORITY ENCODER


VERILOG CODE:-

```
module pri_en(d,y,en);  
input [7:0] d;  
input en;  
output [2:0] y;  
reg [2:0] y;  
always @(d or en )  
begin  
if(en)  
begin  
casex(d)  
8'b00000001:y=3'b000;  
8'b0000001x:y=3'b001;  
8'b000001xx:y=3'b010;  
8'b00001xxx:y=3'b011;  
8'b0001xxxx:y=3'b100;  
8'b001xxxxx:y=3'b101;  
8'b01xxxxxx:y=3'b110;  
8'b1xxxxxxx:y=3'b111;  
endcase  
end  
else  
begin  
y=3'bxxx;  
end  
end  
endmodule
```

TEST BENCH:-

```
module pri_en_tb();
reg [7:0] d;
reg en;
wire [2:0] y;
pri_en dut(d,y,en);
initial
begin
en=1'b1;
d=8'b00000001; #10;
d=8'b00000011; #10;
d=8'b00000101; #10;
d=8'b00001001; #10;
d=8'b00010001; #10;
d=8'b00010001; #10;
d=8'b00110001; #10;
d=8'b01110001; #10;
d=8'b11001001; #10;
#10 d=8'b10111001;
#10 d=8'b00101010;
#10 d=8'b00000001;
#10 d=8'b10100010;
end
initial
$monitor("Input %8b | Output %3b | Enable %b ",d,y,en);
initial #100 $finish;
endmodule
```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

Start Writing Synthesis Report

Report BlackBoxes:

```
+-----+
| BlackBox name |Instances |
+-----+
+-----+
```

Report Cell Usage:

```
+-----+
| Cell |Count |
+-----+
|1| LUT4 | 2|
|2| LUT5 | 2|
|3| LUT6 | 1|
|4| LD | 3|
|5| IBUF | 8|
|6| OBUF | 3|
+-----+
```

Report Instance Areas:

```
+-----+
| Instance |Module |Cells |
+-----+
|1| top | | 19|
+-----+
```

Finished Writing Synthesis Report : Time (s): cpu = 00:00:14 ; elapsed = 00:00:16 . Memory (MB): peak = 1018.668 ; gain = 0.000

POWER REPORT:-


Summary

Power analysis from Implemented netlist. Activity derived from constraints files, simulation files or vectorless analysis.

Total On-Chip Power: 0.158 W
Design Power Budget: Not Specified
Power Budget Margin: N/A
Junction Temperature: 25.3°C
Thermal Margin: 59.7°C (31.5 W)
Effective θ_{JA} : 1.9°C/W
Power supplied to off-chip devices: 0 W
Confidence level: Low

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power



Q21. SEVEN SEGMENT DISPLAY USING ROM

VERILOG CODE:-

```
module ROM_sevenSegment
    #(
        parameter addr_width = 16,
        addr_bits = 4,
        data_width = 7
    )
    (
        input wire [addr_bits-1:0] addr,
        output reg [data_width-1:0] data
    );
always @*
begin
    case(addr)
        4'b0000 : data = 7'b1000000;
        4'b0001 : data = 7'b1111001;
        4'b0010 : data = 7'b0100100;
        4'b0011 : data = 7'b0110000;
        4'b0100 : data = 7'b0011001;
        4'b0101 : data = 7'b0010010;
        4'b0110 : data = 7'b0000010;
        4'b0111 : data = 7'b1111000;
        4'b1000 : data = 7'b0000000;
        4'b1001 : data = 7'b0010000;
        4'b1010 : data = 7'b0001000;
        4'b1011 : data = 7'b0000011;
        4'b1100 : data = 7'b1000110;
        4'b1101 : data = 7'b0100001;
        4'b1110 : data = 7'b0000110;
        default : data = 7'b0001110;
    endcase
end
endmodule
```


TESTBENCH:-

```
`timescale 1ns / 1ps
module ROM_sevenSegment_Test
    ();
    reg [3:0] SW;
    wire [6:0] HEX0;
    wire [6:0] LEDR;

    integer i;
    wire [6:0] data;
    ROM_sevenSegment seven_segment_ROM(.addr(SW), .data(data));

    initial begin
    for(i=0;i<16;i=i+1)
    begin
        SW=i;
        #10;
    end
    end
    assign HEX0 = data;
    assign LEDR = data;
endmodule
```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

Start Writing Synthesis Report

Report BlackBoxes:

```
+-----+
| BlackBox name | Instances |
+-----+
+-----+
```

Report Cell Usage:

```
+-----+
| Cell | Count |
+-----+
| 1 | LUT4 | 7 |
| 2 | IBUF | 4 |
| 3 | OBUF | 7 |
+-----+
```

Report Instance Areas:

```
+-----+
| Instance | Module | Cells |
+-----+
| 1 | top | | 18 |
+-----+
```

Finished Writing Synthesis Report : Time (s): cpu = 00:00:33 ; elapsed = 00:00:43 . Memory (MB): peak = 1018.848 ; gain = 0.000

POWER REPORT:-


Summary

Power analysis from Implemented netlist. Activity derived from constraints files, simulation files or vectorless analysis.

Total On-Chip Power: 2.649 W
Design Power Budget: Not Specified
Power Budget Margin: N/A
Junction Temperature: 30.0°C
Thermal Margin: 55.0°C (29.0 W)
Effective θ_{JA} : 1.9°C/W
Power supplied to off-chip devices: 0 W
Confidence level: Low

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power



Q22. SERIAL ADDER

VERILOG CODE:-

```
`timescale 1ns / 1ps
module serial_adder
(
    input clk,reset,
    input a,b,cin,
    output reg s,cout
);

reg c,flag;


always@(posedge clk or posedge reset)
begin
    if(reset == 1) begin
        s = 0;
        cout = c;
        flag = 0;
    end else begin
        if(flag == 0)
        begin
            c = cin;
            flag = 1;
        end
        cout = 0;
        s = a ^ b ^ c;
        c = (a & b) | (c & b) | (a & c);
    end
end
endmodule
```

TESTBENCH:-

```
module serial_adder_tb();
    reg clk;
    reg reset;
    reg a;
    reg b;
    reg cin;
    wire s;
    wire cout;
    serial_adder uut ( .clk(clk), .reset(reset), .a(a), .b(b), .cin(cin), .s(s), .cout(cout));
    always
        #5 clk = ~clk;
    initial begin
        clk = 1; reset = 0;
        a = 0; b = 0; cin = 0; reset = 1;
        #20;
        reset = 0;
        a = 1; b = 1; cin = 1;    #10;
        a = 1; b = 0; cin = 0;    #10;
        a = 1; b = 1; cin = 0;    #10;
        a = 1; b = 1; cin = 0;    #10;
        reset = 1;
        #10;
        reset = 0;

        a = 1; b = 1; cin = 1;    #10;
        a = 1; b = 0; cin = 0;    #10;
        a = 0; b = 0; cin = 0;    #10;
        a = 1; b = 0; cin = 0;    #10;
        a = 1; b = 1; cin = 0;    #10;
        reset = 1;
        #10;
    end
    initial $monitor(" A=%b | B=%b | Cin=%b | Sum=%b | Cout=%b | Clock =%b",a,b,cin,s,cout,clk);
endmodule
```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

```
-----
Start Writing Synthesis Report
-----

Report BlackBoxes:
+-----+
| BlackBox name |Instances |
+-----+
+-----+

Report Cell Usage:
+-----+
| Cell |Count |
+-----+
|1| |BUFG | 1|
|2| |LUT2 | 3|
|3| |LUT5 | 1|
|4| |LUT6 | 1|
|5| |FDCE | 2|
|6| |FDPE | 1|
|7| |FDRE | 1|
|8| |LDC | 1|
|9| |IBUF | 5|
|10| |OBUF | 2|
+-----+

Report Instance Areas:
+-----+
| Instance |Module |Cells |
+-----+
|1| |top | | 18|
+-----+

-----
Finished Writing Synthesis Report : Time (s): cpu = 00:00:20 ; elapsed = 00:00:28 . Memory (MB): peak = 1014.773 ; gain = 0.000
-----
```

POWER REPORT:-

Summary

Power analysis from Implemented netlist. Activity derived from constraints files, simulation files or vectorless analysis.

Total On-Chip Power: 0.618 W

Design Power Budget: Not Specified

Power Budget Margin: N/A

Junction Temperature: 26.2°C


Thermal Margin: 58.8°C (31.0 W)

Effective θ_{JA} : 1.9°C/W

Power supplied to off-chip devices: 0 W

Confidence level: Low

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity



Q23. FIXED PRIORITY ARBITER

VERILOG CODE:-

```
module fixedpriority_arbiter(output reg [3:0] GNT,  
    input [3:0] REQ,  
    input clk,reset  
);  
always @(posedge clk or negedge reset)  
// PRIORITY 3>1>0>2  
begin  
    if(!reset)  
        GNT<= 4'b0000;  
    else if(REQ[3])  
        GNT<= 4'b1000;  
    else if(REQ[1])  
        GNT<= 4'b0010;  
    else if(REQ[0])  
        GNT<= 4'b0001;  
    else if(REQ[2])  
        GNT<= 4'b0100;  
    else  
        GNT<= 4'b0000;  
    end  
endmodule
```


TESTBENCH:-

```

`timescale 1ns / 1ps
module fixedpriority_arbiter_tb();
wire [3:0] GNT;

reg [3:0] REQ;
reg clk,reset ;


fixedpoint_arbiter dut(.GNT(GNT),.REQ(REQ),.clk(clk),.reset(reset));

initial
clk=0;
always #4 clk <= ~clk ;

initial
begin
reset =0;
#4 reset =1;
repeat(20)
begin
#5 REQ<=$random();
end
end
#100 $finish();
end
initial begin
$monitor("REQ=%b,GNT=%b,reset=%b",REQ,GNT,reset);
end
endmodule

```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

```
-----
Start Writing Synthesis Report
-----

Report BlackBoxes:
+-----+
| BlackBox name |Instances |
+-----+
+-----+

Report Cell Usage:
+-----+
| Cell |Count |
+-----+
|1 |BUFG | 1|
|2 |LUT1 | 1|
|3 |LUT2 | 1|
|4 |LUT3 | 1|
|5 |LUT4 | 1|
|6 |FDCE | 4|
|7 |IBUF | 6|
|8 |OBUF | 4|
+-----+

Report Instance Areas:
+-----+
| Instance |Module |Cells |
+-----+
|1 |top | | 19|
+-----+

-----
Finished Writing Synthesis Report : Time (s): cpu = 00:00:25 ; elapsed = 00:00:35 . Memory (MB): peak = 1015.289 ; gain = 0.000
-----
```

POWER REPORT:-

Summary

Power analysis from Implemented netlist. Activity derived from constraints files, simulation files or vectorless analysis.

Total On-Chip Power:	0.861 W
Design Power Budget:	Not Specified
Power Budget Margin:	N/A
Junction Temperature:	26.6°C
Thermal Margin:	58.4°C (30.8 W)
Effective θJA:	1.9°C/W
Power supplied to off-chip devices:	0 W
Confidence level:	Low

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power

Dynamic:	0.778 W	(90%)
Device Static:	0.083 W	(10%)
Signals:	0.031 W	(4%)
Logic:	0.012 W	(2%)
I/O:	0.735 W	(94%)

Q24. ROUND ROBIN ARBITER

VERILOG CODE:-

```
`timescale 1ns / 1ps
module roundrobin_arbiter(
    input clk,rst_n,
    input [3:0] REQ,
    output reg [3:0] GNT
);
    reg[2:0] pr_state;
    reg[2:0] nxt_state;

    parameter [2:0] Sideal = 3'b000;
    parameter [2:0] S0 = 3'b001;
    parameter [2:0] S1 = 3'b010;
    parameter [2:0] S2 = 3'b011;
    parameter [2:0] S3 = 3'b100;

    always @(posedge clk or negedge rst_n)

    begin
        if(!rst_n)
            pr_state <= Sideal;
        else
            pr_state <=nxt_state;
        end

    always@(*)
    begin
        case(pr_state)
            Sideal:
                begin
                    if(REQ[0])
                        nxt_state = S0;
                    else if (REQ[1])
                        nxt_state = S1;
                    else if (REQ[2])
                        nxt state = S2;
```

```

always@(*)
begin
    case(pr_state)
        Sideal:
            begin
                if(REQ[0])
                    nxt_state = S0;
                else if (REQ[1])
                    nxt_state = S1;
                else if (REQ[2])
                    nxt_state = S2;
                else if (REQ[3])
                    nxt_state = S3;
                else
                    nxt_state =Sideal;
            end
        S0:
            begin
                if (REQ[1])
                    nxt_state = S1;
                else if (REQ[2])
                    nxt_state = S2;
                else if (REQ[3])
                    nxt_state = S3;
                else if (REQ[0])
                    nxt_state =S0;
                else
                    nxt_state =Sideal;
            end
        S1:
            begin
                if (REQ[2])
                    nxt_state = S2;
                else if (REQ[3])

```

```

S1:
begin
    if (REQ[2])
        nxt_state = S2;
    else if (REQ[3])
        nxt_state = S3;
    else if (REQ[0])
        nxt_state = S0;
    else if (REQ[1])
        nxt_state = S1;
    else
        nxt_state = Sideal;
end

S2:
begin
    if (REQ[3])
        nxt_state = S3;
    else if (REQ[0])
        nxt_state = S0;
    else if (REQ[1])
        nxt_state = S1;
    else if (REQ[2])
        nxt_state = S2;
    else
        nxt_state = Sideal;
end

S3:
begin
    if (REQ[0])
        nxt_state = S0;
    else if (REQ[1])
        nxt_state = S1;
    else if (REQ[2])
        nxt_state = S2;
    else if (REQ[3])

```

```

        nxt_state = S2;
    else if (REQ[3])
        nxt_state = S3;
    else
        nxt_state = Sideal;
    end
endcase

end

always @(*)
begin
    case (pr_state)
        S0: GNT=4'b0001;
        S1: GNT=4'b0010;
        S2: GNT=4'b0011;
        S3: GNT=4'b0100;
        default: GNT=4'b0000;
    endcase
end
endmodule

```

TESTBENCH:-


```

`timescale 1ns / 1ps
module roundrobin_arbiter_tb();
    reg clk;
    reg rst_n;
    reg [3:0] REQ;
    wire [3:0] GNT;
    roundrobin_arbiter DUT(.clk(clk), .rst_n(rst_n), .REQ(REQ), .GNT(GNT));

    always #5 clk = ~clk;
    initial begin
        clk = 0;
        rst_n = 1;
        REQ = 4'b0;
        #5 rst_n = 1;
        @(negedge clk) REQ = 4'b1000;
        @(negedge clk) REQ = 4'b1010;
        @(negedge clk) REQ = 4'b0010;
        @(negedge clk) REQ = 4'b0110;
        @(negedge clk) REQ = 4'b1110;
        @(negedge clk) REQ = 4'b1111;
        @(negedge clk) REQ = 4'b0100;
        @(negedge clk) REQ = 4'b0010;
        #5 rst_n = 0;
        #100 $finish;
    end
endmodule

```

RTL SCHEMATIC:-



SYNTHESIS REPORT:-

Start Writing Synthesis Report

Report BlackBoxes:

BlackBox name	Instances

Report Cell Usage:

Cell	Count
BUFG	1
LUT1	1
LUT2	2
LUT3	2
LUT5	1
LUT6	4
MUXF7	2
FDCE	3
IBUF	6
OBUF	4

Report Instance Areas:

Instance	Module	Cells
top		26

Finished Writing Synthesis Report : Time (s): cpu = 00:00:19 ; elapsed = 00:00:25 . Memory (MB): peak = 1017.727 ; gain = 0.000

POWER REPORT:-

Summary

Power analysis from Implemented netlist. Activity derived from constraints files, simulation files or vectorless analysis.

Total On-Chip Power: **1.408 W**
Design Power Budget: **Not Specified**
Power Budget Margin: **N/A**
Junction Temperature: **27.7°C**
Thermal Margin: 57.3°C (30.3 W)
Effective θ_{JA} : 1.9°C/W
Power supplied to off-chip devices: 0 W
Confidence level: **Low**

[Launch Power Constraint Advisor](#) to find and fix invalid switching activity

On-Chip Power

