

Mathematical Explanation of Data Re-Uploading in Variational Quantum Circuits

1 Problem Setting

In the `sin_encoded` experiment, the target function is

$$y = \sin(2\pi x) + \varepsilon, \quad x \in [0, 1], \quad \varepsilon \sim \mathcal{N}(0, \sigma^2). \quad (1)$$

The model is a variational quantum circuit (VQC) whose prediction is an expectation value of a measured observable,

$$f_{\boldsymbol{\theta}}(x) = \langle 0|U^\dagger(x, \boldsymbol{\theta})OU(x, \boldsymbol{\theta})|0\rangle, \quad (2)$$

where O is a Pauli observable and $\boldsymbol{\theta}$ are trainable parameters. Since Pauli expectation values lie in $[-1, 1]$, this output range is well matched to a sine-regression target.

2 Angle Encoding

A common way to load a classical scalar x into a quantum circuit is angle encoding. For one qubit, the feature map can be written as

$$S(x) = R_Y(x), \quad R_Y(x) = \exp\left(-i\frac{x}{2}Y\right). \quad (3)$$

After this rotation, the quantum state contains trigonometric dependence on the input:

$$R_Y(x)|0\rangle = \cos\left(\frac{x}{2}\right)|0\rangle + \sin\left(\frac{x}{2}\right)|1\rangle. \quad (4)$$

Therefore, any observable expectation built from this encoded state is a trigonometric function of x . However, if the input is inserted only once and at one frequency scale, the accessible Fourier spectrum is limited [2].

3 Data Re-Uploading

Data re-uploading increases expressivity by inserting the same classical input multiple times into the circuit, usually interleaved with trainable blocks [1]. A generic data re-uploading circuit has the form

$$U(x, \boldsymbol{\theta}) = W_L(\boldsymbol{\theta}_L)S_L(x) \cdots W_2(\boldsymbol{\theta}_2)S_2(x)W_1(\boldsymbol{\theta}_1)S_1(x), \quad (5)$$

where each $S_\ell(x)$ is a data-dependent encoding block and each $W_\ell(\boldsymbol{\theta}_\ell)$ is a trainable unitary. Repeatedly encoding the same input lets the trainable circuit combine several nonlinear trigonometric components.

In the `sin_encoded` notebook, the re-uploading is implemented across four qubits by first scaling the scalar input and then assigning one scaled copy to each qubit:

$$\tilde{x} = \text{MinMaxScale}(x) \in \left[-\frac{\pi}{4}, \frac{\pi}{4}\right], \quad (6)$$

$$\mathbf{z}(x) = (\tilde{x}, 2\tilde{x}, 3\tilde{x}, 4\tilde{x}). \quad (7)$$

The feature map is then

$$S(x) = \bigotimes_{k=1}^4 R_Y(k\tilde{x}). \quad (8)$$

Equivalently, qubit k receives the rotation angle $k\tilde{x}$. This creates several Fourier components of the same original scalar input.

4 Fourier View

The reason data re-uploading helps is that expectation values of parametrized quantum circuits with angle encodings can be represented as finite Fourier series in the input [2]. Abstractly,

$$f_{\boldsymbol{\theta}}(x) = \sum_{\omega \in \Omega} c_{\omega}(\boldsymbol{\theta}) e^{i\omega x}, \quad (9)$$

or, for real-valued outputs,

$$f_{\boldsymbol{\theta}}(x) = a_0(\boldsymbol{\theta}) + \sum_{\omega \in \Omega_+} [a_{\omega}(\boldsymbol{\theta}) \cos(\omega x) + b_{\omega}(\boldsymbol{\theta}) \sin(\omega x)]. \quad (10)$$

The set Ω of available frequencies is determined by how the input enters the circuit. With only a single encoding $R_Y(\tilde{x})$, the model can express only a small Fourier family. With the four re-uploaded angles $\tilde{x}, 2\tilde{x}, 3\tilde{x}, 4\tilde{x}$, the model has access to a richer frequency set. The trainable ansatz and entangling gates then learn the coefficients $a_{\omega}(\boldsymbol{\theta})$ and $b_{\omega}(\boldsymbol{\theta})$.

This is the quantum analogue of replacing a scalar feature x with classical Fourier features such as

$$\phi(x) = (\sin x, \cos x, \sin 2x, \cos 2x, \sin 3x, \cos 3x, \sin 4x, \cos 4x). \quad (11)$$

The circuit does not explicitly construct this classical vector. Instead, the feature map and subsequent quantum operations implicitly generate and combine these trigonometric components.

5 Why It Helps for Sine Regression

The target function $\sin(2\pi x)$ is itself a Fourier mode. A circuit that sees the input only through one weak angle encoding may not have enough spectral bandwidth to approximate the target accurately after scaling and noise are included. Data re-uploading expands the available basis functions, so the model can fit the dominant sine mode and use additional components to absorb finite-sample and noisy-data effects.

For the four-qubit encoding used in `sin_encoded`, the model input is not four independent features. It is one scalar x represented at four different frequency scales. The improvement therefore comes from a richer encoding of the same information, not from adding extra data.

6 Conclusion

Data re-uploading makes the VQC more expressive by allowing the measured expectation value to contain a richer Fourier expansion of the input. In the `sin_encoded` experiment, the transformation

$$x \mapsto (\tilde{x}, 2\tilde{x}, 3\tilde{x}, 4\tilde{x})$$

is mathematically appropriate for a sine-regression task because it gives the quantum model access to multiple trigonometric frequencies of the same scalar input. [11pt,a4paper]article

[T1]fontenc [utf8]inputenc amsmath,amssymb geometry hyperref

margin=2.5cm

Mathematical Explanation of Data Re-Uploading in Variational Quantum Circuits

7 Problem Setting

In the `sin_encoded` experiment, the target function is

$$y = \sin(2\pi x) + \varepsilon, \quad x \in [0, 1], \quad \varepsilon \sim \mathcal{N}(0, \sigma^2). \quad (12)$$

The model is a variational quantum circuit (VQC) whose prediction is an expectation value of a measured observable,

$$f_{\boldsymbol{\theta}}(x) = \langle 0|U^\dagger(x, \boldsymbol{\theta})OU(x, \boldsymbol{\theta})|0\rangle, \quad (13)$$

where O is a Pauli observable and $\boldsymbol{\theta}$ are trainable parameters. Since Pauli expectation values lie in $[-1, 1]$, this output range is well matched to a sine-regression target.

8 Angle Encoding

A common way to load a classical scalar x into a quantum circuit is angle encoding. For one qubit, the feature map can be written as

$$S(x) = R_Y(x), \quad R_Y(x) = \exp\left(-i\frac{x}{2}Y\right). \quad (14)$$

After this rotation, the quantum state contains trigonometric dependence on the input:

$$R_Y(x)|0\rangle = \cos\left(\frac{x}{2}\right)|0\rangle + \sin\left(\frac{x}{2}\right)|1\rangle. \quad (15)$$

Therefore, any observable expectation built from this encoded state is a trigonometric function of x . However, if the input is inserted only once and at one frequency scale, the accessible Fourier spectrum is limited [2].

9 Proof of Spectral Limitation with Single Encoding

To understand why a single encoding is insufficient for complex regression tasks, we prove that an architecture with only one data-loading operation is strictly bounded to the fundamental frequency of the input.

Goal: Prove that a VQC utilizing a single angle encoding operation generates an output strictly constrained to the base frequency, regardless of the subsequent trainable operations.

Assumptions & Prerequisites:

- A single-qubit system initialized in the state $|0\rangle$.
- An encoding feature map $S(x) = R_Y(x)$.
- Measurement via the Pauli-Z observable $O = Z = \begin{bmatrix} 1 & 0 \\ 0 & -1 \end{bmatrix}$.
- For simplicity, we isolate the encoding by measuring immediately, abstracting away trainable parameters which can only scale or shift amplitudes but cannot fundamentally alter the trigonometric arguments.

Derivation:

The state vector (ket) after the encoding gate is applied is:

$$|\psi\rangle = \begin{bmatrix} \cos\left(\frac{x}{2}\right) \\ \sin\left(\frac{x}{2}\right) \end{bmatrix}$$

The corresponding dual vector (bra) is:

$$\langle\psi| = [\cos(\frac{x}{2}) \quad \sin(\frac{x}{2})]$$

The expectation value is the scalar result of the inner product $\langle\psi|Z|\psi\rangle$:

$$f(x) = [\cos(\frac{x}{2}) \quad \sin(\frac{x}{2})] \begin{bmatrix} 1 & 0 \\ 0 & -1 \end{bmatrix} \begin{bmatrix} \cos(\frac{x}{2}) \\ \sin(\frac{x}{2}) \end{bmatrix}$$

First, applying the observable Z to the ket:

$$\begin{bmatrix} 1 & 0 \\ 0 & -1 \end{bmatrix} \begin{bmatrix} \cos(\frac{x}{2}) \\ \sin(\frac{x}{2}) \end{bmatrix} = \begin{bmatrix} \cos(\frac{x}{2}) \\ -\sin(\frac{x}{2}) \end{bmatrix}$$

Next, multiplying the bra by the resulting vector:

$$f(x) = \cos(\frac{x}{2}) \cos(\frac{x}{2}) - \sin(\frac{x}{2}) \sin(\frac{x}{2})$$

$$f(x) = \cos^2(\frac{x}{2}) - \sin^2(\frac{x}{2})$$

Applying the double-angle trigonometric identity $\cos(2\alpha) = \cos^2(\alpha) - \sin^2(\alpha)$, we obtain the final prediction:

$$f(x) = \cos(x)$$

Conclusion:

The algebraic projection during measurement strictly halves the geometry of the Bloch sphere, converting the $x/2$ angles inside the state vector into an observable output of $\cos(x)$. Because linear quantum operations cannot raise the power of these trigonometric terms prior to measurement, the model is trapped at this fundamental frequency.

10 Data Re-Uploading

Data re-uploading increases expressivity by inserting the same classical input multiple times into the circuit, usually interleaved with trainable blocks [1]. A generic data re-uploading circuit has the form

$$U(x, \boldsymbol{\theta}) = W_L(\boldsymbol{\theta}_L) S_L(x) \cdots W_2(\boldsymbol{\theta}_2) S_2(x) W_1(\boldsymbol{\theta}_1) S_1(x), \quad (16)$$

where each $S_\ell(x)$ is a data-dependent encoding block and each $W_\ell(\boldsymbol{\theta}_\ell)$ is a trainable unitary. Repeatedly encoding the same input lets the trainable circuit combine several nonlinear trigonometric components.

In the `sin_encoded` notebook, the re-uploading is implemented across four qubits by first scaling the scalar input and then assigning one scaled copy to each qubit:

$$\tilde{x} = \text{MinMaxScale}(x) \in \left[-\frac{\pi}{4}, \frac{\pi}{4}\right], \quad (17)$$

$$\mathbf{z}(x) = (\tilde{x}, 2\tilde{x}, 3\tilde{x}, 4\tilde{x}). \quad (18)$$

The feature map is then

$$S(x) = \bigotimes_{k=1}^4 R_Y(k\tilde{x}). \quad (19)$$

Equivalently, qubit k receives the rotation angle $k\tilde{x}$. This creates several Fourier components of the same original scalar input.

11 Proof of Enhanced Expressivity via Parallel Re-Uploading and Entanglement

We now prove that parallel data re-uploading across multiple qubits, when subjected to quantum entanglement, mathematically generates novel frequency harmonics that did not exist in the initial feature map.

Goal: Demonstrate that combining different input frequencies via a trainable ansatz and subsequent measurement forces the emergence of higher-order trigonometric mixed terms, increasing the model's capacity.

Assumptions & Prerequisites:

- A 2-qubit system initialized in $|00\rangle$.
- Parallel angle encoding where Qubit 1 receives x and Qubit 2 receives a scaled input ax (where $a \in \mathbb{R}$).
- A trainable ansatz layer capable of multi-qubit entanglement.
- Measurement via the composite observable $O = Z \otimes Z$.

Derivation:

We begin by encoding the data independently onto the two qubits. The initial state is the tensor product of the two individual states:

$$|\psi_{\text{enc}}\rangle = \left(\cos\left(\frac{x}{2}\right) |0\rangle + \sin\left(\frac{x}{2}\right) |1\rangle \right) \otimes \left(\cos\left(\frac{ax}{2}\right) |0\rangle + \sin\left(\frac{ax}{2}\right) |1\rangle \right)$$

Expanding this tensor product reveals the initial mixed amplitudes. Let us isolate the amplitude corresponding to the $|00\rangle$ basis state:

$$\alpha_{00}^{\text{init}} = \cos\left(\frac{x}{2}\right) \cos\left(\frac{ax}{2}\right)$$

Using the product-to-sum trigonometric identity $\cos(\alpha)\cos(\beta) = \frac{1}{2}[\cos(\alpha - \beta) + \cos(\alpha + \beta)]$, we rewrite this amplitude:

$$\alpha_{00}^{\text{init}} = \frac{1}{2} \left[\cos\left(\frac{(1-a)x}{2}\right) + \cos\left(\frac{(1+a)x}{2}\right) \right]$$

To simplify the subsequent algebra, let $A = \cos\left(\frac{(1-a)x}{2}\right)$ and $B = \cos\left(\frac{(1+a)x}{2}\right)$. The entangling ansatz now performs linear combinations of the system's amplitudes. The new amplitude for the $|00\rangle$ state becomes a weighted sum influenced by the trainable parameters θ :

$$\alpha_{00} = w_1 A + w_2 B$$

To calculate the expected value during measurement, we must compute the squared modulus of this amplitude, $|\alpha_{00}|^2$. It is in the squaring of this entire sum that quantum interference mathematically manifests:

$$|\alpha_{00}|^2 = (w_1 A + w_2 B)^2 = w_1^2 A^2 + w_2^2 B^2 + 2w_1 w_2 AB$$

Let us evaluate the crucial cross-term, $2AB$, which represents the interference between the states:

$$2AB = 2 \cos\left(\frac{(1-a)x}{2}\right) \cos\left(\frac{(1+a)x}{2}\right)$$

Applying the product-to-sum identity once more to the $2AB$ term:

$$2AB = \cos(ax) + \cos(x)$$

Simultaneously, the squared terms A^2 and B^2 evaluate to base harmonic components via half-angle identities (e.g., $A^2 = \frac{1+\cos((1-a)x)}{2}$).

Conclusion:

The resulting expectation value aggregates these components into a finite Fourier series containing frequencies $\{1, a, 1 - a, 1 + a\}$. The $2AB$ cross-term proves that as long as the optimizer maintains non-zero weights in the ansatz ($w_1 w_2 \neq 0$), the original frequencies x and ax survive and combine with the newly generated sums and differences. Thus, parallel data re-uploading strictly increases the spectral expressivity of the model.

12 Fourier View

The reason data re-uploading helps is that expectation values of parametrized quantum circuits with angle encodings can be represented as finite Fourier series in the input [2]. Abstractly,

$$f_{\boldsymbol{\theta}}(x) = \sum_{\omega \in \Omega} c_{\omega}(\boldsymbol{\theta}) e^{i\omega x}, \quad (20)$$

or, for real-valued outputs,

$$f_{\boldsymbol{\theta}}(x) = a_0(\boldsymbol{\theta}) + \sum_{\omega \in \Omega_+} [a_{\omega}(\boldsymbol{\theta}) \cos(\omega x) + b_{\omega}(\boldsymbol{\theta}) \sin(\omega x)]. \quad (21)$$

The set Ω of available frequencies is determined by how the input enters the circuit. With only a single encoding $R_Y(\tilde{x})$, the model can express only a small Fourier family. With the four re-uploaded angles $\tilde{x}, 2\tilde{x}, 3\tilde{x}, 4\tilde{x}$, the model has access to a richer frequency set. The trainable ansatz and entangling gates then learn the coefficients $a_{\omega}(\boldsymbol{\theta})$ and $b_{\omega}(\boldsymbol{\theta})$.

This is the quantum analogue of replacing a scalar feature x with classical Fourier features such as

$$\phi(x) = (\sin x, \cos x, \sin 2x, \cos 2x, \sin 3x, \cos 3x, \sin 4x, \cos 4x). \quad (22)$$

The circuit does not explicitly construct this classical vector. Instead, the feature map and subsequent quantum operations implicitly generate and combine these trigonometric components.

13 Why It Helps for Sine Regression

The target function $\sin(2\pi x)$ is itself a Fourier mode. A circuit that sees the input only through one weak angle encoding may not have enough spectral bandwidth to approximate the target accurately after scaling and noise are included. Data re-uploading expands the available basis functions, so the model can fit the dominant sine mode and use additional components to absorb finite-sample and noisy-data effects.

For the four-qubit encoding used in `sin_encoded`, the model input is not four independent features. It is one scalar x represented at four different frequency scales. The improvement therefore comes from a richer encoding of the same information, not from adding extra data.

14 Conclusion

Data re-uploading makes the VQC more expressive by allowing the measured expectation value to contain a richer Fourier expansion of the input. In the `sin_encoded` experiment, the transformation

$$x \mapsto (\tilde{x}, 2\tilde{x}, 3\tilde{x}, 4\tilde{x})$$

is mathematically appropriate for a sine-regression task because it gives the quantum model access to multiple trigonometric frequencies of the same scalar input.

References

- [1] A. Pérez-Salinas, A. Cervera-Liarta, E. Gil-Fuster, and J. I. Latorre, *Data re-uploading for a universal quantum classifier*, Quantum **4**, 226 (2020). <https://doi.org/10.22331/q-2020-02-06-226>
- [2] M. Schuld, R. Sweke, and J. J. Meyer, *Effect of data encoding on the expressive power of variational quantum-machine-learning models*, Physical Review A **103**, 032430 (2021). <https://doi.org/10.1103/PhysRevA.103.032430>
- [3] K. Mitarai, M. Negoro, M. Kitagawa, and K. Fujii, *Quantum circuit learning*, Physical Review A **98**, 032309 (2018). <https://doi.org/10.1103/PhysRevA.98.032309>
- [4] M. Cerezo, A. Arrasmith, R. Babbush, S. C. Benjamin, S. Endo, K. Fujii, J. R. McClean, K. Mitarai, X. Yuan, L. Cincio, and P. J. Coles, *Variational quantum algorithms*, Nature Reviews Physics **3**, 625–644 (2021). <https://doi.org/10.1038/s42254-021-00348-9>