IMPLEMENTATION OF POS EXPRESSION IN ARM

YADATI KRISHNA
yadati.krishna@gmail.com
FWC22036 IITH Future Wireless Communication (FWC) ASSIGNMENT-8

November 3, 2022

Contents

Abstract

This manual shows how to represent the K-MAP for POS expression for the function "G" shown in below truth table.

U	V	W	G
0	0	0	1
0	0	1	0
0	1	0	1
0	1	1	0
1	0	0	1
1	0	1	0
1	1	0	0
1	1	1	1

1 Components

Components	Values	Quantity
Vaman Board		1
JumperWires	M-F	5
Breadboard		1
USB-C cable		1

2 Implementation



K-map

Karnugh Map : The minimized expression using the K-map can be expressed as

$$G = (V + W')(U + W')(U' + V' + W) \quad (1)$$

The code below realizes the Boolean logic for G using 5V,GND of Vaman Board
2,4,6 GPIO Pins of Vaman Board are configured as input pins and the required Logic for U,V,W are drawn from 5V (Digital '1'),GND (Digital '0'). Built in led at 22nd pin will glow based on G satisfying the Truth table.

https://github.com/KrishnaYadati/Assignments/blob/main/ARM/codes/src/main.c

3 Setup

1. Connect the Vaman to the Laptop through USB.
2. There is a button and an LED to the left of the USB port on the Vaman.There is another button to the right of the LED.
3. Press the right button first and immediately press the left button.The LED will be blinking green.The Vaman is now in bootloader mode.

3.1 The steps for implementation:

1. Login to termux-ubuntu on the android device and execute the following commands:
   Make sure that the required installation of pygmy-sdk had done prior executing below commands

```
proot−distro login debian
cd /data/data/com.termux/files/home/
mkdir arm
svn co https://github.com/KrishnaYadati/
    Assignments/trunk/arm/codes
```

```
cd codes/GCC_Project
make
scp /data/data/com.termux/files/home/arm/codes/
    GCC_Project/output/bin/codes.bin
    usernameofpc@IPaddress:/home/username
```

   Make sure that the appropriate username,IP address of the Laptop is given in the above command.

2. Now execute the following commands on the Laptop terminal
   Make sure that required installation of programmer application and modification of bash file had done prior executing below command

```
bash flash.sh codes.bin
```

3. After finishing the process of flashing with the programmer application press the button to the right of the USB port to reset. Vaman is now flashed with our source code