09 · LOT TILE: User Manual

Doc: LOT-HW-01-UM · **Rev:** A (2026-11-14) · Applies to firmware 0.1.x

IN THE BOX

LOT TILE · charging pad · USB-C cable · this manual

YOUR LOT TILE

- **Front:** screen, camera, **Copy** button.
- **Back:** polished stainless steel. Place this side on the charging pad.

1. CHARGE

Place the tile, back down, on the pad. The screen shows `Charging. 64%`. A full charge takes about 1.5 hours.

2. CONNECT TO WI-FI (FIRST TIME)

1. The screen shows `Wi-Fi: LOT-TILE-4F2A`.
2. On your phone, join the Wi-Fi network **LOT-TILE-4F2A**. A setup page opens. If it does not, go to `http://192.168.4.1`.
3. Choose your home network and enter its password. The tile shows `Connected.` and then a pair code, `Pair: K7Q-2MX`.

3. PAIR WITH LOT-SYSTEMS.COM

1. Open **lot-systems.com → Settings → Devices**.
2. Enter the code from the screen.
3. The tile shows `Hello, <your name>.` and buzzes once. Done.

4. DAILY USE

You see / feel	Meaning
One buzz plus a line, e.g. `Coffee time!`	A notification from LOT
`09:41 · 12°C` under it	The time it arrived and the local temperature
`Offline.`	No Wi-Fi. The tile tries again on its next wake

Copy button

Action	Result
Press	Saves the line on screen to your **Log** on lot-systems.com. The screen shows `Copied.`
Press and hold (about 1 s)	Also takes a photo and attaches it to the same Log entry. The screen shows `Copied. Photo.`
Hold 10 s	Forgets the pairing. The screen shows `Forgotten.` and then a new pair code

Pick the tile up to refresh the screen.

5. QUIET HOURS AND FREQUENCY

Set these in **Settings → Devices** on lot-systems.com: quiet hours, maximum notifications per day, and buzz strength. By default LOT sends at most 8 per day, at least 45 minutes apart, and none during your sleep window.

6. CARE

- The back is mirror-polished 316L stainless steel. Clean it with a microfibre cloth and avoid abrasives.
- The tile is splash-resistant (IP54 target), not waterproof.
- Keep the small vent hole on the side clear. The weather sensor breathes through it.
- Do not charge it above 35 °C ambient. Use only Qi-compatible pads.

7. PRIVACY

- The camera is fully powered off except during a long press.
- Photos go only to your own Log. Sensor readings are temperature, humidity, pressure, air quality class and light level. No audio, location or motion data leaves the device.
- To revoke the tile, go to **Settings → Devices → Remove**. It stops working until it is paired again.

8. SPECIFICATIONS

Size	40 × 40 × 6.5 mm (EVT edition)
Body	Two-part 316L stainless steel, mirror back, brushed walls
Screen	1.08" reflective memory LCD, 160 × 68
Radio	Wi-Fi 2.4 GHz 802.11 b/g/n, Bluetooth LE 5
Sensors	Bosch BME688 (temperature, humidity, pressure, air quality AI), Bosch BMI270 motion, ambient light
Camera	VGA, photo-to-Log
Battery	Li-polymer, about 150 mAh, ≥ 5 days typical
Charging	Qi-compatible wireless, 5 W pad included

LOT® · lot-systems.com · Made by LOT Systems / COSMO® CIA