NAECON 2026 - IEEE National Aerospace and Electronics Conference
August 10-13, 2025. Lansing, Michigan, USA

Reconfigurable Multi-Channel Graphene Microring Modulator for WDM Optical Interconnects

Ramaa Saket Suri
Dept. of ECE
Purdue University
Indianapolis, USA
rsuri@purdue.edu

Mukesh Kumar
Dept. of Electrical Engineering
Indian Institute of Technology, Indore
Indore, India
mukesh.kr@iiti.ac.in

Maher E. Rizkalla
Dept. of ECE
Purdue University
Indianapolis, USA
mrizkall@purdue.edu

John J. Lee
Dept. of ECE
Purdue University
Indianapolis, USA
lee2278@purdue.edu

NAECON 2026 - IEEE National Aerospace and Electronics Conference | 979-8-3195-0667-2/26/$31.00 ©2026 IEEE | DOI: 10.1109/NAECON70028.2026.11675012

***Abstract*—The reconfigurable optical interconnects of large-scale AI data centers demand nanosecond-scale wavelength agility while operating within milliwatt power budgets. We present a Hybrid Electro-Optic Tunable Multichannel Modulator (HETM), a four-channel graphene electro-optic silicon-on-insulator (SOI) microring modulator that treats Q-factor variation as a characterized design constraint, achieving 110 ns switching, greater than 4 nm tuning per channel, 50 GHz ITU-T spacing, and less than 10 mW total power.**

***Index Terms*—Graphene photonics, microring resonators, electro-optic modulation, silicon-on-insulator photonics, reconfigurable optical interconnects, wavelength-division multiplexing.**

I. Introduction

The escalating bandwidth demands of modern data centers, driven by the rapid growth of AI and machine learning workloads, have created an urgent need for optical interconnects capable of dynamic, energy-proportional wavelength modulation [1], [2]. Disaggregated computing architectures — in which processing, memory, and storage resources are interconnected across a reconfigurable optical fabric rather than fixed electrical buses — require wavelength channels that can be re-assigned in real time at nanosecond-to-microsecond timescales, with minimal per-channel power overhead [1].

Current wavelength-division multiplexing (WDM) systems address this requirement using thermally tuned silicon microring resonators, which achieve wide tuning ranges through the thermo-optic effect. However, thermal tuning is fundamentally constrained because millisecond-scale response times prevent packet-granular wavelength switching, and the static power required to maintain tuned channels — typically 10–100 mW per ring — accumulates prohibitively in high-channel-count systems [3], [4]. Carrier-injection silicon modulators offer faster response but introduce severe free-carrier absorption, degrading resonator quality factors in cascaded configurations and producing unacceptable inter-channel crosstalk.

Graphene has emerged as a compelling active medium for integrated photonics owing to its gate-tunable optical conductivity, broadband spectral response, and sub-picosecond carrier dynamics [5], [6]. The voltage-controlled interband-to-intraband transition in graphene, described by the Kubo formalism [6], [7], enables electro-optic modulation at speeds exceeding 100 GHz with switching energies in the femtojoule range — fundamentally superior to both thermal and carrier-injection approaches. Prior demonstrations of graphene-integrated ring resonators have confirmed 30 GHz modulation bandwidth at telecom wavelengths [8], and double-layer graphene architectures have since achieved 60 GHz bandwidth with sub-femtojoule switching energy [5], establishing a strong technical foundation for high-speed channel modulation.

Despite this progress, graphene-integrated ring modulators have remained single-channel devices operating at fixed wavelengths. The reason is a system-level challenge that does not appear in single-ring characterization: the inherent coupling between refractive index modulation and optical absorption in graphene means that any gate-voltage-induced resonance shift is accompanied by a predictable change in the resonator loss rate, and therefore in the loaded quality factor Q_L. In a single-ring modulator, this Q_L variation is an inconvenience. In a cascaded multi-channel modulator, if uncharacterized, the resonance linewidths of individual rings will vary with operating point in ways that produce wavelength-selective crosstalk between channels, undermining the channel isolation that WDM systems depend on.

This paper introduces a hybrid electro-optic tunable multi-channel modulator (HETM), which addresses this challenge by treating the absorption-index relationship as a fully characterized, analytically predictable design constraint. The HETM operating point is selected by maximizing the electro-optic figure of merit $|\Delta n/\Delta\alpha|$ (Δn is the change in refractive index and $\Delta\alpha$ is the change in the absorption), which peaks at the chemical potential of Graphene $|\mu_c| \approx 0.45$ eV and defines a regime in which the achievable tuning range is large, the Q_L at any operating point within the tuning window remains above a design floor of 5,800, and the resonance linewidth variation is bounded and known in advance. The ring geometry, coupling gap, and graphene coverage are then co-optimized to satisfy the 30 dB channel isolation requirement at 50 GHz spacing across the entire tuning range under this bounded Q_L variation — rather than assuming a fixed Q_L and discovering crosstalk violations at the system level.

Combined with a polarization-diverse wavelength interleaving scheme that contributes additional crosstalk rejection for spectrally adjacent channels, the HETM simultaneously satisfies the speed, power, selectivity, and the 30 dB channel

Authorized licensed use limited to: Purdue University. Downloaded on September 22,2026 at 23:54:26 UTC from IEEE Xplore. Restrictions apply.

isolation requirement at 50 GHz ITU-T spacing that prior approaches have not achieved in combination.

II. Theoretical Framework

A. Temporal Coupled-Mode Theory and the Q-Factor Constraint

The dynamic response of a microring resonator side-coupled to a bus waveguide is governed by temporal coupled-mode theory (TCMT), which treats each resonant mode as a damped harmonic oscillator exchanging energy with external channels [10], [11]. For a single resonant mode with amplitude $a(t)$ normalized so that $|a|^2$ equals the stored energy:

$$\frac{da}{dt} = \left(i\omega_0 - \frac{1}{\tau_0} - \frac{1}{\tau_e}\right) a + \sqrt{\frac{2}{\tau_e}}\, s_{\text{in}} \tag{1}$$

where ω_0 is the cold-cavity resonance frequency, $1/\tau_0$ is the intrinsic energy decay rate (absorption, radiation, and scattering losses), $1/\tau_e$ is the external coupling decay rate to the bus waveguide, and s_{in} is the input field amplitude. The steady-state power transmission through the bus waveguide is [10]:

$$T(\omega) = \left| \frac{1/\tau_0 - 1/\tau_e}{1/\tau_0 + 1/\tau_e + i(\omega - \omega_0)} \right|^2 \tag{2}$$

At resonance ($\omega = \omega_0$), critical coupling — maximum extinction, $T = 0$ — requires $\tau_0 = \tau_e$. The loaded quality factor is:

$$Q_L = \frac{\omega_0 \tau_0 \tau_e}{\tau_0 + \tau_e} \tag{3}$$

and the 3-dB resonance linewidth is $\Delta\omega = \omega_0/Q_L$. In a multi-channel modulator, $\Delta\omega$ directly determines the adjacent-channel isolation: a wider linewidth increases the transmission tail at the neighboring channel wavelength. For a cascade of N rings, the total crosstalk from channel i into channel j accumulates as:

$$\text{CT}_{ij} = \sum_{k=1}^{N} T_k(\omega_j) \tag{4}$$

where $T_k(\omega_j)$ is the through-port transmission of ring k evaluated at the center frequency of channel j. Because $T_k(\omega_j)$ depends on Q_L of ring k, any gate-voltage-induced variation in Q_L must be characterized and bounded to guarantee that Eq. (4) remains below the system isolation target across the full tuning range. This is the design constraint that the HETM operating-point optimization satisfies.

B. Graphene Electro-Optic Response and Operating-Point Optimization

The surface optical conductivity of graphene $\sigma(\omega, \mu_c)$ is described by the Kubo formula, comprising intraband (Drude) and interband contributions [6], [7]:

$$\sigma = \sigma_{\text{intra}}(\omega, \mu_c, T) + \sigma_{\text{inter}}(\omega, \mu_c, T) \tag{5}$$

At C-band wavelengths ($\hbar\omega \approx 0.8$ eV) and room temperature ($T = 300$ K), the interband term dominates when $|\mu_c| < 0.4$ eV, because direct valence-to-conduction band transitions are energetically allowed. As $|\mu_c|$ increases through the Pauli-blocking threshold ($|\mu_c| = \hbar\omega/2 \approx 0.4$ eV), interband absorption is progressively suppressed as the conduction band fills and fewer final states are available for photon-excited electrons [12], [13]. Above threshold, the intraband Drude response dominates, with lower absorption but sustained refractive index modulation. The graphene-induced perturbation to the waveguide effective index is [5], [9]:

$$\Delta n_{\text{eff}} + i\frac{\Delta\alpha_{\text{eff}}}{2k_0} = \frac{\Gamma_g}{2\omega\varepsilon_0}\, \sigma(\omega, \mu_c) \tag{6}$$

where Γ_g is the power confinement factor of the optical mode in the graphene layer. For the SOI geometry described in Section III, $\Gamma_g = 2.0\%$ with 85% of the optical power confined in the silicon core, yielding $\Delta n_{\text{eff}} \approx 1\text{–}2 \times 10^{-3}$ and $\Delta\alpha_{\text{eff}} \approx 5\text{–}12$ dB/cm over the tuning range.

The key design criterion for the HETM is the electro-optic figure of merit:

$$\text{FOM} = \left| \frac{\Delta n_{\text{eff}}}{\Delta\alpha_{\text{eff}}} \right| \tag{7}$$

computed from Eq. (6) as a function of μ_c. The FOM peaks sharply at $|\mu_c| \approx 0.45$ eV — precisely at the interband-to-intraband transition — where the refractive index change per unit absorption change is maximized. The HETM fixes its nominal operating point at $\mu_c^{(0)} = 0.45$ eV and applies gate voltage to sweep μ_c over the range 0.30–0.60 eV, corresponding to a resonance tuning range of ± 2.5 nm. Within this window, $\Delta\alpha_{\text{eff}}$ is bounded between 5 and 12 dB/cm, which translates to a bounded Q_L variation of 8,500 (at $\mu_c = 0.60$ eV, near full Pauli blocking) to 5,800 (at $\mu_c = 0.30$ eV, near the absorption peak). This Q_L range is known analytically before fabrication and is incorporated into the ring geometry and coupling gap design to guarantee that the 30 dB channel isolation requirement is met at 50 GHz channel spacing at every operating point in the tuning window.

The resonance wavelength shift resulting from the effective index change is:

$$\Delta\lambda = -\frac{\lambda_0}{n_g}\, \Delta n_{\text{eff}} \tag{8}$$

For $\lambda_0 = 1550$ nm and group index $n_g \approx 4.2$ for the SOI platform [15], a change $\Delta n_{\text{eff}} = 1.5 \times 10^{-3}$ produces $\Delta\lambda \approx 0.55$ nm. Over the dual-gate voltage swing of ± 3 V, the achievable per-ring tuning range exceeds ± 2.5 nm. The chemical potential is controlled by an electrostatic dual-gate configuration:

$$\mu_c = \hbar v_F \sqrt{\frac{\pi \varepsilon_0 \varepsilon_r |V_g - V_{\text{Dirac}}|}{e \cdot t_{\text{ox}}}} \tag{9}$$

Authorized licensed use limited to: Purdue University. Downloaded on September 22,2026 at 23:54:26 UTC from IEEE Xplore. Restrictions apply.




Fig. 1. (a) SOI waveguide cross-section of the HETM modulation unit. The 500 nm × 220 nm silicon ridge sits on a 2 μm SiO_2 BOX layer with SiO_2 upper cladding. Monolayer graphene is deposited on the ridge top surface, gated through a 10 nm Al_2O_3 dielectric. (b) Simulated TE_{00} mode profile, showing $\Gamma_g = 2.0\%$ graphene confinement factor and 85% of optical power in the silicon core, confirming high electro-optic interaction efficiency.

where $v_F \approx 10^6$ m/s, $\varepsilon_r = 9$ for Al_2O_3, and $t_{ox} = 10$ nm, giving a tuning efficiency of approximately 0.15 eV/V. The dual-gate arrangement provides symmetric bipolar control about the Dirac point, halving the required single-gate voltage swing while doubling the accessible carrier concentration range [14].

III. Device Architecture

A. Silicon-on-Insulator Waveguide Platform

The HETM is built on a silicon-on-insulator (SOI) platform, as illustrated in Fig. 1. The waveguide cross-section comprises a 500 nm-wide, 220 nm-thick silicon ridge on a 2 μm SiO_2 buried oxide (BOX) layer, with SiO_2 upper cladding. This geometry is selected for three reasons. First, the high refractive index contrast of the Si/SiO_2 system produces tight optical mode confinement, with 85% of the TE_{00} mode power confined in the silicon core and a graphene confinement factor of $\Gamma_g = 2.0\%$ — approximately four times higher than achievable in silicon nitride geometries — directly improving the per-volt tuning efficiency through Eq. (6). Second, the SOI platform is fully CMOS-compatible and widely available from commercial photonic foundries, supporting a direct path to fabrication. Third, the waveguide dimensions support single-mode guidance for both TE and TM polarizations, with a wavelength splitting of 0.3-0.5 nm between the TE_{00} and TM_{00} resonances.

B. Dual-Gate Graphene Modulation

Each microring incorporates a dual-gate graphene section spanning 20 μm of ring circumference. Monolayer graphene is contacted by source/drain electrodes on the silicon ridge surface. Applying equal and opposite voltages to the top gate (via the Al_2O_3 dielectric) and the silicon back gate realizes the symmetric dual-gate bias. It is described by Eq. (9), giving 0.15 eV/V tuning efficiency. For a ± 3 V swing, the chemical potential spans 0.3–0.6 eV, covering the full tuning window.

The electro-optic switching speed is governed by the total RC time constant of the gate structure, including contact pad parasitics and interconnect capacitance. The full dual-gate voltage window of ± 3 V is used for maximum wavelength coverage, while smaller steps demonstrate the dynamic linearity of the electro-optic response. The 110 ns rise time represents more than three orders of magnitude improvement over thermally tuned silicon microring resonators, with no thermal actuation required anywhere in the modulation path.

C. 4-Channel Wavelength-Interleaving Geometry

The HETM uses four microring resonators with radii of 19.8700, 19.8751, 19.8803, and 19.8854 μm, chosen so that their resonance wavelengths are offset by integer multiples of 0.4 nm from a common center wavelength λ_0: placing resonances at λ_0, $\lambda_0 + 0.4$ nm, $\lambda_0 + 0.8$ nm, and $\lambda_0 + 1.2$ nm within one free spectral range (FSR) period. Each ring couples to the bus waveguide through a directional coupler with gap $g = 200$ nm, selected jointly with the ring geometry to maintain the 30 dB isolation target across the bounded Q_L tuning range (see Section IV). The electro-optic tuning range of ± 2.5 nm per ring provides 5 nm of continuous channel coverage, giving each ring full 50 GHz ITU-T grid coverage with a margin exceeding 1 nm on each side.

Adjacent channels are assigned to orthogonal polarizations: channels 1 and 3 use TE polarization; channels 2 and 4 use TM polarization. Because spectrally adjacent channels are always orthogonally polarized, inter-channel crosstalk is suppressed both by the resonator roll-off and by polarization orthogonality, the latter providing additional rejection at the polarization beam combiner on the output. This architectural choice is significant: it relaxes the Q_L requirement on each individual ring, because the nearest-neighbor crosstalk, which is the most demanding isolation specification, is handled partly by polarization. Consequently, the bounded Q_L variation from graphene absorption does not violate the 30 dB isolation requirement at 50 GHz spacing, even at the worst-case operating point of $\mu_c = 0.30$ eV where Q_L is at its minimum of 5,800.

IV. Simulation Methodology

The HETM design is validated through a hierarchical simulation approach. Synopsys RSoft provides eigenmode analysis for waveguide effective index, group index, and graphene confinement factor Γ_g and the dispersive optical constants of the SOI platform [15]. A 5 nm mesh in the graphene layer was used to capture the electro-optic effects in Graphene. The software also performs 3D full-vectorial validation of the ring resonators, coupling regions, and polarization splitters. Synopsys OptSim assembles the extracted compact models — with gate-voltage-dependent graphene parameters drawn from Eq. (5)–(6) — into a complete four-channel system for spectral and transient response simulation.

The graphene conductivity is computed at $T = 300$ K with scattering rate $\Gamma = 15$ meV, validated against published experimental graphene-microring data with less than 10% deviation across the C-band [8], [9]. Geometry optimization uses a multi-objective genetic algorithm over the parameter space (R: 15–30 μm; width: 600–1000 nm; coupling gap:

Authorized licensed use limited to: Purdue University. Downloaded on September 22,2026 at 23:54:26 UTC from IEEE Xplore. Restrictions apply.

150–300 nm; graphene coverage: 15–25 μm arc length), with objectives of maximum FOM, minimum insertion loss, and minimum Q_L variation across the tuning window. The optimal solution ($R = 20$ μm, $w = 500$ nm, $g = 200$ nm, graphene arc = 20 μm) is used throughout.

V. Results and Discussion

A. Electro-Optic Response and Operating-Point Characterization

Fig. 2 presents the simulated graphene electro-optic response as a function of μ_c. The effective index change Δn_{eff} increases monotonically from 0.5×10^{-3} at $\mu_c = 0.20$ eV to 2.3×10^{-3} at $\mu_c = 0.60$ eV. The absorption $\Delta\alpha_{\text{eff}}$ exhibits a non-monotonic profile with a minimum near $\mu_c = 0.50$ eV reflecting the onset of Pauli blocking. The FOM $|\Delta n/\Delta\alpha|$ peaks at $\mu_c \approx 0.45$ eV, confirming the analytically predicted optimal operating point. The tuning efficiency extracted from the slope of Δn_{eff} versus gate voltage is 0.83 nm/V, consistent with Eq. (8) and with prior experimental results on graphene-SOI ring modulators [5], [8].

Within the design tuning window of 0.30–0.60 eV, the bounded $\Delta\alpha_{\text{eff}}$ range of 5–12 dB/cm corresponds to a Q_L variation from 8,500 at the high-μ_c end to 5,800 at the low-μ_c end — a 32% variation that is fully predictable from Eq. (5) and Eq. (3). This bounded variation is the foundational design input: the ring coupling gap $g = 200$ nm is selected so that the worst-case $Q_L = 5{,}800$ resonance, combined with the polarization-rejection contribution from the interleaving architecture, satisfies the 30 dB isolation requirement at 50 GHz channel spacing across all operating states.

B. Single-Ring Spectral Response

Fig. 3 presents the spectral response of a single HETM ring at representative gate voltages. At zero bias ($\mu_c = 0.45$ eV, nominal operating point), the resonance shows a Lorentzian lineshape with 22 dB extinction ratio and $Q_L = 8{,}500$, confirming near-critical coupling at the design bias. As the gate voltage is swept to ± 3 V, the resonance shifts by ± 1.5 nm per step (0.83 nm/V), and Q_L varies between 5,800 and 8,500 depending on direction, consistent with the operating-point analysis. The extinction ratio remains above 20 dB throughout the tuning range, because the coupling gap was optimized for the worst-case Q_L rather than the nominal value. The insertion loss at the worst-case bias point ($\mu_c = 0.30$ eV) is 3.1 dB, rising from 2.5 dB at the nominal operating point.

C. Four-Channel Modulator Response

Fig. 4 presents the complete four-channel modulator spectral response, demonstrating 50 GHz ITU-T channel spacing with alternating TE/TM polarization assignment. Each channel exhibits an extinction ratio above 20 dB and a 3-dB bandwidth exceeding 25 GHz, compatible with 25 Gbaud modulation. Adjacent-channel isolation meets the 30 dB requirement at 50 GHz spacing in all operating states across the tuning window, and non-adjacent channel isolation exceeds 45 dB. The worst-case isolation occurs when the ring biased to




Fig. 2. Simulated graphene electro-optic response at C-band versus chemical potential μ_c. The effective index change Δn_{eff} increases monotonically, while absorption $\Delta\alpha_{\text{eff}}$ exhibits a minimum near $\mu_c = 0.5$ eV. The figure of merit $|\Delta n/\Delta\alpha|$ peaks at $\mu_c \approx 0.45$ eV, defining the HETM nominal operating point. The shaded region indicates the design tuning window (0.30–0.60 eV) within which Q_L remains above 5,800.




Fig. 3. Simulated spectral response of a single HETM ring at gate voltages $V_g = 0$, ± 2 V, and ± 3 V. Extinction ratio exceeds 20 dB across the full tuning range.

$\mu_c = 0.30$ eV (lowest Q_L) is adjacent to a channel operating at $\mu_c = 0.60$ eV (highest Q_L, narrowest linewidth); even in this maximally asymmetric case, the combined spectral roll-off and polarization rejection at the output combiner maintains compliance with the 30 dB target, as confirmed by the isolation-versus-spacing analysis in Fig. 5(b).

The accumulated cascade insertion loss is 10–12.4 dB across the four-ring chain, with 2.5–3.1 dB per ring depending on gate bias. The SOI waveguide propagation loss contributes negligibly (<0.1 dB per ring at the 20 μm radius), confirming that graphene absorption is the dominant loss mechanism.

D. Performance Benchmarking

Fig. 6 and Table I compare the HETM against representative silicon photonic modulator technologies. The HETM exhibits a 10–90% electro-optic rise time of 110 ns (Fig. 7), representing approximately four orders of magnitude improvement in reconfiguration speed over the passive thermal response time of thermally tuned silicon microring devices, with per-channel power below 1 mW — more than two orders of magnitude below the 10–100 mW range of heater-driven silicon resonators

Authorized licensed use limited to: Purdue University. Downloaded on September 22,2026 at 23:54:26 UTC from IEEE Xplore. Restrictions apply.




Fig. 4. Simulated four-channel modulator response at nominal operating point. TE-polarized channels 1 and 3 (solid); TM-polarized channels 2 and 4 (dashed). Adjacent-channel isolation meets the 30 dB requirement at 50 GHz spacing across all operating states within the design tuning window.




Fig. 5. Crosstalk analysis of the HETM. (a) Spectral crosstalk at target channel 2 showing total crosstalk from all other channels. (b) Isolation versus channel spacing: the 30 dB requirement (dashed) is met at 50 GHz spacing (≈0.4 nm) and exceeded at larger spacings. (c) Polarization crosstalk matrix for all four channels, showing co-polarization (blue) and cross-polarization (red) isolation; cross-polarization provides additional rejection for adjacent TE/TM channel pairs. (d) BER performance versus OSNR, confirming that −30 dB crosstalk produces negligible penalty relative to the ideal case across the FEC operating range.

[3], [4]. Compared to silicon carrier-injection modulators, the HETM offers a substantially larger tuning range (>4 nm versus <1 nm) and a higher biased Q_L (5,800–8,500 versus ∼2,000), because graphene's electro-optic mechanism does not flood the resonator with free carriers.

The key differentiator of the HETM relative to prior graphene ring demonstrations is not any individual metric but the combination: prior work has shown high speed or wide tuning in single-ring, single-channel configurations. The HETM demonstrates that these properties can be maintained in a four-channel cascaded configuration by treating the Q_L-versus-bias relationship as a design input rather than an uncharacterized perturbation, and by using polarization-diverse interleaving to satisfy the channel isolation requirement across the full tuning window.

VI. Conclusion

We have presented the hybrid electro-optic tunable multi-channel modulator (HETM), demonstrating that the inherent absorption-index coupling of graphene need not be an obstacle to multi-channel electro-optic modulation when it is treated as a characterized, bounded design constraint rather than an uncontrolled perturbation. By identifying the optimal electro-optic operating point at $|\mu_c| \approx 0.45$ eV — where the figure of merit $|\Delta n/\Delta\alpha|$ is maximized — and co-designing the ring coupling geometry to maintain channel isolation across the full bounded Q_L variation range (5,800–8,500), the HETM achieves reliable four-channel operation with no active feedback or thermal compensation elements. Polarization-diverse wavelength interleaving ensures that the 30 dB isolation requirement at 50 GHz channel spacing is satisfied at every operating point across the tuning window.




Fig. 6. Performance benchmarking of the HETM versus thermally tuned silicon microring resonators and silicon carrier-injection modulators. The HETM occupies a previously unoccupied region of the speed-power space while maintaining competitive Q_L and tuning range.

Simulation results for the four-channel HETM confirm a 110 ns electro-optic rise time, total power consumption below 10 mW, extinction ratios above 20 dB, and a per-channel tuning range exceeding 4 nm. Energy per bit ranges from 2.2 to 22.5 fJ/bit across 25–100 Gb/s data rates, compared to ∼100 pJ/bit for thermally tuned silicon approaches — a reduction of more than four orders of magnitude in switching

Authorized licensed use limited to: Purdue University. Downloaded on September 22,2026 at 23:54:26 UTC from IEEE Xplore. Restrictions apply.




Fig. 7. Electro-optic switching characterization of the HETM. (a) Dynamic tuning response: gate voltage (blue) and resonance wavelength (red) versus time for a ± 2 V step sequence, confirming linear and symmetric tuning. (b) Step response showing 10–90% rise time of 110 ns. (c) Frequency response of the electro-optic path; the 3-dB bandwidth is limited by the gate RC pole. (d) Energy per bit versus data rate: the HETM achieves 2.2–22.5 fJ/bit across 25–100 Gb/s, compared to $\sim$100 pJ/bit for thermal tuning approaches.

energy. These results are achieved entirely through electro-optic actuation, with no thermal elements in the modulation path. Reduction of cascade insertion loss below 6 dB is achievable through either a reduced graphene arc length with proportionally higher drive voltage, or by shifting the nominal operating point deeper into the Pauli-blocking regime; both directions are identified as priorities for the next design iteration. Tuning speed beyond the current 110 ns rise time is achievable through two approaches: Reducing the gate capacitance and the series resistance (Graphene sheet resistance and contact resistance). By reducing the graphene contact area (shorter arc length, narrower contact width) the capacitance reduces directly. The tradeoff is reduced tuning range, which can be partially compensated by higher voltage as discussed earlier.

Future work will focus on experimental validation through SOI foundry fabrication with CVD (Chemical Vapor Deposition) graphene transfer and direct measurement of the operating-point Q_L map against Kubo-formula predictions. A planned transceiver integration study will combine the HETM with a WDM multiplexer, demultiplexer, and photodetector array to validate end-to-end link performance. A scalability analysis projects linear growth in total insertion loss and power consumption as the four-channel baseline is tiled to larger channel counts, providing a pathway toward deployment in reconfigurable optical add-drop multiplexer (ROADM) subsystems for disaggregated AI data center architectures.

TABLE I
PERFORMANCE METRIC SUMMARY AND COMPARISON

Reference	Tuning Speed	Tuning Range (nm)	Power/Ch (mW)
Padmaraju 2014 [16]	$\sim$1–10 ms	$>$10	20–100
Qiu 2014 [17]	$\sim$10 ns	$\sim$1	$<$2
Sorianello 2018 [18]	$\sim$1 ns	$\sim$2	$<$1
Ding 2015 [9]	$\sim$10 ns	$\sim$1	$<$2
Phare 2015 [8]	$<$1 ns	N/A	$<$1
Bogaerts 2020 [19]	$\sim$1 ns	$\sim$0.5	5–10
This work (HETM)	110 ns	$>$4	$<$1

REFERENCES

[1] S. J. Ben Yoo, "New trends in photonic switching and optical network architectures for data centers and computing systems," *J. Opt. Commun. Netw.*, vol. 15, no. 8, pp. C288–C305, Aug. 2023.

[2] A. Novick et al., "High-bandwidth density silicon photonic resonators for energy-efficient optical interconnects," *Appl. Phys. Rev.*, vol. 10, no. 4, 2023.

[3] W.-C. Hsu, N. Nujhat, B. Kupp, J. F. Conley, and A. X. Wang, "On-chip wavelength division multiplexing filters using extremely efficient gate-driven silicon microring resonator array," *Sci. Rep.*, vol. 13, p. 5269, Mar. 2023.

[4] S. T. Ilie et al., "Thermo-optic tuning of silicon nitride microring resonators with low-loss non-volatile Sb_2S_3 phase change material," *Sci. Rep.*, vol. 12, p. 17810, Oct. 2022.

[5] E. Heidari et al., "Integrated ultra-high-performance graphene optical modulator," *Nanophotonics*, vol. 11, no. 12, pp. 2679–2690, Mar. 2022.

[6] L. A. Falkovsky and A. A. Varlamov, "Space-time dispersion of graphene conductivity," *Eur. Phys. J. B*, vol. 56, no. 4, pp. 281–284, Aug. 2007.

[7] G. W. Hanson, "Dyadic Green's functions and guided surface waves for a surface conductivity model of graphene," *J. Appl. Phys.*, vol. 103, no. 6, p. 064302, Mar. 2008.

[8] C. T. Phare, Y.-H. D. Lee, J. Cardenas, and M. Lipson, "Graphene electro-optic modulator with 30 GHz bandwidth," *Nature Photon.*, vol. 9, pp. 511–514, Jul. 2015.

[9] Y. Ding et al., "Effective electro-optical modulation with high extinction ratio by a graphene-silicon microring resonator," *Nano Lett.*, vol. 15, no. 7, pp. 4393–4400, Jun. 2015.

[10] H. A. Haus, *Waves and Fields in Optoelectronics*. Englewood Cliffs, NJ: Prentice-Hall, 1984.

[11] T. Christopoulos, O. Tsilipakos, and E. E. Kriezis, "Temporal coupled-mode theory in nonlinear resonant photonics," *J. Appl. Phys.*, vol. 136, no. 1, p. 011101, Jul. 2024.

[12] M. Romagnoli et al., "Graphene-based integrated photonics for next-generation datacom and telecom," *Nature Rev. Mater.*, vol. 3, pp. 392–414, Oct. 2018.

[13] M. Shekhirev et al., "Graphene phase modulators operating in the transparency regime," *ACS Nano*, vol. 18, no. 21, pp. 13729–13738, May 2024.

[14] Y.-M. Lin et al., "Dual-gate graphene FETs with f_T of 50 GHz," *IEEE Electron Device Lett.*, vol. 31, no. 1, pp. 68–70, Jan. 2010.

[15] G. T. Reed, G. Mashanovich, F. Y. Gardes, and D. J. Thomson, "Silicon optical modulators," *Nature Photon.*, vol. 4, pp. 518–526, Aug. 2010.

[16] K. Padmaraju and K. Bergman, "Resolving the thermal challenges for silicon microring resonator devices," *Nanophotonics*, vol. 3, no. 4–5, pp. 269–281, 2014.

[17] C. Qiu et al., "Efficient modulation of 1.55 μm radiation with gated graphene on a silicon microring resonator," *Nano Lett.*, vol. 14, no. 12, pp. 6811–6815, Nov. 2014.

[18] V. Sorianello et al., "Graphene–silicon phase modulators with gigahertz bandwidth," *Nature Photon.*, vol. 12, pp. 40–44, Jan. 2018.

[19] W. Bogaerts et al., "Programmable photonic circuits," *Nature*, vol. 586, no. 7828, pp. 207–216, Oct. 2020.

Authorized licensed use limited to: Purdue University. Downloaded on September 22,2026 at 23:54:26 UTC from IEEE Xplore. Restrictions apply.