

J1: stripped cable wires enter from TOP; solder on BOTTOM.
1 BLACK = GND; 2 RED = 3V3; 3 YELLOW = SDA; 4 GREEN = SCL.


J1
WIRE BLACK RED YELLOW GREEN



J2
M20-7820442 FEMALE



J3
M20-9990446 MALE



J4
B4B-PH-K-S



J5
BM04B-SRSS-TB



J2 female and J3 male: 2.54 mm pitch, four positions.
J4: JST PH, 2 mm pitch, through-hole, top entry.
J5: JST SH, 1 mm pitch, Qwiic, SMT on BOTTOM.

All five pin-number mappings: 1=GND, 2=3V3, 3=SDA, 4=SCL.
PH wiring is defined by this board; check the mating cable.
3.3 V I2C only. No regulator, level shifter or added pull-ups.
Check cable continuity before power. Wire colors alone are not proof.

26 x 16 mm. One copper layer: B.Cu. No vias or jumpers.
Local milling: 16 unplated solder holes, all solder joints on BOTTOM.
CAM is mirrored once for machining BOTTOM copper face-up.

All connectors parallel. Bottom copper only. No crossover or active parts.

Sheet: /
File: nezha-wire-hub.kicad_sch

Title: Nezha 3.3V wire / header / PH / Qwiic hub

Size: A4	Date: 2026-10-29	**Rev: A**
KiCad E.D.A. 9.0.8		Id: 1/1