DIMMER PANEL "DP"

Incoming Line: 120/208V, 3PH, 4W
Mains Rating: 200 AMP
Total Load: 49020 Watts

Dimmer Module	Load Capacity	Number of Fixtures	Connected Load	Circuit Number	Load Location	Fixture Type	Load Type	Channel/Zone Number	Remarks
1	2400	9	1800	1	NAVE	INCAND.	Dimmer	1	Emerg. UPS-1
1	2400	9	1800	2	NAVE	INCAND.	Dimmer	1	Emerg. UPS-2
2	2400	14	1120	3	NAVE	INCAND.	Dimmer	2	
2	2400	4	2300	4	FOUNTAIN	INCAND.	Dimmer	2	
3	2400	4	2300	5	NAVE	INCAND.	Dimmer	3	
3	2400	4	2300	6	NAVE	INCAND.	Dimmer	3	
4	2400	4	2300	7	NAVE	INCAND.	Dimmer	4	
4	2400	4	2300	8	NAVE	INCAND.	Dimmer	4	
5	2400	4	2300	9	NAVE	INCAND.	Dimmer	5	
5	2400	4	2300	10	NAVE	INCAND.	Dimmer	5	
6	2400	2	1150	11	NAVE	INCAND.	Dimmer	6	
6	2400	2	1150	12	CHOIR	INCAND.	Dimmer	7	
7	2400	2	1150	13	CHOIR	INCAND.	Dimmer	8	
7	2400	2	1150	14	CHOIR	INCAND.	Dimmer	9	
8	2400	2	1150	15	CHOIR	INCAND.	Dimmer	10	
8	2400	2	1150	16	CHOIR	INCAND.	Dimmer	11	
9	2400	4	2300	17	CHOIR	INCAND.	Dimmer	12	
9	2400	2	1150	18	SANCTUARY	INCAND.	Dimmer	13	
10	2400	2	1150	19	SANCTUARY	INCAND.	Dimmer	14	
10	2400	2	1150	20	ALTAR	INCAND.	Dimmer	15	
11	2400	2	1150	21	SANCTUARY	INCAND.	Dimmer	16	
11	2400		0	22	SPARE		Dimmer		
12	2400		0	23	SPARE		Dimmer		
12	2400		0	24	SPARE		Dimmer		
TOTAL			34620						

DIMMER CIRCUIT #1 & 2 SHALL BE FEED BY EMERGEMCY BATTERY UNIT "UPS"

PANEL "B"

120/208 VOLTS, 3 PHASE, 4 WIRE — MAIN BKR: M.L.S. — LOCATION HALLWAY — FEEDER (B) — 100 A. BUSSING — ENTER CAB'T. AT BOT. — FLUSH MTG.

LOCATION	WATTAGE ΦA	ΦB	ΦC	LTG	REC	MIS	CIR	BKR	BKR	CIR	MIS	REC	LTG	WATTAGE ΦA	ΦB	ΦC	LOCATION
EXISTING	500			·	·	·	1	20-1	20-1	2	·	·	·	500			EXISTING
EXISTING		500		·	·	·	3	20-1	20-1	4	·	·	·		500		EXISTING
EXISTING			500	·	·	·	5	20-1	20-1	6	·	·	·			500	EXISTING
EXISTING	500			·	·	·	7	20-1	20-1	8	·	·	·	500			EXISTING
EXISTING		500		·	·	·	9	20-1	20-1	10	·	·	·		500		EXISTING
EXISTING			500	·	·	·	11	20-1	20-1	12	·	·	·			500	EXISTING
EXISTING	500			·	·	·	13	15-1	20-1	14	·	·	·	500			EXISTING
EXISTING		500		·	·	·	15	15-1	20-1	16	·	·	·		500		EXISTING
EXISTING			500	·	·	·	17	20-1	20-1	18	·	·	·			500	EXISTING
EXISTING	500			·	·	·	19	20-1	20-1	20	·	·	·	500			EXISTING
EXISTING		500		·	·	·	21	20-1	20-1	22	·	·	·		500		EXISTING
EXISTING			500	·	·	·	23	20-1	20-1	24	·	·	·			500	SPARE
SPARE	·			·	·	·	25	20-1	20-1	26	·	·	·	·			SPARE
SPARE		·		·	·	·	27	20-1	20-1	28	·	·	·		·		SPARE
SPARE			·	·	·	·	29	20-1	20-1	30	·	·	·			·	SPARE
SPARE LOAD	0	0	0											0	0	0	SPARE LOAD

ΦA: 4000W — ΦB: 4000W — ΦC: 4000W

TOTAL CONNECTED LOAD: 4000 WATTS x 3 = 12000 WATTS OR 33.3 AMPS AT 208 VOLTS, 3 PHASE
LCL: 0 WATTS
FDL: 12000 WATTS + 0 WATTS (LCL) = 12000 WATTS OR 33.3 AMPS

(1) RECONNECT EXISTING BRANCH CIRCUITS TO NEW CIRCUIT BREAKERS SAME SIZE AS EXISTING. VERIFY EXACT BREAKER SIZE IN FIELD. PROVIDE UPDATED PANEL DIRECTORY.

PANEL "A"

120/208 VOLTS, 3 PHASE, 4 WIRE — MAIN BKR: M.L.S. — LOCATION WOMAN — FEEDER (A) — 100 A. BUSSING — ENTER CAB'T. AT BOT. — FLUSH MTG.

LOCATION	WATTAGE ΦA	ΦB	ΦC	LTG	REC	MIS	CIR	BKR	BKR	CIR	MIS	REC	LTG	WATTAGE ΦA	ΦB	ΦC	LOCATION
EXISTING	500			·	·	·	1	20-1	20-1	2	·	·	·	500			EXISTING
EXISTING		500		·	·	·	3	20-1	20-1	4	·	·	·		500		EXISTING
EXISTING			500	·	·	·	5	20-1	20-1	6	·	·	·			500	EXISTING
EXISTING	500			·	·	·	7	20-1	20-1	8	·	·	·	500			EXISTING
EXISTING		500		·	·	·	9	20-1	20-1	10	·	·	·		500		EXISTING
EXISTING			500	·	·	·	11	20-1	20-1	12	·	·	·			500	EXISTING
TOILETS	900			3	2	·	13	15-1	20-1	14	1	·	·	100			HEARING IMPAIRED TRANSMITTER
EF-1		695		·	·	1	15	15-1	20-1	16	2	·	·		200		CD/TAPE PLAYER
EF-2			695	·	·	1	17	20-1	20-1	18	1	·	·			500	PA RACK
SPARE	·			·	·	·	19	20-1	30-1	20	·	·	·	·			
SPARE		·		·	·	·	21	20-1	20-1	22	·	·	·		·		SPARE
SPARE			·	·	·	·	23	20-1	20-1	24	·	·	·			·	SPARE
SPARE	·			·	·	·	25	20-1	20-1	26	·	·	·	·			SPARE
SPARE		·		·	·	·	27	20-1	20-1	28	·	·	·		·		SPARE
SPARE			·	·	·	·	29	20-1	20-1	30	·	·	·			·	SPARE
SPARE	0	0	0											0	0	0	SPARE LOAD

ΦA: 3000W — ΦB: 2895W — ΦC: 3195W

TOTAL CONNECTED LOAD: 3195 WATTS x 3 = 9585 WATTS OR 26.6 AMPS AT 208 VOLTS, 3 PHASE
LCL: 900 WATTS x 25% = 225 WATTS
FDL: 9585 WATTS + 225 WATTS (LCL) = 9810 WATTS OR 27.3 AMPS

(1) RECONNECT EXISTING BRANCH CIRCUITS TO NEW CIRCUIT BREAKERS SAME SIZE AS EXISTING. VERIFY EXACT BREAKER SIZE IN FIELD. PROVIDE UPDATED PANEL DIRECTORY.

PANEL "C"

120/208 VOLTS, 3 PHASE, 4 WIRE — MAIN BKR: M.L.S. — LOCATION BASEMENT — FEEDER (C) — 100 A. BUSSING — ENTER CAB'T. AT BOT. — SURF MTG.

LOCATION	WATTAGE ΦA	ΦB	ΦC	LTG	REC	MIS	CIR	BKR	BKR	CIR	MIS	REC	LTG	WATTAGE ΦA	ΦB	ΦC	LOCATION
EXTERIOR RECEPT.	180			·	·	·	1	20-1	15-1	2	·	·	·	695			EXISTING SUMP PUMP
MECH. CONTROL PANEL		500		·	·	·	3	20-1	20-1	4	·	·	·		720		EXISTING BASEMENT RECEPTS
DUCT SMOKE DETECTOR			200	·	·	·	5	20-1	20-1	6	·	·	·			720	EXISTING BASEMENT LIGHTS
EMERGENCY BATTERY UNIT "UPS"	3700			·	·	·	7	30-1		8				900			-
SPARE		500		·	·	·	9	20-1	20-3	10	·	·	·		900		EXISTING ORGAN BLOWER
SPARE			500	·	·	·	11	20-1		12						900	-
SPACE	·			·	·	·	13	15-1	20-1	14	·	·	·	·			SPACE
SPACE		·		·	·	·	15	15-1	20-1	16	·	·	·		·		SPACE
SPACE			·	·	·	·	17	20-1	20-1	18	·	·	·			·	SPACE
SPARE LOAD	0	0	0											0	0	0	SPARE LOAD

ΦA: 4775W — ΦB: 2620W — ΦC: 2320W

TOTAL CONNECTED LOAD: 4775 WATTS x 3 = 14325 WATTS OR 39.8 AMPS AT 208 VOLTS, 3 PHASE
0 WATTS
14325 WATTS + 0 WATTS (LCL) = 14325 WATTS OR 39.8 AMPS
LCL:
FDL:

FIXTURE SCHEDULE

Q+4

- A 5/40 — FIXTURE TYPE "A" SHALL BE A CUSTOM CHANDELIER PROVIDED BY OTHERS AND INSTALLED BY THIS CONTRACTOR WITH THE TYPE OF LAMPS AS INDICATED ON THE ELECTRICAL DRAWINGS. COORDINATE THE ORDERING OF THE CHANDELIER WITH THE FIXTURE SUPPLIER TO INSURE THAT ALL MOUNTING HARDWARE IS PROVIDED WITH THE CHANDELIER AND THAT THE WIRING REQUIREMENTS OF THE CHANDELIER ARE IN ACCORDANCE WITH THE ELECTRICAL DRAWINGS.
- B 2/40 — FIXTURE TYPE "B" SHALL BE A CUSTOM WALL SCONCE PROVIDED BY OTHERS AND INSTALLED BY THIS CONTRACTOR WITH THE TYPE OF LAMPS AS INDICATED ON THE ELECTRICAL DRAWINGS. COORDINATE THE ORDERING OF THE WALL SCONCE WITH THE FIXTURE SUPPLIER TO INSURE THAT ALL MOUNTING HARDWARE IS PROVIDED WITH THE SCONCE
- C 2/32 — FIXTURE TYPE "C" SHALL BE A 2' X 4', SURFACE MOUNTED FLUORESCENT UNIT WITH 2-32 WATT, T-8 RAPID START LAMPS. FIXTURE SHALL HAVE A 100% VIRGIN ACRYLIC, INJECTION MOLDED PRISMATIC REFRACTOR. FIXTURE SHALL BE METULUX #SA-240-IMA-120-120-EB82 COLUMBIA #WWW4-232-EB8120 OR EQUAL BY LITHONIA, PRUDENTIAL OR H.E WILLIAMS.
- D 2/26 — FIXTURE TYPE "D" SHALL BE A 7-3/8" ROUND RECESSED FLUORESCENT DOWNLIGHT WITH OPEN SPECULAR CLEAR ALZAK REFLECTOR AND 2-26 WATT PL LAMPS MOUNTED HORIZONTALLY. FIXTURE SHALL BE INFINITY #PH75-226Q-EB-1-120 OR EQUAL BY INDY.
- DD 2/26 — FIXTURE TYPE "DD" SHALL BE A 7-3/8" ROUND RECESSED FLUORESCENT DOWNLIGHT WITH OPEN SPECULAR CLEAR ALZAK REFLECTOR AND 2-26 WATT PL LAMPS MOUNTED HORIZONTALLY. FIXTURE SHALL HAVE EMERGENCY BATTERY UNIT WITH REMOTE TEST SWITCH. FIXTURE SHALL BE INFINITY #PH75-226Q-EB-1-120-EM OR EQUAL BY INDY. EXIT SIGNS SHALL COMPLY WITH U.L. STANDARD 1994.

28-Single face
2-Double face

- E – — FIXTURE TYPE "E" SHALL BE AN INSTITUTIONAL SURFACE MOUNTED NON-ELECTRIC EXIT SIGN WITH GREEN LEGEND AND RATED FOR 15 YEARS LIFE. SIGN SHALL BE COMPLETE WITH 3/8" TRANSPARENT POLYCARBONATE COVER. AT EACH REQUIRED EXIT, ONE SIGN SHALL ABOVE DOOR HEIGHT AND ONE SIGN AT +12" ABOVE FLOOR TO BOTTOM OF SIGN. SIGN SHALL BE EMERGI-LITE #SLX-2061-G OR #AFPC-SLX-2061-G OR EQUAL BY ISOLITE CORP.OR PERMEX.
- F1 1/575 — FIXTURE TYPE "F1" SHALL BE A 575 WATT THEATRICAL ELLIPSOIDAL SPOTLIGHT AS SPECIFIED UNDER SECTION 16580, LIGHTING AND DIMMING CONTROLS.
- F2 1/575 — FIXTURE TYPE "F2" SHALL BE 575 WATT THEATRICAL FLOODLIGHT AS SPECIFIED UNDER SECTION 16580, LIGHTING AND DIMMING CONTROLS.
- G 4/40 — FIXTURE TYPE "G" SHALL BE A MINI BRACELET BATH MIRROR LIGHT MOUNTED OVER MIRROR AND ON BOTH SIDES OF THE MIRROR. FIXTURE SHALL BE 24"-36" WITH 4-6 KX200 CANDELABRA 40W LAMPS AS REQUIRED. FIXTURES SHALL BE LIGHTOLIER #44222-PC AND/OR #44232-PC.
- H 2/26 — FIXTURE TYPE "H" SHALL BE A 14" SQ. SURFACE MOUNTED FLUORESCENT UNIT WITH 2-26 WATT, PL LAMPS. FIXTURE SHALL HAVE A 100% VIRGIN ACRYLIC, INJECTION MOLDED PRISMATIC REFRACTOR. FIXTURE SHALL BE KENALL #S141D-P-MW-26Q-2-120.
- HH 2/26 — FIXTURE TYPE "HH" SHALL BE A 14" SQ. SURFACE MOUNTED FLUORESCENT UNIT WITH 2-26 WATT, PL LAMPS AND EMERGENCY BATTERY PACK. FIXTURE SHALL HAVE A 100% VIRGIN ACRYLIC, INJECTION MOLDED PRISMATIC REFRACTOR. FIXTURE SHALL BE KENALL #S141D-P-MW-26Q-2-120-EL.

FEEDER SCHEDULE

FEEDER	VOLTAGE	FROM	TO	KW LOADS	AMPS	APPROX. DISTANCE (VERIFY)	CONDUCTORS "THW"	CONDUIT	GROUND WIRE	REMARKS
C	120/208	MSA	PANEL "C"	14.3	39.8	20	4#4	1 1/4	8	-
CU-2	120/208	MSA	CONDENSING UNIT CU-2	30.2	83.9	100	3#1	1 1/4	6	-
CU-1	120/208	MSA	CONDENSING UNIT CU-1	30.2	83.8	100	3#1	1 1/4	6	-
AH-2	120/208	MSA	AIR HANDLER AH-2	11.2	31	50	3#8	1	8	-
AH-1	120/208	MSA	AIR HANDLER AH-2	11.2	31	50	3#8	1	8	-
A	120/208	MSA	PANEL "A"	9.6	26.7	150	4#4	2	8	NEW & EXIST. CONDUIT
B	120/208	MSA	PANEL "B"	12.0	33.3	50	4#4	1 1/4	8	NEW & EXIST. CONDUIT
DP	120/208	MSA	DIMMER PANEL "DP"	34.6	96.2	30	4#1/0	2"	6	-
MSA	120/208	METER SECTION	MSA DISTRIB. SECTION	153.3	425.8	20	8#350Kcmil	(2)3"	1	-

AS-BUILT
MAMMOTH ELECTRIC, INC.
DATED

Onuma & Associates
Architecture, Planning, Consulting
511 Mission Street
South Pasadena, CA 91030
tel 626. 799. 9920
fax 626. 799. 8260
e-mail: info@onuma.com

Consultants

RANDALL ENGINEERING
CONSULTING ELECTRICAL ENGINEER
2309 ALESSANDRO STREET
ALTADENA, CA 91001
323-667-9081 FAX: 323-667-9083

REMODEL
FOR
SAINT EDMUND'S
EPISCOPAL CHURCH
1175 SAN GABRIEL BLVD., SAN MARINO, CA., 91108-8048

STAMPS

REGISTERED PROFESSIONAL ENGINEER — RUSSELL F. RANDALL — No. 4848 Exp. 6-2002 — ELECTRICAL — STATE OF CALIFORNIA

REVISIONS

DESCRIPTION	DATE	BY

PROJECT NUMBER: RE-123
SCALE: AS NOTED
PRINTED: 12/27/00
TITLE: PANEL SCHEDULES AND DIMMER PANEL "DP"
SHEET: E-8
44 OF 44

1=1.00
K:\Drawings\99042 St Edmunds Church\e-08.dwg,DWG
12/28/0 14:00