

Morfeas WEB Help Manual

Current New Web UI

Contents

1	Introduction	2
2	Main Page	2
2.1	What You See	2
2.2	Main Table	2
2.3	Search	3
2.4	Context Menu	3
3	Menu Overview	3
4	Network Configuration	3
4.1	Fields	3
4.2	Buttons	4
4.3	Operator Notes	4
5	Add Devices	4
5.1	Devices Table	4
5.2	Toolbar	4
5.3	Add Form	5
5.4	Operator Notes	5
6	Channel Replace Workflows	5
6.1	Single-Channel Replace	5
6.1.1	Typical Flow	5
6.1.2	Type Safety	5
6.1.3	Offline Type Display	6
6.2	TC16 Group Replace	6
6.2.1	When the Option Appears	6
6.2.2	How It Works	6
6.2.3	Important Notes	6
7	Backup and Restore Channels	7
7.1	FTP Server Setup	7
7.2	Backup to FTP	7
7.3	Restore from FTP	7
7.4	Step-by-Step Example	7
7.4.1	Connect and Load Backup List	7
7.4.2	Create a Backup	7

7.4.3	Restore a Backup	8
7.5	Operator Notes	8
8	Check System Status	8
8.1	Tabs	8
8.1.1	Details	8
8.1.2	System Logs	9
8.1.3	System Journal	9
8.2	How to Use the Tabs	9
8.2.1	Details Tab	9
8.2.2	System Logs Tab	9
8.2.3	System Journal Tab	10
9	Advanced Settings	10
9.1	Machine Identifier	10
9.2	SDAQNet (CAN-IFs)	10
9.3	Time Synchronization	10
9.4	ISOstandard	10
10	System Update	10
10.1	Current Behavior	11
10.2	Reminder Dot	11
10.3	Important Note	11
11	System Reboot and System Shutdown	11
11.1	System Reboot	11
11.2	System Shutdown	12
12	Version	12
13	Troubleshooting	12
13.1	The Web Page Does Not Open	12
13.2	FTP Backup Cannot Connect	12
13.3	No Backup Files Are Listed	12
13.4	Replace or Replace TC16 Option Is Missing	13
13.5	No Eligible TC16 Target Is Listed	13
13.6	Logs or Journal Look Empty	13
13.7	Update Reminder Dot Is Still Visible	13
14	Help PDF Maintenance	13
15	Legacy Documentation Status	13

Introduction

Morfeas WEB is the browser user interface for daily operation and configuration of the Morfeas system. This manual describes the current **new** Morfeas web interface and is intended for operators and service users.

Unless a site-specific deployment says otherwise, open the system in a browser with:

- `http://<device-ip>/`

This manual does not describe the retired legacy web layout.

Screenshot Placeholder: Main Landing Page

Insert a current screenshot of the ISO Channels Linker landing page, showing the top bar, menu button, search bar, and the main channel table.

Main Page

The landing page is **ISO Channels Linker**. It is the main operational screen.

What You See

The page contains:

- a top bar with the FTP backup directory chip and rolling system summary,
- a search bar,
- action buttons for importing and adding channels,
- the main ISO channel table,
- a right-click context menu for channel actions,
- a menu button that opens all secondary pages.

Main Table

The table shows the configured ISO channels and related runtime information. Typical columns include:

- status,
- ISO channel name,
- device type,
- connection anchor,
- current value,
- history,
- next calibration,
- minimum and maximum values,
- description.

The page refreshes automatically while it is visible, so operators normally do not need to reload manually.

Search

Use **Search Input** to filter channels in the current table.

Context Menu

Right-click a row to access actions such as:

- Edit,
- Delete,
- Scale,
- Calibration,
- Export,
- device-specific actions such as Replace or Replace TC16 when the selected channel supports them.

Menu Overview

The main menu is grouped as follows.

Menu Item	Purpose
Network Configuration	Edit hostname and Ethernet IPv4 settings.
Add Devices	View current devices and add or remove supported devices.
Backup & Restore Channels	Configure FTP backup target, create backups, and restore saved bundles.
Check System Status	View live runtime details, log files, and system journal output.
Advanced Settings	View MAC/CAN information, configure NTP server, and manage ISOstandard XML.
System Update	Check for available Morfeas web updates and apply them when desired.
System Reboot	Reboot the device.
System Shutdown	Power off the device.
Version	Show current web and core version information.
Help	Download this manual as PDF.

Network Configuration

Open **Network Configuration** from the menu to edit hostname and Ethernet settings.

Fields

The page contains:

- **Hostname**
- **Mode:** Static or DHCP
- **Network IP**
- **Gateway**
- **DNS addr**

Preset buttons are available at the top of the page for quick loading of predefined values.

Buttons

- **Load Last:** reload the last confirmed configuration into the form.
- **Set:** apply the current values.
- **Close:** close the popup window.

Operator Notes

- If you change the device IP address, reconnect the browser to the new HTTP address after the change is applied.
- DHCP mode disables manual IPv4 entry.
- Presets are convenience values only. Review them before applying.

Screenshot Placeholder: Network Configuration Page

Insert a screenshot showing Hostname, Mode, Network IP, Gateway, DNS addr, and the Load Last / Set / Close buttons.

Example Message (Progress):

Applying configuration: validating and writing system network settings...

Example Message (Success):

Configuration applied. If the IP changed, reconnect to the new device address in your browser.

Example Message (Failure):

Apply failed: <error details>

Add Devices

Open **Add Devices** to manage the current device inventory.

Devices Table

The upper table shows the current devices with columns such as:

- Bus,
- Device Type,
- Device Name or Address,
- IP Address.

Toolbar

- **Refresh:** reload the current device list.
- **Remove:** remove selected removable devices.

- **Add...:** open the add form.

Add Form

The add form lets the user enter:

- device type,
- CAN interface,
- device name,
- additional device properties required by that device family.

Operator Notes

- Some devices, such as automatically detected SDAQ devices, may not be removable from this page.
- The popup refreshes while active, and pauses when the popup is no longer in focus.
- If the remove action is not available or shows a warning, review whether the selected device is auto-detected and protected from removal.

Channel Replace Workflows

Morfeas WEB supports both single-channel replacement and grouped TC16 replacement.

Single-Channel Replace

Single-channel replace uses the standard Edit Link popup in replace mode.

Typical Flow

1. In the main ISO channel table, right-click the channel you want to replace.
2. Choose the standard replace action.
3. The popup opens with the source type locked and the target path chosen through device search.
4. Select the replacement device path.
5. Review ISO code, description, min/max, alarms, unit, and calibration fields.
6. Click **Save**.

Type Safety

The replace flow enforces compatibility rules.

Screenshot Placeholder: Single-Channel Replace Popup

Insert a screenshot of the replace popup showing the locked source type, search button, ISO code, limits, alarms, and Save button.

- Family mismatch is blocked.
- If the source SDAQ subtype is known, subtype mismatch is blocked.
- If the source SDAQ subtype is unknown, replacement is still allowed, but the user is warned to replace within the same type.

Offline Type Display

When an SDAQ channel has been identified before and later goes offline, the UI can display the last known type in a stale form such as:

- SDAQ-TC1 (last known)

If the subtype has never been identified, the type may be shown as unknown.

Example Message (Warning):

Subtype unknown, make sure replace within same type.

Example Message (Blocked Replace):

Subtype mismatch: expected SDAQ-TC1, got SDAQ-AI8.

TC16 Group Replace

The dedicated **Replace TC16** flow is separate from single-channel replace. It is intended for a full 16-channel SDAQ-TC16 source group.

When the Option Appears

Replace TC16 only appears when the selected source channel belongs to a resolvable offline TC16 group that is complete as channels CH1 through CH16. If the group is partial, the option is not shown and normal single-channel replace must be used.

How It Works

1. Right-click any channel belonging to the full TC16 source group.
2. Choose **Replace TC16**.
3. The UI highlights and selects all 16 source channels.
4. A dedicated Replace TC16 popup opens.
5. The popup shows the source group summary and the source channel mapping.
6. Choose one eligible unlinked TC16 target device.
7. Confirm the operation.
8. All 16 source channels are remapped to the target device in one atomic operation.

Important Notes

- Replace TC16 is all-or-nothing.
- If any validation fails, no channel mapping is changed.
- Target selection is at device-group level, not one channel at a time.
- If no eligible target is listed, there is currently no fully free TC16 target device available.

Screenshot Placeholder: Replace TC16 Popup

Insert a screenshot showing the source group summary, CH1..CH16 mapping chips, available target list, and the Apply Replace TC16 button.

Example Message (Success):

Replace TC16 complete: 16 channels updated.

Example Message (Failure):

Failed to apply TC16 replace. [tc16_target_not_unlinked]

Backup and Restore Channels

Open **Backup & Restore Channels** for FTP-based backup and restore.

FTP Server Setup

The page contains:

- **Host IP**
- **Engine Number**
- **Connect & Fetch**
- **Disconnect**

The default host value is prefilled for the expected FTP server. Credentials are stored server-side and are not edited in the UI.

Backup to FTP

Use **Backup Now** to create and upload a backup bundle for the current configuration.

Restore from FTP

Select a backup file from the list and click **Restore Selected**.

Step-by-Step Example**Connect and Load Backup List**

1. Open **Backup & Restore Channels**.
2. Confirm or enter the FTP server IP.
3. Enter the engine number.
4. Click **Connect & Fetch**.
5. Wait for the connection result.
6. If the connection succeeds, the backup list is loaded for that engine directory.

Create a Backup

1. Make sure the FTP connection is active.
2. Click **Backup Now**.
3. Wait for the success message.
4. Confirm that the new file appears in the backup list.

Restore a Backup

1. Make sure the FTP connection is active.
2. Select one file from the backup list.
3. Click **Restore Selected**.
4. Wait for the restore result message.

Operator Notes

- Backup and restore both require a reachable FTP server.
- If the server is unavailable, the page shows an error and no system state is changed.
- The FTP directory chip on the main page shows the currently connected engine directory when configuration exists.
- If two sessions edit the FTP configuration, the page can detect configuration updates from the other session.

Screenshot Placeholder: FTP Backup and Restore Page

Insert a screenshot showing the FTP Server Setup, Backup Now, Restore Selected, and the available backup list.

Example Message (Connect Success):

Connected to FTP at 10.193.135.70. Configuration saved.

Example Message (Connect Failure):

Connection failed: FTP connect failed

Example Message (Backup Success):

Backup complete

Example Message (Restore Failure):

Restore failed: <error details>

Check System Status

Open **Check System Status** to inspect runtime data and logs.

Tabs

The page has three tabs.

Details

This tab shows live system and bus information in tables. Depending on the device and services, values may include:

- CPU temperature,

- uptime,
- bus utilization,
- bus error rate,
- detected SDAQ count,
- incomplete SDAQ count,
- bus voltage,
- bus amperage,
- shunt temperature,
- last calibration timestamps.

System Logs

This tab is used for Morfeas application logger files.

- **Preview Logger:** choose one log file to preview.
- **Reload:** reload the logger list.
- **Export Logs:** select one or more log files and export them as one combined text file.

The preview area shows the selected file content in a terminal-style viewer.

System Journal

This tab is used for journal output from system services.

- **Scope:** choose all services, Morfeas system, Apache2, or SSH.
- **Lines:** choose how many lines to load.
- **Reload:** reload the journal view.
- **Export Journal:** export the currently requested journal text.

Screenshot Placeholder: System Status Tabs

Insert a screenshot showing the Details, System logs, and System Journal tabs with one example content area visible.

How to Use the Tabs

Details Tab

Use this tab first when checking current runtime health. If a service is active but values look stale, compare with the Logs or Journal tabs.

System Logs Tab

Use this tab for Morfeas component logs when you want application-level detail such as handler messages, update logs, backup logs, or runtime component reports.

System Journal Tab

Use this tab when the problem looks system-level rather than application-level, for example:

- service startup failures,
- Apache problems,
- SSH availability,
- reboot or shutdown investigation.

Advanced Settings

Open **Advanced Settings** for machine information, NTP, and ISOstandard management.

Machine Identifier

Displays the MAC address.

SDAQNet (CAN-IFs)

Displays the current CAN interface information for `can0` and `can1`. These values are informational and read-only on this page.

Time Synchronization

The page shows the current NTP server and allows entering a new IPv4 NTP server. Use **Apply** to store the new value.

Example Message (Apply Success):

Applied NTP server: 192.168.1.10

Example Message (Validation Error):

NTP server must be a valid IPv4 address.

ISOstandard

This section lets the user:

- view the currently selected ISOstandard source,
- select a different available ISOstandard file,
- upload a new ISOstandard XML file,
- review the loaded ISO point definitions in a table.

System Update

Open **System Update** to manage Morfeas web software updates.

Current Behavior

The page supports:

- checking whether an update is available,
- applying the update,
- deferring the update,
- reloading the page after service recovery.

Reminder Dot

A red dot on the menu item indicates that the system has recorded an available update. The reminder stays visible until a later check confirms that no update is pending, or until a successful update clears it.

Important Note

The current update flow is intended for the Morfeas web deployment path. Core update is handled separately.

Screenshot Placeholder: System Update Page

Insert a screenshot showing Check Again, Update Now, Update Later, Reload Page, and the status box.

Example Message (Update Available):

Update available. Click "Update Now" to apply, or "Update Later" to postpone.

Example Message (Update Success):

Update flow completed and web service is reachable. Refresh page (Ctrl+F5) to load latest files.

Example Message (Update Failed):

System update failed: <error details>

System Reboot and System Shutdown

The system control pages provide single-confirmation actions for reboot and shutdown.

System Reboot

Use **Reboot Now** when you want to restart the device and return to service after boot. The page shows post-action guidance so the operator knows when to reconnect and refresh the browser.

Example Message (Reboot Accepted):

Reboot command accepted. Wait about 60–90 seconds, then open the device URL again and refresh the browser.

System Shutdown

Use **Shutdown Now** when you want to power off the device. After shutdown, the device must be powered on again manually before the web interface becomes available.

Example Message (Shutdown Accepted):

Shutdown command accepted. Device will go offline. Power it on manually when needed.

Version

The **Version** page shows version and commit information for:

- the Morfeas web repository,
- the Morfeas core repository,
- the related commit dates.

Use this page when confirming what software is installed on a device.

Troubleshooting

This section gives quick operator guidance for common problems.

Screenshot Placeholder: Troubleshooting Section Reference

Optionally insert a screenshot collage of the key popups or status messages that operators most commonly use during troubleshooting.

The Web Page Does Not Open

- Confirm that you are using the current device IP address over HTTP.
- If the IP was recently changed, reconnect to the new address.
- If the device was rebooted or updated, wait for services to come back and refresh the browser.
- If still unavailable, check **System Journal** or use SSH to verify Apache and Morfeas services.

FTP Backup Cannot Connect

- Check that the FTP server IP is reachable from the device.
- Confirm that the engine number is correct.
- If the page says configuration was removed, reconnect first.
- If the internal FTP server is currently unavailable, backup and restore cannot be tested end-to-end.

No Backup Files Are Listed

- Verify that the selected engine directory contains backup files.
- Confirm that the FTP configuration belongs to the expected engine number.
- Reload after reconnecting to the FTP server.

Replace or Replace TC16 Option Is Missing

- Confirm that the selected row supports that replace mode.
- For Replace TC16, confirm that the source is a complete offline TC16 group with channels CH1 through CH16.
- If the source group is partial, use normal single-channel replace instead.

No Eligible TC16 Target Is Listed

- No full unlinked TC16 target device is currently available.
- If channels on the target are already linked, the target is blocked.
- Refresh the popup after any device or link changes.

Logs or Journal Look Empty

- Use **Reload** once to refresh the selected tab.
- Verify that the correct logger file or journal scope is selected.
- If the service has not produced messages yet, the view may be temporarily empty.

Update Reminder Dot Is Still Visible

- The reminder is based on the stored update flag.
- Run **Check Again** in the System Update page to refresh the latest status.
- After a successful update or a clean re-check, the reminder should clear.

Help PDF Maintenance

The Help menu downloads a PDF file from:

- docs/help_manual.pdf

The maintained source for this file is located under:

- Morfeas_WEB/docs/manual/

This keeps the active user manual next to the current web code instead of inside the archived legacy documentation tree.

Legacy Documentation Status

The old documentation tree under `LOG-web/Docs/Morfeas_WEB_Docs` is retained only as historical reference. Its structure and API descriptions belong to the legacy implementation and should not be used as the active operator manual for the current web UI.