Ve216 Introduction to Signals and Systems: Summary
May 3, 2020, 18:11
Yong Long, UM-SJTU Joint Institute
(Based on Lecture Notes by Prof. Jeffrey A. Fessler)

Signals and Systems: Summary 1

- Circuits: $v(t) = Ri(t)$, $v(t) = L\frac{\mathrm{d}}{\mathrm{d}t}i(t)$, $i(t) = C\frac{\mathrm{d}}{\mathrm{d}t}v(t)$
- Notation: $x(t) = \begin{cases} e^{-t}, & t > 2, \\ 0, & \text{otherwise} \end{cases} = e^{-t}u(t-2)$
- Time transformation:
  - $x\left(\frac{t-t_0}{w}\right)$. First scale according to w, then shift according to t_0.
  - $x(at - b)$. First time-delay by b, then time-scale by a
- Integrator system $y(t) = \int_{-\infty}^{t} x(\tau)\,d\tau = x(t) * u(t)$
- Even symmetry: $x(-t) = x(t)$, Odd symmetry: $x(-t) = -x(t)$
- $\text{Ev}\{x(t)\} = \frac{1}{2}(x(t) + x(-t))$, $\text{Od}\{x(t)\} = \frac{1}{2}(x(t) - x(-t))$, $x(t) = \text{Ev}\{x(t)\} + \text{Od}\{x(t)\}$.

- Average value: $A \triangleq \lim_{T\to\infty} \frac{1}{2T} \int_{-T}^{T} x(t)\,dt$
- Energy: $E \triangleq \int_{-\infty}^{\infty} |x(t)|^2\,dt$
- Average power: $P \triangleq \lim_{T\to\infty} \frac{1}{2T} \int_{-T}^{T} |x(t)|^2\,dt$
- Energy signal: $E < \infty$, $P = 0$.
- Power signal: $E = \infty$, $0 < P < \infty$.
- Power of periodic signal: $P = \frac{1}{T_0} \int_0^{T_0} |x(t)|^2\,dt$

- Step function: $u(t) = 1$ for $t > 0$.
- Rect function: $\text{rect}(t) = 1$ for $-1/2 < t < 1/2$, $\text{rect}(t) = u(t + 1/2) - u(t - 1/2) = u(t + 1/2)u(1/2 - t)$
- Impulse functions
  - Sifting property: $\int_{-\infty}^{\infty} x(t)\delta(t - t_0)\,dt = x(t_0)$ if $x(t)$ is continuous at t_0
  - Sampling property: $x(t)\delta(t - t_0) = x(t_0)\delta(t - t_0)$ if $x(t)$ is continuous at t_0
  - unit area property: $\int_{-\infty}^{\infty} \delta(t - t_0)\,dt = 1$ for any t_0
  - scaling property: $\delta(at + b) = \frac{1}{|a|}\delta(t + b/a)$ for $a \neq 0$.
  - symmetry property: $\delta(t) = \delta(-t)$
  - support property: $\delta(t - t_0) = 0$ for $t \neq t_0$
  - relationships with unit step function: $\delta(t) = \frac{\mathrm{d}}{\mathrm{d}t}u(t)$, $u(t) = \int_{-\infty}^{t} \delta(\tau)\,d\tau$

Continuous-time system properties
- Stability (BIBO): all bounded input signals produce bounded output signals
- Invertibility: each output signal is the response to only one input signal
- Causal: output signal value $y(t)$ at any time t depends only on present and past input signal values.
- Static (memoryless): output at any time only depends on input signal at the same time. (otherwise dynamic)
- Time invariant:

- $x(t) \xrightarrow{\mathcal{T}} y(t)$ implies that $x(t - t_0) \xrightarrow{\mathcal{T}} y(t - t_0)$
- Recipe for showing time-invariance.
  - Determine output signal $y(t)$ due to a generic input signal $x(t)$.
  - Determine the delayed output signal $y(t - t_0)$, by replacing t with $t - t_0$ in $y(t)$ expression.
  - Determine output signal $y_d(t)$ due to a delayed input signal $x_d(t) = x(t - t_0)$.
  - If $y_d(t) = y(t - t_0)$, then system is time-invariant.
- Linear systems:
  - superposition property: $\mathcal{T}[\sum_k a_k x_k(t)] = \sum_k a_k \mathcal{T}[x_k(t)]$
  - additivity property: $\mathcal{T}[x_1(t) + x_2(t)] = \mathcal{T}[x_1(t)] + \mathcal{T}[x_2(t)]$
  - scaling property: $\mathcal{T}[ax(t)] = a\mathcal{T}[x(t)]$

LTI systems

input-output relationship described by convolution integral:

$$y(t) = \int_{-\infty}^{\infty} x(t - \tau)h(\tau)\, d\tau = \int_{-\infty}^{\infty} h(t - \tau)x(\tau)\, d\tau$$

Properties:
- Commutative property: $x(t) * h(t) = h(t) * x(t)$
- Associative property: $[x(t) * h_1(t)] * h_2(t) = x(t) * [h_1(t) * h_2(t)]$
- Distributive property: $x(t) * [h_1(t) + h_2(t)] = [x(t) * h_1(t)] + [x(t) * h_2(t)]$
- The order of serial connection of LTI systems does not affect the overall impulse response.
- $x(t) * \delta(t) = x(t)$
- Delay property: $x(t) * \delta(t - t_0) = x(t - t_0)$
- $\delta(t - t_0) * \delta(t - t_1) = \delta(t - t_0 - t_1)$
- Time-invariance: If $y(t) = x(t) * h(t)$, then $x(t - t_0) * h(t - t_1) = y(t - t_0 - t_1)$

LTI system properties
- causal: $h(t) = 0$ for all $t < 0$
- static: $h(t) = k\delta(t)$, otherwise dynamic
- stable: $\int_{-\infty}^{\infty} |h(t)|\, dt < \infty$
- invertible: $h(t) * h_i(t) = \delta(t)$ for some $h_i(t)$
  If $h(t) * x(t) = 0$ for some nonzero signal $x(t)$, then not invertible
- step response: $h(t) = \frac{d}{dt}s(t)$, where $u(t) \xrightarrow{\text{LTI}} s(t)$

Linear, constant coefficient, differential equation systems
- LTI and causal if initially at rest
- dynamic unless $N = M = 0$
- homogenous solution, natural response:
  $y_h(t) = \sum_l C_l e^{s_l t}$, where s_l's are the N roots of the characteristic polynomial $\sum_{k=0}^{N} a_k s^k = 0$.
- particular solution, forced response: $y_p(t) = P_0 x(t) + P_1 \frac{d}{dt}x(t) + \cdots$

Signals and Systems: Summary 2

Fourier Series
- Analysis equation: $c_k = \frac{1}{T_0} \int_0^{T_0} x(t) e^{-jk\omega_0 t}\, dt,\ k = 0, \pm 1, \pm 2, \dots$.
- DC value: $c_0 = \frac{1}{T_0} \int_0^{T_0} x(t)\, dt$.
- Synthesis equation: $x(t) = \sum_{k=-\infty}^{\infty} c_k e^{jk\omega_0 t}$
- Combined trigonometric form: $x(t) = c_0 + \sum_{k=1}^{\infty} 2\,|c_k| \cos(k\omega_0 t + \angle c_k)$, if $x(t)$ is real.
- Trigonometric form: $x(t) = c_0 + 2\sum_{k=1}^{\infty} A_k \cos(k\omega_0 t) - B_k \sin(k\omega_0 t)$, where $A_k = \mathrm{real}\{c_k\}$ and $B_k = \mathrm{Imag}(c_k)$

Convergence properties
- Error signal $e_N(t) = x(t) - x_N(t)$ where $x_N(t) = \sum_{k=-N}^{N} c_k e^{jk\omega_0 t}$ when c_k's chosen according to above FS analysis equation
- Error signal energy $E_N = \int_{T_0} |e_N(t)|^2\, dt \to 0$ as $N \to \infty$, provided $x(t)$ square integrable: $\int_{T_0} |x(t)|^2\, dt < \infty$
- $e_N(t) \to 0$ as $N \to \infty$ provided Dirichlet conditions hold
- Near the discontinuity there will usually be overshoot and/or undershoot that persists even as N increases, which is called Gibbs phenomenon.

One-signal properties (Fourier series transformations)
- Amplitude transformation: $ax(t) + b \leftrightarrow \begin{cases} b + ac_0, & k = 0 \\ ac_k, & k \neq 0. \end{cases}$
- Time transformation: $x(at + b) \leftrightarrow \begin{cases} c_k e^{jk\omega_0 b}, & a > 0 \\ c_{-k} e^{-jk\omega_0 b}, & a < 0. \end{cases}$ $\quad \omega_1 = |a|\omega_0$
- Time shift: $x(t - t_0) \leftrightarrow c_k e^{-jk\omega_0 t_0}$
- Conjugation: $[x(t)]^* \leftrightarrow c_{-k}^*$
- Complex modulation (frequency shift): $x(t) e^{j\omega_0 tN} \leftrightarrow c_{k-N}$
- Differentiation: $y(t) = \frac{d}{dt} x(t) \leftrightarrow jk\omega_0\, c_k$

Properties
- If $x(t)$ is real, then $c_{-k} = c_k^*$.
- Linearity (add coefficients if same period T_0)
- Multiplication $c_k = \sum_{l=-\infty}^{\infty} a_l b_{k-l}$. (discrete convolution)
- Filtering: see below
- Circular convolution: skip
- Total harmonic distortion: THD $= (1 - 2|c_1|^2/P) \cdot 100\%$
- Power of $ce^{jk\omega_0 t}$ is $|c|^2$
- Power of $A\cos(\omega t + \phi)$ is $A^2/2$
- Parseval's theorem:
  $P = \frac{1}{T_0} \int_{T_0} |x(t)|^2\, dt = \sum_{k=-\infty}^{\infty} |c_k|^2$
- Power density spectrum: $|c_k|^2$
- Magnitude spectrum: $|c_k|$. Phase spectrum: $\angle c_k$

Foundations of Filtering
- $x(t) = e^{st} \xrightarrow{\text{LTI}} y(t) = H(s)e^{st}$
- Laplace transform of $h(t)$, aka system function: $H(s) = \int_{-\infty}^{\infty} h(t) e^{-st}\, dt$
- $x(t) = e^{j\omega t} \xrightarrow{\text{LTI}} y(t) = H(j\omega)e^{j\omega t} = |H(j\omega)|e^{j(\omega t + \angle H(j\omega))}$
- Fourier transform of $h(t)$, aka frequency response: $H(j\omega) = \int_{-\infty}^{\infty} h(t) e^{-j\omega t}\, dt = H(s)|_{s=j\omega} = |H(j\omega)|e^{j\angle H(j\omega)}$
- $x(t) = \sum_k c_k e^{j\omega_k t} \xrightarrow{\text{LTI}} y(t) = \sum_k c_k H(j\omega_k)e^{j\omega_k t}$
- If $h(t)$ is real, then $H^*(s) = H(s^*)$ and $H(-j\omega) = H^*(j\omega)$. (Hermitian symmetry)
- If $h(t)$ is real, $x(t) = \cos(\omega t + \phi) \xrightarrow{\text{LTI}} y(t) = |H(j\omega)| \cos(\omega t + \phi + \angle H(j\omega))$
- $x(t) = \sum_k A_k \cos(\omega_k t + \phi_k) \to \boxed{\text{LTI } h(t)} \to y(t) = \sum_k A_k |H(j\omega_k)| \cos(\omega_k t + \phi_k + \angle H(j\omega_k))$

Fourier Transform
- Fourier transform (analysis): $F(\omega) = \int_{-\infty}^{\infty} f(t)e^{j\omega t}\,dt$.
- Inverse Fourier transform (synthesis): $f(t) = \frac{1}{2\pi}\int_{-\infty}^{\infty} F(\omega)e^{j\omega t}\,d\omega$
- The FT of a signal $f(t)$ exists (converges) if $f(t)$ is absolutely integrable, *i.e.*, $\int_{-\infty}^{\infty} |f(t)|\,dt < \infty$. (more rigorously, $f(t)$ satisfies the Dirichlet conditions)
- For periodic signals: $x(t) = \sum_{k=-\infty}^{\infty} c_k e^{jk\omega_0 t} \xleftrightarrow{\mathcal{F}} X(\omega) = \sum_{k=-\infty}^{\infty} c_k 2\pi\delta(\omega - k\omega_0)$.
- $x(t) = \sum_{n=-\infty}^{\infty} g(t - nT_0) \xleftrightarrow{\mathcal{F}} X(\omega) = \sum_{k=-\infty}^{\infty} \omega_0 G(k\omega_0)\delta(\omega - k\omega_0)$
- Energy density spectrum: $|X(\omega)|^2$
- Energy over a spectral band: $E_B = \frac{1}{2\pi}\int_B |X(\omega)|^2\,d\omega$
- Symmetry properties
$$
\begin{array}{ccccccccc}
f(t) & = & f_R^e(t) & + & jf_I^e(t) & + & f_R^o(t) & + & jf_I^o(t) \\
& & \updownarrow & & \updownarrow & & & \times & \\
F(\omega) & = & F_R^e(\omega) & + & jF_I^e(\omega) & + & F_R^o(\omega) & + & jF_I^o(\omega)
\end{array}
$$

Signals and Systems: Summary 3

Sampling

- Impulse train sampling: $x_s(t) = x(t)\left[\sum_{n=-\infty}^{\infty} \delta(t - nT_s)\right] \stackrel{\mathcal{F}}{\longleftrightarrow} X_s(\omega) = \frac{1}{T_s}\sum_{k=-\infty}^{\infty} X(\omega - k\omega_s)$.
- If $x(t)$ is bandlimited to $\pm\omega_{\max}$, then one can recover $x(t)$ from its samples $x(nT_s)$ (or equivalently from $x_s(t)$) if ω_s exceeds the Nyquist sampling rate $2\omega_{\max}$.
- A lowpass filter with cutoff frequency $\omega_{\max} < \omega_c < \omega_s - \omega_{\max}$ will recover $X(\omega)$ from $X_s(\omega)$ and hence $x(t)$ from $x_s(t)$.
- In time domain:

$$x_r(t) = \sum_{n=-\infty}^{\infty} x(nT_s)\frac{\omega_c T_s}{\pi}\operatorname{sinc}\left(\frac{\omega_c(t - nT_s)}{\pi}\right)$$

- More generally, for a periodic signal $p(t)$ with fundamental frequency ω_0:

$$y(t) = x(t)p(t) = x(t)\sum_{k=-\infty}^{\infty} c_k e^{jk\omega_0 t} \stackrel{\mathcal{F}}{\longleftrightarrow} Y(\omega) = \sum_{k=-\infty}^{\infty} c_k X(\omega - k\omega_0),$$

  for which the sampling requirements in general depend on c_k's
- Non-sinc interpolation:

$$x_s(t) \rightarrow \boxed{h_1(t)} \rightarrow y(t) \stackrel{\mathcal{F}}{\longleftrightarrow} Y(\omega) = X_s(\omega)H_1(\omega)$$

Modulation

- Double sideband suppressed carrier amplitude modulation or DSB/SC-AM.
  - Modulation property $y(t) = x(t)c(t) = x(t)\cos(\omega_c t + \theta_c) \stackrel{\mathcal{F}}{\longleftrightarrow} Y(\omega) = \frac{1}{2}[e^{j\theta_c}X(\omega - \omega_c) + e^{-j\theta_c}X(\omega + \omega_c)]$
  - Synchronous demodulation:

$$y(t) \rightarrow \bigotimes_{\underset{\cos(\omega_c t + \theta_c)}{\uparrow}} \rightarrow w(t) \rightarrow \boxed{H(\omega) = 2\operatorname{rect}\left(\frac{\omega}{2\omega_{\max}}\right)} \rightarrow x(t),$$

  where $\omega_{\max}$ is the maximum frequency of $M(\omega)$.

$$W(\omega) = \frac{1}{4}e^{2j\theta_c}X(\omega - 2\omega_c) + \frac{1}{2}X(\omega) + \frac{1}{4}e^{-2j\theta_c}X(\omega + 2\omega_c)$$

- DSB/WC-AM(with carrier)
  - Modulation property: $y(t) = (A + x(t))\cos(\omega_c t) \stackrel{\mathcal{F}}{\longleftrightarrow} Y(\omega) = A\pi[\delta(\omega - \omega_c) + \delta(\omega + \omega_c)] + \frac{1}{2}[X(\omega - \omega_c) + X(\omega + \omega_c)]$
  - Asynchronous demodulation: $y(t) \rightarrow \boxed{\text{Envelop detector}} \rightarrow \boxed{\text{DC blocking filter}} \rightarrow \hat{x}(t)$
  - Two basic assumptions are required, so that the envelop is easily tracked.
    - $x(t)$ be positive. Solution: $x(t) + A$.
    - $x(t)$ vary slowly compared to ω_c.
- Frequency-division multiplexing
  - Different stations are allocated different carrier frequencies, separated by (at least) the allowed bandwidth of each station.
  - Superheterodyning receiver

$$y(t) \rightarrow \boxed{\text{tunable bandpass at } \omega_c,\ 900\text{kHz wide}} \rightarrow \boxed{\text{mix at } \omega_0 = \omega_c + \omega_{\text{IF}}} \rightarrow \boxed{\text{bandpass at } \omega_{\text{IF}}/2\pi = 455\text{kHz} \pm 5\text{kHz}}$$

$$\rightarrow \boxed{\text{asynchronous demodulate}} \rightarrow \text{audio}$$

Bilateral Laplace transform
- $X(s) = \int_{-\infty}^{\infty} x(t)e^{-st}\,dt = \mathcal{F}\{x(t)e^{-\sigma t}\}, s = \sigma + j\omega$
- ROC is subset of $\mathbb{C}$ where $x(t)e^{-\operatorname{real}\{s\}\,t}$ is absolutely integrable
- ROC is "strips" (including RHP or LHP or all of $\mathbb{C}$)
  - ROC never contains poles
  - ROC of bounded finite signal is $\mathbb{C}$
  - ROC of right-sided signal is a RHP
  - ROC of left-sided signal is a LHP
  - ROC of two-sided signal is a strip
  - ROC of rational LT is strip bounded by poles
- $X(\omega) = X(s)|_{s=j\omega}$ if ROC includes $j\omega$ axis
- pole-zero plots + gain + ROC describe rational LT
- For rational $H(s)$:
  - pole locations describe modes of system
  - system is stable if ROC of $H(s)$ includes $j\omega$ axis
  - system is causal if ROC is a RHP
  - a causal system is stable iff all poles within LHP
  - if $M > N$, then there are $M - N$ poles at $s = \infty$, so system is unstable and non-causal.
- PFE for inverse LT when rational
- magnitude, phase response from pole-zero by geometry (draw vectors from pole/zero to $(0, j\omega)$, angle counter-clock wise from real axis)

Methods for finding response $y(t)$ of LTI system due to input $x(t)$
- Convolution $x(t) \xrightarrow{\text{LTI}} y(t) = x(t) * h(t)$
- LTI/convolution properties, *e.g.* if $x_1(t) \xrightarrow{\text{LTI}} y_1(t)$, and $x_2(t) \xrightarrow{\text{LTI}} y_2(t)$, then

$$x(t) = a_1 x_1(t - t_1) + a_2 x_2(t - t_2) \xrightarrow{\text{LTI}} y(t) = a_1 y_1(t - t_1) + a_2 y_2(t - t_2).$$

- Impulse properties (for finite set of impulses):

$$x(t) = \sum_{k=1}^{n} a_k \delta(t - t_k) \xrightarrow{\text{LTI}} y(t) = \sum_{k=1}^{n} a_k h(t - t_k)$$

- Eigenfunctions $x(t) = e^{s_0 t} \xrightarrow{\text{LTI}} y(t) = H(s_0)e^{s_0 t}$
- $x(t) = e^{j\omega t} \xrightarrow{\text{LTI}} y(t) = H(j\omega)e^{j\omega t} = |H(j\omega)|e^{j(\omega t + \angle H(j\omega))}$
- $x(t) = \sum_k c_k e^{j\omega_k t} \xrightarrow{\text{LTI}} y(t) = \sum_k c_k H(j\omega_k)e^{j\omega_k t}$
- If $h(t)$ is real, then $x(t) = \cos(\omega t + \phi) \xrightarrow{\text{LTI}} y(t) = |H(j\omega)| \cos(\omega t + \phi + \angle H(j\omega))$
- $x(t) = \sum_k A_k \cos(\omega_k t + \phi_k) \to \boxed{\text{LTI } h(t)} \to y(t) = \sum_k A_k |H(j\omega_k)| \cos(\omega_k t + \phi_k + \angle H(j\omega_k))$
- Fourier series $x(t) = \sum_{k=-\infty}^{\infty} c_k e^{jk\omega_0 t} \xrightarrow{\text{LTI}} y(t) = \sum_{k=-\infty}^{\infty} c_k H(jk\omega_0)e^{jk\omega_0 t}$
- Fourier transform convolution property $X(\omega) \xrightarrow{\text{LTI}} Y(\omega) = X(\omega)H(\omega)$. (Useful whenever $Y(\omega) = X(\omega)H(\omega)$ easily inverted.)
- Laplace transform convolution property $X(s) \xrightarrow{\text{LTI}} Y(s) = X(s)H(s)$. (Best for rational $X(s)$ and $H(s)$.)

LTI system properties

	Time	Fourier	Laplace (rational)
Invertible	$h(t) * h_i(t) = \delta(t)$, for some $h_i(t)$	$\forall \omega,\ H(\omega) \neq 0$	no zeros on $j\omega$ axis
Causal	$h(t) = 0$ for $t < 0$	?	ROC is a RHP
Stable	$\int_{-\infty}^{\infty} |h(t)|\, dt < \infty$	?	ROC includes $j\omega$ axis
Memory	$h(t) \neq \delta(t)$	$H(\omega)$ not constant	$H(s)$ not constant

Table of Laplace transform pairs

$f(t)$	$F(s)$	ROC
$\delta(t)$	1	$\forall s$
$u(t)$	$\dfrac{1}{s}$	$\text{real}\{s\} > 0$
$t^n u(t)$	$\dfrac{n!}{s^{n+1}}$	$\text{real}\{s\} > 0$
$e^{-at} u(t)$	$\dfrac{1}{s+a}$	$\text{real}\{s\} > \text{real}\{-a\}$
$-e^{-at} u(-t)$	$\dfrac{1}{s+a}$	$\text{real}\{s\} < \text{real}\{-a\}$
$t^n e^{-at} u(t)$	$\dfrac{n!}{(s+a)^{n+1}}$	$\text{real}\{s\} > \text{real}\{-a\}$

$f(t)$	$F(s)$	notes
$\sin(\omega_0 t)\, u(t)$	$\dfrac{\omega_0}{s^2 + \omega_0^2}$	$\text{real}\{s\} > 0$
$\cos(\omega_0 t)\, u(t)$	$\dfrac{s}{s^2 + \omega_0^2}$	$\text{real}\{s\} > 0$
$e^{-at} \cos(\omega_0 t)\, u(t)$	$\dfrac{s+a}{(s+a)^2 + \omega_0^2}$	$\text{real}\{s\} > \text{real}\{-a\}$
$e^{-at} \sin(\omega_0 t)\, u(t)$	$\dfrac{\omega_0}{(s+a)^2 + \omega_0^2}$	$\text{real}\{s\} > \text{real}\{-a\}$
$u_n(t) = \dfrac{d^n}{dt^n}\delta(t)$	s^n	$\forall s$
$u_{-n}(t) = \underbrace{u(t) * \ldots * u(t)}_{n \text{ times}}$	$\dfrac{1}{s^n}$	$\text{real}\{s\} > 0$

Properties of the Laplace Transform

	Time	Laplace	ROC (of result)
Linearity	$a_1 f_1(t) + a_2 f_2(t)$	$a_1 F_1(s) + a_2 F_2(s)$	contains $\text{ROC}_1 \cap \text{ROC}_2$
Time shift	$f(t - \tau)$	$e^{-s\tau} F(s)$	same
Time-scaling	$f(at),\ a \neq 0$	$\dfrac{1}{\lvert a \rvert} F\left(\dfrac{s}{a}\right)$	aROC
Time reversal	$f(-t)$	$F(-s)$	$-$ROC
Convolution	$f_1(t) * f_2(t)$	$F_1(s) \cdot F_2(s)$	contains $\text{ROC}_1 \cap \text{ROC}_2$
Frequency shift	$f(t) e^{j\omega_0 t}$	$F(s - j\omega_0)$	same
Frequency shift	$f(t) e^{s_0 t}$	$F(s - s_0)$	$\text{ROC} + \text{real}\{s_0\}$
Time Differentiation	$\dfrac{d^n}{dt^n} f(t)$	$s^n F(\omega)$	contains ROC
s-domain Differentiation	$(-t)^n f(t)$	$\dfrac{d^n}{ds^n} F(\omega)$	same
Integration	$\int_{-\infty}^{t} f(\tau)\, d\tau = f(t) * u(t)$	$\dfrac{1}{s} F(s)$	contains $\text{ROC} \cap \{\text{real}\{s\} > 0\}$
DC Value	$\int_{-\infty}^{\infty} f(t)\, dt = F(0)$		must contain $s = 0$

Table of Fourier Series for Common Signals

Name	Waveform	c_0	$c_k, k \neq 0$	Comments
Sawtooth		$\frac{X_0}{2}$	$j\frac{X_0}{2\pi k}$	
Impulse train		$\frac{X_0}{T_0}$	$\frac{X_0}{T_0}$	
Rectangular wave		$\frac{TX_0}{T_0}$	$\frac{TX_0}{T_0}\operatorname{sinc}\left(\frac{Tk\omega_0}{2\pi}\right)$	$\frac{Tk\omega_0}{2\pi} = \frac{Tk}{T_0}$
Square wave		0	$-j\frac{2X_0}{\pi k}$	$c_k = 0$, k even
Triangular wave sine		$\frac{X_0}{2}$	$\frac{-2X_0}{(\pi k)^2}$	$c_k = 0$, k even

Table of Fourier transform pairs

$f(t)$	$F(\omega)$
$\delta(t)$	1
1	$2\pi\,\delta(\omega) = \delta\left(\dfrac{\omega}{2\pi}\right)$
$u(t)$	$\pi\,\delta(\omega) + \dfrac{1}{j\omega}$
$\mathrm{sgn}(t)$	$\dfrac{2}{j\omega}$
$\mathrm{e}^{j\omega_0 t}$	$2\pi\,\delta(\omega - \omega_0)$
$\cos\omega_0 t$	$\pi\,\delta(\omega - \omega_0) + \pi\,\delta(\omega + \omega_0)$
$\sin\omega_0 t$	$\dfrac{\pi}{j}\,\delta(\omega - \omega_0) - \dfrac{\pi}{j}\,\delta(\omega + \omega_0)$
e^{-bt^2}	$\sqrt{\pi/b}\,\mathrm{e}^{-\omega^2/(4b)}$
$\displaystyle\sum_{n=-\infty}^{\infty}\delta(t - nT_0)$	$\displaystyle\sum_{k=-\infty}^{\infty}\omega_0\,\delta(\omega - k\omega_0)$

$f(t)$	$F(\omega)$
$\dfrac{1}{b^2 + t^2}$	$\dfrac{\pi}{b}\,\mathrm{e}^{-b\lvert\omega\rvert}$
$\mathrm{e}^{-b\lvert t\rvert}$	$\dfrac{2b}{b^2 + \omega^2}$
$\mathrm{rect}\left(\dfrac{t}{T}\right)$	$T\,\mathrm{sinc}\left(T\dfrac{\omega}{2\pi}\right)$
$\mathrm{tri}(t)$	$\mathrm{sinc}^2\left(\dfrac{\omega}{2\pi}\right)$
$\dfrac{\omega_0}{2\pi}\,\mathrm{sinc}\left(\dfrac{\omega_0}{2\pi}t\right)$	$\mathrm{rect}\left(\dfrac{\omega}{\omega_0}\right)$
$\mathrm{sinc}^2(t)$	$\mathrm{tri}\left(\dfrac{\omega}{2\pi}\right)$
$\mathrm{e}^{-at}\,u(t)$	$\dfrac{1}{j\omega + a}$
$\dfrac{t^{n-1}}{(n-1)!}\,\mathrm{e}^{-at}\,u(t)$	$\dfrac{1}{(j\omega + a)^n}$
$\dfrac{j}{\pi t}$	$\mathrm{sgn}(\omega)$

b is a real positive number throughout. a is a real or complex number throughout, with positive real part.

Properties of the Continuous-Time Fourier Transform

	Time	Fourier
Synthesis, Analysis	$f(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} F(\omega) e^{j\omega t} \, d\omega$	$F(\omega) = \int_{-\infty}^{\infty} f(t) e^{-j\omega t} \, dt$
Eigenfunction	$h(t) * e^{j\omega_0 t} = H(\omega_0) e^{j\omega_0 t}$	$H(\omega) 2\pi \delta(\omega - \omega_0)$ $= H(\omega_0) 2\pi \delta(\omega - \omega_0)$
Linearity	$a_1 f_1(t) + a_2 f_2(t)$	$a_1 F_1(\omega) + a_2 F_2(\omega)$
Time transformation	$f(at + b), \ a \neq 0$	$\frac{1}{|a|} e^{j\omega b/a} F(\omega/a)$
Time shift	$f(t - \tau)$	$F(\omega) e^{-j\omega\tau}$
Time reversal	$f(-t)$	$F(-\omega)$
Time-scaling	$f(at), \ a \neq 0$	$\frac{1}{|a|} F\left(\frac{\omega}{a}\right)$
Convolution	$f_1(t) * f_2(t)$	$F_1(\omega) \cdot F_2(\omega)$
Time-domain Multiplication	$f_1(t) \cdot f_2(t)$	$\frac{1}{2\pi} F_1(\omega) * F_2(\omega)$
Frequency shift	$f(t) e^{j\omega_0 t}$	$F(\omega - \omega_0)$
Modulation (cosine)	$f(t) \cos(\omega_0 t)$	$\frac{F(\omega - \omega_0) + F(\omega + \omega_0)}{2}$
Time. Differentiation	$\frac{d^n}{dt^n} f(t)$	$(j\omega)^n F(\omega)$
Freq. Differentiation	$(-jt)^n f(t)$	$\frac{d^n}{d\omega^n} F(\omega)$
Integration	$\int_{-\infty}^{t} f(\tau) \, d\tau = f(t) * u(t)$	$\frac{1}{j\omega} F(\omega) + \pi F(0) \delta(\omega)$
Conjugation	$f^*(t)$	$F^*(-\omega)$
Duality	$F(t)$	$2\pi f(-\omega)$
Relation to Laplace	$F(\omega) = \left. F(s) \right|_{s=j\omega}$, if ROC includes $j\omega$ axis	
Parseval's Theorem	$\int_{-\infty}^{\infty} f_1(t) f_2^*(t) \, dt = \frac{1}{2\pi} \int_{-\infty}^{\infty} F_1(\omega) F_2^*(\omega) \, d\omega$	
Parseval/Rayleigh Theorem	$E = \int_{-\infty}^{\infty} |f(t)|^2 \, dt = \frac{1}{2\pi} \int_{-\infty}^{\infty} |F(\omega)|^2 \, d\omega$	
DC Value	$\int_{-\infty}^{\infty} f(t) \, dt = F(0)$	

A function that satisfies $f(t) = f^*(-t)$ is said to have **Hermitian symmetry**.

Topics

Chap. 1
- signal classes
- signal notation
- * time transformations
- amplitude transformations
- signal operations
- integrator system (running integral operation)
- * even/odd signals
- * energy and power signals
- periodicity
- * unit step / rect signals
- * unit impulse function
- * impulse function properties (sifting, sampling)
- CT systems
- block diagrams
- system classes
- * amplitude properties: linearity, stability, invertibility
- * time properties: causality, memory, time-invariance

Chap. 2
- impulse response $h(t)$
- convolution for CT LTI systems
- * graphical convolution
- * properties of convolution and LTI systems
- impulse response vs step response
- * properties of convolution and impulse response
- LTI system properties characterized by $h(t)$(causality, memory, stability, invertibility)
- diffeq systems
- solutions of diffeq

Ch. 3
- eigenfunctions of LTI systems (complex-exponential signals)
- * Fourier series (3.3)
- Convergence of Fourier series (Gibbs phenomenon)(3.4)
- Properties of Fourier series (3.5)
- trigonometric forms of FS
- system transfer function (Laplace)
- frequency response (Fourier)
- Parsevals Relation for CT Periodic Signals(3.5.7)
- Power density spectrum
- magnitude/phase spectrum
- * Fourier Series and LTI Systems (3.8)
- differentiation/modulation properties
- Filtering (3.9)
- * Filters described by diffeqs (3.10)
- Rational transfer functions for diffeq systems

Ch. 4
- Defined FT and inverse FT by limits of FS
- Existence of FT

- * FT of many important signals
- * FT properties
- FT of periodic signals
- Parsevals relation (Energy density spectrum)
- * convolution property and LTI systems
- * Application of FT to RLC and diffeq systems

Ch. 6
- *Ideal filters (6.3)
- Real filters (6.4)
- Bode Plots (6.2.3)
- Bandwidth
- Tim-bandwidth product

Ch. 7
- DSP, A/D conversion
- * impulse train sampling, sampling theorem
- * Nyquist sampling rate
- * lowpass reconstruction
- * sinc interpolation
- * linear interpolation (first order hold)
- * nearest neighbor interpolation (zero order hold)
- non-impulse sampling

Ch. 8
- * double sideband, suppressed carrier, amplitude modulation (DSB/SC-AM)
- * double sideband, with carrier, amplitude modulation (DSB/WC-AM)
- * synchronous demodulation
- * asynchronous demodulation
- Frequency-division multiplexing (superheterodyning receiver)
- Systems-level analysis of communication system

Ch. 9
- Laplace transform definition / computation by integration
- * ROC of Laplace transform / properties
- relation to Fourier transform
- * rational Laplace transforms / pole-zero plot
- * inverse Laplace transform by PFE
- FT magnitude from pole-zero plot
- properties of LT
- * ROC and causality and stability of LTI systems
- * System functions and block diagram representations
- Feedback Control

The items with a * are virtually guaranteed to be on the exam.

Tips for Exam Preparation

- **Study lecture slides.** Read through lecture slides and the summary notes carefully. Make sure that you fully understand all the lecture materials.
- **Study homework solutions.** Review your HW sets and the posted solutions on Canvas.
- **Attend exam recitation classes.** TAs will posted times on Canvas.