

PCB v1.0 Important information

Figure 1. Explained

1. 12 volt or 9 volt selection jumper

! open = for 6581 SID only!! (12 volts)

! closed = for 8580 SID (9 volts)

2. Socket 2 6581 / 8580 SID type selection jumpers

! both closed left = 6581

! both closed right = 8580

3. Socket 1 6581 / 8580 SID type selection jumpers

! both closed left = 6581

! both closed right = 8580

4. Audio channel selection jumper

! closed on Socket 1 side = left & right channel for socket 1

! closed on Socket 2 side = left channel for socket 2 & right channel for socket 1

5. Address line A5 for adressess above \$1F (SKPico 2nd SID for example)

! both pins are routed to the same GPIO for using addresses higher then \$20

6. Uart debugging output port

! TX on the right

! RX on the left

7. Optional 330k pulldown resistor hooked up to EXT-IN for 8580 filter bypass in socket 2

! solder closed = enabled

8. Optional 330k pulldown resistor hooked up to EXT-IN for 8580 filter bypass in socket 1

! solder pad closed = enabled

9. Optional 1MHz crystal socket (not included in BOM)

! solder pad closed = enabled (when a crystal is socketed)

! this disables the internal clock generation on the Pico

10. Optional 1k resistor for 6581 SID in socket 2

! ATTENTION!: *This solder pad label is incorrect, it should read 6581!*

! solder pad closed = enabled

11. Optional 1k resistor for 6581 SID in socket 2

! ATTENTION!: *This solder pad label is incorrect, it should read 6581!*

! solder pad closed = enabled

12. Socket 2 audio out via dupont connector

! Ground and S2 as labeled

13. Socket 1 audio out via dupont connector

! Ground and S1 as labeled

14. Reset button

